

UTILITY PATENT APPLICATION TRANSMITTAL

Attorney Docket No.

1075.1129/JDH

First Named Inventor or Application Identifier:

Tomonori MASE et al.

Express Mail Label No.

(Only for new nonprovisional applications under 37 CFR 1.53(b))

APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents.

ADDRESS TO: **Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231**

1. ☒ Fee Transmittal Form
2. ☒ Specification, Claims & Abstract [Total Pages: 413]
3. ☒ Drawing(s) (35 USC 113) [Total Sheets: 215]
4. ☐ Oath or Declaration [Total Pages:]
- a. ☐ Newly executed (original or copy)
- b. ☐ Copy from a prior application (37 CFR 1.63(d)) (for continuation/divisional with Box 17 completed)
- i. ☐ **DELETION OF INVENTOR(S)**
Signed statement attached deleting inventor(s) named in the prior application, see 37 CFR 1.63(d)(2) and 1.33(b).
5. ☐ Incorporation by Reference (usable if Box 4b is checked)
The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under Box 4b, is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.
6. ☐ Microfiche Computer Program (Appendix)
7. ☐ Nucleotide and/or Amino Acid Sequence Submission (if applicable, all necessary)
- a. ☐ Computer Readable Copy
- b. ☐ Paper Copy (identical to computer copy)
- c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

8. ☐ Assignment Papers (cover sheet & document(s))
9. ☐ 37 CFR 3.73(b) Statement (when there is an assignee) [☐ Power of Attorney
10. ☐ English Translation Document (if applicable)
11. ☐ Information Disclosure Statement (IDS)/PTO-1449 [☐ Copies of IDS Citations
12. ☐ Preliminary Amendment
13. ☒ Return Receipt Postcard (MPEP 503) (Should be specifically itemized)
14. ☐ Small Entity Statement(s) [☐ Statement filed in prior application, status still proper and desired.
15. ☐ Certified Copy of Priority Document(s) (if foreign priority is claimed)
16. ☐ Other:

17. If a **CONTINUING APPLICATION**, check appropriate box and supply the requisite information:[☐ Continuation [☐ Divisional [☐ Continuation-in-part (CIP) of prior application No: /]

18. CORRESPONDENCE ADDRESS

STAAS & HALSEY LLP
Attn: James D. Halsey, Jr.
700 Eleventh Street, N.W., Suite 500
Washington, DC 20001

Telephone: (202) 434-1500
Facsimile: (202) 434-1501

03/30/00
jc644 U.S. PTOjc625 U.S. PTO
09/539805
03/30/00

09539805 033000

SPECIFICATION

TITLE OF THE INVENTION

METHOD FOR CONTROLLING MAGNETIC TAPE UNIT

5

BACKGROUND OF THE INVENTION

1) Field of the Invention

The present invention relates to a method for controlling a tape operation of a magnetic tape unit in response to a command from a command issuing apparatus (for example, a host computer/upper apparatus such as a CPU).

2) Description of the Related Art

With an increasing demand for higher-speed computer systems in recent years, there is a requirement for a more efficient backup/restore operation to copy data between a DASD (Direct Access Storage Device) and a magnetic tape.

In order to store large amounts of data on a magnetic tape at a high speed, there is provided a technique called streaming. The streaming is a process of successively performing READ or WRITE from/on a magnetic tape by buffering.

When an upper apparatus such as a CPU accesses to a magnetic tape via a magnetic tape controller having a data buffer, for example, the magnetic tape controller such controls that a read/write process

between the upper apparatus and the buffer, and a read/write process between the buffer and the magnetic tape are carried out asynchronously to perform a streaming process.

5 As above, the streaming control (asynchronous control by buffering) is performed when successively reading/writing a data block on the magnetic tape unit, thereby lessening the frequency of the start/stop operation of the magnetic tape, thus improving the
10 read/write performance of the magnetic tape unit.

When the upper apparatus issues a command to reverse the direction of travel of the magnetic tape, or when a tape mark is detected, or when the upper apparatus issues a command in the read/write control
15 system while the magnetic tape unit carries out such the streaming, it is necessary to stop the streaming for a time to synchronize the process carried out on the channel's side connected to the upper apparatus with the process carried out on the magnetic tape
20 unit's side.

With reference to FIGS. 175 through 201, a structure of a known magnetic tape controller and streaming process/command processing by the magnetic tape controller will be described hereinafter.

25 FIG. 175 is a block diagram showing a hardware structure of the magnetic tape controller. As shown in FIG. 175, a magnetic tape controller (MTC; Magnetic

Tape Controller) 10 is disposed between a CPU 20 (host computer, upper apparatus) 20 and a magnetic tape unit (MTU; Magnetic Tape Unit) 30 to control operations of the MTU 30 in response to commands from the CPU 20.

5 The MTC 10 comprises a channel interface circuit 11, a data compressing circuit 12, a data decompressing circuit 13, a host interface controller (HIC; Host Interface Controller) 14, a format controller (FMT: ForMaT controller) 15, a command
10 buffer 16 and a data buffer 17.

 The channel interface circuit 11 controls a channel interface with the CPU 20. The data compressing circuit 12 performs data compression in, for example, EDRC (Enhanced Data Recording
15 Capability) system. The data decompressing circuit 13 decompresses the compressed data.

 The HIC 14 performs format conversions and controls in order to send/receive data with the CPU 20. The FMT 15 performs format conversions and
20 controls in order to send/receive data with the MTU 30. The command buffer 16 is to communicate between the HIC 14 and the FMT 15, storing commands directing operations and the like that should be performed by the HIC 14 and the FMT 15. The data buffer 17
25 temporarily stores each block of data (write data) that should be written on the magnetic tape or data (read data) that has been read out from the magnetic

The command buffer 16 comprises, as shown in FIG. 176, a command pointer table for HIC (HQP) 16-1, a command list table for HIC (HQL) 16-2, a command pointer table for FMT (FQP) 16-3 and a command list table for MFT (FQL) 16-4.

10

15

25

MTU 30 and records the data on the magnetic tape. On the other hand, at the time of reading, the FMT 15 reads data on the magnetic tape from the MTU 30 and stores the data in the data buffer 17, and the HIC 14 transfers the read data in the data buffer 17 to the CPU 20.

The HQL 16-2 functions as a command queue for storing commands directing operations that should be carried out by the HIC 14 in response to directions from the CPU 20 (commands 1 to 3 in FIG. 176) in the order they were generated. In the HQL 16-2, there are recorded block pointers (BPNT) indicating positions in the data buffer 17 of data blocks (DATA 1 to DATA 3 in FIG. 176) corresponding to respective commands, block lengths (BLEN) of the data blocks, block IDs (BID) of the data blocks, etc.

The FQL 16-4 functions as a command queue storing commands having been carried out by the FMT 15 in accordance with the directions from the CPU 20 (commands 1 and 2 in FIG. 176) in the order their processes were completed. In the FQL 16-4, there are recorded block pointers (BPNT) indicating positions in the data buffer 17 of data blocks (DATA 1 to DATA 3 in FIG. 176) corresponding to respective commands, block lengths (BLEN) of the data blocks, block IDs (BID) of the data blocks, flags (TM) each showing that a tape mark recorded on the magnetic tape has been detected in the MTU 30, etc.

In the FMT 15, information XBID about a block ID managed by the FMT 15 is stored in a register 15a. The XBID indicates a position of a head relative to the magnetic tape (ID of a data block at which the head is really positioned) in the MTU 30.

Next, operations of the MTC 10 structured as above will be described.

With reference to FIGS. 177 through 182, streaming sequences by the MTC 10 will be described.

10 [Read streaming sequence]

FIGS. 177 and 178 are diagrams for illustrating states of the command buffer 16 and the data buffer 17 when a read streaming sequence is executed.

15 In the MTC 10, when the channel interface circuit 11 receives a read command issued from the CPU 20, the HIC 14 sets a prefetch direction flag in the HQP 16-1. The FMT 15 has a look at the prefetch direction flag set in the HQP 16-1, makes the MTU 30 read a plurality of data blocks from the magnetic tape, writes the data in the data buffer 17, and registers command lists for the read blocks in the FQL 16-4.

20 In the MTU 30, a mechanical operation is such carried out that the head of the MTU 30 is moved in the forward direction relative to the magnetic tape MT, at this time. For instance, data blocks "DATA 1, DATA 2, DATA 3" are read in order. Here, the three

data blocks are written in the data buffer 17. The number of data blocks to be preferentially read is set according to a capacity of the data buffer 17, for example, and the preferentially read operation is such
5 controlled as to be halted when a quantity of the write data exceeds the capacity of the data buffer 17.

As shown in FIG. 177, commands "READ 1, READ 2, READ 3" corresponding to the respective data blocks written in the data buffer 17 are set in order in the
10 command queue of the FQL 16-4.

A predetermined number (here, 3) of the data blocks are written in the data buffer 17 as in the above manner, the latest command pointer and the latest block ID are then stored in the FQP 16-3, and a prefetch
15 completion flag is set as well.

After the prefetch completion flag is set in the FQP 16-3, the HIC 14 compares a value of the command pointer in the HQP 16-1 with a value of the command pointer in the FQP 16-3, and transfers a data block
20 corresponding to a difference therebetween to the CPU 20. At this time, the HQP 16-1 and the HQL 16-2 are successively updated as shown in FIG. 178. Namely, each time a data block in the data buffer 17 is transferred to the CPU 20, a command having been
25 executed is recorded in the FQL 16-2, the command pointer in the FQP 16-1 is updated and a block ID of the latest data block having been transferred is

stored.

FIG. 178 depicts a state in which transfer (reading) of all the three data blocks to the CPU 20 is completed. In the state shown in FIG. 178, both
 5 the block IDs in the HQP 16-1 and the FQP 16-3 indicate an ID (for example, 3) of the third data block.

In data transfer to the CPU 20, if data read out from the magnetic tape has been compressed, the data is first inputted to the data decompressing
 10 circuit 13, then transferred to the CPU 20.

The MTC 10 can send read data to the channel to transfer the same to the CPU 20 in response to read commands successively issued from the CPU 20 after carrying out the above preferential read operation as
 15 long as read data exists in the data buffer 17, without any mechanical operation (real read operation) of the MTU 30. Accordingly, the MTU 30 is not required to perform the mechanical operation for each data block, so that the data transfer efficiency at the time of
 20 read operation is improved.

When the FMT 15 detects a tape mark during the read operation, a TM flag is set in the FQL 16-4.

[Write streaming sequence]

Next, description will be made of a case where
 25 the MTC 10 such controls the MTU 30 as to record predetermined data (data blocks "DATA 1", "DATA 2", "DATA 3") on the magnetic tape according to directions

from the CPU 20, with reference to FIGS. 179 and 180. FIGS. 179 and 180 are diagrams depicting states of the command buffer 16 and the data buffer 17 when a write streaming sequence is executed. Incidentally, the
5 prefetch direction flag and prefetch completion flag are not set in the HQP 16-1 and the HQP 16-3, respectively, when a write operation is performed, as shown in FIGS. 179 and 180.

In the MTC 10, when the channel interface
10 circuit 11 receives write commands issued from the CPU 20, the HIC 14 successively stores the write commands (WRITE 1, WRITE 2, WRITE 3) in the HQL 16-2, and registers the latest command pointer and the latest block ID in the HQP 16-1. The data blocks, "DATA 1",
15 "DATA 2" and "DATA 3", are successively written in the data buffer 17 in response to the respective write commands.

When completing a writing of a predetermined number of data blocks (here, 3) in the data buffer 17,
20 the HIC 14 stores the latest command pointer and the latest block ID in the HQP 16-1, and reports completion of the writing to the CPU 20.

Note that when intending to write data that should be written on the magnetic tape in a compressed
25 form, that data is first inputted to the data compressing circuit 12 from the channel interface circuit 11 to be compressed in the EDRC system therein,

then written in the data buffer 17.

On the other hand, the FMT 15 compares a value of the command pointer in the HQP 16-1 with a value of the command pointer in the FQP 16-3. When the FMT 15 detects that a difference therebetween is generated, the FMT 15 recognizes that commands are registered in the HQL 16-2, thus successively transfers data blocks corresponding to the difference from the data buffer 17 to the MTU 30 to store the data on the magnetic tape.

At this time, the FQP 16-3 and the FQL 16-4 are successively updated, as shown in FIG. 180. Namely, each time a data block in the data buffer 17 is transferred to the MTU 30 to be recorded in the magnetic tape, a command having been executed is recorded in the FQL 16-4, and the latest command pointer and the latest block ID are registered in the FQP 16-3.

FIG. 180 depicts a state in which a writing of the second data block "DATA 2" on the magnetic tape is completed. In the state shown in FIG. 180, a block ID in the HQP 16-1 indicates an ID (for example, 3) of the third data block, whereas a block ID in the HQP 16-3 indicates an ID (for example, 2) of the second data block.

As above, the MTC 10 stores write commands successively issued from the CPU 20 and data blocks that should be written on the magnetic tape in the HQL

16-2 and the data buffer 17, respectively, for a time, thereby processing the write commands asynchronously with the MTU 30.

Since the FMT 15 can perform a write streaming operation such as writing data on the magnetic tape when data blocks are accumulated to some extent in the data buffer 17, the frequency of execution of the start/stop operation of the MTU 30 is decreased, which increases a write performance of the MTU 30.

10 [Other command sequence]

FIGS. 181 and 182 are diagrams illustrating states of the command buffer 16 and the data buffer 17 when a command sequence other than a read command and a write command is executed.

15 Other than a read command and a write command, there are, for example, a read backward command (RB), a back space block command (BSP), a back space file command (BSPF), a forward space block command (SP), a forward space file command (FSPF) and a write tape
20 mark command (WTM) as commands causing tape operations of the MTU 30.

When the CPU 20 issues such a command and the channel interface circuit 11 receives the command in the MTC 10, the HIC 14 registers the command in the
25 HQL 16-2 and stores the latest command pointer in the HQP 16-1 as shown in FIG. 181.

On the other hand, the FMT 15 compares a value

of the command pointer in the HQP 16-1 with a value
of the command pointer in the FQP 16-3. When the FMT
15 detects that a difference is generated therebetween,
the FMT 15 recognizes that a command is registered in
5 the HQL 16-2, thus carries out a process according to
the command (command processing), then registers the
command in the FQL 16-4 and the latest command pointer
in the FQP 16-3 as well, as shown in FIG. 182.

When the HIC 14 has a look at a difference
10 between a value of the command pointer in the FQP 16-3
and a value of the command pointer in the HQP 16-1 and
recognizes that the FMT 15 completes the command
processing, the HIC 14 reports completion of the
command processing to the CPU 20.

15 When processing a command other than a read
command and a write command, the process is serially
carried out without the streaming process as above,
whereby a process (process by the HIC 14) on the
channel's side connected to the CPU 20 is synchronized
20 with a process (process by the FMT 15) on the side of
the MTU 30.

Next, a command processing by the FMT 15 will
be described with reference to FIGS. 183 through 199.
[Idle process]

25 FIG. 183 is a flowchart (Steps S11 to S30) for
illustrating an idle process by the FMT 15. As shown
in FIG. 183, the FMT 15 periodically reads the HQP 16-1

of the command buffer 16 in the idle process to refer to it (Step S11).

When the prefetch direction flag is set in the HQP 16-1 (YES route at Step S12), it is determined whether or not a command corresponding to the prefetch direction flag is a read command (RD command) (Step S22). When the command is an RD command (YES route at Step S22), the FMT 15 executes a read process (RD process) while referring to FIGS. 184 and 185 (Step S23), and goes back to Step S11. When the command is not an RD command (NO route at Step S22), the FMT 15 executes a read backward process (RB process) to be described later while referring to FIGS. 186 and 187 (Step S24), then goes back to Step S11.

On the other hand, when the prefetch direction flag is not set in the HQP 16-1 (NO route at Step S12), the FMT 15 compares a value of the command pointer in the HQP 16-1 with a value of the command pointer in the FQP 16-3 (Step S13). When [a value of the command pointer in the HQP 16-1] is not larger than [a value of the command pointer in the FQP 16-3] (NO route at Step S13), the FMT 15 determines that a command to be processed is not registered in the command buffer 16, and goes back to Step S11.

When it is determined that [a value of the command pointer in the HQP 16-1] is larger than [a value of the command pointer in the FQP 16-3] (YES

route), the FMT 15 refers to the HQL 16-2 (Step S14), and determines a type of the command registered in the HQL 16-2 (Steps S15 to S20).

Namely, when the command is a write command
5 (WR command) (YES route at Step S15), the FMT 15 executes a write process (WR process) to be described later while referring to FIGS. 188 and 189 (Step S25), then goes back to Step S11.

When the command is a back space block command
10 (BSP command) (from NO route at Step S15 to YES route at Step S16), the FMT 15 executes a back space block process (BSP process) to be described later while referring to FIGS. 190 and 191 (Step S26), then goes back to Step S11. When the command is a back space
15 file command (BSPF command) (from NO route at Step S16 to YES route at Step S17), the FMT 15 executes a back space file process (BSPF process) to be described later while referring to FIGS. 192 and 193 (Step S27), then goes back to Step S11.

20 When the command is a forward space block command (SP command) (from NO route at Step S17 to YES route at Step S18), the FMT 15 executes a forward space block process (SP process) to be described later while referring to FIGS. 194 and 195 (Step S28), then goes
25 back to Step S11. When the command is a forward space block command (FSPF command) (from NO route at Step S18 to YES route at Step S19), the FMT 15 executes a

forward space file process (FSPF process) to be described later while referring to FIGS. 196 and 197 (Step S29), then goes back to Step S11.

When the command is a write tape mark command (WTM command) (from NO route at Step S19 to YES route at Step S20), the FMT 15 executes a write tape mark process (WTM process) to be described later while referring to FIGS. 198 and 199 (Step S30), then goes back to Step S11.

When the command is not a WTM command (NO route at Step S20), the FMT 15 executes a process according to the command (other command processing) (Step S21), then goes back to Step S11.

[Read Process (RD process)]

FIG. 184 is a flowchart for illustrating a read process by the FMT 15. FIG. 185 is a diagram in which a part of the flowchart shown in FIG. 184 (processes A1, B1 and C1) is tabulated in order to explain the read process by the FMT 15.

As shown in FIGS. 184 and 185, process A1, process B1 and process C1 are repeatedly executed at the time of the RD process by the FMT 15 until the streaming is stopped.

In the process A1, the FMT 15 makes the MTU 30 execute a read operation according to the RD command, besides updating XBID by adding 1 to XBID registered in the register 15a.

In the process B1, the FMT 15 determines whether or not a tape mark is read out in the read operation by the MTU 30 executed in the process A1 (Step S31). When a tape mark (TM) is read out (YES route at Step S31), the FMT 15 sets a TM flag and sets "0" as the block length BLEN (Step S32), and sets XBID as BID (Step S34). On the other hand, when data other than the tape mark (TM) is read out (NO route at Step S31), the FMT 15 clears the TM flag and sets "LEN" as the block length BLEN (Step S33), then reads XBID as BID from the register 15a and sets the same (Step S34). Here, "LEN" is a block length set in a hard register after the data is transferred from the MTU 30 to the data buffer 17.

In the process C1, the FMT 15 registers BID, BLEN and TM flag obtained in the process B1 in the FQL 16-4 in the command buffer 16, registers a value obtained by adding BLEN to BPNT of the next command ahead as a block pointer BPNT, and updates the command pointer and BID in the FQP 16-3.

[Read Backward Process (RB process)]

FIG. 186 is a flowchart for illustrating a read backward process by the FMT 15. FIG. 187 is a diagram in which the flowchart (processes A2, B2 and C2) shown in FIG. 186 is tabulated in order to explain the read backward process by the FMT 15.

As shown in FIGS. 186 and 187, the process A2,

the process B2 and the process C2 are executed at the time of the RB process by the FMT 15.

In the process A2, the FM 15 makes the MTU 30 execute a back read operation according to the RB
 5 command, and updates XBID by subtracting 1 from XBID registered in the register 15a.

In the process B2, the FMT 15 determines whether or not a tape mark is read out in the real back read operation by the MTU 30 executed in the process
 10 A2 (Step S41) as does in the RD process. When the tape mark (TM) is read out (YES route at Step S41), the FMT 15 sets a TM flag along with "0" as a block length BLEN (Step S42), and sets XBID as BID (Step S44). On the other hand, when data other than the tape mark (TM)
 15 is read out (NO route at Step S41), the FMT 15 clears the TM flag, sets "LEN" as the block length BLEN (Step S43), then reads out XBID as BID from the register 15a and sets the same (Step S44). Here, "LEN" is a block length to be set in the hard register after data is
 20 transferred from the MTU 30 to the data buffer 17.

In the process C2, the FMT 15 registers the BID, BLEN and TM flag obtained in the process B2 in the FQL 16-4 in the command buffer 16 as does in the RD process, registers a value obtained by adding BLEN
 25 to BPNT of the next command ahead as a block pointer BPNT, and updates the command pointer and BID in the FQP 16-3.

[Write Process (WR Process)]

FIG. 188 is a flowchart for illustrating a write process by the FMT 15. FIG. 189 is a diagram in which a part (processes A3, B3 and C3) of the flowchart shown in FIG. 188 is tabulated in order to explain the write process by the FMT 15.

As shown in FIGS. 188 and 189, the process A3, the process B3 and the process C3 are repeatedly executed at the time of the WR process by the FMT 15 until the streaming is stopped (until judged YES at Step S50).

In the process A3, the FMT 15 makes the MTU 30 execute a write operation according to a WR command, and updates XBID by adding 1 to XBID registered in the register 15a.

In the process B3, the FMT 15 sets "LEN" as a block length BLEN, reads XBID as BID from the register 15a and sets the same. Here, "LEN" is a block length to be set in the hard register after data is transferred from the CPU 20 to the data buffer 17.

In the process C3, the FMT 15 registers the BID and BLEN obtained in the process B3 in the FQL 16-4 in the command buffer 16, registers a value as a block pointer BPNT obtained by adding BLEN to BPNT of the next command ahead, and updates the command pointer and BID in the FQP 16-3.

[Back Space Block Process (BSP Process)]

FIG. 190 is a flowchart for illustrating a back space block process by the FMT 15. FIG. 191 is a diagram in which the flowchart (processes A4, B4 and C4) shown in FIG. 190 in order to explain a back space
 5 block process by the FMT 15.

As shown in FIGS. 190 and 191, the process A4, the process B4 and the process C4 are executed at the time of the BSP process by the FMT 15.

In the process A4, the FMT 15 makes the MTU
 10 30 execute a back space operation (operation to move a position of the head backward by one data block relative to the magnetic tape) according to a BSP command, and updates XBID by subtracting 1 from XBID registered in the register 15a.

15 The FMT 15 reads XBID as BID from the register 15a and sets the same in the process B4. In the process C4, the FMT 15 registers the BID obtained in the process B4 in the FQL 16-4 in the command buffer 16, and updates the command pointer and BID in the FQP
 20 16-3.

[Back Space File Process (BSPF process)]

FIG. 192 is a flowchart for illustrating a back space file process by the FMT 15. FIG. 193 is a diagram in which a part (processes A5, B5 and C5) of the
 25 flowchart shown in FIG. 192 is tabulated in order to explain the back space file process by the FMT 15.

As shown in FIG. 192 and 193, the process A5

and the process B5 are repeatedly executed at the time of the BSPF process by the FMT 15 until a tape mark (TM) is detected (until judged YES at Step S51). When a TM is detected (YES route at Step S51), the process
 5 C5 is executed.

In the process A5, the FMT 15 makes the MTU 30 execute a back space operation (operation to move a position of the head backward for one data block relative to the magnetic tape) according to the BSPF
 10 command, and updates XBID by subtracting 1 from XBID registered in the register 15a. Thereafter, the FMT 15 reads XBID as BID from the register 15a and sets the same in the process B5. By repeating the
 15 processes A5 and B5, the magnetic tape is driven backward until a position of the head relative to the magnetic tape reaches a position of the nearest TM (a position at the end of the file).

In the process C5, the FMT 15 registers the BID obtained in the process B5 in the FQL 16-4 in the
 20 command buffer 16, and updates the command pointer and BID in the FQP 16-3.

[Forward Space Block Process (SP process)]

FIG. 194 is a flowchart for illustrating a forward space block process by the FMT 15. FIG. 195
 25 is a diagram in which the flowchart (processes A6, B6 and C6) shown in FIG. 194 is tabulated in order to explain the forward space block process by the FMT 15.

As shown in FIGS. 194 and 195, the process A6, the process B6 and the process C6 are executed at the time of an SP process by the FMT 15.

In the process A6, the FMT 15 makes the MTU
5 30 execute a forward space operation (operation to
move a position of the head forward by one data block
relative to the magnetic tape) according to an SP
command, and updates XBID by adding 1 to XBID
registered in the register 15a.

10 In the process B6, the FMT 15 reads XBID as
BID from the register 15a and sets the same. In the
process C6, the FMT 15 registers BID obtained in the
process B6 in the FQL 16-4 in the command buffer 16,
and updates the command pointer and BID in the FQP
15 16-3.

[Forward Space File Process (FSPF process)]

FIG. 196 is a flowchart for illustrating a forward space file process by the FMT 15. FIG. 197 is a diagram in which a part (processes A7, B7 and C7) of the flowchart shown in FIG. 196 is tabulated in order to explain the forward space file process by the FMT 15.

As shown in FIG. 196 and 197, the process A7 and the process B7 are repeatedly executed at the time of the FSPF process by the FMT 15 until a tape mark (TM) is detected (until judged YES at Step S51). When a TM is detected (YES route at Step S52), the process

C7 is executed.

In the process A7, the FMT 15 makes the MTU 30 execute a forward space operation (operation to move a position of the head forward by one data block relative to the magnetic tape) according to an FSPF 5 command, and updates XBID by adding 1 to XBID registered in the register 15a. Thereafter, the FMT 15, in the process B7, reads XBID as BID from the register 15a, and sets the same. By repeating these 10 processes A7 and B7, the magnetic tape is driven forward until a position of the head relative to the magnetic tape reaches a position of the nearest TM (position at the head of the file).

In the process C7, the FMT 15 registers the 15 BID obtained in the process B7 in the FQL 16-4 in the command buffer 16, and updates the command pointer and BID in the FQP 16-3.

[Write Tape Mark Process (WTM Process)]

FIG. 198 is a flowchart for illustrating a 20 write tape mark process by the FMT 15. FIG. 199 is a diagram in which the flowchart (processes A8, B3 and C8) shown in FIG. 198 is tabulated in order to explain the write tape mark process by the FMT 15.

As shown in FIGS. 198 and 199, the process A8, 25 the process B8 and the process C8 are executed at the time of the WTM process by the FMT 15.

In the process A8, the FMT 15 makes the MTU

30 execute a write table mark operation (operation to write a tape mark on the magnetic tape) according to a WTM command, and updates XBID by adding 1 to XBID registered in the register 15a.

5 In the process B8, the FMT 15 sets a TM flag, reads XBID as BID from the register 15a and sets the same. In the process C8, the FMT 15 registers the BID and TM flag obtained in the process B8 in the FQL 16-4 in the command buffer 16, and updates the command
10 pointer and BID in the FQP 16-3.

FIGS. 200(A) and 200(B) are diagrams for illustrating a state of data writing on the magnetic tape, commands issued from the CPU 20 when a process of additionally writing a multi-file is carried out,
15 and tape operations in the MTU 30 in response to the commands.

FIG. 200(A) depicts a state of data writing on the magnetic tape MT immediately after a writing of a file consisting of a plurality of data blocks (data 1 in the drawing) on the magnetic tape MT is
20 completed. FIG. 200(B) depicts a state of data writing on the magnetic tape MT after a file consisting of a plurality of data blocks (data 2 in the drawing) is additionally written in the state shown in FIG.
25 200(A).

In FIGS. 200(A) and 200(B), each arrow indicates a tape operation (a direction and a quantity

of movement of the head H relative to the magnetic tape MT) carried out in response to each command from the CPU 20. Each arrow is given a type of command (capital letters) directing execution of the tape operation indicated by the arrow. Further, the types of the commands are given numbers in parentheses, (1) to (24), arranged in order the commands were issued from the CPU 20. In FIGS. 200(A) and 200(B), the rightward direction signifies a forward direction of the tape, whereas the leftward direction signifies a backward direction of the same.

As shown in FIG. 200(A), after the last data block (data 1 in the drawings) of a certain file is written on the magnetic tape MT in response to a WR command [cf. (1)], a close process [cf. (2) to (7)] for the file is carried out. Namely, a tape mark TM-a is written on the magnetic tape MT in response to a WTM command [cf. (2)], two end-of-file labels (hereinafter abbreviated as EOF; EOF1, EOF2 in the drawings) are successively written on the magnetic file MT according to a WR command [cf. (3), (4)], two tape marks, TM-b and TM-c, are successively written on the magnetic tape in response to WTM commands [cf. (5), (6)], and the magnetic tape MT is moved backward until TM-b is detected by the head H in response to a BSPF command [cf. (7)]. The MTU 30 waits in a state in which the head H is located between the last two

tape marks, TM-b and TM-c, after writing the file.

When the CPU 20 additionally write the second file on the magnetic tape in which the file has been written as shown in FIG. 200(A), an open process [cf. (8) to (22)] for the second file is carried out. Incidentally, it is assumed that an OS (Operating System) actuated by the CPU 20 reads EOF1 twice so as to recognize it, thereby issuing a command such as to recognize a position at which the second file should be additionally written, in the open process at the time of data writing.

In the file open process at the time of data writing, the magnetic tape MT is moved until TM-b is detected by the head H in response to a BSPF command [cf. (8)], then moved backward until TM-a is detected by the head H so as to skip EOF1 and EOF2 in response to a BSPF command [cf. (9)]. Thereafter, the magnetic tape is moved forward until TM-a is detected by the head H in response to an FSPF command [cf. (10)]. After EOF1 is once read in response to an RD command, the magnetic tape is moved forward until TM-b is detected by the head H so as to skip EOF 2 in response to an FSPF command [cf. (12)]. When TM-c is read in response to an RD command [cf. (13)], a Unit Exception report is made.

As shown in FIGS. 200(A) and 200(b), processes [cf. (14) to (19)] similar to those described above

10

15

20

25

the arrow. The types of the commands are given numbers in parentheses (1) to (13) in order the commands were issued from the CPU 20. In FIG. 201, the rightward direction signifies a tape forward direction (forward), whereas the leftward direction signifies a tape backward direction (backward), as well.

As shown in FIG. 201, after the last data block (data 1 in the drawing) of the first file is read out from the magnetic tape MT in response to an RD command [cf. (1)], a close process [cf. (2), (3)] for the first file is carried out. Namely, the magnetic tape MT is moved forward in response an FSPF command [cf. (2)] until TM-a is detected by the head H, and moved forward according to an FSPF command [cf. (3)] until TM-b is detected by the head H so as to skip EOF1 and EOF2. The head H is thereby located at the leading position of the second file (between TM-b and HDR 1).

Next, the open process [cf. (4) to (11)] for the second file is executed. Incidentally, the OS (Operation System) actuated by the CPU 20 reads EOF 1 once to recognize the same, thereby issuing a command so as to recognize a position at which the second file is read out in the file open process at the time of data reading.

In the file open process at the time of data reading, the magnetic tape MT is moved backward until

TM-b is detected by the head H in response to a BSPF command [cf. (4)], and moved backward until TM-a is detected by the head H to skip EOF1 and EOF 2 in response to a BSPF command [cf. (5)]. The magnetic
5 tape MT is then moved forward until TM-a is detected by the head H in response to an FSPF command [cf. (6)] so as to read EOF 1 in response to an RD command [cf. (7)], and moved forward until TM-b is detected by the head H so as to skip EOF 2 in response to an FSPF command
10 [cf. (8)], and two headers, HDR1 and HDR 2, are successively read according to RD commands [cf. (9), (10)]. Further, the magnetic tape MT is moved forward until TM-d is detected by the head H in response to an FSPF command [cf. (11)], the file open process is
15 thereby completed. Thereafter, a plurality of data blocks (data 2 in the drawing) belonging to the second file are successively read according to RD commands [cf. (12), (13)].

In the MTU 30, when data blocks are
20 successively written or read, the streaming control (asynchronous control by buffering) by the MTC 10 can lessen the frequency of the start/stop operation of the magnetic tape, thus improving the read/write performance, as described above.

25 However, when a tape mark is detected during the streaming operation or a tape operation according to a command (for example, SP command, BSPF command

or the like) other than the RD command and the WR command, it is necessary to temporarily stop the tape operation (streaming operation) by the MTU 30, then carry out a re-position operation for a position of the head relative to the magnetic tape when the next command is executed to synchronize a process (process by the HIC 14) on the channel's side connected to the CPU 20 with a process (process by the FMT 15) on the side of the MTU 30.

For instance, a magnetic tape on which data has been recorded in the multi-file form includes a lot of tape mark blocks. When the streaming process is carried out on such a magnetic tape, the start/stop operation of the magnetic tape is carried out each time a tape mark is detected.

Particularly, on such the magnetic tape, the close/open process as described above with reference to FIGS. 200(A), 200(B) and 201 is carried out for the file, the end (a part including two tape marks, TM-a and TM-b, and two EOFs, EOF1 and EOF2) of the file on the magnetic tape MT is moved back and forth relative to the head H in response to commands from the CPU 20. For this reason, the frequency of the start/stop operation of the magnetic tape is increased, thus throughput of the job by the CPU 20 is noticeably decreased.

In the file open process, the OS of the CPU

20 reads EOF1 at least once to recognize it in order to accurately confirm a position at which the second file is additionally written or read, as described above.

5 Some type of the MTU 30 has a low accuracy of positioning of the head relative to the magnetic tape MT, while some type of the MTU 30 has a high accuracy of positioning of the head relative to the magnetic tape MT. Such the type having a high accuracy is not
10 required to read/recognize EOF1 (or EOF2) in every occasion. In other words, the MTU 30 having a low accuracy (reliability) of positioning of the head is required to perform all the open process for a file as described above with reference to FIGS. 200(A),
15 200(B) and 201, but the MTU 30 having a high accuracy (reliability) of positioning of the head is not required to perform all the open process for a file.

 It is possible that the CPU 20 such controls as to switch a command according to a type of the MTU
20 30 in order to issue a different command depending on the type of the MTU 30. In such case, it would be necessary to modify the OS and the like actuated by the CPU 20, in addition, a load of the processing on the CPU 20 would increase, which are undesirable.

25 In consequence, it is desirable to increase a speed of the file open/close process by not only the MTU 30 having a high accuracy of positioning of the

head by but also the MTU 30 having a low accuracy of positioning of the head without modifying a command (OS and the like) issued from the side of the CPU 20 at the time of the file close/open process in order
5 that the CPU 20 may cope with even the MTU 30 having a low accuracy of positioning of the head.

SUMMARY OF THE INVENTION

In the light of the above disadvantages, an
10 object of the present invention is to provide a method for controlling a magnetic tape unit in which a tape operation relating to EOF identification in an open process for a file is emulated, thereby simplifying not only the tape operation in the open process but
15 also an operation in a close process for the file. As a result, open-process performance, close-process performance, further a process performance of a system accessing to a magnetic tape unit can be improved.

To accomplish the above object, the present
20 invention provides a method for controlling a magnetic tape unit in response to a command from a command issuing apparatus comprising the steps of, in an open process for a file recorded on a magnetic tape, fixing a position of a head (hereinafter referred to as a real
25 head position) relative to the magnetic tape at a predetermined position in the magnetic tape unit, and when receiving a command from the command issuing

apparatus, executing emulation in which a tape operation according to the command is virtually carried out in the magnetic tape unit without making the magnetic tape unit carry out a real tape operation.

5 In a close process for the file, an end-of-file label read by the magnetic tape unit in response to a command from the command issuing apparatus is saved in a save area, and in an open process for the file, the end-of-file label is transferred to the command
10 issuing apparatus from the save area in response to a command directing to read the end-of-file label without making the magnetic tape unit carry out a real read operation.

 In a close process for the file, an end-of-file
15 label written by the magnetic tape unit in response to a command from the command issuing apparatus is saved in a save area, and in an open process for the file, the end-of-file label is transferred to the command issuing apparatus from the save area in
20 response to a command directing to read the end-of-file label without making the magnetic tape unit carry out a real read operation.

 In a close process for the file, the magnetic tape unit is made to carry out a real read operation
25 to really read an end-of-file label, which is skipped in the magnetic tape unit in response to a command from the command issuing apparatus, the read end-of-file

label is saved in a save area, and in an open process for the file, the end-of-file label is transferred to the command issuing apparatus from the save area in response to a command directing to read the end-
5 of-file label without making the magnetic tape unit carry out a real read operation.

When, in an open process for the file, a command directing to read the end-of-file label is received in a state in which the end-of-file label is
10 not saved in the save area, the magnetic tape unit is made to carry out a real read operation to really read the end-of-file label, and the read end-of-file label is transferred to the command issuing apparatus.

A data buffer for temporarily storing write
15 data to the magnetic tape and read data from the magnetic tape therein is interposed between the command issuing apparatus and the magnetic tape unit to asynchronously carry out a read/write process between the command issuing apparatus and the data buffer and
20 a read/write process between the data buffer and the magnetic tape unit.

A tape operation of the magnetic tape unit is such controlled that, on the magnetic tape, the first tape mark is written after the last data block of the
25 file, the first end-of-file label (hereinafter referred to as EOF1) and the second end-of-file label (hereinafter referred to as EOF2) are written after

the first tape mark, the second tape mark is written after the second end-of-file label, and the third tape mark is further written after the second tape mark when the file is the last on the magnetic tape, whereas the next file is written over the third tape mark to be written when the next file is additionally written after the file, and the emulation is executed between immediately before the first tape mark and immediately after the third tape mark while fixing the head at the predetermined position which is immediately after the second tape mark. While the emulation is executed, a virtual position of the head (hereinafter referred to as a virtual head position) relative to the magnetic tape in the magnetic tape unit is managed as a relative position of the head relative to the predetermined position.

When a command requiring the real head position in the magnetic tape unit is received while the emulation is executed, a sum of the predetermined position and the relative position is generated, and the sum is reported as the real head position to the command issuing apparatus. When the magnetic tape unit is shifted to a real operation while the emulation is executed, the real head position in the magnetic tape unit is generated as a sum of the predetermined position and the relative position, and the head in the magnetic tape unit is re-positioned at the real

head position.

According to this invention, emulation is executed under conditions [1] to [8] below.

- [1] In a state in which both of EOF1 and EOF2 are saved
5 in the save areas, and in a state in which reading/writing up to the second tape mark is completed and the real head position is the predetermined position in the magnetic tape unit,
(1-1) when any one of a read back command (hereinafter
10 abbreviated as RB command), a back space block command (hereinafter abbreviated as BSP command) and a back space file command (hereinafter abbreviated as BSPF command) is received, with the virtual head position being immediately after the second tape mark;
15 (1-2) when any one of a read command (hereinafter abbreviated as RD command), an RB command, a BSP command, a BSPF command, a forward space block command (hereinafter abbreviated as SP command), a forward space file command (hereinafter abbreviated as FSPF
20 command) and a write tape mark command (hereinafter abbreviated as WTM command) is received, with the virtual head position being immediately after EOF2;
(1-3) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an
25 FSPF command is received, with the virtual head position being immediately after EOF1;
(1-4) when any one of an RD command, an RB command,

a BSP block command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being immediately after the first tape mark;
or

- (1-5) when any one of an RD command, an SP command and an FSPF command is received, with the virtual head position being immediately after the last data block.
- [2] In a state in which both of EOF1 and EOF2 are saved in the save areas, and in a state in which reading/writing up to the third tape mark is completed and the real head position is the predetermined position in the magnetic tape unit,
- (2-1) when any one of an RB command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the third tape mark;
- (2-2) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command, an FSPF command and a WTM command is received, with the virtual head position being immediately after the second tape mark;
- (2-3) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being immediately after EOF2;
- (2-4) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head

position being immediately after EOF1;

(2-5) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head

5 position being immediately after the first tape mark;
or

(2-6) when any one of an RD command, an SP command and an FSPF command is received, with the virtual head position being immediately after the last data block.

10 [3] In a state in which only EOF1 is saved in the save area, and in a state in which reading/writing up to the second tape mark is completed and the real head position is the predetermined position in the magnetic tape unit,

15 (3-1) when any one of an RB command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the second tape mark;

(3-2) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command, an FSPF
20 command and a WTM command is received, with the virtual head position being immediately after EOF2;

(3-3) when any one of an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being
25 immediately after EOF1;

(3-4) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an

FSPF command is received, with the virtual head position being immediately after the first tape mark;
or

(3-5) when any one of an RD command, a SP command and
5 an FSPF command is received, with the virtual head
position being immediately after the last data block.

[4] In a state in which only EOF1 is saved in the save area, and in a state in which reading/writing up to the third tape mark is completed and the real head position is the predetermined position in the magnetic tape unit,

(4-1) when any one of an RD command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the third tape mark;

15 (4-2) when any one of an RD command, an RB command,
a BSP command, a BSPF command, an SP command, an FSPF
command and a WTM command is received, with the virtual
head position being immediately after the second tape
mark;

20 (4-3) when any one of an RD command, an RB command,
a BSP command, a BSPF command, an SP command and an
FSPF command is received, with the virtual head
position being immediately after EOF2;

(4-4) when any one of an RB command, a BSP command,
25 a BSPF command, an SP command and an FSPF command is
received, with the virtual head position being
immediately after EOF1;

(4-5) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being immediately after the first tape mark;

5 or

(4-6) when any one of an RD command, an SP command and an FSPF command is received, with the virtual head position being immediately after the last data block.

[5] In a state in which only EOF2 is saved in the save area, and in a state in which reading/writing up to the second tape mark is completed and the real head position is the predetermined position in the magnetic tape unit,

(5-1) when any one of an RB command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the second tape mark;

(5-2) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command, an FSPF command and a WTM command is received, with the virtual head position being immediately after EOF2;

(5-3) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being immediately after EOF1;

(5-4) when any one of an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being

immediately after the first tape mark; or

(5-5) when any one of an RD command, an SP command and an FSPF command is received, with the virtual head position being immediately after the last data block.

5 [6] In a state in which only EOF2 is saved in the save area, and in a state in which reading/writing up to the third tape mark is completed and the real head position is the predetermined position in the magnetic tape unit,

10 (6-1) when any one of an RB command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the third tape mark;

(6-2) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command, an FSPF
15 command and a WTM command is received, with the virtual head position being immediately after the second tape mark;

(6-3) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an
20 FSPF command is received, with the virtual head position being immediately after EOF2;

(6-4) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an
25 FSPF command is received, with the virtual head position being immediately after EOF1;

(6-5) when any one of an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is

received, with the virtual head position being immediately after the first tape mark; or

(6-6) when any one of an RD command, an SP command and an FSPF command is received, with the virtual head
5 position being immediately after the last data block.

[7] In a state in which neither EOF1 nor EOF2 is saved in the save area, and in a state in which reading/writing up to the second tape mark is completed and the real head position is the

10 predetermined position in the magnetic tape unit,
(7-1) when any one of an RB command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the second tape mark;

(7-2) when any one of an RD command, an RB command,
15 a BSP command, an SP command, an FSPF command and a WTM command is received, with the virtual head position being immediately after EOF2;

(7-3) when any one of an RB command, a BSP command, a BSPF command, a BSPF command, an SP command and an
20 FSPF command is received, with the virtual head position being immediately after EOF1;

(7-4) when any one of an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being
25 immediately after the first tape mark; or

(7-5) when any one of an RD command, an SP command and an FSPF command is received, with the virtual head

position being immediately after the last data block.

[8] In a state in which neither EOF1 nor EOF2 is saved in the save area, and in a state in which reading/writing up to the third tape mark is completed

5 and the real head position is the predetermined position in the magnetic tape unit,

(8-1) when any one of an RB command, a BSP command and a BSPF command is received, with the virtual head position being immediately after the third tape mark;

10 (8-2) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command, an FSPF command and a WTM command is received, with the virtual head position being immediately after the second tape mark;

15 (8-3) when any one of an RD command, an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is received, with the virtual head position being immediately after EOF2;

(8-4) when any one of an RB command, a BSP command, 20 a BSPF command, an SP command and an FSPF command is received, with the virtual head position being immediately after EOF1;

(8-5) when any one of an RB command, a BSP command, a BSPF command, an SP command and an FSPF command is 25 received, with the virtual head position being immediately after the first tape mark; or

(8-6) when any one of an RD command, an SP command and

an FSPF command is received, with the virtual head position being immediately after the last data block.

When, in a close process for the file, a command requiring to write the third tape mark is received after the second tape mark is written on the magnetic tape, completion of a writing of the third tape mark is reported to the command issuing apparatus without writing the third tape mark.

In the above case, when a command directing to position the head outside a region from immediately before the first tape mark to immediately after the third tape mark is received, the third tape mark is written, and the magnetic tape unit is then made to carry out a tape operation according to the command. When EOD (End Of Data) is detected after the second tape mark in the magnetic tape unit during a tape operation in response to a command from the command issuing apparatus, detection of the third tape mark is reported in lieu of the EOD to the command issuing apparatus.

The present invention further provides a method for controlling a magnetic tape unit in response to a command from a command issuing apparatus comprising the steps of, in a close process for a file recorded on a magnetic tape, controlling a tape operation of the magnetic tape unit such that, on the magnetic tape, the first tape mark is written after

the last data block of the file, at least one end-of-file label is written after the first tape mark, and the second tape mark is written after the end-of-file label, and reporting completion of a writing
5 of the third tape mark to the command issuing apparatus without writing the third tape mark even if a command requiring to write the third tape mark is received.

When a command in a motion system involving unloading and rewinding is received, the third tape
10 mark is written, and the magnetic tape unit is then made to carry out a tape operation according to the command in the motion system. When EOD (End Of Data) is detected after the second tape mark in the magnetic tape unit during a tape operation in response to a
15 command from the command issuing apparatus, detection of the third tape mark is reported in lieu of detection of the EOD to the command issuing apparatus.

In the case where a plurality of end-of-file labels are recorded as one physical block on the
20 magnetic tape by a packeting function, when a command directing to read one of the plurality of end-of-file labels is received in a close process for the file, the physical block including the end-of-file label to be read may be read out from the magnetic tape and
25 stored in the data buffer, and, in an open process for the file, an end-of-file label corresponding to a command directing to read the one of the plurality of

end-of-file labels may be read out from the data buffer in response to the command and transferred to the command issuing apparatus.

The method for controlling a magnetic tape unit according to this invention can provide the following effects and advantages:

(1) By emulating a tape operation relating to EOF identification in the open process for a file, it is possible to decrease a frequency of the mechanical tape operation in the magnetic tape unit, thus simplify the tape operation in the open process. As a result, a time required for the open process for a file is largely shortened, and open-process, close-process performance and process performance of a system accessing to the magnetic tape unit is largely improved.

(2) When head position accuracy of the magnetic tape unit is low, it is possible to carry out a command processing in response to a command from the command issuing apparatus as before if the emulation is not executed. Namely, it is possible to readily speed up the open process for a file in a magnetic tape unit having a high head positioning accuracy without modifying a command issued from the command issuing apparatus in the open process for the file, thereby coping with even a magnetic tape unit having a low head positioning accuracy.

(3) By emulating a tape operation relating to EOF identification in the open process for a file and emulating an operation of writing the third tape mark in the close process for the file, it is possible to
5 simplify the tape operation in not only the open process but also the close process. Consequently, a time required for not only the open process but also the close process is shortened, thus a time required to process a job is further shortened. This largely
10 improves file close/open process performance, further process performance of a system accessing to the magnetic tape unit.

(4) Even if a process is terminated while the third tape mark is not recorded on the magnetic tape due to
15 a failure such as power-off or the like after an operation of writing the third tape mark is emulated, EOD immediately after the second tape mark is assumed to be the third tape mark after the recovery of the failure, the command processing can be continuously
20 carried out as usual in the magnetic tape unit without making the magnetic tape unit carry out any special recovery process such as a writing of the third tape mark.

(5) By emulating an operation of writing the third
25 tape mark in the close process for a file, it is possible to simplify the tape operation in the close process for the file. This improves file close

process performance, further process performance of a system accessing to the magnetic tape unit.

(6) By using a packeting function of EDRC or the like, it is possible to emulate a larger number of tape operations, thus shorten a time required for the open process for a file. This leads to large improvements of the file open process performance, and further the processing performance of a system accessing to the magnetic tape unit via the interface converting apparatus.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a hardware structure of a magnetic tape controller to which a method for controlling a magnetic tape unit according to a first embodiment of this invention is applied;

FIG. 2(A) is a diagram showing structures of a command buffer and a data buffer, and a register for XBID according to the first embodiment, whereas FIG. 2(B) is a diagram showing save areas and control areas in a RAM according to the first embodiment;

FIGS. 3(A) through 3(G) are diagrams for illustrating emulation status (ES) according to the first embodiment;

FIG. 4 is a flowchart for illustrating a command processing (read process) by a format controller of a magnetic tape controller according to

the first embodiment;

FIG. 5 is a diagram in which a part of the flowchart shown in FIG. 4 is tabulated in order to illustrate the command processing (read process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 6 is a flowchart for illustrating a command processing (read backward process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 7 is a diagram in which a part of the flowchart shown in FIG. 6 is tabulated in order to illustrate the command processing (read backward process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 8 is a flowchart for illustrating a command processing (write process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 9 is a diagram in which a part of the flowchart shown in FIG. 8 is tabulated in order to illustrate the command processing (write process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 10 is a flowchart for illustrating a command processing (back space block process) by the format controller in the magnetic tape controller

according to the first embodiment;

FIG. 11 is a diagram in which a part of the flowchart shown in FIG. 10 is tabulated in order to illustrate the command processing (back space block process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 12 is a flowchart for illustrating a command processing (back space file process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 13 is a diagram in which a part of the flowchart shown in FIG. 12 is tabulated in order to illustrate the command processing (back space file process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 14 is a flowchart for illustrating a command processing (forward space block process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 15 is a diagram in which a part of the flowchart shown in FIG. 14 is tabulated in order to illustrate the command processing (forward space block process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 16 is a flowchart for illustrating a command processing (forward space file process) by the

format controller in the magnetic tape controller according to the first embodiment;

FIG. 17 is a diagram in which a part of the flowchart shown in FIG. 16 is tabulated in order to
5 illustrate the command processing (forward space file process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 18 is a flowchart for illustrating a command processing (write tape mark process) by the
10 format controller in the magnetic tape controller according to the first embodiment;

FIG. 19 is a diagram in which a part of the flowchart shown in FIG. 18 is tabulated in order to
15 illustrate the command processing (write tape mark process) by the format controller in the magnetic tape controller according to the first embodiment;

FIG. 20 is a diagram for illustrating emulation executing conditions according to the first embodiment;

20 FIG. 21 is a diagram for illustrating emulation executing conditions according to the first embodiment;

FIGS. 22(A) and 22(B) are diagrams showing a state of data writing on the magnetic tape, and for
25 illustrating an example of commands issued from an upper apparatus when a multi-file is additionally written, and tape operations/emulation operations in

response to the commands in the magnetic tape unit according to the first embodiment;

FIGS. 23(A) and 23(B) are diagrams for illustrating an operation [command processing (1) in FIG. 22(A)] according to the first embodiment, FIG. 23(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 23(B) showing a state of data saving/storing;

FIGS. 24(A) and 24(B) are diagrams for illustrating an operation [command processing (2) in FIG. 22(A)] according to the first embodiment, FIG. 24(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 24(B) showing a state of data saving/storing;

FIGS. 25(A) and 25(B) are diagrams for illustrating an operation [command processing (3) in FIG. 22(A)] according to the first embodiment, FIG. 25(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 25(B) showing a state of data saving/storing;

FIGS. 26(A) and 26(B) are diagrams for illustrating an operation [command processing (4) in FIG. 22(A)] according to the first embodiment, FIG. 26(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 26(B) showing a state of data saving/storing;

FIGS. 27(A) and 27(B) are diagrams for

illustrating an operation [command processing (5) in
FIG. 22(A)] according to the first embodiment, FIG.
27(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
5 FIG. 27(B) showing a state of data saving/storing;

FIGS. 28(A) and 28(B) are diagrams for
illustrating an operation [command processing (6) in
FIG. 22(A)] according to the first embodiment, FIG.
28(A) showing a state of data writing on the magnetic
10 tape, a real head position and a virtual head position,
FIG. 28(B) showing a state of data saving/storing;

FIGS. 29(A) and 29(B) are diagrams for
illustrating an operation [command processing (7) in
FIG. 22(A)] according to the first embodiment, FIG.
15 29(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 29(B) showing a state of data saving/storing;

FIGS. 30(A) and 30(B) are diagrams for
illustrating an operation [command processing (8) in
20 FIG. 22(A)] according to the first embodiment, FIG.
30(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 30(B) showing a state of data saving/storing;

FIGS. 31(A) and 31(B) are diagrams for
25 illustrating an operation [command processing (9) in
FIG. 22(A)] according to the first embodiment, FIG.
31(A) showing a state of data writing on the magnetic

tape, a real head position and a virtual head position,
FIG. 31(B) showing a state of data saving/storing;

FIGS. 32(A) and 32(B) are diagrams for
illustrating an operation [command processing (10) in
5 FIG. 22(A)] according to the first embodiment, FIG.
32(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 32(B) showing a state of data saving/storing;

FIGS. 33(A) and 33(B) are diagrams for
10 illustrating an operation [command processing (11) in
FIG. 22(A)] according to the first embodiment, FIG.
33(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 33(B) showing a state of data saving/storing;

FIGS. 34(A) and 34(B) are diagrams for
15 illustrating an operation [command processing (12) in
FIG. 22(A)] according to the first embodiment, FIG.
34(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
20 FIG. 34(B) showing a state of data saving/storing;

FIGS. 35(A) and 35(B) are diagrams for
illustrating an operation [command processing (13) in
FIG. 22(A)] according to the first embodiment, FIG.
35(A) showing a state of data writing on the magnetic
25 tape, a real head position and a virtual head position,
FIG. 35(B) showing a state of data saving/storing;

FIGS. 36(A) and 36(B) are diagrams for

illustrating an operation [command processing (14) in
FIG. 22(A)] according to the first embodiment, FIG.
36(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
5 FIG. 36(B) showing a state of data saving/storing;

FIGS. 37(A) and 37(B) are diagrams for
illustrating an operation [command processing (15) in
FIG. 22(A)] according to the first embodiment, FIG.
37(A) showing a state of data writing on the magnetic
10 tape, a real head position and a virtual head position,
FIG. 37(B) showing a state of data saving/storing;

FIGS. 38(A) and 38(B) are diagrams for
illustrating an operation [command processing (16) in
FIG. 22(A)] according to the first embodiment, FIG.
15 38(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 38(B) showing a state of data saving/storing;

FIGS. 39(A) and 39(B) are diagrams for
illustrating an operation [command processing (17) in
20 FIG. 22(B)] according to the first embodiment, FIG.
39(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 39(B) showing a state of data saving/storing;

FIGS. 40(A) and 40(B) are diagrams for
25 illustrating an operation [command processing (18) in
FIG. 22(B)] according to the first embodiment, FIG.
40(A) showing a state of data writing on the magnetic

tape, a real head position and a virtual head position,
FIG. 40(B) showing a state of data saving/storing;

FIGS. 41(A) and 41(B) are diagrams for
illustrating an operation [command processing (19) in
5 FIG. 22(B)] according to the first embodiment, FIG.
41(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 41(B) showing a state of data saving/storing;

FIGS. 42(A) and 42(B) are diagrams for
10 illustrating an operation [command processing (20) in
FIG. 22(B)] according to the first embodiment, FIG.
42(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 42(B) showing a state of data saving/storing;

FIGS. 43(A) and 43(B) are diagrams for
15 illustrating an operation [command processing (21) in
FIG. 22(B)] according to the first embodiment, FIG.
43(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
20 FIG. 43(B) showing a state of data saving/storing;

FIGS. 44(A) and 44(B) are diagrams for
illustrating an operation [command processing (22) in
FIG. 22(B)] according to the first embodiment, FIG.
44(A) showing a state of data writing on the magnetic
25 tape, a real head position and a virtual head position,
FIG. 44(B) showing a state of data saving/storing;

FIGS. 45(A) and 45(B) are diagrams for

illustrating an operation [command processing (23) in
FIG. 22(B)] according to the first embodiment, FIG.
45(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
5 FIG. 45(B) showing a state of data saving/storing;

FIGS. 46(A) and 46(B) are diagrams for
illustrating an operation [command processing (24) in
FIG. 22(B)] according to the first embodiment, FIG.
46(A) showing a state of data writing on the magnetic
10 tape, a real head position and a virtual head position,
FIG. 46(B) showing a state of data saving/storing;

FIG. 47 is a diagram showing a state of data
writing on the magnetic tape, and for illustrating an
example of commands issued from the upper apparatus
15 when data is read out from two consecutive files and
tape operations/emulation operations in response to
the commands in the magnetic tape unit according to
the first embodiment;

FIGS. 48(A) and 48(B) are diagrams for
20 illustrating an operation [command processing (1) in
FIG. 47] according to the first embodiment, FIG. 48(A)
showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
48(B) showing a state of data saving/storing;

FIGS. 49(A) and 49(B) are diagrams for
25 illustrating an operation [command processing (2) in
FIG. 47] according to the first embodiment, FIG. 49(A)

showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
49(B) showing a state of data saving/storing;

FIGS. 50(A) and 50(B) are diagrams for
5 illustrating an operation [command processing (3) in
FIG. 47] according to the first embodiment, FIG. 50(A)
showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
50(B) showing a state of data saving/storing;

10 FIGS. 51(A) and 51(B) are diagrams for
illustrating an operation [command processing (4) in
FIG. 47] according to the first embodiment, FIG. 51(A)
showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
15 51(B) showing a state of data saving/storing;

FIGS. 52(A) and 52(B) are diagrams for
illustrating an operation [command processing (5) in
FIG. 47] according to the first embodiment, FIG. 52(A)
showing a state of data writing on the magnetic tape,
20 a real head position and a virtual head position, FIG.
52(B) showing a state of data saving/storing;

FIGS. 53(A) and 53(B) are diagrams for
illustrating an operation [command processing (6) in
FIG. 47] according to the first embodiment, FIG. 53(A)
25 showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
53(B) showing a state of data saving/storing;

FIGS. 54(A) and 54(B) are diagrams for illustrating an operation [command processing (7) in FIG. 47] according to the first embodiment, FIG. 54(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 54(B) showing a state of data saving/storing;

FIGS. 55(A) and 55(B) are diagrams for illustrating an operation [command processing (8) in FIG. 47] according to the first embodiment, FIG. 55(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 55(B) showing a state of data saving/storing;

FIGS. 56(A) and 56(B) are diagrams for illustrating an operation [command processing (9) in FIG. 47] according to the first embodiment, FIG. 56(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 56(B) showing a state of data saving/storing;

FIGS. 57(A) and 57(B) are diagrams for illustrating an operation [command processing (10) in FIG. 47] according to the first embodiment, FIG. 57(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 57(B) showing a state of data saving/storing;

FIGS. 58(A) and 58(B) are diagrams for illustrating an operation [command processing (11) in FIG. 47] according to the first embodiment, FIG. 58(A)

showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
58(B) showing a state of data saving/storing;

FIGS. 59(A) and 59(B) are diagrams for
5 illustrating an operation [command processing (12) in
FIG. 47] according to the first embodiment, FIG. 59(A)
showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
59(B) showing a state of data saving/storing;

10 FIGS. 60(A) and 60(B) are diagrams for
illustrating an operation [command processing (13) in
FIG. 47] according to the first embodiment, FIG. 60(A)
showing a state of data writing on the magnetic tape,
a real head position and a virtual head position, FIG.
15 60(B) showing a state of data saving/storing;

FIGS. 61(A) and 61(B) are diagrams showing a
state of data writing on the magnetic tape, and for
illustrating another example of commands issued from
the upper apparatus when a multi-file is additionally
20 written and tape operations/emulation operations in
response to the commands in the magnetic tape unit
according to the first embodiment;

FIG. 62 is a diagram showing a state of data
writing on the magnetic tape, and for illustrating
25 still another example of commands issued from the
upper apparatus when data is read out from two
consecutive files and tape operations/emulation

operations in response to the commands in the magnetic tape unit according to the first embodiment;

FIG. 63 is a diagram in which, when a multi-file is additionally written as shown in FIGS. 22(A) and 22(B), a time required for a command processing carried out applying the method according to the first embodiment and executing emulation is compared with a time required for the command processing carried out applying a known method without executing emulation;

FIG. 64 is a diagram in which, when data is read out from two consecutive files as shown in FIG. 47, a time required for a command processing carried out applying the method according to the first embodiment and executing emulation is compared with a time required for the command processing carried out applying the known method without executing emulation;

FIG. 65 is a diagram in which, when a multi-file is additionally written as shown in FIGS. 61(A) and 61(B), a time required for a command processing carried out applying the method according to the first embodiment and executing emulation is compared with a time required for the command processing carried out applying the known method without executing emulation;

FIG. 66 is a diagram in which, when data is

read out from two consecutive files, a time required for a command processing carried out applying the method according to the first embodiment and executing emulation is compared with a time required for the
5 command processing carried out applying the known method without executing emulation;

FIG. 67 is a block diagram showing a hardware structure of a system to which a method for controlling a magnetic tape unit according to a second embodiment
10 of this invention is applied;

FIG. 68 is a block diagram showing a hardware structure of an interface converting apparatus to which the method for controlling a magnetic tape unit according to the second embodiment of this invention
15 is applied;

FIGS. 69(A) through 69(D) are diagrams for illustrating four identification patterns for EOFs (Pattern 1 to Pattern 4) according to the second embodiment;

20 FIGS. 70(A) through 70(G) are diagrams for illustrating emulation status (ES) in Pattern 1 according to the second embodiment;

FIGS. 71(A) through 71(G) are diagrams for illustrating emulation status (ES) in Pattern 2
25 according to the second embodiment;

FIGS. 72(A) through 72(G) are diagrams for illustrating emulation status (ES) in Pattern 3

according to the second embodiment;

FIGS. 73(A) through 73(G) are diagrams for illustrating emulation status (ES) in Pattern 4 according to the second embodiment;

5 FIGS. 74(A) and 74(B) are diagrams for illustrating emulation executing conditions in Pattern 1 according to the second embodiment;

FIGS. 75(A) and 75(B) are diagrams for illustrating emulation executing conditions in
10 Pattern 1 according to the second embodiment;

FIGS. 76(A) and 76(B) are diagrams for illustrating emulation executing conditions in Pattern 2 according to the second embodiment;

FIGS. 77(A) and 77(B) are diagrams for
15 illustrating emulation executing conditions in Pattern 2 according to the second embodiment;

FIGS. 78(A) and 78(B) are diagrams for illustrating emulation executing conditions in Pattern 3 according to the second embodiment;

20 FIGS. 79(A) and 79(B) are diagrams for illustrating emulation executing conditions in Pattern 3 according to the second embodiment;

FIGS. 80(A) and 80(B) are diagrams for illustrating emulation executing conditions in
25 Pattern 4 according to the second embodiment;

FIGS. 81(A) and 81(B) are diagrams for illustrating emulation executing conditions in

Pattern 4 according to the second embodiment;

FIG. 82 is a diagram showing structures of save areas and control areas in a RAM according to the second embodiment;

5 FIG. 83 is a flowchart for illustrating command processing by a control unit in the interface converting apparatus according to the second embodiment;

10 FIG. 84 is a diagram in which a part of a read process in Pattern 1 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

15 FIG. 85 is a diagram in which a part of a read process in Pattern 2 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

20 FIG. 86 is a diagram in which a part of a read process in Pattern 3 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

25 FIG. 87 is a diagram in which a part of a read process in Pattern 4 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate

the same;

FIG. 88 is a diagram in which a part of a read backward process in Pattern 1 by the control unit in the interface converting apparatus according to the
5 second embodiment is tabulated in order to illustrate the same;

FIG. 89 is a diagram in which a part of a read backward process in Pattern 2 by the control unit in the interface converting apparatus according to the
10 second embodiment is tabulated in order to illustrate the same;

FIG. 90 is a diagram in which a part of a read backward process in Pattern 3 by the control unit in the interface converting apparatus according to the
15 second embodiment is tabulated in order to illustrate the same;

FIG. 91 is a diagram in which a part of a read backward process in Pattern 4 by the control unit in the interface converting apparatus according to the
20 second embodiment is tabulated in order to illustrate the same;

FIG. 92 is a diagram in which a part of a write process in Pattern 1 by the control unit in the interface converting apparatus according to the
25 second embodiment is tabulated in order to illustrate the same;

FIG. 93 is a diagram in which a part of a write

process in Pattern 2 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

5 FIG. 94 is a diagram in which a part of a write process in Pattern 3 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

10 FIG. 95 is a diagram in which a part of a write process in Pattern 4 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

15 FIG. 96 is a diagram in which a part of a back space block process in Pattern 1 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

20 FIG. 97 is a diagram in which a part of a back space block process in Pattern 2 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

25 FIG. 98 is a diagram in which a part of a back space block process in Pattern 3 by the control unit in the interface converting apparatus according to the

second embodiment is tabulated in order to illustrate the same;

FIG. 99 is a diagram in which a part of a back space block process in Pattern 4 by the control unit
5 in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 100 is a diagram in which a part of a back space file process in Pattern 1 by the control unit
10 in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 101 is a diagram in which a part of a back space file process in Pattern 2 by the control unit
15 in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 102 is a diagram in which a part of a back space file process in Pattern 3 by the control unit
20 in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 103 is a diagram in which a part of a back space file process in Pattern 4 by the control unit
25 in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 104 is a diagram in which a part of a forward space block process in Pattern 1 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to
5 illustrate the same;

FIG. 105 is a diagram in which a part of a forward space block process in Pattern 2 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to
10 illustrate the same;

FIG. 106 is a diagram in which a part of a forward space block process in Pattern 3 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to
15 illustrate the same;

FIG. 107 is a diagram in which a part of a forward space block process in Pattern 4 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to
20 illustrate the same;

FIG. 108 is a diagram in which a part of a forward space file process in Pattern 1 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to
25 illustrate the same;

FIG. 109 is a diagram in which a part of a forward space file process in Pattern 2 by the control

unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 110 is a diagram in which a part of a forward space file process in Pattern 3 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 111 is a diagram in which a part of a forward space file process in Pattern 4 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 112 is a diagram in which a part of a write tape mark process in Pattern 1 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 113 is a diagram in which a part of a write tape mark process in Pattern 2 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIG. 114 is a diagram in which a part of a write tape mark process in Pattern 3 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate

the same;

FIG. 115 is a diagram in which a part of a write tape mark process in Pattern 4 by the control unit in the interface converting apparatus according to the second embodiment is tabulated in order to illustrate the same;

FIGS. 116(A) and 116(B) are diagrams showing a state of data writing on the magnetic tape, and for illustrating an example of commands issued from the upper apparatus when a multi-file is additionally written and tape operations/emulation operations in response to the commands in the magnetic tape unit according to the second embodiment;

FIGS. 117(A) and 117(B) are diagrams for illustrating an operation [command processing (1) in FIG. 116(A)] according to the second embodiment, FIG. 117(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 117(B) showing a state of data saving/storing;

FIGS. 118(A) and 118(B) are diagrams for illustrating an operation [command processing (2) in FIG. 116(A)] according to the second embodiment, FIG. 118(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 118(B) showing a state of data saving/storing;

FIGS. 119(A) and 119(B) are diagrams for illustrating an operation [command processing (3) in

FIG. 116(A)] according to the second embodiment, FIG. 119(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 119(B) showing a state of data saving/storing;

5 FIGS. 120(A) and 120(B) are diagrams for illustrating an operation [command processing (4) in FIG. 116(A)] according to the second embodiment, FIG. 120(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, 10 FIG. 120(B) showing a state of data saving/storing;

 FIGS. 121(A) and 121(B) are diagrams for illustrating an operation [command processing (5) in FIG. 116(A)] according to the second embodiment, FIG. 121(A) showing a state of data writing on the magnetic 15 tape, a real head position and a virtual head position, FIG. 121(B) showing a state of data saving/storing;

 FIGS. 122(A) and 122(B) are diagrams for illustrating an operation [command processing (6) in FIG. 116(A)] according to the second embodiment, FIG. 20 122(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 122(B) showing a state of data saving/storing;

 FIGS. 123(A) and 123(B) are diagrams for illustrating an operation [command processing (7) in 25 FIG. 116(A)] according to the second embodiment, FIG. 123(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position,

FIG. 123(B) showing a state of data saving/storing;

FIGS. 124(A) and 124(B) are diagrams for illustrating an operation [command processing (8) in FIG. 116(A)] according to the second embodiment, FIG.

5 124(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 124(B) showing a state of data saving/storing;

FIGS. 125(A) and 125(B) are diagrams for illustrating an operation [command processing (9) in
10 FIG. 116(A)] according to the second embodiment, FIG. 125(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 125(B) showing a state of data saving/storing;

FIGS. 126(A) and 126(B) are diagrams for
15 illustrating an operation [command processing (10) in FIG. 116(A)] according to the second embodiment, FIG. 126(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 126(B) showing a state of data saving/storing;

20 FIGS. 127(A) and 127(B) are diagrams for illustrating an operation [command processing (11) in FIG. 116(A)] according to the second embodiment, FIG. 127(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position,
25 FIG. 127(B) showing a state of data saving/storing;

FIGS. 128(A) and 128(B) are diagrams for illustrating an operation [command processing (12) in

FIG. 116(A)] according to the second embodiment, FIG. 128(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 128(B) showing a state of data saving/storing;

5 FIGS. 129(A) and 129(B) are diagrams for illustrating an operation [command processing (13) in FIG. 116(A)] according to the second embodiment, FIG. 129(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, 10 FIG. 129(B) showing a state of data saving/storing;

 FIGS. 130(A) and 130(B) are diagrams for illustrating an operation [command processing (14) in FIG. 116(A)] according to the second embodiment, FIG. 130(A) showing a state of data writing on the magnetic 15 tape, a real head position and a virtual head position, FIG. 130(B) showing a state of data saving/storing;

 FIGS. 131(A) and 131(B) are diagrams for illustrating an operation [command processing (15) in FIG. 116(A)] according to the second embodiment, FIG. 20 131(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 131(B) showing a state of data saving/storing;

 FIGS. 132(A) and 132(B) are diagrams for illustrating an operation [command processing (16) in 25 FIG. 116(A)] according to the second embodiment, FIG. 132(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position,

FIG. 132(B) showing a state of data saving/storing;

FIGS. 133(A) and 133(B) are diagrams for illustrating an operation [command processing (17) in FIG. 116(B)] according to the second embodiment, FIG.

5 133(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 133(B) showing a state of data saving/storing;

FIGS. 134(A) and 134(B) are diagrams for illustrating an operation [command processing (18) in FIG. 116(B)] according to the second embodiment, FIG.

10 134(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 134(B) showing a state of data saving/storing;

FIGS. 135(A) and 135(B) are diagrams for illustrating an operation [command processing (19) in FIG. 116(B)] according to the second embodiment, FIG.

15 135(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 135(B) showing a state of data saving/storing;

20 FIGS. 136(A) and 136(B) are diagrams for illustrating an operation [command processing (20) in FIG. 116(B)] according to the second embodiment, FIG.

136(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, 25 FIG. 136(B) showing a state of data saving/storing;

FIGS. 137(A) and 137(B) are diagrams for illustrating an operation [command processing (21) in

FIG. 116(B)] according to the second embodiment, FIG. 137(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 137(B) showing a state of data saving/storing;

5 FIGS. 138(A) and 138(B) are diagrams for illustrating an operation [command processing (22) in FIG. 116(B)] according to the second embodiment, FIG. 138(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, 10 FIG. 138(B) showing a state of data saving/storing;

 FIGS. 139(A) and 139(B) are diagrams for illustrating an operation [command processing (23) in FIG. 116(B)] according to the second embodiment, FIG. 139(A) showing a state of data writing on the magnetic 15 tape, a real head position and a virtual head position, FIG. 139(B) showing a state of data saving/storing;

 FIGS. 140(A) and 140(B) are diagrams for illustrating an operation [command processing (24) in FIG. 116(B)] according to the second embodiment, FIG. 20 140(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 140(B) showing a state of data saving/storing;

 FIG. 141 is a diagram showing a state of data writing on the magnetic tape, and for illustrating an 25 example of commands issued from the upper apparatus when data is read out from two consecutive files and tape operations/emulation operations in response to

the commands in the magnetic tape unit according to the second embodiment;

FIGS. 142(A) and 142(B) are diagrams for illustrating an operation [command processing (1) in FIG. 141] according to the second embodiment, FIG. 142(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 142(B) showing a state of data saving/storing;

FIGS. 143(A) and 143(B) are diagrams for illustrating an operation [command processing (2) in FIG. 141] according to the second embodiment, FIG. 143(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 143(B) showing a state of data saving/storing;

FIGS. 144(A) and 144(B) are diagrams for illustrating an operation [command processing (3) in FIG. 141] according to the second embodiment, FIG. 144(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 144(B) showing a state of data saving/storing;

FIGS. 145(A) and 145(B) are diagrams for illustrating an operation [command processing (4) in FIG. 141] according to the second embodiment, FIG. 145(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 145(B) showing a state of data saving/storing;

FIGS. 146(A) and 146(B) are diagrams for

illustrating an operation [command processing (5) in
FIG. 141] according to the second embodiment, FIG.
146(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
5 FIG. 146(B) showing a state of data saving/storing;

FIGS. 147(A) and 147(B) are diagrams for
illustrating an operation [command processing (6) in
FIG. 141] according to the second embodiment, FIG.
147(A) showing a state of data writing on the magnetic
10 tape, a real head position and a virtual head position,
FIG. 147(B) showing a state of data saving/storing;

FIGS. 148(A) and 148(B) are diagrams for
illustrating an operation [command processing (7) in
FIG. 141] according to the second embodiment, FIG.
15 148(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 148(B) showing a state of data saving/storing;

FIGS. 149(A) and 149(B) are diagrams for
illustrating an operation [command processing (8) in
20 FIG. 141] according to the second embodiment, FIG.
149(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 149(B) showing a state of data saving/storing;

FIGS. 150(A) and 150(B) are diagrams for
25 illustrating an operation [command processing (9) in
FIG. 141] according to the second embodiment, FIG.
150(A) showing a state of data writing on the magnetic

tape, a real head position and a virtual head position,
FIG. 150(B) showing a state of data saving/storing;

FIGS. 151(A) and 151(B) are diagrams for
illustrating an operation [command processing (10) in
5 FIG. 141] according to the second embodiment, FIG.
151(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 151(B) showing a state of data saving/storing;

FIGS. 152(A) and 152(B) are diagrams for
10 illustrating an operation [command processing (11) in
FIG. 141] according to the second embodiment, FIG.
152(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
FIG. 152(B) showing a state of data saving/storing;

FIGS. 153(A) and 153(B) are diagrams for
15 illustrating an operation [command processing (12) in
FIG. 141] according to the second embodiment, FIG.
153(A) showing a state of data writing on the magnetic
tape, a real head position and a virtual head position,
20 FIG. 153(B) showing a state of data saving/storing;

FIGS. 154(A) and 154(B) are diagrams for
illustrating an operation [command processing (13) in
FIG. 141] according to the second embodiment, FIG.
154(A) showing a state of data writing on the magnetic
25 tape, a real head position and a virtual head position,
FIG. 154(B) showing a state of data saving/storing;

FIGS. 155(A) and 155(B) are diagrams showing

a state of data writing on the magnetic tape, and for illustrating another example of commands issued from the upper apparatus when a multi-file is additionally written, and tape operations/emulation operations in
5 response to the commands in the magnetic tape unit according to the second embodiment;

FIG. 156 is a diagram showing a state of data writing on the magnetic tape, and for illustrating another example of commands issued from the upper
10 apparatus when data is read out from two consecutive files, and tape operations/emulation operations in the magnetic tape in response to the commands in the magnetic tape unit according to the second embodiment;

FIGS. 157(A) and 157(B) are diagrams for
15 illustrating operations [command processing (1) in FIG. 156] according to the second embodiment, FIG. 157(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 157(B) showing a state of data saving/storing;

20 FIGS. 158(A) and 158(B) are diagrams for illustrating operations [command processing (2) in FIG. 156] according to the second embodiment, FIG. 158(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position,
25 FIG. 158(B) showing a state of data saving/storing;

FIGS. 159(A) and 159(B) are diagrams for illustrating operations [command processing (3) in

FIG. 156] according to the second embodiment, FIG. 158(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 158(B) showing a state of data saving/storing;

5 FIGS. 160(A) and 160(B) are diagrams for illustrating operations [command processing (4) in FIG. 156] according to the second embodiment, FIG. 160(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, 10 FIG. 160(B) showing a state of data saving/storing;

 FIGS. 161(A) and 161(B) are diagrams for illustrating operations [command processing (5) in FIG. 156] according to the second embodiment, FIG. 161(A) showing a state of data writing on the magnetic 15 head, a real head position and a virtual head position, FIG. 161(B) showing a state of data saving/storing;

 FIGS. 162(A) and 162(B) are diagrams for illustrating operations [command processing (6) in FIG. 156] according to the second embodiment, FIG. 20 162(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 162(B) showing a state of data saving/storing;

 FIGS. 163(A) and 163(B) are diagrams for illustrating operations [command processing (7) in 25 FIG. 156] according to the second embodiment, FIG. 163(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position,

FIGS. 164(A) and 164(B) are diagrams for illustrating operations [command processing (8) in FIG. 156] according to the second embodiment, FIG.

5 164(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 164(B) showing a state of data saving/storing;

FIGS. 165(A) and 165(B) are diagrams for illustrating operations [command processing (9) in FIG. 156] according to the second embodiment, FIG. 165(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 165(B) showing a state of data saving/storing;

FIGS. 166(A) and 166(B) are diagrams for
15 illustrating operations [command processing (10) in
FIG. 156] according to the second embodiment, FIG.
166(A) showing a state of data writing on the magnetic
head, a real head position and a virtual head position,
FIG. 166(B) showing a state of data saving/storing;

FIGS. 167(A) and 167(B) are diagrams for illustrating operations [command processing (11) in FIG. 156] according to the second embodiment, FIG. 167(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 167(B) showing a state of data saving/storing;

FIGS. 168(A) and 168(B) are diagrams for illustrating operations [command processing (12) in

FIG. 156] according to the second embodiment, FIG. 168(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 168(B) showing a state of data saving/storing;

5 FIGS. 169(A) and 169(B) are diagrams for illustrating operations [command processing (13) in FIG. 156] according to the second embodiment, FIG. 169(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, 10 FIG. 169(B) showing a state of data saving/storing;

 FIGS. 170(A) and 170(B) are diagrams for illustrating operations [command processing (14) in FIG. 156] according to the second embodiment, FIG. 170(A) showing a state of data writing on the magnetic 15 head, a real head position and a virtual head position, FIG. 170(B) showing a state of data saving/storing;

 FIGS. 171(A) and 171(B) are diagrams for illustrating operations [command processing (15) in FIG. 156] according to the second embodiment, FIG. 20 171(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position, FIG. 171(B) showing a state of data saving/storing;

 FIGS. 172(A) and 172(B) are diagrams for illustrating operations [command processing (16) in 25 FIG. 156] according to the second embodiment, FIG. 172(A) showing a state of data writing on the magnetic head, a real head position and a virtual head position,

FIG. 172(B) showing a state of data saving/storing;

FIG. 173 is a diagram in which, when data is read out from two consecutive files as shown in FIG. 141, a time required for a command processing carried out applying the method according to the second embodiment and executing emulation is compared with a time required for the command processing carried out applying the known method without executing emulation;

FIG. 174 is a diagram in which, when data is read out from two consecutive files as shown in FIG. 156, a time required for a command processing carried out applying the method according to the second embodiment and executing emulation is compared with a time required for the command processing carried out applying the known method without executing emulation;

FIG. 175 is a block diagram showing a hardware structure of a known magnetic tape controller;

FIG. 176 is a diagram showing structures of a command buffer and a data buffer and a register for XBID for carrying out streaming;

FIG. 177 is a diagram for illustrating states of the command buffer and the data buffer when a read streaming sequence is executed;

FIG. 178 is a diagram for illustrating states of the command buffer and the data buffer when the read

streaming sequence is executed;

FIG. 179 is a diagram for illustrating states of the command buffer and the data buffer when a write streaming sequence is executed;

5 FIG. 180 is a diagram for illustrating states of the command buffer and the data buffer when the write streaming sequence is executed;

FIG. 181 is a diagram for illustrating states of the command buffer and the data buffer when a
10 command sequence other than the read command sequence and the write command sequence is executed;

FIG. 182 is a diagram for illustrating states of the command buffer and the data buffer when the
15 command sequence other than the read command sequence and the write command sequence is executed;

FIG. 183 is a flowchart for illustrating a command processing (idle process) by a format controller in a known magnetic tape controller;

FIG. 184 is a flowchart for illustrating a
20 command processing (read process) by the format controller in the known magnetic tape controller;

FIG. 185 is a diagram in which a part of the flowchart shown in FIG. 184 is tabulated in order to illustrate the command process (read process) by the
25 format controller in the known magnetic tape controller;

FIG. 186 is a flowchart for illustrating a

command processing (read backward process) by the
format controller in the known magnetic tape
controller;

FIG. 187 is a diagram in which a part of the
5 flowchart shown in FIG. 186 is tabulated in order to
illustrate the command processing (read backward
process) by the format controller in the known
magnetic tape controller;

FIG. 188 is a flowchart for illustrating a
10 command processing (write process) by the format
controller in the known magnetic tape controller;

FIG. 189 is a diagram in which a part of the
flowchart shown in FIG. 188 is tabulated in order to
illustrate the command processing (write process) by
15 the format controller in the known magnetic tape
controller;

FIG. 190 is a flowchart for illustrating a
command processing (back space block process) by the
format controller in the known magnetic tape
20 controller;

FIG. 191 is a diagram in which a part of the
flowchart shown in FIG. 190 is tabulated in order to
illustrate the command processing (back space block
process) by the format controller in the known
25 magnetic tape controller;

FIG. 192 is a flowchart for illustrating a
command processing (back space file process) by the

format controller in the known magnetic tape controller;

FIG. 193 is a diagram in which a part of the flowchart shown in FIG. 192 is tabulated in order to
5 illustrate the command processing (back space file process) by the format controller in the known magnetic tape controller;

FIG. 194 is a flowchart for illustrating a command processing (forward space block process) by
10 the format controller in the known magnetic tape controller;

FIG. 195 is a diagram in which a part of the flowchart shown in FIG. 194 is tabulated in order to
15 illustrate the command processing (forward space block process) by the format controller in the known magnetic tape controller;

FIG. 196 is a flowchart for illustrating a command processing (forward space file process) by the
20 format controller in the known magnetic tape controller;

FIG. 197 is a diagram in which a part of the flowchart shown in FIG. 196 is tabulated in order to
25 illustrate the command processing (forward space file process) by the format controller in the known magnetic tape controller;

FIG. 198 is a flowchart for illustrating a command processing (write tape mark process) by the

of a read process in Pattern 1 by a control unit in an interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

5 FIGS. 206 and 207 are diagrams in which a part of a read process in Pattern 2 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

10 FIGS. 208 and 209 are diagrams in which a part of a read process in Pattern 3 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

15 FIGS. 210 and 211 are diagrams in which a part of a read process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

20 FIG. 212 is a diagram in which a part of a read backward process in Pattern 1 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

25 FIG. 213 is a diagram in which a part of a read backward process in Pattern 2 by the control unit in the interface converting apparatus according to the

third embodiment is tabulated in order to illustrate the same;

FIG. 214 is a diagram in which a part of a read backward process in Pattern 3 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIG. 215 is a diagram in which a part of a read backward process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 216 and 217 are diagrams in which a part of a write process in Pattern 1 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 218 and 219 are diagrams in which a part of a write process in Pattern 2 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 220 and 221 are diagrams in which a part of a read backward process in Pattern 3 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 222 and 223 are diagrams in which a part of a read backward process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to
5 illustrate the same;

FIG. 224 is a diagram in which a part of a back space block process in Pattern 1 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate
10 the same;

FIG. 225 is a diagram in which a part of a back space block process in Pattern 2 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate
15 the same;

FIG. 226 is a diagram in which a part of a back space block process in Pattern 3 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate
20 the same;

FIG. 227 is a diagram in which a part of a back space block process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate
25 the same;

FIG. 228 is a diagram in which a part of a back space file process in Pattern 1 by the control unit

in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIG. 229 is a diagram in which a part of a back space file process in Pattern 2 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIG. 230 is a diagram in which a part of a back space file process in Pattern 3 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIG. 231 is a diagram in which a part of a back space file process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 232 and 233 are diagrams in which a part of a forward space block process in Pattern 1 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 234 and 235 are diagrams in which a part of a forward space block process in Pattern 2 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in

order to illustrate the same;

FIGS. 236 and 237 are diagrams in which a part of a forward space block process in Pattern 3 by the control unit in the interface converting apparatus
5 according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 238 and 239 are diagrams in which a part of a forward space block process in Pattern 4 by the control unit in the interface converting apparatus
10 according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 240 and 241 are diagrams in which a part of a forward space file process in Pattern 1 by the control unit in the interface converting apparatus
15 according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 242 and 243 are diagrams in which a part of a forward space file process in Pattern 2 by the control unit in the interface converting apparatus
20 according to the third embodiment is tabulated in order to illustrate the same;

FIG. 244 and 245 are diagrams in which a part of a forward space file process in Pattern 3 by the control unit in the interface converting apparatus
25 according to the third embodiment is tabulated in order to illustrate the same;

FIGS. 246 and 247 are diagrams in which a part

of a forward space file process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

5 FIG. 248 is a diagram in which a part of a write tape mark process in Pattern 1 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

10 FIG. 249 is a diagram in which a part of a write tape mark process in Pattern 2 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

15 FIG. 250 is a diagram in which a part of a write tape mark process in Pattern 3 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

20 FIG. 251 is a diagram in which a part of a write tape mark process in Pattern 4 by the control unit in the interface converting apparatus according to the third embodiment is tabulated in order to illustrate the same;

25 FIGS. 252(A) and 252(B) are diagrams showing a state of data writing on the magnetic tape, and for illustrating an example of commands issued from the

upper apparatus when a multi-file is additionally written, and tape operations/emulation operations in response to the commands in the magnetic tape unit according to the third embodiment;

5 FIGS. 253(A) and 253(B) are diagrams for illustrating an operation [command processing (1) in FIG. 252(A)] according to the third embodiment, FIG. 253(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position,
10 FIG. 253(B) showing a state of data saving/storing;

 FIGS. 254(A) and 254(B) are diagrams for illustrating an operation [command processing (2) in FIG. 252(A)] according to the third embodiment, FIG. 254(A) showing a state of data writing on the magnetic
15 tape, a real head position and a virtual head position, FIG. 254(B) showing a state of data saving/storing;

 FIGS. 255(A) and 255(B) are diagrams for illustrating an operation [command processing (3) in FIG. 252(A)] according to the third embodiment, FIG.
20 255(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 255(B) showing a state of data saving/storing;

 FIGS. 256(A) and 256(B) are diagrams for illustrating an operation [command processing (4) in
25 FIG. 252(A)] according to the third embodiment, FIG. 256(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position,

FIGS. 257(A) and 257(B) are diagrams for illustrating an operation [command processing (5) in FIG. 252(A)] according to the third embodiment, FIG.

FIGS. 258(A) and 258(B) are diagrams for illustrating an operation [command processing (6) in
10 FIG. 252(A)] according to the third embodiment, FIG.

FIGS. 259(A) and 259(B) are diagrams for
15 illustrating an operation [command processing (7) in
FIG. 252(A)] according to the third embodiment, FIG.

20 FIGS. 260(A) and 260(B) are diagrams for
illustrating an operation [command processing (8) in
FIG. 252(A)] according to the third embodiment, FIG.

FIGS. 261(A) and 261(B) are diagrams for illustrating an operation [command processing (9) in

FIG. 252(A)] according to the third embodiment, FIG. 261(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 261(B) showing a state of data saving/storing;

5 FIGS. 262(A) and 262(B) are diagrams for illustrating an operation [command processing (10) in FIG. 252(A)] according to the third embodiment, FIG. 262(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, 10 FIG. 262(B) showing a state of data saving/storing;

 FIGS. 263(A) and 263(B) are diagrams for illustrating an operation [command processing (11) in FIG. 252(A)] according to the third embodiment, FIG. 263(A) showing a state of data writing on the magnetic 15 tape, a real head position and a virtual head position, FIG. 263(B) showing a state of data saving/storing;

 FIGS. 264(A) and 264(B) are diagrams for illustrating an operation [command processing (12) in FIG. 252(A)] according to the third embodiment, FIG. 20 264(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 264(B) showing a state of data saving/storing;

 FIGS. 265(A) and 265(B) are diagrams for illustrating an operation [command processing (13) in 25 FIG. 252(A)] according to the third embodiment, FIG. 265(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position,

FIG. 252(B)] according to the third embodiment, FIG. 270(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, FIG. 270(B) showing a state of data saving/storing;

5 FIGS. 271(A) and 271(B) are diagrams for illustrating an operation [command processing (19) in FIG. 252(B)] according to the third embodiment, FIG. 271(A) showing a state of data writing on the magnetic tape, a real head position and a virtual head position, 10 FIG. 271(B) showing a state of data saving/storing;

 FIGS. 272(A) and 272(B) are diagrams for illustrating an operation [command processing (20) in FIG. 252(B)] according to the third embodiment, FIG. 272(A) showing a state of data writing on the magnetic 15 tape, a real head position and a virtual head position, FIG. 272(B) showing a state of data saving/storing;

 FIGS. 273(A) and 273(B) are diagrams showing a state of data writing on the magnetic tape, and for illustrating another example of commands issued from 20 the upper apparatus when a multi-file is additionally written, and tape operations/emulation operations in response to the commands in the magnetic tape unit according to the third embodiment;

 FIG. 274 is a diagram in which, when a 25 multi-file is additionally written as shown in FIGS. 252(A) and 252(B), a time required for a command processing carried out applying the method according

to the third embodiment and executing emulation is compared with a time required for the command processing carried out applying the known method without executing emulation; and

5 FIG. 275 is a diagram in which, when a multi-file is additionally written as shown in FIGS. 273(A) and 273(B), a time required for a command processing carried out applying the method according to the third embodiment and executing emulation is
10 compared with a time required for the command processing carried out applying the known method without executing emulation.

FIGS. 276(A) through 276(C) are diagrams for illustrating a modification of the method for
15 controlling a magnetic tape unit according to the second embodiment of this invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Hereinafter, description will be made of
20 embodiments of this invention referring to the drawings.

[1] Description of a First Embodiment

[1-1] Basic Structure

FIG. 1 is a block diagram showing a hardware
25 structure of a magnetic tape controller to which a method for controlling a magnetic tape unit according to a first embodiment of this invention is applied.

FIG. 2(A) is a diagram showing structures of a command buffer and a data buffer, and a register for XBID according to the first embodiment. FIG. 2(B) is a diagram showing structures of save areas and control areas in a RAM according to the first embodiment.

As shown in FIGS. 1 and 2(A), hardware of the magnetic tape controller (MTC) 10 according to the first embodiment has almost a similar structure to that described above with reference to FIGS. 175 and 176. Like reference characters designate like or corresponding parts in FIGS. 175 and 176, detailed descriptions of which are thus omitted.

According to this embodiment, when a CPU (command issuing apparatus, host computer, upper apparatus) 20 has an access to a magnetic tape MT (MTU 30) through the MTC 10 having a command buffer 16 and a data buffer 17, the MTC 10 so controls as to carry out a read/write process between the CPU 20 and the data buffer 17 and a read/write process between the data buffer 17 and the magnetic tape MT (MTU 30) asynchronously, thereby performing the above-described streaming process while referring to FIGS. 177 through 182.

On the magnetic tape MT according to this embodiment, data is stored in the multi-file form, as well. Namely, the MTU 30 successively writes a plurality of files on the magnetic tape MT or

successively reads out a plurality of files recorded on the magnetic tape MT.

On the magnetic tape MT according to this embodiment, the first tape mark TM-a is written after the last data block (data 1 in the drawings) of a file as shown in FIG. 3(B), the first end-of-file label (hereinafter abbreviated as EOF1) and the second end-of-file label (hereinafter abbreviated as EOF2) are successively written after the first tape mark TM-a as shown in FIGS. 3(C) and 3(D), and the second tape mark TM-b is written after EOF 2 as shown in FIG. 3(E). After that, if the file is the last on the magnetic tape MT, the third tape mark TM-c is further written after the second tape mark TM-b, as shown in FIG. 3(F). When the next file is additionally written after the file, the third tape mark TM-c is overwritten with two headers (HDR 1, HDR 2), and the two headers (HDR1, HDR2) are written, as shown in FIG. 20, for example.

According to this embodiment, the CPU 20 issues various commands so as to read at least either EOF1 or EOF2 in order to recognize a position of the head relative to the magnetic tape MT in the MTU 30 in the close/open process for a file recorded as above on the magnetic tape TM.

According to this embodiment, no modification is made on both the hardware and software of the MTU

30 and the CPU 20, but modification is made on only firmware of the MTC 10.

Note that the MTC 10 according to this embodiment is provided with a RAM 18 accessible from
5 an HIC 14 and an FMT 15. In the RAM 18, there are newly secured six areas 18a through 18f, as shown in FIG. 2(B).

The area 18a is a control area for monitoring a state of emulation to be described later, which being
10 an area in which emulation status (ES; 0 to 6) to be described later is held.

The area 18b is a control area for monitoring a virtual position of the head (virtual head position) relative to the magnetic tape MT when the emulation
15 to be described later is executed, which being an area in which an emulation pointer (EP; -4 to +1) to be described later is held.

The area 18c is a save area (Save Data Area 1: SDT1) for saving EOF1 when EOF1 is detected during
20 a real operation of the MTU 30. The area 18d is a save area (Save Length Area 1: SLN1) for saving a block length of the EOF1.

The area 18e is a save area (Save Data Area 2: SDT2) for saving EOF2 when the EOF2 is detected
25 during a real operation of the MTU 30. The area 18f is a save area (Save Length Area 2: SLN2) for saving a block length of the EOF2.

[1-2] Control Method according to the First Embodiment

Hereinafter, description will be made of a method for controlling a magnetic tape unit according to the first embodiment of this invention with reference to FIGS. 3 through 66.

[1-2-1] Basic Operation

First, description will be briefly made of a basic operation in the method according to the first embodiment. According to the first embodiment, in the open process for a file recorded on the magnetic tape MT, the MTC 10 fixes a position of the head (hereinafter referred to as a real head position) relative to the magnetic tape MT at a predetermined position [to be described later with reference to FIG. 3(E)] in the MTU 30, and carries out emulation in which a tape operation in response to a command from the CPU 20 is assumed to be virtually executed in the MTU 30 when receiving the command without making the MTU 30 carry out a real tape operation.

At this time, if EOF1 or EOF2 is read by the MTU 30 in response to an RD command from the CPU 20 in the close process for a file, the EOF1 or the EOF2 is saved in the save area 18c or 18e in the RAM 18. When an RD command directing a reading of the EOF1 or the EOF2 is issued from the CPU 20 in the open process for the file, the EOF1 or the EOF2 is read out from

the save area 18c or 18e in response to the RD command, and transferred to the CPU 20.

When EOF1 or EOF2 is written by the MTU 30 in response to a WR command from the CPU 20 in the closing
5 process for the file, the EOF1 or the EOF2 is saved in the save area 18c or 18e in the RAM 18. When an RD command directing a reading of the EOF1 or the EOF2 is issued from the CPU 20 in the opening process for the file, the EOF1 or the EOF2 is read out from the
10 save area 18c or 18e in response to the RD command, and transferred to the CPU 20.

Further, when either EOF1 or EOF2 is skipped by the MTU 30 in response to an SP command or an FSPF command from the CPU 20 in the closing process for the
15 file, the MTU 30 is made to carry out a real read operation to really read the EOF1/EOF2, and the read EOF1/EOF2 is saved in the save area 18c or 18e in the RAM 18. When an RD command directing a reading of the EOF1 or EOF2 is issued from the CPU 20 in the open
20 process for the file, the EOF1 or the EOF2 is read out from the save area 18c or 18e in response to the RD command, and transferred to the CPU 20.

[1-2-2] Emulation Status

Next, description will be made of emulation
25 status (hereinafter abbreviated as ES) according to the first embodiment with reference to FIGS. 3(A) through 3(G).

Described here are a relation between a value of ES held in the control area 18a in the RAM 18 and a real position of the head (a real head position; XBID to be stored in the register 15a of the FMT 15) relative to the magnetic tape MT, and a relation between a virtual head position (a virtual position of the head relative to the magnetic tape MT) that can be assumed when emulation is executed at each ES and a value of an emulation pointer (hereinafter abbreviated as EP) to be held in the control area 18b in the RAM 18 correspondingly to the virtual head position. Incidentally, a black triangle indicates a real head position, whereas a white triangle indicates a virtual head position in FIGS. 3(A) through 3(G).

FIG. 3(A) shows a state at the time that ES=0 (initial state). As shown in FIG. 3(A), the state at the time that ES=0 is a state in which a reading or a writing of an arbitrary data block (data 1 in the drawings) on the magnetic tape MT is completed, and a real head position relative to the magnetic tape MT is immediately after the data block. The real head position at the time that ES=0 (hereinafter referred to as XBID) is assumed to be n (BID of the arbitrary data block). At this time, a value of EP takes only -4.

FIG. 3(B) shows a state at the time that ES=1. As shown in FIG. 3(B), the state at the time that ES=1

is a state in which the first tape mark TM-a is detected or written, and the real head position is immediately after the first tape mark TM-a. XBID at the time that ES=1 is $n+1$. At this time, a value of EP takes only
 5 -3.

FIG. 3(C) shows a state at the time that ES=2. As shown in FIG. 3(C), the state at the time that ES=2 is a state in which EOF1 is detected or written, and the real head position is immediately after EOF1.
 10 XBID at the time that ES=2 is $n+2$. At this time, a value of EP takes only -2.

FIG. 3(D) shows a state at the time that ES=3. As shown in FIG. 3(D), the state at the time that ES=3 is a state in which EOF 2 is detected or written, and
 15 the real head position is immediately after EOF2. XBID at the time that ES=3 is $n+3$. At this time, a value of EP takes only -1.

FIG. 3(E) shows a state at the time that ES=4. As shown in FIG. 3(E), the state at the time that ES=4
 20 is a state in which the second tape mark TM-b is detected or written, and the real head position is immediately after the second tape mark TM-b. XBID at the time that ES=4 is $n+4$. At this time, a value of EP can take five values, -4, -3, -2, -1 and 0.

25 FIG. 3(F) shows a state at the time that ES=5. As shown in FIG. 3(F), the state at the time that ES=5 is a state in which the third tape mark TM-c is detected

or written, and the real head position is immediately after the third tape mark TM-c. XBID at the time that ES=5 is $n+5$. At this time, a value of EP takes only +1.

5 FIG. 3(G) shows a state at the time that ES=6. As shown in FIG. 3(G), the state at the time that ES=6 is a state in which the third tape mark TM-c is detected or written, and the real head position is between the second tape mark TM-b and the third tape mark TM-c. 10 XBID at the time that ES=6 is $n+4$. At this time, a value of EP can take six values, -4, -3, -2, -1, 0 and +1.

According to this embodiment, emulation is executed when the real head position is immediately after the second tape mark TM-b, as shown in FIGS. 3(E) 15 and 3(G). A predetermined position at which the head is fixed when the emulation is executed is set to a position immediately after the second tape mark TM-b. A virtual head position used in the emulation, i.e., 20 a value of EP, is managed as a relative position of the head relative to the predetermined position. Namely, a value of EP takes 0 when the virtual head position is immediately after the second tape mark TM-b. A value of EP is subtracted 1 therefrom when 25 the virtual head position is moved backward by one EOF or one take mark, while added 1 thereto when the virtual head position is moved forward by one EOF or

one tape mark.

[1-2-3] Command Processing

The idle process by the FMT 15 is similar to the idle process described above with reference to FIG. 183, detailed descriptions of which are thus omitted. When being directed the command processing by the HIC 14, the FMT 15 takes a branched route to or shifts to a command processing (cf. Steps S24 to S30 in FIG. 183) corresponding to a type of the command directed by the HIC 14, in the idle process. In each command processing, the FMT 15 executes a control according to flowcharts or control tables (control matrices) shown in FIGS. 4 through 19.

Before explaining each command processing, distinctive operations ① through ⑥ of the method according to the first embodiment will be described:

① In processes A10 to A80 in the command processing, the FMT 15 determines which a real operation or emulation is carried out in the MTU 30 on the basis of a value of ES and a value of EP held in the control areas 18a and 18b, respectively, in the RAM 18, and controls the MTU 30 according to a result of the determination, as will be described later. At this time, when the real operation is carried out, a value of the real head position XBID held in the register 15a is updated.

② If a virtual head position differs from a real head

position when the MTU 30 carries out a real operation in response to a command, a position of the re-positioned head is calculated by adding a relative position EP to the real head position XBID, and the head is repositioned at the above relative position in the MTU 30. After that, the MTU 30 performs a mechanical operation in response to the command, and a value of XBID in the register 15a is updated. Incidentally, a value of the real head position XBID to which the relative position EP should be added takes $n+4$ shown in FIG. 3(E) or 3(G) at this time.

③ When emulation is executed, the MTU 30 neither performs a mechanical operation nor updates a value of XBID in the register 15a, but reports a value obtained by adding the relative position EP to the real head position XBID as a present head position to the CPU 20 via the HIC 14. At this time, a value of the real head position XBID to which the relative position EP should be added takes $n+4$ as shown in FIG. 3(E) or 3(G), as well.

④ In processes B10 to B80 in the command processing, the FMT 15 updates ES and EP in the RAM 18 according to a command and a type of a data block that should be an object of the command processing, as will be described later. The ES and EP updated are used by the FMT 15 when a direction to carry out the next command processing is received from the HIC 14.

- ⑤ In processes B10, B30, B60 and B70 in the command processing, if it is determined that a data block that should be an object of a the processing is EOF1 or EOF2 when the RD process, the WR process, the SP process and the FSPF process involving a real operation of the MTU 30 is executed, the FMT 15 stores not only the data block in the save area 18c or 18e in the RAM 18, but also a block length of the data block in the save area 18d or 18f in the RAM 18. If emulation is executed in the RD process in response to an RD command when the open process for a file is carried out, for example, the FMT 15 stores the data block (EOF1 or EOF2) in the save area 18c or 18e in the data buffer 17 as data read out from the magnetic tape MT.
- ⑥ In processes C1 to C3 in the command processing, the FMT 15 registers a block ID (BID), a data buffer pointer (BPNT) and a block length (BLEN) updated in the processes B10 to B30 in the FQL 16-4, updates a command pointer (queue pointer) in the FQP 16-3 and updates a data buffer pointer when carrying out the RD process, the RB process and the WR process. In processes C4 to C8 in the command processing, the FMT 15 registers BID in the FQL 16-4 and updates a command pointer (queue pointer) in the FQP 16-3 when executing the BSP process, the BSPF process, the SP process, the FSPF process and the WTM process. Incidentally, the processes C1 through C8 according to the first

embodiment are basically similar to those described above with reference to FIGS. 184 through 199.

[1-2-3-1] RD (Read) Process

FIG. 4 is a flowchart for illustrating the RD process by the FMT 15 in the MTC 10 according to the first embodiment. FIG. 5 is a diagram in which a part (processes A10 and B10) of the flowchart shown in FIG. 4 is tabulated in order to explain the RD process in more detail.

As shown in FIG. 4, in the RD process by the FMT 15, the process A10, the process B10 and the process C1 are repeatedly carried out until the streaming is stopped (until judged YES at Step S35). The process C1 is similar to that described above with reference to FIGS. 184 and 185, detailed descriptions of which are thus omitted. Hereinafter, the process A10 and the process B10 will be described in detail with reference to a control table (control matrix) shown in FIG. 5.

In the process A10, the FMT 15 refers to RAM 18 to recognize a value of ES and a value of EP. When recognizing that $ES=0$ and $EP=-4$ [cf. FIG. 3(A)], the FMT 15 makes the MTU 30 really execute a read operation (real READ), and adds 1 to a value of the real head position XBID in the register 15a. In the process B10, the FMT 15 determines whether the a type of a data block read by the MTU 30 is a tape mark (hereinafter

abbreviated as TM) or any other. When determining that a type of the data block is TM, the FMT 15 updates ES to "1" in the RAM 18, updates EP to "-3", and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1000). When determining that the data block is other than TM in the process B10, the FMT 15 holds ES=0 and EP=-4 in the RAM 18, and sets "0" to TM flag, "LEN (block length of the data block)" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1001).

When recognizing ES=1 and EP=-3 [cf. FIG. 3(B)], the FMT 15 makes the MTU 30 really execute the read operating (real READ), and adds 1 to a value of the real head position XBID in the register 15a. In the process B10, the FMT 15 determines which one the type of the data block read in the MTU 30 is of EOF, TM or any other. When determining that the data block is EOF, the FMT 15 updates ES to "2" and EP to "-2" in the RAM 18, and sets "0" to TM flag, "LEN" to BLEN and "XBID" to BID in the FQL 16-4. The FMT 15 saves EOF (EOF1) read out from the magnetic tape MT in the save area (SDT1) in the RAM 18, and saves a block length LEN of the EOF in the save area (SLN1) in the RAM 18 (process ID = 1100). When determining that the data block is TM in the process B10, the FMT 15 holds ES=1 and EP=-3 in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID

= 1101). When determining that the data block is other than EOF and TM in the process B10, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "0" to TM flag, "LEN" to BLEN and "XBID" to BID
 5 in the FQL 16-4 (process ID = 1102).

When recognizing that ES=2 and EP=-2 in the process A10 [cf. FIG. 3(C)], the FMT 15 makes the MTU 30 really carry out the read operation (real READ), and adds 1 to a value of the real head position XBID
 10 in the register 15a. In the process B10, the FMT 15 determines which one the type of a data block read by the MTU 30 is of EOF, TM or any other. When determining that the data block is EOF, the FMT updates ES to "3" and EP to "-1" in the RAM 18, and sets "0" to TM flag,
 15 "LEN" to BLEN and "XBID" to BID in the FQL 16-4. Further, the FMT 15 saves EOF (EOF2) read out from the magnetic tape MT to the data buffer 17 in the save area (SDT2) 18e in the RAM 18, and saves a block length LEN of the EOF in the save area (SLN2) 18f in the RAM 18
 20 (process ID = 1200). When determining that the data block is TM in the process B10, the FMT 15 updates EP to "1" and EP to "-3" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1201). When determining that the data
 25 block is other than EOF and TM in the process B10, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "0" to TM flag, "LEN" to BLEN and "XBID" to

BID in the FQL 16-4 (process ID = 1202).

When recognizing that ES=3 and EP=-1 in the process A10 [cf. FIG. 3(D)], the FMT 15 makes the MTU 30 really carry out the read operation (real READ), and adds 1 to a value of the real head position XBID in the register 15a. In the process B10, the FMT 15 determines whether the type of a data block read by the MTU 30 is TM or any other. When determining that the data block is TM, the FMT 15 updates ES to "4" and EP to "0" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1300). When determining in the process B10 that the data block is other than TM, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "0" to TM flag, "LEN" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1301).

When recognizing that ES=4 and EP=-4 in the process A10 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B10, the FMT 15 updates EP to "-3" while holding ES at a value of "4" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 1400).

When recognizing that ES=4 and EP=-3 in the process A10 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B10, the FMT 15 updates EP to "-2" while holding ES at a value of

"4" in the RAM 18, writes EOF1 saved in the save area (SDT1) 18c in the RAM 18 into the data buffer 17, and sets "0" to TM flag, "SLN1 (block length of EOF1 saved in the save area 18d in the RAM 18) to BLEN and
 5 "XBID+EP" to BID in the FQL 16-4 (process ID = 1410).

When recognizing that ES=4 and EP=-2 in the process A10 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B10, the FMT 15 updates EP to "-1" while holding ES at a value of
 10 "4" in the RAM 18, writes EOF2 saved in the save area (SDT2) 18e in the RAM 18 into the data buffer 17, and sets "0" to TM flag, "SLN2 (block length of EOF2 saved in the save area 18f in the RAM 18) to BLEN and
 "XBID+EP" to BID in the FQL 16-4 (process ID = 1420).

15 When recognizing that ES=4 and EP=-1 in the process A10 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B10, the FMT 15 updates EP to "0" while holding ES at a value of
 "4" in the RAM 18, and sets "1" to TM flag, "0" to BLEN
 20 and "XBID+EP" to BID in the FQL 16-4 (process ID = 1430).

When recognizing that ES=4 and EP=0 in the process A10 [cf. FIG. 3(E)], the FMT 15 makes the MTU 30 really carry out the read operation (real READ),
 25 and adds 1 to a value of the real head position XBID in the register 15a. In the process B10, the FMT determines which type of a data block read by the MTU

MT to the data buffer 17 in the save area (SDT1) in the RAM 18 and a block length LEN of the EOF in the save area (SLN1) 18d in the RAM 18 (process ID = 1500). When determining that the data block is TM in the process B10, the FMT 15 updates ES to "1" and EP to
 5 "-3" in the RAM 18, and sets "1" to TM flag and "XBID" to BID in the FQL 16-4 (process ID = 1501). When determining that the data block is other than EOF and TM in the process B10, the FMT 15 updates ES to "0"
 10 and EP to "-4" in the RAM 18, and sets "0" to TM flag and "XBID" to BID in the FQL 16-4 (process ID = 1502).

When recognizing that ES=6 and EP=-4 in the process A10 [cf. FIG. 3(G)], the FMT 15 executes emulation of the MTU 30. In the process B10, the FMT
 15 15 updates EP to "-3" while holding ES at a value of "6" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 1600).

When recognizing that ES=6 and EP=-3 in the process A10 [cf. FIG. 3(G)], the FMT 15 executes emulation of the MTU 30. In the process B10, the FMT
 20 15 updates EP to "-2" while holding ES at a value of "6" in the RAM 18, writes EOF1 saved in the save area (SDT1) 18c in the RAM 18 into the data buffer 17, and
 25 sets "0" to FM flag, "SLN1" (block length of EOF1 saved in the save area 18d in the RAM 18) to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 1610).

the read operation (real READ), and adds 1 to a value of the real head position XBID in the register 15a. In the process B10, the FMT 15 determines whether the type of a data block read by the MTU 30 is TM or any
 5 other. When determining that the data block is TM, the FMT 15 updates ES to "1" and EP to "-3" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1650). When determining that the data block is other than TM in
 10 the process B10, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "0" to TM flag, "LEN" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 1651).

[1-2-3-2] RB (Read Backward) Process

15 FIG. 6 is a flowchart for illustrating the RB process by the FMT 15 in the MTC 10 according to the first embodiment. FIG. 7 is a diagram in which a part (processes A20 and B20) of the flowchart in FIG. 6 is tabulated in order to explain the RB process in more
 20 detail.

As shown in FIG. 6, the process A20, the process B20 and the process C2 are carried out in the RB process by the FMT 15. The process C2 is the same as that described above with reference to FIGS. 186
 25 and 187, descriptions of which are thus omitted. Hereinafter, the process A20 and the process B20 will be described in detail with reference to a control

30 really carry out the read backward operation (real RB), and subtracts 1 from a value of the real head position XBID in the register 15a. In the process B20, the FMT 15 determines whether the type of a data block read by the MTU 30 is TM or any other. When determining that the data block is TM, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 2100). When determining that the data block is other than TM in the process B20, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "0" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 2101).

When recognizing that ES=2 and EP=-2 [cf. FIG. 3(C)] in the process A20 or that ES=3 and EP=-1 in the process A20 [cf. FIG. 3(D)], processes similar to the processes of process IDs = 2100 and 2101 described above are carried out in the process A20 and process B20 (process IDs = 2200, 2201, 2300 and 2301).

When recognizing that ES=4 and EP=-4 in the process A20 [cf. FIG. 3(E)], the FMT 15 re-positions the head at a position XBID+EP [position n in FIG. 3(E)] in the MTU 30, makes the MTU 30 really carry out the read backward operation (real RB), and subtract 1 from a value of the real head position XBID in the register 15a. In the process B20, the FMT 15 carries out processes similar to the processes of process IDs

= 2100 and 2101 (process IDs = 2400, 2401).

When recognizing that ES=4 and EP=-3 in the process A20 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B20, the FMT 15 sets ES as undetermined and updates EP to "-4" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 2410).

When recognizing that ES=4 and EP=-2 in the process A20 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B20, the FMT 15 sets ES as undetermined and updates EP to "-3", and sets "0" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 2420).

When recognizing that ES=4 and EP=-1 in the process A20 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B20, the FMT 15 sets ES as undetermined and updates EP to "-2" in the RAM 18, and sets "0" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 2430).

When recognizing that ES=4 and EP=0 in the process A20 [cf. FIG. 3(E)], the FMT 15 executes emulation of the MTU 30. In the process B20, the FMT 15 sets ES as undetermined and updates EP to "-1" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 2440).

When recognizing that ES=5 and SP=+1 in the process A20 [cf. FIG. 3(F)], the FMT 15 makes the MTU

process A20 [cf. FIG. 3(G)], the FMT 15 executes emulation of the MTU 30. In the process B20, the FMT 15 sets ES as undetermined and updates EP to "-1" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and
 5 "XBID+EP" to BID in the FQL 16-4 (process ID = 2640).

When recognizing that ES=6 and EP=+1 in the process A20 [cf. FIG. 3(G)], the FMT 15 executes emulation of the MTU 30. In the process B20, the FMT 15 sets ES as undetermined and updates EP to "0" in
 10 the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 2650).

[1-2-3-3] WR (Write) Process

FIG. 8 is a flowchart for illustrating a WR process by the FMT 15 in the MTC 10 according to the first embodiment. FIG. 9 is a diagram in which a part
 15 (processes A30 and B30) of the flowchart shown in FIG. 8 is tabulated in order to explain the WR process in more detail.

As shown in FIG. 8, the process A30, the
 20 process B30 and the process C3 are repeatedly carried out in the WR process by the FMT 15 until the streaming is stopped (until judged YES at Step S50). The process C3 is the same as that described above with reference to FIGS. 188 and 189, descriptions of which
 25 are thus omitted. Hereinafter, the process A30 and the process B30 will be described in detail with reference to a control table (control matrix) shown

in FIG. 9.

In the process A30, the FMT 15 first refers to the RAM 15 to recognize a value of ES and a value of EP. When recognizing that ES=0 and EP=-4 [cf. FIG. 3(A)], the FMT 15 makes the MTU 30 really carry out a write operation (real WR), and adds 1 to a value of a real head position XBID in the register 15a. In the process B30, the FMT 15 holds ES=0 and EP=-4 in the RAM 18, and sets "LEN" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 3000).

When recognizing that ES=1 and EP=-3 in the process A30 [cf. FIG. 3(B)], the FMT 15 makes the MTU 30 really carry out the write operation (real WR), and adds 1 to a value of the real head position XBID in the register 15a. In the process B30, the FMT 15 determines whether the type of a data block written by the MTU 30 is EOF or any other. When determining that the data block is EOF, the FMT 15 updates ES to "2" and EP to "-2", and sets "LEN" to BLEN and "XBID" to BID in the FQL 16-4. Further, the FMT 15 saves EOF (EOF1) stored in the data buffer 17 in the save area (SDT1) 18c in the RAM 18, and saves a block length LEN of the EOF in the save area (SLN1) 18d in the RAM 18. When determining that the data block is other than EOF in the process B30, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "LEN" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 3101).

When recognizing that ES=2 and EP=-2 in the process A30 [cf. FIG. 3(C)], the FMT 15 makes the MTU 30 really carry out the write operation (real WR), and adds 1 to a value of the real head position XBID in the register 15a. In the process B30, the FMT 15 determines whether the type of a data block written by the MTU 30 is EOF or any other. When determining that the data block is EOF, the FMT 15 updates ES to "3" and EP to "-1" in the RAM 18, and sets "LEN" to BLEN and "XBID" to BID in the FQL 16-4. Further, the FMT 15 saves EOF (EOF2) stored in the data buffer 17 in the save area (SDT2) 18e in the RAM 18, and saves a block length LEN of the EOF in the save area (SLN2) 18f in the RAM 18 (process ID = 3200). When determining that the data block is other than EOF in the process B30, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "LEN" to BLEN and "XBID" to BID in the FQL 16-4 (process ID= 3201).

When recognizing that ES=3 and EP=-1 in the process A30 [cf. FIG. 3(D)], the FMT 15 makes the MTU really carry out the write operation (real WR), and adds 1 to a value of the real head position XBID in the register 15a. In the process B30, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "LEN" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 3300).

When recognizing that ES=4 and EP=-4 in the

When recognizing that $ES=4$ and $EP=-1$ in the process A30 [cf. FIG. 3(E)], the FMT 15 re-positions the head at a position $XBID+EP$ [position $n+3$ in FIG. 3(E)] in the MTU 30, makes the MTU 30 really carry out
 5 the write operation (real WR), and adds 1 to a value of the real head position $XBID$ in the register 15a. In the process B30, the FMT 15 updates ES to "0" and EP to "-4" in the RAM 18, and sets "LEN" to $BLEN$ and "XBID" to BID in the FQL 16-4, as does in the process
 10 of process ID = 3300.

When recognizing that $ES=4$ and $EP=0$ in the process A30 [cf. FIG. 3(E)], the FMT 15 makes the MTU 30 really carry out the write operation (real WR), and adds 1 to a value of the real head position $XBID$ in
 15 the register 15a. In the process B30, the FMT 15 carries out processes similar to the processes of process IDs = 3100, 3101 described above (process IDs = 3440, 3441).

When recognizing that $ES=5$ and $EP=+1$ in the process A30 [cf. FIG. 3(F)], the FMT 15 makes the MTU 30 really carry out the write operation (real WR), and adds 1 to a value of the real head position $XBID$ in
 20 the register 15a. In the process B30, the FMT 15 carries out processes similar to the processes of process IDs = 3100 and 3101 described above (process
 25 IDs = 3500, 3501).

When recognizing that $ES=6$ and $EP=-4$ in the

3(G)] in the MTU 30, makes the MTU 30 really carry out the write operation (real WR), and adds 1 to a value of the real head position XBID in the register 15a. In the process B30, the FMT 15 executes processes
 5 similar to the processes of process IDs = 3100 and 3101 described above (process IDs = 3650, 3651).

[1-2-3-4] BSP (Back Space Block) Process

FIG. 10 is a flowchart for illustrating a BSP process by the FMT 15 according to the first embodiment.
 10 FIG. 11 is a diagram in which a part (processes A40 and B40) of the flowchart shown in FIG. 10 is tabulated in order to explain the BSP process in more detail.

As shown in FIG. 10, the process A40, the process B40 and the process C4 are carried out in the
 15 BSP process by the FMT 15. The process C4 is the same as that described above with reference to FIG. 190 and 191, descriptions of which are thus omitted.

Hereinafter, the process A40 and the process B40 will be described in detail with reference to a control
 20 table (control matrix) shown in FIG. 11.

In the process A40, the FMT 15 refers to RAM 18 to recognize a value of ES and a value of EP. When recognizing that ES=0 and EP=-4 [cf. FIG. 3(A)], the FMT 15 makes the MTU 30 really carry out a back space
 25 operation (real BSP) for one data block, and subtracts 1 from a value of the real head position XBID in the register 15a. In the process B40, the FMT 15 holds

When recognizing that ES=5 and EP=+1 in the process A40 [cf. FIG. 3(F)], the FMT 15 makes the MTU 30 really carry out the back space operation (real BSP) for one data block, and subtracts 1 from a value of the real head position XBID in the register 15a. In the process B40, the FMT 15 updates ES to "6" and EP to "0", and sets "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 4500).

When recognizing that ES=6 and EP=-4 in the process A40 [cf. FIG. 3(G)], the FMT 15 carries out, in the process A40 and the process B40, a process similar to the process of process ID = 4400 described above (process ID = 4600).

When recognizing that ES=6 and EP=-3 in the process A40 [cf. FIG. 3(G)], the FMT 15 executes emulation of the MTU 30. In the process B40, the FMT 15 updates ES to "4" and EP to "-4" in the RAM 18, and sets "1" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 4610).

When recognizing that ES=6 and EP=-2 in the process A40 [cf. FIG. 3(G)], the FMT 15 executes emulation of MTU 30. In the process B40, the FMT 15 updates ES to "4" and EP to "-3" in the RAM 18, and sets "0" to TM flag, "0" to BLEN and "XBID+EP" to BID in the FQL 16-4 (process ID = 4620).

When recognizing that ES=6 and EP=-1 in the process A40 [cf. FIG. 3(G)], the FMT 15 executes

be described with reference to a control table
(control matrix) shown in FIG. 15.

As shown in FIG. 15, the process A60 and the
process B60 are almost the same as the process A10 and
5 the process B10 described above with reference to FIG.
5. Processes of process IDs = 6000 to 6651 shown in
FIG. 15 correspond to the processes of process IDs =
1000 to 1651 shown in FIG. 5, respectively. Namely,
the MTU 30 is generally required to carry out only the
10 forward space operation for one data block in the SP
process. However, according to the first embodiment,
the MTU 30 is, in the SP process, made to carry out
operations almost similar to those performed in the
RD process.

15 Note that BLEN is undetermined in the FQL 16-4
in the process B60. In the processes of process IDs
= 6410, 6420, 6610 and 6620, the operation of writing
data into the data buffer 17 from the RAM 18 performed
in the processes of the process IDs = 1410, 1420, 1610
20 and 1620 is omitted.

[1-2-3-7] FSPF (Forward Space File) Process

FIG. 16 is a flowchart for illustrating an FSPF
process by the FMT 15 in the MTC 10 according to the
first embodiment. FIG. 17 is a diagram in which a part
25 (processes A70 and B70) of the flowchart shown in FIG.
16 is tabulated in order to explain the FSPF process
in more detail.

As shown in FIG. 16, the process A70 and the process B70 are repeatedly carried out in the FSPF process by the FMT 15 until TM is detected (until judged YES at Step S51). When TM is detected (YES
 5 route at Step S52), the process C7 is carried out. The process C7 is the same as that described above with reference to FIGS. 196 and 197, descriptions of which are thus omitted. Hereinafter, the process A70 and the process B70 will be described with reference to
 10 a control table (control matrix) shown in FIG. 17.

As shown in FIG. 17, the process A70 and the process B70 are the same as the process A60 and the process B70 described above with reference to FIG. 15. Processes of process IDs = 7000 to 7651 shown in FIG.
 15 17 correspond to the processes of process IDs = 5000 to 5651 shown in FIG. 15. Namely, the MTU 30 is generally required to carry out only the forward space operation for one data block in the FSPF process. However, according to the first embodiment, the MTU
 20 30 is made to carry out operations almost similar to those performed in the RD process, in the FSPF process.

[1-2-3-8] WTM (Write Tape Mark) Process

FIG. 18 is a flowchart for illustrating a WTM process by the FMT 15 in the MTC 10 according to the
 25 first embodiment. FIG. 19 is a diagram in which a part (processes A80 and B80) of the flowchart shown in FIG. 18 is tabulated in order to explain the WTM process

in more detail.

As shown in FIG. 18, the process A80, the process B80 and a process C8 are carried out in the WTM process by the FMT 15. The process C8 is the same
 5 as that described above with reference to FIGS. 198 and 199, descriptions of which are thus omitted. Hereinafter, the process A80 and the process B80 will be described in detail with reference to a control table (control matrix) shown in FIG. 19.

10 In the MTU 30, when a writing is carried out in response to a command in a write system (WR, WTM), an EOD (End Of Data) mark is written after a written data block. Therefore, when a command in the write system is executed, the host (CPU 20) recognizes that
 15 there is no data block after a data block written in response to the command. In consequence, whenever a real write tape mark operation is carried out at the time that $EP = -4, -3, -2$ or $+1$, ES is updated to "1" and EP is updated to "-3", as will be described later
 20 with reference to FIG. 19.

In the process A80, the FMT 15 refers to the RAM 18 to recognize a value of ES and a value of EP. When recognizing that $ES=0$ and $EP=-4$ [cf. FIG. 3(A)], the FMT 15 makes the MTU 30 really carry out a write
 25 tape mark operation (real WTM), and adds 1 to a value of the real head position XBID in the register 15a. In the process B80, the FMT 15 updates ES to "1" and

= 8640).

When recognizing that ES=6 and EP=+1 in the process A80 [cf. FIG. 3(G)], the FMT 15 re-positions the head at a position XBID+EP [position n+5 in FIG. 3(G)] in the MTU 30, makes the MTU 30 really carry out the write tape mark operation (real WTM), and adds 1 to a value of the real head position XBID in the register 15a. In the process B80, the FMT 15 updates ES to "1" and holds EP at a value of "-3" in the RAM 18, besides setting "1" to TM flag, "0" to BLEN and "XBID" to BID in the FQL 16-4 (process ID = 8650).

[1-2-4] Emulation Executing Conditions

According to the first embodiment, emulation of the tape operation of the MTU 30 is executed by carrying out the processes of process IDs = 1000 to 8650 described above with reference to FIGS. 4 through 19.

Now, emulation executing conditions according to the first embodiment will be described with reference to FIGS. 20 and 21. In FIGS. 20 and 21, there are summarized conditions applied when emulation of the MTU 30 is executed in the command processing described above with reference to FIGS. 4 through 19.

FIG. 20 shows a relation between a value of EP and a type of a command at the time that ES=4, at which emulation should be executed. As shown in FIG.

20, emulation executing conditions at the time that ES=4 are as follows:

In the case where any one of RB command, BSP command and BSPF command is executed when ES=4 and
 5 EP=0;

In the case where any one of RD command, RB command, BSP command, BSPF command, SP command, FSPF command and WTM command is executed when ES=4 and EP=-1;

10 In the case where any one of RD command, RB command, BSP command, BSPF command, SP command and FSPF command is executed when ES=4 and EP=-2;

In the case where any one of RD command, RB command, BSP command, BSPF command, SP command and
 15 FSPF command is executed when ES=4 and EP=-3; and

In the case where any one of RD command, SP command and FSPF command is executed when ES=4 and EP=-4.

FIG. 21 shows a relation between a value of
 20 EP and a type of a command at the time that ES=6, at which emulation should be executed. As shown in FIG. 21, emulation executing conditions at the time that ES=6 are as follows:

In the case where any one of RB command, BSP
 25 command and BSPF command is executed when ES=6 and EP=+1;

In the case where any one of RD command, RB

according to the first embodiment in response to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 shown in FIGS. 22(A) and 22(B) are the same as those described above with reference to FIGS. 200(A) and 200(B).

Namely, the FIG. 22(A) shows a state of data writing on the magnetic tape MT immediately after a writing of a file consisting of a plurality of data blocks (data 1) on the magnetic tape MT is completed, similarly to FIG. 200(A). FIG. 22(B) shows a state of data writing on the magnetic tape MT after a file consisting of a plurality of data blocks (data 2) is additionally written in the state shown in FIG. 22(A), similarly to FIG. 200(B).

In FIGS. 22(A) and 22(B), each arrow designates a tape operation (a direction and a quantity of movement of the head H relative to the magnetic tape MT) performed in response to each command from the CPU 20, as well. Each arrow is given a type (capital letters) of command directing execution of a tape operation designated by the arrow. Further, the types of commands are given numbers in parentheses in the order the commands were issued from the CPU 20. Incidentally, the rightward direction signifies a tape forward direction, whereas the leftward direction signifies a tape backward

direction, in FIGS. 22(A) and 22(B).

As shown in FIG. 22, after the last data block (data 1) of a certain file is written on the magnetic tape MT in response to a WR command [cf. (1)], the close process for the file is carried out [cf. (2) to (7)].
 5 At this time, EOF1 is saved in the save area (SDT1) 18c and a block length thereof is also saved in the save area (SLN1) 18d when a WR command (3) is executed, according to the first embodiment. When a WR command
 10 (4) is executed, EOF1 is saved in the save area (SDT2) 18e and a block length thereof is also saved in the save area (SLN2) 18f. When finishing a writing of the file, the MTU 30 waits with the head H being located between the last two tape marks, TM-b and TM-c.

15 When the CPU 20 additionally writes the second file on the magnetic tape MT in which the file has been already written as shown in FIG. 22(A), the open process for the second file [cf. (8) to (22)] is carried out. The OS (Operation System) actuated by
 20 the CPU 20 reads EOF1 two times to recognize the same when the file open process is carried out in the case of data writing, thereby issuing a command so as to recognize a position at which the file should be written.

25 When carrying out the open process [cf. (8) to (22)] shown in FIGS. 22(A) and 22(B), the MTC 10 (FMT 15) emulates the command processing (8) to (19)

enclosed by broken lines in the drawings, using the method according to the first embodiment. During which, the MTC 10 does not perform any mechanical operation with the head H being located between the
 5 last two tape marks, TM-b and TM-c, as shown in FIG. 22(A). According to the first embodiment, EOF1 having been saved in the save area (SDT1) 18c is read out and transferred to the CPU 20 via the data buffer 17 when emulation of an RD command (11) is executed.

10 Hereinafter, the command processing (1) to (24) shown in FIGS. 22(A) and 22(B) will be described in detail with reference to FIGS. 23 through 46.

(A) of FIGS. 23 through 46 shows a state of data block writing on the magnetic tape MT, a real head position (real pointer; XBID) and a virtual head position (EP) when each of the command processing (1) to (24) is carried out. (B) of FIGS. 23 through 46 shows a state of data saving/storing in the RAM 18 when each of the command processing (1) to (24) is carried
 15 out.
 20

(1) WR Process

FIG. 23(A) shows a state in which the FMT 15 receives a WR command from the HIC 14, carries out a process of process ID = 3000, completes a user data
 25 writing, then is about to shift to a the close process for a file. In which, the real head position (XBID) is N. At this time, EP and EP in the respective control

areas 18a and 18b in the RAM 18 indicate the initial state (ES=0, EP=-4), as shown in FIG. 23(B).

Incidentally, the save areas 18c to 18f in the RAM 18 indicate the undetermined state.

5 (2) WTM Process

FIG. 24(A) shows a state in which the FMT 15 receives a WTM command at (2) in FIG. 22(A) from the HIC 14, carries out a process of process ID = 8000, completes a writing of a tape mark TM-a so that the
10 real head position (XBID) is N+1. At this time, "1" is held as ES in the control area 18a, whereas "-3" is held as EP in the control area 18b, as shown in FIG. 24(B).

(3) WR Process (EOF1 Write Process)

15 FIG. 25(A) shows a state in which the FMT 15 receives a WR command (direction to write EOF1) (3) in FIG. 22, carries out a process of process ID = 3100, and completes a writing of EOF1, so that the real head position (XBID) is N+2. At this time, "2" is held as
20 ES in the control area 18a, whereas "-2" is held as EP in the control area 18b, as shown in FIG. 25(B). EOF1 is stored in the save area (SDT1) 18c in the RAM 18, and a block length (80 bytes) thereof is stored in the save area (SLN1) 18d in the RAM 18. Thereafter,
25 the EOF 1 and the block length thereof are held in the save areas 18c and 18d, respectively.

(4) WR Process (EOF2 Write Process)

FIG. 26(A) shows a state in which the FMT 15 receives a WR command (direction to write EOF2) (4) in FIG. 22(A) from the HIC 14, carries out a process of process ID = 3200, and completes a writing of EOF2 so that the real head position (XBID) is N+3. At this time, "3" is held as ES in the control area 18a, whereas "-1" is held as EP in the control area 18b, as shown in FIG. 26(B). EOF2 is stored in the save area (SDT2) 18e in the RAM 18, and a block length (80 bytes) thereof is stored in the save area (SLN2) 18f in the RAM 18. Thereafter, the EOF2 and the block length thereof are held in the save areas 18e and 18f, respectively.

(5) WTM Process

FIG. 27(A) shows a state in which the FMT 15 receives a WTM command (5) shown in FIG. 22(A) from the HIC 14, carries out a process of process ID = 8300, and completes a writing of a tape mark TM-b so that the real head position (XBID) is N+4. At this time, "4" is held as ES in the control area 18a, whereas "0" is held as EP in the control area 18b, as shown in FIG. 27(B).

(6) WTM Process

FIG. 28(A) shows a state in which the FMT 15 receives the WTM command (6) in FIG. 22(A) from the HIC 14, carries out a process of process ID = 8440, and completes a writing of a tape mark TM-c so that the real head position (XBID) is N+5. At this time,

"5" is held as ES in the control area 18a, whereas "+1" is held as EP in the control area 18b, as shown in FIG. 28(B).

(7) BSPF Process

5 FIG. 29(A) shows a state in which the FMT 15 receives a BSPF command (7) shown in FIG. 22(A) from the HIC 14, carries out a process of process ID = 5500, and completes the back space operation so that the real head position (XBID) is N+4. At this time, "6" is held as ES in the control area 18a, whereas "0" is held as EP in the control area 18b, as shown in FIG. 29(B).

(8) BSPF Process

15 FIG. 30(A) shows a state in which the FMT 15 receives a BSPF command (8) shown in FIG. 22(A) from the HIC 14, and carries out a process of process ID = 5640 so as to execute emulation. At this time, the real head position (XBID) is still N+4, not changed. As shown in FIG. 30(B), "6" is held as ES in the control area 18a, whereas "-1" is held as EP in the control area 18b. Further, $XBID + EP = N + 3$ is registered as a value of BID in the FQL 16-4.

(9) BSPF Process

25 FIG. 31(A) shows a state in which the FMT 15 receives a BSPF command (9) shown in FIG. 22(A) from the HIC 14, and carries out processes of process IDs = 5630, 5620 and 5610 in order so as to execute emulation. At this time, the real head position

as a block length in the FQL 16-4, and $XBID+EP = N+2$ is registered as a value of BID in the FQL 16-4.

(12) FSPF Process

FIG. 34(A) shows a state in which the FMT 15 receives an FSPF command (12) shown in FIG. 22(A) from the HIC 14, and carries out processes of process IDs = 7620 and 7630 in order so as to execute emulation. At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 34(B), ES is held at a value of "6" in the save area 18a, whereas EP in the control area 18b is changed to "-1" and "0" in order. As a value of BID in the FQL 16-4, $XBID+EP = N+4$ is finally registered.

(13) RD Process

FIG. 35(A) shows a state in which the FMT 15 receives an RD command (13) shown in FIG. 22(A) from the HIC 14, and carries out a process of process ID = 1640 so as to execute emulation. At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 35(B), "6" is held as ES in the control area 18a, whereas "+1" is held as EP in the control area 18b. When the emulation is executed, "1" is set to a flag indicating tape mark detection in the FQL 16-4, and $XBID+EP = N+2$ is registered as a value of BID in the FQL 16-4.

(14) BSPF Process

FIG. 36(A) shows a state in which the FMT

"-2", "-3" and "-4" in order. $XBID+EP = N$ is finally registered as a value of BID in FQL 16-4.

(17) FSPF process

FIG. 39(A) shows a state in which the FMT 15 receives an FSPF command (17) shown in FIG. 22(B) from the HIC 14, and carries out a process of process ID = 7600 so as to execute emulation, as does in the command process (10). At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 39(B), "6" is held as ES in the control area 18a, whereas "-3" is held as EP in the control area 18b. Further, $XBID+EP = N+1$ is registered as a value of BID in the FQL 16-4.

(18) RD Process

FIG. 40(A) shows a state in which the FMT 15 receives an RD command (18) shown in FIG. 22(B) from the HIC 14, and carries out a process of process ID = 1610 so as to execute emulation, as does in the command process (11). At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 40(B), "6" is held as ES in the control area 18a, whereas "-2" is held as EP in the control area 18b. When the emulation is executed, contents EOF1 in the save area 18c are again stored in the data buffer 17, then transferred to the CPU 2. On that occasion, a value (80 bytes) in the save area 18d is registered as a block length in the FQL 16-4, and $XBID+EP = N+2$

is registered as a value of BID in the FQL 16-4.

(19) FSPF Process

FIG. 41(A) shows a state in which the FMT 15 receives an FSPF command (19) shown in FIG. 22(B) from the HIC 14, and carries out processes of process IDs = 7620 and 7630 in order so as to execute emulation, as does in the command process (12). At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 41(B), ES is held at a value of "6" in the control area 18a, whereas EP in the control area 18b is changed to "-1" and "0" in order. As a value of BID in the FQL 16-4, $XBID+EP = N+4$ is finally registered.

(20) WR Process

FIG. 42(A) shows a state in which the FMT 15 receives a WR command (direction to write HDR1) (20) shown in FIG. 22(B), carries out a process of process ID = 3641, and completes the writing of HDR1 so that the real head position (XBID) is $N+5$. At this time, "0" is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b, as shown in FIG. 42(B). As a value of BID in the FQL 16-4, $XBID = N+5$ is registered.

(21) WR Process (HRD2 Write Process)

FIG. 43(A) shows a state in which the FMT 15 receives a WR command (direction to write HDR2) (21) shown in FIG. 22(B) from the HIC 14, carries out a

process of process ID = 3000, and completes the writing of HRD2 so that the real head position (XBID) is N+6. At this time, "0" is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b, as shown in FIG. 43(B). As a value of BID in the FQL 16-4, XBID = N+6 is registered.

(22) WTM Process

FIG. 44(A) shows a state in which the FMT 15 receives a WTM command (22) shown in FIG. 22(B) from the HIC 14, carries out a process of process ID = 8000, and completes the writing of a tape mark TM-d so that the real head position (XBID) is N+7. At this time, "1" is held as ES in the control area 18a, whereas "-3" is held as EP in the control area 18a, as shown in FIG. 44(B). As a value of BID in the FQL 16-4, XBID = N+7 is registered.

(23) WR Process

FIG. 45(A) shows a state in which the FMT 15 receives a WR command (direction to write data 2) (21) shown in FIG. 22(B) from the HIC 14, carries out a process of process ID = 3101, and completes a writing of data 2 so that the real head position (XBID) is N+8. At this time, "0" is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b, as shown in FIG. 45(B). As a value of BID in FQL 16-4, XBID = N+8 is registered.

(24) WR Process

FIG. 46(A) shows a state in which the FMT 15 receives a WR command (direction to write data 2) (24) shown in FIG. 22(B) from the HIC 14, carries out a process of process ID = 3000, and completes a writing of data 2 so that the real head position (XBID) is N+9. At this time, "0" is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b. As a value of BID in the FQL 16-4, XBID = N+9 is registered.

10 [1-3-2] Example 2 of Emulation Execution

FIG. 47 is a diagram for illustrating a state of data writing on the magnetic tape MT, an example of commands issued from the CPU 20 when data is read out from two consecutive files, and tape operations/emulation operations in the MTU 30 according to the first embodiment performed in response to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 are the same as those described above with reference to FIG. 201.

Namely, FIG. 47 shows a state of data writing on the magnetic tape MT when two files are successively written, similarly to FIG. 201.

25 In FIG. 47, each arrow indicates a tape operation (a direction and a quantity of movement of the head H relative to the magnetic tape MT) performed

in response to a corresponding command from the CPU 20. A type of command (capital letters) directing execution of the tape operation indicated by each arrow is given to the arrow. Further, the types of the commands are given numbers in parentheses, (1) to (13), in the order the commands were issued from the CPU 20. Incidentally, the rightward direction signifies a tape forward direction, whereas the leftward direction signifies a tape backward direction, in FIG. 47.

As shown in FIG. 47, after the last data block (data 1) of the first file is read out from the magnetic tape MT according to an RD command [cf. (1)], the close process [cf. (2), (3)] is carried out.

When an FSPF command (3) is executed, a real read operation is carried out in the forward space operation in the MTU 30 to read EOF1 and EOF2, the EOF1 and a block length thereof are saved in the save area (SDT1) 18c and the save area (SLN1) 18d, respectively, whereas EOF2 and a block length thereof are saved in the save area (SDT2) 18e and the save area (SLN2) 18f, respectively, according to the first embodiment.

When the close operation is completed, the MTU 30 waits with the head H being located at the leading position (between TM-b and HDR1) of the second file. The open process for the second file [cf. (4) to (11)] is carried out. Wherein, the OS (Operating System)

actuated by the CPU 20 reads once EOF1 to recognize the same, thereby issuing a command so as to confirm a position at which the second file is read out, when the file open process is carried out in order to read
 5 data.

When the open process [cf. (4) to (11)] shown in FIG. 47 is carried out, the MTC 10 (FMT 15) emulates the command processing (4) to (8) enclosed by a broken line in the drawing, using the method according to the
 10 first embodiment. During which, the MTC 10 does not perform any mechanical operation with the head H being stopped at the leading position (between TM-b and HDR1) of the second file, as shown in FIG. 47. According to the first embodiment, EOF1 having been
 15 saved in the save area (SDT1) 18c is read out and transferred to the CPU 20 via the data buffer 17, when emulation is executed in response to an RD command (7).

Hereinafter, command processing (1) to (13) shown in FIG. 47 will be described in detail with
 20 reference to FIGS. 48 through 60.

(A) of FIGS. 48 through 60 shows a state of data block writing on the magnetic tape MT, a real head position (real pointer: XBID) and a virtual head position (EP), when each of the command processing (1)
 25 to (13) is carried out. (B) of FIG. 48 through 60 shows a state of data saving/storing in the RAM 18, when each of the command processing (1) to (13) is carried out.

(1) RD Process

FIG. 48(A) shows a state in which the FMT 15 receives an RD command (1) shown in FIG. 47 from the HIC 14, carries out a process of process ID = 1001, completes a reading of the last data block (data 1) of the first file, and is about to shift to the close process for the file. At this time, the real head position (XBID) is N. As shown in FIG. 48(B), ES and EP in the respective control areas 18a and 18b at this time indicate the initial state (ES=0, EP=-4). Incidentally, each of the save areas 18c to 18f in the RAM 18 indicates the undetermined state. As a value of BID in the FQL 16-4, XBID = N is registered.

(2) FSPF Process

FIG. 49(A) shows a state in which the FMT 15 receives an FSPF command (2) shown in FIG. 47 from the HIC 14, carries out a process of process ID = 7000, and completes the forward space operation so that the real head position (XBID) is N+1. At this time, "1" is held as ES in the control area 18a, whereas "-3" is held as EP in the control area 18b, as shown in FIG. 49(B). Further, as a value of BID in the FQL 16-4, XBID = N+1 is registered.

(3) FSPF Process

FIG. 50(A) shows a state in which the FMT 15 receives an FSPF command (3) shown in FIG. 47 from the HIC 14, carries out processes of process IDs = 7100,

7200 and 7300 in order, and completes the real read operation (operation to read EOF1 and EOF2) in the forward space operation in the MTU 30 so that the real head position (XBID) is $N+4$. At this time, ES and EP in the control areas 18a and 18b are changed to (ES=2, EP=-2), (ES=3, EP=-1), and (ES=4, EP=0) in order. Finally, "4" is held as ES in the control area 18a, whereas "0" is held as EP in the control area 18b. EOF1 is stored in the save area (SDT1) 18c in the RAM 18, and a block length (80 bytes) thereof is stored in the save area (SLN1) 18d in the RAM 18. EOF2 is stored in the save area (SDT2) 18e in the RAM 18, and a block length (80 bytes) thereof is stored in the save area (SLN2) 18f in the RAM 18. Thereafter, EOF1 and a block length thereof are held in the save areas 18c and 18d, respectively, whereas EOD2 and a block length thereof are held in the save areas 18e and 18f, respectively. As a value of BID in the FQL 16-4, XBID = $N+4$ is finally registered.

20 (4) BSPF Process

FIG. 51(A) shows a state in which the FMT 15 receives a BSPF command (4) shown in FIG. 47 from the HIC 14, and carries out a process of process ID = 5440 so as to execute emulation. At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 51(B), "4" is held as ES in the control area 18a, whereas "-1" is held as EP in the control

so as to execute emulation. At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 54(B), "4" is held as ES in the control area 18a, whereas "-2" is held as EP in the control area 18b. When the emulation is executed, contents EOF1 in the save area 18c are stored in the data buffer 17, then transferred to the CPU 20. At that time, a value (80 bytes) in the save area 18d is registered as a block length in the FQL 16-4, and $XBID+EP = N+2$ is registered as a value of BID in the FQL 16-4.

(8) FSPF Process

FIG. 55(A) shows a state in which the FMT 15 receives an FSPF command (8) shown in FIG. 47 from the HIC 14, and carries out processes of process IDs = 7420 and 7430 in order so as to execute emulation. At this time, the real head position (XBID) is still $N+4$, not changed. As shown in FIG. 55(B), ES in the control area 18a is held at a value of "4", whereas EP in the control area 18b is changed to "-1" and "0" in order. As a value of BID in the FQL 16-4, $XBID+EP = N+4$ is finally registered.

(9) RD Process

FIG. 56(A) shows a state in which the FMT 15 receives an RD command (9) shown in FIG. 47 from the HIC 14, carries out a process of process ID = 1442, and completes a reading of HDR1 so that the real head position (XBID) is $N+5$. As shown in FIG. 56(B), "0"

is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b, at this time. As a value of BID in the FQL 16-4, XBID = N+5 is registered.

5 (10) RD Process

FIG. 57(A) shows a state in which the FMT 15 receives an RD command (10) shown in FIG. 47 from the HIC 14, carries out a process of process ID = 1001, and completes a reading of HDR2 so that the real head position (XBID) is N+6. As shown in FIG. 57(B), "0" is held as ES in the control area 18b, whereas "-4" is held as EP in the control area 18b, at this time. As a value of BID in the FQL 16-4, XBID = N+6 is registered.

15 (11) FSPF Process

FIG. 58(A) shows a state in which the FMT 15 receives an FSPF command (11) shown in FIG. 47 from the HIC 14, carries out a process of process ID = 7000, and completes the forward space operation so that the real head position (XBID) is N+7. As shown in FIG. 58(B), "1" is held as ES in the control area 18a, whereas "-3" is held as EP in the control area 18b, at this time. Further, as a value of BID in the FQL 16-4, XBID = N+7 is registered.

25 (12) RD Process

FIG. 59(A) shows a state in which the FMT 15 receives an RD command (12) shown in FIG. 47 from the

HIC 14, carries out a process of process ID = 1102, and completes a reading of data 2 so that the real head position (XBID) is $N+8$. As shown in FIG. 59(B), "0" is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b, at this time. As a value of BID in the FQL 16-4, $XBID = N+8$ is registered.

(13) RD Process

FIG. 60(A) shows a state in which the FMT 15 receives an RD command (13) shown in FIG. 47 from the HIC 14, carries out a process of process ID = 1001, and completes a reading of data 2 so that the real head position (XBID) is $N+9$. As shown in FIG. 60(B), "0" is held as ES in the control area 18a, whereas "-4" is held as EP in the control area 18b, at this time. As a value of BID in the FQL 16-4, $XBID = N+9$ is registered.

[1-3-3] Example 3 of Emulation Execution

FIGS. 61(A) and 61(B) are diagrams showing a state of data writing on the magnetic tape MT, and for illustrating another example of commands issued from the CPU 20 when a multi-file is additionally written, and tape operations/emulation operations in the MTU 30 according to the first embodiment in response to the commands.

FIG. 61(A) shows a state of data writing on the magnetic tape MT immediately after a writing of

a file consisting of a plurality of data blocks (data 1) on the magnetic tape MT is completed, similarly to FIG. 22(A). FIG. 61(B) shows a state of data writing on the magnetic tape MT when a file consisting of a plurality of data blocks (data 2) is additionally written in a state shown in FIG. 61(A), similarly to FIG. 22(B).

In FIGS. 61(A) and 61(B), each arrow indicates a tape operation (a direction and a quantity of movement of the head H relative to the magnetic tape MT) performed in response to a corresponding command from the CPU 20. Each of the arrows is given a type (capital letters) of a command directing execution of a tape operation indicated by the arrow. Further, types of the command are given numbers in parentheses, (1) to (19), in the order the commands were issued from the CPU 20. Incidentally, the rightward direction signifies a tape forward direction, whereas the leftward direction signifies a tape backward direction, in FIGS. 61(A) and 61(B).

As shown in FIG. 61(A), the close process for a file [cf. (2) to (7)] is carried out after the last data block (data 1) of a certain file is written on the magnetic tape MT in response to a WR command [cf. (1)].

At this time, EOF1 is saved in the save area (SDT1) 18c, and a block length thereof is saved in the

save area (SLN1) 18d when a WR command (3) is executed, according to the first embodiment. When a WR command (4) is executed, EOF2 is saved in the save area (SDT2) 18e, and a block length thereof is saved in the save
 5 area (SLN2) 18f.

When finishing a writing of the file, the MTU 30 waits with the head H being located between the last two tape marks, TM-b and TM-c.

When the CPU 20 additionally writes the second
 10 file on the magnetic tape MT in which the file has been written as shown in FIG. 61(A), the open process for the second file [cf. (8) to (17)] is carried out. Incidentally, unlike the OS (Operating System) described above with reference to FIGS. 22(A) and
 15 22(B), the OS actuated by the CPU 20 reads once EOF1 to recognize the same such as to confirm a position at which the second file should be written when the file open process is carried out in order to write data, thereby issuing a command.

20 In the open process [cf. (8) to (17)] shown in FIGS. 61(A) and 61(B), the MTC 10 (FMT 15) emulates the command processing (8) through (14) enclosed by a broken line in the drawing, using the method according to the first embodiment. During which,
 25 the MTC 10 does not perform any mechanical operation with the head H being stopped between the last two tape marks, TM-b and TM-c, as shown in FIG. 61(A).

line in the drawing, using the method according to the first embodiment. During which, the MTC 10 does not perform any mechanical operation with the head H being located at the leading position (between TM-b and
 5 DHR1) of the second file as shown in FIG. 62.

According to the first embodiment, EOF2 having been saved in the save area (SDT2) is read out and transferred to the CPU 20 via the data buffer 17, when the emulation is executed in response to an RD
 10 command (9). When the emulation is executed in response to an RD command (11), EOF1 having been saved in the save area (SDT1) 18c is read out and transferred to the CPU 20 via the data buffer 17.

[1-3-5] Comparison of Performance (Comparison of
 15 Command Processing Times)

FIG. 63 is a diagram in which, when a process of additionally writing a multi-file is carried out as shown in FIGS. 22(A) and 22(B), a command processing time in the case where emulation is executed applying
 20 the method according to the first embodiment is compared with a command processing time in the case where the known method is applied without emulation.

FIG. 63 shows time periods required for each command processing, comparing a case with emulation
 25 with a case without emulation. As shown in FIG. 63, a number in parentheses is entered in a remarks column of a command corresponding to each of the command

processing (1) to (24) shown in FIGS. 22(A) and 22(B).
 A command without a number in parentheses in its
 remarks column does not relate to the tape operation
 in the MTU 30, a process corresponding to which is
 5 completed within the MTC 10.

As shown in FIG. 63, with respect to the
 command processing (1) to (7), and (20) to (24) and
 a time required for each of command processing not
 relating to the tape operation, times required for
 10 each process are equal in either case where emulation
 is carried out or not. In contrast, a time required
 for each of the command processing (8) to (19) is
 uniformly 0.000500 second since the process is
 completed within the MTC 10 without the real tape
 15 operation (mechanical operation) in the MTC 10 when
 the emulation is executed. In consequence, a time
 required for all the command processing when emulation
 is executed is 2.734931 second, which is much shorter
 than 9.111926 second that is a time required for all
 20 the command processing without emulation.

FIG. 64 is a diagram in which, when data is
 read out from two consecutive files as shown in FIG.
 47, a time required for command processing in the case
 where emulation is executed is compared with a time
 25 required for command processing in the case where a
 known method without emulation is applied.

FIG. 64 shows time periods required for each

command processing, comparing a case where emulation is not executed with a case where emulation is executed. In FIG. 64, a number in parentheses is entered in a remarks column of a command corresponding to each of the command processing (1) to (13) shown in FIG. 47. A command without a number in parentheses in its remarks column does not relate to the tape operation of the MTU 30, a process corresponding to which is completed within the MTC 10.

As shown in FIG. 64, with respect to the command processing (1) to (3) and (9) to (13) in which no emulation is executed and command processing not relating to the tape operation, times required for each process are equal in either case where emulation is executed or not. In contrast, a time required for each of the command processing (4) to (8) is uniformly 0.000500 second since the process is completed within the MTC 10 without the real tape operation (mechanical operation) in the MTU 30 when emulation is executed. In consequence, a time required for all the command processing in the case where emulation is executed is 2.827571 second, which is much shorter than 5.514830 second that is a time required for all the command processing without emulation.

FIG. 65 is a diagram in which, when a process of additionally writing a multi-file is carried out as shown in FIGS. 61(A) and 61(B), a time required for

command processing in the case where emulation is executed applying the method according to the first embodiment is compared with a time required for a processing in the case where a known method without
 5 emulation is applied.

FIG. 65 shows time periods required for each command processing, comparing command processing without emulation with command processing with emulation. In FIG. 65, a number in parentheses is
 10 entered in a remarks column of a command corresponding to each of the command processes (1) to (19) shown in FIGS. 61(A) and 61(B). A command without a number in parentheses in its remarks column has no relation to the tape operation of the MTU 30, a process
 15 corresponding to which is completed within the MTC 10.

As shown in FIG. 65, with respect to the command processing (1) to (7) and (15) to (19) in which no emulation is executed and the command processing not relating to the tape operation, times required for
 20 each process are equal in either case where emulation is executed or not. In contrast, a time required for each of the command processing (8) to (14) is uniformly 0.000500 second since the process is completed within the MTC 10 without the real tape operation (mechanical
 25 operation) in the MTU 30 when emulation is executed. In consequence, a time required for all the command processing when emulation is executed is 2.728100

second, which is much shorter than 5.831600 second that is a time required for all the command processing without emulation.

FIG. 66 is a diagram in which, when data is read out from two consecutive files as shown in FIG. 62, a time required for command processing with emulation applying the method according to the first embodiment is compared with a time required for command processing applying a known method without emulation.

FIG. 66 shows time periods required for each command processing, comparing a case where emulation is not executed with a case where emulation is executed. In FIG. 66, a number in parentheses is entered in a remarks column of a command corresponding to each of the command processing (1) to (20) shown in FIG. 62. A command without a number in parentheses in its remarks column has no relation to the tape operation in the MTU 30, a process corresponding to which is completed within the MTC 10.

As shown in FIG. 66, with respect to the command processing (1) to (4) and (16) to (20) in which no emulation is executed and command processing not relating to the tape operation, times required for each process are equal in either case where emulation is executed or not. In contrast, a time required for each of the command processing (5) to (15) is uniformly

0.000500 second since the process is completed within the MTC 10 without the real tape operation (mechanical operation) in the MTU 30 when emulation is executed. In consequence, a time required for all the command processing in the case where emulation is executed is 4.145200 second, which is largely shorter than 8.781900 second that is a time required for all the command processing without emulation.

[1-4] Effects of the First Embodiment

According to the method for controlling a magnetic tape unit of the first embodiment of this invention, the tape operation relating to EOF discrimination in the file open process in the MTC 10 is emulated to decrease the frequency of the mechanical tape operation in the MTU 30, thereby simplifying the tape operation required in the open process. It is thus possible to largely reduce a time required for the file open process (a time required to process a job), and improve a performance of the file open process, further a process performance of the system accessing to the MTU 30.

When a head positioning accuracy of the MTU 30 is low, it is possible to carry out the command processing as before according to a command from the CPU 20 without emulation. Namely, there is no necessity of any modification on the command (OS or the like) issued from the CPU 20 at the time of a file

open process, so that the method according to the first embodiment is applied to a MTU 30 having a low head positioning accuracy. On the other hand, it is possible to readily speed-up the file open process in
 5 a MTU 30 having a high-accuracy of head positioning.

[2] Description of a Second Embodiment

[2-1] Basic Structure

FIG. 67 is a block diagram showing a hardware structure of a system to which a method for controlling
 10 a magnetic tape unit according to a second embodiment of this invention is applied. As shown in FIG. 67, in a system according to the second embodiment, an interface converting apparatus 40 is interposed between the MTC 10 and the CPU 20. Hereinafter,
 15 "interface" is abbreviated as "I/F". According to the second embodiment, emulation, which is executed in a process in the MTC 10 according to the first embodiment, is executed in a process in the I/F converting apparatus 40.

20 FIG. 68 is a block diagram showing a hardware structure of the I/F converting apparatus 40. As shown in FIG. 68, the I/F converting apparatus 40 comprises a host-facing I/F circuit 41, a control unit 42, an MTC-facing I/F circuit 43, a command buffer 44,
 25 a data buffer 45 and a RAM 46.

The host-facing I/F circuit 41 controls an interface with the CPU 20, which is connected to, for

example, BMC (Block Multiplexer Channel), ESCON (Enterprise System Connection) channel or the like.

The control unit 42 converts/processes a command issued from the CPU 20 to a command suited to the MTC 10, or controls transfer of write data or read data.

The MTC-facing I/F circuit 43 controls an interface with the MTC 10, which is connected to, for example, SCSI (Small Computer System Interface) or the like.

The command buffer 44 temporarily stores a command issued from the CPU 20. The data buffer 45 temporarily stores write data that should be transferred from the CPU 20 to MTC 10 and written on the magnetic tape MT, or read data read out from the magnetic tape MT by the MTU 30 that should be transferred from the MTC 10 to the CPU 20.

The RAM 46 is generally used as a working area or the like when the control unit 42 carries out a process. According to the second embodiment, five areas 46a to 46e are secured in the RAM 46 as shown in FIG. 82 in order to store data necessary to execute emulation in the I/F converting unit 40, as will be described later.

The area 46a is a control area for monitoring a state of emulation to be described later, in which emulation status (ES; 00 to 63) to be described later

[2-2] Controlling Method According to the Second Embodiment

Hereinafter, description will be made of a method for controlling a magnetic tape unit according to the second embodiment of this invention with reference to FIGS. 69 through 174.

[2-2-1] Basic Operation

The basic operation of the method according to the second embodiment is almost similar to the that according to the first embodiment described above. Unlike a case where emulation is executed by the MTC 10 as in the first embodiment, there may occur a situation where EOF1 or EOF 2 cannot be saved in the area 46c or 46d in the RAM 46 in the file open process when emulation of the tape operation of the MTU 30 is executed by the I/F converting apparatus 40 according to the second embodiment.

Namely, when a command issued from the CPU 20 at the time of the file open process is a command in a skip system such as SPF command, FSPF command or the like, the MTC 10 is capable of making the MTU 30 carry out a real read operation as described above when processing the command [cf. FIGS. 15, 17, 50(A) and 50(B) in the first embodiment, for example]. However, since the I/F converting apparatus 40 does not directly control the MTU 30, the I/F converting apparatus 40 cannot identify which a data block

skipped by a command in the skip system is EOF1, EOF2 or any other than they. Identification patterns for EOF1 and EOF2 by the I/F converting apparatus 40 will be described later with reference to FIGS. 69(A) to 5 69(D).

According to the method of the second embodiment, when an RD command directing a reading of EOF1/EOF2 is issued from the CPU 20 in a state in which the EOF1/EOF2 is not saved in the save area 46c/46d 10 in the RAM 46 at the time of the file open process, the MTU 30 is made to carry out a real read process to really read EOF1/EOF2 in response to the RD command without executing emulation, and the EOF1/EOF2 read out by the MTU 30 is transferred to the CPU 20.

15 [2-2-2] Identification Patterns for EOFs

FIGS. 69(A) through 69(D) are diagrams for illustrating four identification patterns (Pattern 1 to Pattern 4) for EOFs by the I/F converting apparatus 40 according to the second embodiment.

20 If emulation is executed by the I/F converting apparatus 40, the I/F converting apparatus 40 cannot identify EOF1 or EOF2 when EOF1 or EOF2 is skipped by a command in the skip system at the time of file open process, thus cannot save EOF1 or EOF2 in the save area 25 46c or 46d in the RAM 46, as described above. As identification patterns for EOF1 and EOF 2, there are provided four kinds of patterns, 1 to 4, below.

Pattern 1 shown in FIG. 69(A) is in the case where both EOF1 and EOF2 can be identified and saved in the save areas 46c and 46d in the RAM 46. When emulation is executed by the MTC 10 as in the first embodiment, the identification pattern for EOF1 and EOF2 is always Pattern 1.

Pattern 2 shown in FIG. 69(B) is in the case where only EOF1 can be identified and saved in the save area 46c in the RAM 46.

10 Pattern 3 shown in FIG. 69(C) is in the case where only EOF2 can be identified and saved in the save area 46d in the RAM 46.

15 Pattern 4 shown in FIG. 69(D) is in the case where neither EOF1 nor EOF2 can be identified and saved in the save area 46c or 46d in the RAM 46.

Hereinafter, various types of command processing will be described with respect to the above four patterns, 1 to 4.

[2-2-3] Emulation Status

20 Now, description will be made of emulation status (hereinafter abbreviated as ES) according to the second embodiment with reference to FIGS. 70 through 73.

25 Here is described a relation between a value of ES held in the control area 46a in the RAM 46 and a real head position (real BID) relative to the magnetic tape MT.

Status monitoring is carried out on the basis of a value of ES in the I/F converting apparatus 40 according to the second embodiment. Particularly, when a value of ES is "4x" or "6x" (X = 0, 1, 2 or 3), execution of emulation is possible. In a state in which execution of emulation is possible as this (ES=4x or 6x), a virtual head position (a virtual position of the head relative to the magnetic tape MT) is managed with an emulation pointer (hereinafter abbreviated as EP). A value of EP is expressed as a relative position from the real head position. In FIGS. 70 through 73, a black triangle indicates the real head position, whereas a white triangle indicated the virtual head position when execution of emulation is possible.

(1) Emulation Status (ES) in Pattern 1

FIGS. 70(A) through 70(G) are diagrams for illustrating emulation status (ES) in Pattern 1 according to the second embodiment.

FIG. 70(A) shows a state at the time that ES = 00 (initial state). As shown in FIG. 70(A), a state at the time that ES = 00 is a state in which reading/writing of an arbitrary data block (data 1 in the drawings) from/on the magnetic tape TM is completed, and the real head position relative to the magnetic tape MT is immediately after the data block. The real head position (hereinafter referred to as

BID is $n+4$ when $ES=4$. At this time, a value of EP can take five values, -4, -3, -2, -1 and 0.

FIG. 70(F) shows a state at the time that $ES=50$. As shown in FIG. 70(F), the state at the time that $ES=50$ is a state in which the third tape mark TM-c is detected or written, and the real head position is immediately after the third tape mark TM-c. The real BID is $n+5$ when $ES=50$. At this time, a value of EP is undetermined.

FIG. 70(G) shows a state at the time that $ES=60$. As shown in FIG. 70(G), the state at the time that $ES=60$ is a state in which the third tape mark TM-c is detected or written, and the real head position is between the second tape mark TM-b and the third tape mark TM-c. The real BID at the time that $ES=60$ is $n+4$. At this time, a value of EP can take six values, -4, -3, -2, -1, 0 and +1.

(2) Emulation Status (ES) in Pattern 2

FIGS. 71(A) through 71(G) are diagrams for illustrating emulation status (ES) in Pattern 2 according to the second embodiment.

Like FIGS. 70(A) through 70(C), FIG. 71(A) through 71(C) show states at the time that $ES = 00, 10$ and 20 .

FIG. 71(D) shows a state at the time that $ES=31$. As shown in FIG. 71(D), the state at the time that $ES=31$ is a state in which EOF2 is skipped, and the real head

position is immediately after EOF2. The real BID at the time that ES=31 is $n+3$. At this time, a value of EP is undetermined.

FIG. 71(E) shows a state at the time that ES=41.

- 5 As shown in FIG. 71(E), the state at the time that ES=41 is a state in which EOF2 is skipped, the second tape mark TM-b is then detected or written, and the real head position is immediately after the second tape mark TM-b. The real BID at the time that ES=41 is $n+4$.
- 10 At this time, a value of EP can take five values, -4, -3, -2, -1 and 0.

FIG. 71(F) shows a state at the time that ES=51.

- As shown in FIG. 71(F), the state at the time that ES=51 is a state in which the EOF2 is skipped, the third tape
- 15 mark TM-c is then detected or written, and the real head position is immediately after the third tape mark TM-c. The real BID at the time that ES=51 is $n+5$. At this time, a value of EP is undetermined.

FIG. 71(G) shows a state at the time that ES=61.

- 20 As shown in FIG. 71(G), the state at the time that ES=61 is a state in which EOF2 is skipped, the third tape mark TM-c is then detected or written, and the real head position is between the second tape mark TM-b and the third tape mark TM-C. The real BID at the time
- 25 that ES=61 is $n+4$. At this time, a value of EP can take six values, -4, -3, -2, -1, 0 and +1.

(3) Emulation Status (ES) in Pattern 3

FIGS. 72(A) through 72(G) are diagrams for illustrating emulation status (ES) in Pattern 3 according to the second embodiment.

Like FIGS. 70(A) and 70(B), FIGS. 72(A) through 72(B) show states at the time that ES = 00 and 10.

FIG. 72(C) shows a state at the time that ES=22. As shown in FIG. 72(C), the state at the time that ES=22 is a state in which EOF1 is skipped, and the real head position is immediately after EOF1. The real BID at the time that ES=22 is $n+2$. At this time, a value of EP is undetermined.

FIG. 72(D) shows a state at the time that ES=32. As shown in FIG. 72(D), the state at the time that ES=32 is a state in which EOF1 is skipped, EOF2 is then detected or written, and the real head position is immediately after EOF2. The real BID at the time that ES=32 is $n+3$. At this time, a value of EP is undetermined.

FIG. 72(E) shows a state at the time that ES=42. As shown in FIG. 72(E), the state at the time that ES=42 is a state in which EOF1 is skipped, the second tape mark TM-b is then detected or written, and the real head position is immediately after the second tape mark TM-b. The real BID at the time that ES=42 is $n+4$. At this time, a value of EP can take five values, -4, -3, -2, -1 and 0.

FIG. 72(F) shows a state at the time that ES=52. As shown in FIG. 72(F), the state at the time that ES=52 is a state in which EOF1 is skipped, the third tape mark TM-c is then detected or written, and the real head position is immediately after the third tape mark TM-c. The real BID at the time that ES=52 is n+5. At this time, a value of EP is undetermined.

FIG. 72(G) shows a state at the time that ES=62. As shown in FIG. 72(G), the state at the time that ES=62 is a state in which EOF1 is skipped, the third tape mark TM-c is then detected or written, and the real head position is between the second tape mark TM-b and the third tape mark TM-c. The real BID at the time that ES=62 is n+4. At this time, a value of EP can take six values, -4, -3, -2, -1, 0 and +1.

(4) Emulation Status (ES) in Pattern 4

FIGS. 73(A) through 73(G) are diagrams for illustrating emulation status in Pattern 4 according to the second embodiment.

Like FIGS. 70(A) and 70(B), FIGS. 73(A) and 73(B) show states at the time that ES = 00 and 10. Like FIG. 72(C), FIG. 73(C) shows a state at the time that ES = 22.

FIG. 73(D) shows a state at the time that ES=33. As shown in FIG. 73(D), the state at the time that ES=33 is a state in which EOF1 is skipped, EOF2 is then skipped, and the real head position is immediately

to be described later with reference to FIGS. 83 through 115 are carried out, whereby emulation of the tape operation of the MTU 30 is executed.

Hereinafter, emulation executing conditions according to the second embodiment will be described with reference to FIGS. 74 through 81.

(1) Emulation Executing Conditions for Pattern 1

FIGS. 74(A), 74(B), 75(A) and 75(B) are diagrams for illustrating emulation executing conditions for Pattern 1 according to the second embodiment.

As shown in FIG. 74(A), emulation executing conditions at the time that ES=40 are as below, shown in FIG. 74(B). The state at the time that ES=40 is in Pattern 1 (where both of EOF1 and EOF2 are saved in the save areas 46c and 46d), and is a state in which reading/writing of data up to the second tape mark TM-b is completed in the MTU 30 so that the real head position is immediately after the second tape mark TM-b, as stated above.

- ① In a case where, when ES=40 and EP =0, any one of RB command, BSP command and BSPF command is executed;
- ② In a case where, when ES=40 and EP=-1, any one of RD command, RB command, BSP command, BSPF command, SP command, FSPF command and WTM command is executed;
- ③ In the case where, when ES=40 and EP=-2, any one of RD command (involving data transfer), RB command,

- ④ In the case where, when ES=61 and EP=-2, any one of RB command, BSP command, BSPF command, SP command and FSPF command is executed;
- ⑤ In the case where, when ES=61 and EP=-3, any one of RD command (involving data transfer), RB command, BSP command, BSPF command, SP command and FSPF command is executed; and
- ⑥ In the case where, when ES=61 and EP=-4, any one of RD command, SP command and FSPF command is executed;
- (3) Emulation Executing Conditions in Pattern 3
- FIGS. 78(A), 78(B), 79(A) and 79(B) are diagrams for illustrating emulating execution conditions according to the second embodiment.
- As shown in FIG. 78(A), the emulation executing conditions at the time that ES=42 are as below, shown in FIG. 78(B). The state at the time that ES=42 is in Pattern 3 (state in which only EOF2 is saved in the save area 46d), and is a state in which reading/writing data up to the second tape mark TM-b is completed in the MTU 30 and the real head position is immediately after the second tape mark TM-b, as stated above.
- ① In the case where, when ES=42 and EP=0, any one of RB command, BSP command and BSPF command is executed;
- ② In the case where, when ES=42 and EP=-1, any one of RD command, RB command, BSP command, BSPF command,

- SP command, FSPF command and WTM command is executed;
- ③ In the case where, when ES=42 and EP=-2, any one of RD command (involving data transfer), RB command, BSP command, BSPF command, SP command and FSPF command is executed;
- ④ In the case where, when ES=42 and EP=-3, any one of RB command, BSP command, BSPF command, SP command and FSPF command is executed; and
- ⑤ In the case where, when ES=42 and EP=-4, any one of RD command, SP command and FSPF command is executed.

As shown in FIG. 79(A), emulation executing conditions in a state at the time that ES=62 are as below, shown in FIG. 79(B). The state at the time that ES=62 is in Pattern 3 (state in which only EOF2 is saved in the save area 46d), and is a state in which reading/writing of data up to the third tape mark TM-c is completed in the MTU 30 and the real head position is immediately after the second tape mark TM-b, as stated above.

- ① In the case where, when ES=62 and EP=+1, any one of RB command, BSP command and BSPF command is executed;
- ② In the case where, when ES=62 and EP=0, any one of RD command, RB command, BSP command, BSPF command, SP command, FSPF command and WTM command is executed;
- ③ In the case where, when ES=62 and EP=-1, any one of RD command, RB command, BSP command, SBPF command,

SP command and FSPF command is executed;

④ In the case where, when ES=62 and EP=-2, any one of RD command (involving data transfer), RB command, BSP command, BSPF command, SP command and FSPF command is executed;

⑤ In the case where, when ES=62 and EP=-3, any one of RB command, BSP command, BSPF command, SP command and FSPF command is executed; and

⑥ In the case where, when ES=62 and EP=-4, any one of RD command, SP command and FSPF command is executed.

(4) Emulation Executing Conditions in Pattern 4

FIGS. 80(A), 80(B), 81(A) and 81(B) are diagrams for illustrating emulation executing conditions in Pattern 4 according to the second embodiment.

As shown in FIG. 80(A), emulation executing conditions at the time that ES=43 are as below, shown in FIG. 80(B). The state at the time that ES=43 is in Pattern 4 (state in which neither EOF1 nor EOF2 is saved in the save area 46c or 46d), and is a state in which reading/writing of data up to the second tape mark TM-b is completed in the MTU 30 and the real head position is immediately after the second tape mark TM-b, as stated above.

① In the case where, when ES=43 and EP=0, any one of RB command, BSP command and BSPF command is executed;

- ② In the case where, when $ES=43$ and $EP=-1$, any one of RD command, RB command, BSP command, BSPF command, SP command, FSPF command and WTM command is executed;
- ③ In the case where, when $ES=43$ and $EP=-2$, any one
5 of RB command, BSP command, BSPF command, SP command and FSPF command is executed;
- ④ In the case where, when $ES=43$ and $EP=-3$, any one of RB command, BSP command, BSPF command, SP command and FSPF command is executed; and
- 10 ⑤ In the case where, when $ES=43$ and $EP=-4$, any one of RD command, SP command and FSPF command is executed.

As shown in FIG. 81(A), emulation executing conditions at the time that $ES=63$ are as shown in FIG. 81(B). The state at the time that $ES=63$ is in Pattern
15 4 (neither EOF1 nor EOF2 is not saved in the save area 46c or 46d), and is a state in which reading/writing of data up to the third tape mark TM-c is completed in the MTU 30 and the real head position is immediately after the second tape mark TM-b, as stated above.

- 20 ① In the case where, when $ES=63$ and $EP=+1$, any one of RB command, BSP command and BSPF command is executed;
- ② In the case where, when $ES=63$ and $EP=0$, any one of RD command, RB command, BSP command, BSPF command,
25 SP command, FSPF command and WTM command is executed;
- ③ In the case where, when $ES=63$ and $EP=-1$, any one of RD command, RB command, BSP command, BSPF command,

in the control areas 46a and 46b in the RAM 46. In addition, a process of re-positioning the magnetic head, and a process of re-storing EOF1/EOF2 are carried out.

- 5 At this time, if a relative position (EP) and a real head position differ from each other when a real operation is carried out in the MTU 30, the control unit 42 makes to carry out a process of re-positioning the magnetic head. If emulation of EOF1/EOF2 can be
- 10 executed in the read command processing (RD process), the control unit 42 restores a data block (EOF1/EOF2) in the save area 46c/46d in the RAM 46 into the data buffer 45, and transfers the data block to the CPU 20 at Step S4 to be described later.
- 15 After the pre-process is completed, it is determined at Step S2 whether emulation is possible or not (whether or not decision on that emulation is executed or not is made in the pre-process). When emulation is impossible (NO route), a real operation
- 20 (SCSI process; Step S3) is carried out, then data is transferred (Step S4). When emulation is possible (YES route), data is transferred without the real operation at Step S3 (Step S4). Incidentally, data transfer at Step S4 is carried out when a process in
- 25 response to an RD command or a WR command is carried out.

embodiment sends back a value of SBID+EP as a channel block ID to the CPU 20, along with a value of SBID as a device ID. If a command such as a read BID command or the like is issued from the CPU 20 when emulation
 5 is not executed (when ES is 00, 10, 20, 22, 30, 31, 32, 33, 50, 51, 52 or 53), the control unit 42 of the I/F converting apparatus 40 according to the second embodiment issues a read position command to the device (MCU10/MTU30) to obtain ID, and reports it to
 10 the CPU 20, as before.

The pre-process (Step S1) and the post-process (Step S5) described above are carried out according to control tables (control matrices; cf. FIGS. 84 to 115) according to a type of command and
 15 an identification pattern for EOFs. Hereinafter, the pre-process and the post-process carried out according to a type of command and an identification pattern for EOFs will be described in detail with reference to FIGS. 84 through 115.

20 [2-2-5-1] RD (Read) Process

① RD Process in Pattern 1 (cf. FIG. 84)

When the I/F converting apparatus 40 receives an RD command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP
 25 in the pre-process. When the control unit 42 recognizes that ES=00 [cf. FIG. 70(A)], the control unit 42 makes the MTU 30 carry out a real operation

(real READ). In the post-process, the control unit 42 determines whether a type of a data block read by the MTU 30 is a tape mark (hereinafter abbreviated as TM) or any other than it. When it is determined that the data block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES (control area 46a) to "10" in the RAM 46 (process ID = 1.00.00). When it is determined that the data block is other than TM in the post-process, the control unit 42 holds ES=00 in the RAM 46 (process ID = 1.00.01).

When it is recognized that ES=10 in the pre-process [cf. FIG. 70(B)], the control unit 42 makes the MTU 30 carry out the real operation (real READ). In the post-process, the control unit 42 determines which one the type of a data block read by the MTU 30 is of EOF, TM or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 1.10.00). When it is determined in the post-process that the data block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and holds ES=10 in the RAM 46 (process ID = 1.10.01). When it is determined in the post-process that the data block is other than EOF and TM, the control unit 42 updates

ES to "00" in the RAM 46 (process ID = 1.10.02).

When it is recognized in the pre-process that ES=20 [cf. FIG. 70(C)], the control unit 42 makes the MTU 30 carry out the real operation (real READ). In the post-process, the control unit 42 determines which one the type of a data block read by the MTU 30 is of EOF, TM or any other. When it is determined that the data block is EOF (EOF2), the control unit 42 saves the data block (EOF2) in the save area (SDT2) 46d in the RAM 46, and updates ES to "30" in the RAM 46 (process ID = 1.20.00). When it is determined in the post-process that the data block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 1.20.01). When it is determined in the post-process that the data block is other than EOF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 1.20.02).

When it is recognized in the pre-process that ES=30 [cf. FIG. 70(D)], the control unit 42 makes the MTU 30 carry out the real operation (real READ). In the post-process, the control unit 42 determines whether the type of a data block read in the MTU 30 is TM or any other. When it is determined that the data block is TM, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the save area 46e [(real BID) - (SBID)]. When

When it is recognized in the pre-process that ES=40 and EP=-1 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding
 5 ES at a value of "40" in the RAM 46 (process ID = 1.40.30).

When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 70(E)], the control unit 42 makes the MTU 30 carry out the real operation (real
 10 READ). In the post-process, the control unit 42 determines which one the type of a data block read by the MTU 30 is of EOF, TM or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save
 15 area (SDT1) 46c in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 1.40.40). When it is determined in the post-process that the data block is TM, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the
 20 save area 46e [(real BID) - (SBID)]. When confirming that the difference is "1", the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "50" in the RAM 46 (process ID = 1.40.41). When it is determined in the
 25 post-process that the data block is other than EOF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 1.40.42).

ES=60 and EP=-1 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "60" in the RAM 46 (process ID =
 5 1.60.30).

When it is recognized in the pre-process that ES=60 and EP=0 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding
 10 ES at a value of "60" in the RAM 46 (process ID = 1.60.40).

When it is recognized in the pre-process that ES=60 and EP=+1 [cf. FIG. 70(G)], the control unit 42 re-positions the head at a position SBID+EP [position
 15 n+5 in FIG. 70(G)] in the MTU 30, then makes the MTU 30 carry out the real operation (real REA). In the post-process, the control unit 42 determines which one the type of a data block read by the MTU 30 is of EOF, TM or any other. When it is determined that the data
 20 block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, adds 1 to SBID in the RAM 46, and updates ES to "20" in the RAM 64 (process ID = 1.60.50). When it is determined in the post-process that the data block
 25 is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 1.60.51).

n+2 in FIG. 71(E)] in the MTU 30, then makes the MTU 30 carry out a real operation (real READ). In the post-process, the control unit 42 determines whether the type of a data block read by the MTU 30 is EOF or
 5 any other. When it is determined that the data block is EOF (EOF2), the control unit 42 saves the data block (EOF2) in the save area (SDT2) 46d in the RAM 46, subtracts 3 from SBID in the RAM 46, and updates ES to "30" in the RAM 46 (process ID = 1.41.20). When
 10 it is determined in the post-process that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 1.41.21).

When it is recognized in the pre-process that ES=41 and EP=-1 [cf. FIG. 71(E)], the control unit 42
 15 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding EP at a value of "41" in the RAM 46 (process ID = 1.41.30).

When it is recognized in the pre-process that
 20 ES=41 and EP=0 [cf. FIG. 71(E)], processes almost similar to those of process IDs = 1.40.40, 1.40.41 and 1.40.42 described above are carried out in the pre-process and the post-process (process IDs = 1.41.40, 1.41.41, 1.41.42). Note that ES is updated
 25 to "51" in the post-process of process ID = 1.41.41.

When it is recognized in the pre-process that ES=51 [cf. FIG. 71(F)], processes almost similar to

those of process IDs = 1.10.00, 1.10.01 and 1.10.02 described above are carried out in the pre-process and the post-process (process IDs = 1.51.00, 1.51.01, 1.51.02).

5 When it is recognized in the pre-process that ES=61 and EP=-4 [cf. FIG. 71(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates ES to "-3" while holding ES at a value of "61" in the RAM 46 (process ID =
10 1.61.00).

 When it is recognized in the pre-process that ES=61 and EP=-3 [cf. FIG. 71(G)], the control unit 42 executes emulation of the MTU 30, and restores a data block (EOF1) in the save area (SDT1) 46c in the RAM
15 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "61" in the RAM 46 (process ID = 1.61.10).

 When it is recognized in the pre-process that ES=61 and EP=-2 [cf. FIG. 71(G)], processes almost
20 similar to those of process IDs = 1.41.20 and 1.41.21 described above are carried out in the pre-process and the post-process (process IDs = 1.61.20, 1.61.21).

 When it is recognized in the pre-process that ES=61 and EP=-1 [cf. FIG. 71(G)], the control unit 42
25 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "61" in the RAM 46 (process ID =

1.61.30).

When it is recognized in the pre-process that ES=61 and EP=0 [cf. FIG. 71(G)], the control unit 42 executes emulation of the MTU 30. In the post-process,
 5 the control unit 42 updates EP to "+1" while holding ES at a value of "61" in the RAM 46 (process ID = 1.61.40).

When it is recognized in the pre-process that ES=61 and EP=+1 [cf. FIG. 71(G)], processes almost
 10 similar to those of process IDs = 1.60.50, 1.60.51 and 1.60.52 described above are carried out in the pre-process and the post-process (process IDs = 1.61.50, 1.61.51, 1.61.52).

③ RD Process in Pattern 3 (cf. FIG. 86)

15 When it is recognized in the pre-process that ES=22 [cf. FIG. 72(C)], processes almost similar to those of process IDs = 1.20.00, 1.20.01 and 1.20.02 described above are carried out in the pre-process and the post-process (process IDs = 1.22.00, 1.22.01,
 20 1.22.02). Note that ES in the RAM 46 is updated to "32" in the post-process of process ID = 1.22.00.

When it is recognized in the pre-process that ES=32 [cf. FIG. 72(D)], processes almost similar to those of process IDs = 1.31.00 and 1.31.01 described
 25 above are carried out in the pre-process and the post-process (process IDs = 1.32.00, 1.32.01). Note that ES in the RAM 46 is updated to "42" in the

control unit 42 updates EP to "-1" while holding ES at a value of "42" in the RAM 46 (process ID = 1.42.20).

When it is recognized in the pre-process that ES=42 and EP=-1 [cf. FIG. 72(E)], the control unit 42
 5 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "42" in the RAM 46 (process ID = 1.42.30).

When it is recognized in the pre-process that
 10 ES=42 and EP=0 [cf. FIG. 72(E)], processes almost similar to those of process IDs = 1.40.40, 1.40.41 and 1.40.42 described above are carried out in the pre-process and the post-process (process IDs = 1.42.40, 1.42.41, 1.42.42). Note that ES in the RAM
 15 46 is updated to "52" in the post-process of process ID = 1.42.41.

When it is recognized in the pre-process that ES=52 [cf. FIG. 72(F)], processes similar to those of process IDs = 1.10.00, 1.10.01 and 1.10.02 described
 20 above are carried out in the pre-process and the post-process (process IDs = 1.52.00, 1.52.01, 1.52.02).

When it is recognized in the pre-process that ES=62 and EP=-4 [cf. FIG. 72G]], the control unit 42
 25 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "62" in the RAM 46 (process ID =

00000"00000000

1.62.00).

When it is recognized in the pre-process that ES=62 and EP=-3 [cf. FIG. 72(G)], processes similar to those of process IDs = 1.42.10 and 1.42.11 described above are carried out in the pre-process and the post-process (process IDs = 1.62.10, 1.62.11).

When it is recognized in the pre-process that ES=62 and EP=-2 [cf. FIG. 72(G)], the control unit 42 executes emulation of the MTU 30, and restores a data block (EOF2) in the save area (SDT2) 46d in the RAM 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "62" in the RAM 46 (process ID = 1.62.20).

When it is recognized in the pre-process that ES=62 and EP=-1 [cf. FIG. 72(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "62" in the RAM 64 (process ID = 1.62.30).

When it is recognized in the pre-process that ES=62 and EP=0 [cf. FIG. 72(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding ES at a value of "62" in the RAM 64 (process ID = 1.62.40).

When it is recognized in the pre-process that ES=62 and EP=+1 [cf. FIG. 72(G)], processes similar

process (process IDs = 1.43.20, 1.43.21). Note that ES in the RAM 46 is updated to "32" in the post-process of process ID = 1.43.20.

When it is recognized in the pre-process that
 5 ES=43 and EP=-1 [cf. FIG. 73(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit updates EP to "0" while holding ES at a value of "43" in the RAM 46 (process ID = 1.43.30).

When it is recognized in the pre-process that
 10 ES=41 and EP=0 [cf. FIG. 73(E)], processes almost similar to those of process IDs = 1.40.40, 1.40.41 and 1.40.42 described above are carried out in the pre-process and the post-process (process IDs = 1.43.40, 1.43.41, 1.43.42). Note that ES in the RAM
 15 46 is updated to "53" in the post-process of process ID = 1.43.41.

When it is recognized in the pre-process that ES=53 [cf. FIG. 73(F)], processes similar to those of process IDs = 1.10.00, 1.10.01 and 1.10.02 described
 20 above are carried out in the pre-process and the post-process (process IDs = 1.53.00, 1.53.01, 1.53.02).

When it is recognized in the pre-process that ES=63 and EP=-4 [cf. FIG. 73(G)], the control unit 42
 25 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "63" in the RAM 46 (process ID =

to those of process IDs = 1.60.50, 1.60.51 and 1.60.52 are carried out in the pre-process and the post-process (process IDs = 1.63.50, 1.63.51, 1.63.52).

[2-2-5-2] RB (Read Backward) Process

5 Like the MTC 10 according to the first embodiment, the I/F converting apparatus 40 according to the second embodiment makes an error report to the CPU 20 when receiving an RB command from the CPU 20. When making the MTU 30 really carry out a read backward
10 operation (real RB) in the RB process, the I/F converting apparatus 40 updates ES to "00" as will be described later. When executing emulation of the MTU 10, the I/F converting unit 40 updates EP while holding ES=4x or 6x, as will be described later.

15 ① RB Process in Pattern 1 (cf. FIG. 88)

 When the I/F converting apparatus 40 receives an RB command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES=00
20 [cf. FIG. 70(A)], the control unit 42 makes the MTU 30 carry out a real operation (real RB). In the post-process, the control unit 42 holds ES=00 in the RAM 46 (process ID = 2.00.00).

 When it is recognized in the pre-process that
25 ES=10 [cf. FIG. 70(B)], the control unit 42 makes the MTU 30 carry out the real operation (real RB). In the post-process, the control unit 42 updates ES to "00"

IDs = 2.32.00 to 2.62.50 shown in FIG. 90 correspond to the processes of process IDs = 2.30.00 to 2.60.50 shown in FIG. 88, respectively. Note that ES in the RAM 46 is updated to "42" in the post-processes of process IDs = 2.42.10 and 2.42.40, and ES in the RAM 46 is updated to "62" in the post-processes of process IDs = 2.52.00 and 2.62.10, 2.62.40 to 2.62.50.

④ RB Process in Pattern 4 (cf. FIG. 91).

As shown in FIG. 91, pre-processes and post-processes in the RB process in Pattern 4 are almost similar to the pre-processes and the post-processes in the RB process in Pattern 1 described above with reference to FIG. 88. Processes of process IDs = 2.33.00 to 2.63.50 shown in FIG. 91 correspond to the processes of process IDs = 2.30.00 to 2.60.50 shown in FIG. 88, respectively. Note that ES in the RAM 46 is updated to "43" in the post-processes of process IDs = 2.43.10 to 2.43.40, and ES in the RAM 46 is updated to "63" in the post-processes of process IDs = 2.53.00 and 2.63.10 to 2.63.50.

[2-2-5-3] WR (Write) Process

① WR Process in Pattern 1 (cf. FIG. 92)

When the I/F converting apparatus 40 receives a WR command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES=00 [cf. 70(A)], the control unit 42 makes the MTU 30 carry

42 updates ES to "00" in the RAM 46 (process ID = 3.20.01).

When it is recognized in the pre-process that ES=30 [cf. FIG. 70(D)], the control unit 42 makes the
 5 MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.30.00).

When it is recognized in the pre-process that ES=40 and EP=-4 [cf. FIG. 70(E)], the control unit 42
 10 re-positions the head at a position SBID+EP [position n in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.40.00).

15 When it is recognized in the pre-process that ES=40 and EP=-3 [cf. FIG. 70(E)], the control unit 42 re-positions the head at a position SBID+EP [position n+1 in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the
 20 post-process, the control unit 42 determines whether the type of a data block written by the MTU 30 is EOF or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data block in the save area (SDT1) 46c in the RAM 46,
 25 subtracts 3 from SBID in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 3.40.10). When it is determined in the post-process that the data

block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.40.11).

When it is recognized in the pre-process that ES=40 and EP=-2 [cf. FIG. 70(E)], the control unit 42
 5 re-positions the head at a position SBID+EP [position n+2 in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 determines whether the type of a data block written by the MTU 30 is EOF
 10 or any other. When it is determined that the data block is EOF (EOF2), the control unit 42 saves the data block (EOF2) in the save area (SDT2) 46d in the RAM 46, subtracts 3 from SBID in the RAM 46, and updates ES to "30" in the RAM 46 (process ID = 3.40.20). When
 15 it is determined in the post-process that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.40.21).

When it is recognized in the pre-process that ES=40 and EP=-1 [cf. FIG. 70(E)], the control unit 42
 20 re-positions the head at a position SBID+EP [position at n+3 in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.40.30).

25 When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 70(E)], processes similar to those of process IDs = 3.10.00 and 3.10.01 described

When it is recognized in the pre-process that ES=60 and EP=0 [cf. FIG. 70(G)], processes similar to those of process IDs = 3.10.00 and 3.10.01 described above are carried out in the pre-process and the
 5 post-process (process IDs = 3.60.40, 3.60.41).

When it is recognized in the pre-process that ES=60 and EP=+1 [cf. FIG. 70(G)], the control unit 42 re-positions the head at a position SBID+EP [position n+5 in FIG. 70(G)] in the MTU 30, and makes the MTU
 10 30 carry out the real operation (real WR). In the post-process, the control unit 42 determines whether the type of a data block written by the MTU 30 is EOF or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data
 15 block (EOF1) in the save area (SDT1) 46c in the RAM 46, adds 1 to SBID in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 3.60.50). When it is determined in the post-process that the data block is other than EOF, the control unit updates ES to "00"
 20 in the RAM 46 (process ID = 3.60.51).

② WR Process in Pattern 2 (cf. FIG. 93)

As shown in FIG. 93, pre-processes and post-processes in the WR process in Pattern 2 are similar to the pre-processes and the post-processes
 25 in the WR process in Pattern 1 described above with reference to FIG. 92. Processes of process IDs = 3.31.00 to 3.61.51 shown in FIG. 93 correspond to the

post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 4.40.00).

When it is recognized in the pre-process that ES=40 and EP=-3 [cf. FIG. 70(E)], the control unit 42
5 executes emulation of the MTU 30. In the post-process, the control unit 42 updates ES to "-4" while holding ES at a value of "40" in the RAM 46 (process ID = 4.40.10).

When it is recognized in the pre-process that
10 ES=40 and EP=-2 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "40" in the RAM 46 (process ID = 4.40.20).

When it is recognized in the pre-process that
15 ES=40 and EP=-1 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "40" in the RAM 46 (process ID =
20 4.40.30).

When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 70(E)], the control unit 42
executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-1" while holding
25 ES at a value of "40" in the RAM 46 (process ID = 4.40.40).

When it is recognized in the pr-process that

ES=50 [cf. FIG. 70(F)], the control unit 42 makes the MTU 30 carry out the real operation (real BSP). In the post-process, when TM is detected during the back space operation, the control unit 42 determines a
 5 difference between a real BID of the TM and BID stored in the save area 46e [(SBID) - (real BID)]. When confirming that the difference is "1", the control unit stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "60" and EP to
 10 "0" in the RAM 46 (process ID = 4.50.00).

When it is recognized that ES=60 and EP=-4 [cf. FIG. 70(G)], the control unit 42 re-positions the head at a position SBID+EP [position n in FIG. 70(G)] in the MTU 30, and makes the MTU 30 carry out the real
 15 operation (real BSP). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 4.60.00).

When it is recognized in the pre-process that ES=60 and EP=-3 [cf. FIG. 70(G)], the control unit 42
 20 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "60" in the RAM 46 (process ID = 4.60.10).

When it is recognized in the pre-process that
 25 ES=60 and EP=-2 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding

shown in FIG. 96, respectively. Note that ES in the RAM 46 is updated to "41" in the post-processes of process IDs = 4.41.10 to 4.41.40, and ES in the RAM 46 is updated to "61" in the post-processes of process
 5 IDs = 4.51.00 and 4.61.10 to 4.61.50.

③ BSP Process in Pattern 3 (cf. FIG. 98)

As shown in FIG. 98, pre-processes and post-processes in the BSP process in Pattern 3 are almost similar to the pre-processes and the post-
 10 processes in the BSP process in Pattern 1 described above with reference to FIG. 96. Processes of process IDs = 4.22.00 to 4.62.50 shown in FIG. 98 correspond to the processes of process IDs = 4.20.00 to 4.60.50 shown in FIG. 96, respectively. Note that ES in the
 15 RAM 46 is updated to "22" in the post-process of process ID = 4.32.00, ES in the RAM 46 to "42" in the post-processes of process IDs = 4.42.10 to 4.42.40, and ES in the RAM 46 to "62" in the post-processes of process IDs = 4.52.00 and 4.62.10 to 4.62.50.

20 ④ BSP Process in Pattern 4 (cf. FIG. 99)

As shown in FIG. 99, pre-processes and post-processes in the BSP process in Pattern 4 are almost similar to the pre-processes and the post-
 processes in the BSP process in Pattern 1 described
 25 above with reference to FIG. 96. Processes of process ID = 4.33.00 to 4.63.50 shown in FIG. 99 correspond to the processes of process IDs = 4.30.00 to 4.60.50

When it is recognized in the pre-process that ES=60 and EP=-3 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding
5 ES at a value of "60" in the RAM 46 (process ID = 5.60.10).

When it is recognized in the pre-process that ES=60 and EP=-2 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process,
10 the control unit 42 updates EP to "-4" while holding ES at a value of "60" in the RAM 64 (process ID = 5.60.20).

When it is recognized in the pre-process that ES=60 and EP=-1 [cf. FIG. 70(G)], the control unit 30
15 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "60" in the RAM 46 (process ID = 5.60.30).

When it is recognized in the pre-process that
20 ES=60 and EP=0 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 update EP to "-1" while holding ES at a value of "60" in the RAM 46 (process ID = 5.60.40).

25 When it is recognized in the pre-process that ES=60 and EP=+1 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process,

the control unit 42 updates EP to "0" while holding ES at a value of "60" in the RAM 46 (process ID = 5.60.50).

② BSPF Process in Pattern 2 (cf. FIG. 101)

5 As shown in FIG. 101, pre-processes and post-processes in the BSPF process in Pattern 2 are almost similar to the pre-processes and the post-processes in the BSPF process in Pattern 1 described above with reference to FIG. 100. Processes of
10 process IDs = 5.31.00 to 5.61.50 correspond to the processes of process IDs = 5.30.00 to 5.60.50 shown in FIG. 100, respectively. Note that ES in the RAM 46 is updated to "41" in the post-processes of process IDs = 5.41.10 to 5.41.40, and ES in the RAM 46 is
15 updated to "61" in the post-processes of process IDs = 5.51.00 and 5.61.10 to 5.61.50.

③ BSPF Process in Pattern 3 (cf. FIG. 102)

 As shown in FIG. 102, pre-processes and post-processes in the BSPF process in Pattern 3 are
20 almost similar to the pre-processes and the post-processes in the BSPF process in Pattern 1 described above with reference to FIG. 100. Processes of process IDs = 5.22.00 to 5.62.50 correspond to the processes of process IDs = 5.20.00 to 5.60.50 shown
25 in FIG. 100, respectively. Note that ES in the RAM 46 is updated to "42" in the post-processes of process IDs = 5.42.10 to 5.42.40, and ES in the RAM 46 is

updated to "62" in the post-processes of process IDs
= 5.52.00 and 5.62.10 to 5.62.50.

④ BSPF Process in Pattern 4 (cf. FIG. 103)

As shown in FIG. 103, pre-processes and
5 post-processes in the BSPF process in Pattern 4 are
almost similar to the pre-processes and the post-
processes in the BSPF process in Pattern 1 described
above with reference to FIG. 100. Processes of
process IDs = 5.33.00 to 5.63.50 correspond to the
10 processes of process IDs = 5.30.00 to 5.60.50 shown
in FIG. 100, respectively. Note that ES in the RAM
46 is updated to "43" in the post-processes of process
IDs = 5.43.10 to 5.43.40, and ES in the RAM 46 is
updated to "63" in the post-processes of process IDs
15 = 5.53.00 and 5.63.10 to 5.63.50.

[2-2-5-6] SP (Forward Space Block) Process

① SP Process in Pattern 1 (cf. FIG. 104)

When the I/F converting apparatus 40 receives
an SP command, the control unit 42 first refers to the
20 RAM 46 to recognize a value of ES and a value of EP.
When it is recognized that ES=00 [cf. FIG. 70(A)], the
control unit 42 makes the MTU 30 carry out a real
operation (real SP). In the post-process, the
control unit 42 determines whether the type of a data
25 block detected during the forward space operation in
the MTU 30 is TM or any other. When it is determined
that the data block is TM, the control unit 42 stored

space operation in the MTU 30 is of EOF, TM or any other. When it is determined that the data block is EOF (EOF2), the control unit 42 updates ES to "31" in the RAM 46 (process ID = 6.20.00). when it is determined in the

5 post-process that the data block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 6.20.01). When it is determined in the post-process that the data block is

10 other than EOF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 6.20.02).

When it is recognized in the pre-process that ES=30 [cf. FIG. 70(D)], the control unit 42 makes the MTU 30 carry out the real operation (real SP). In the

15 post-process, the control unit 42 determines whether the type of a data block detected during the forward space operation in the MTU 30 is TM or any other. When it is determined that the data block is TM, the control unit 42 determines a difference between a real BID of

20 the TM and SBID stored in the save area 46e [(real BID) - (SBID)]. When confirming that the difference is "3", the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "40" and EP to "0" in the RAM 46 (process ID = 6.30.00).

25 When it is determined in the post-process that the data block is other than TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 6.30.01).

5

10

15

20

25

SP). In the post-process, the control unit 42 determines which one the type of a data block detected during the forward space operation is of EOF, TM or any other. When it is determined that the data block
 5 is EOF (EOF1), the control unit 42 updates ES to "22" in the RAM 46 (process ID = 6.40.40). It is determined in the post-process that the data block is TM, the control unit 42 determines a difference between a real
 10 BID of the TM and SBID stored in the save area 46e $[(real\ BID) - (SBID)]$. When confirming that the difference is "1", the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates Es to "50" in the RAM 46 (process ID = 6.40.41). When it is determined that the data block
 15 is other than OEF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 6.40.42).

When it is recognized in the pre-process that ES=50 [cf. FIG. 70(F)], processes almost similar to the processes of process IDs = 6.10.00, 6.10.01 and
 20 6.10.02 described above are carry out in the pre-processes and the post-processes (process IDs = 6.50.00, 6.50.01, 6.50.02). Note that ES in the RAM 46 is updated to "22" in the post-process of process ID = 6.50.00.

25 When it is recognized in the pre-process that ES=60 and EP=-4 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process,

the control unit 42 updates ES to "-3" while holding ES at a value of "60" in the RAM 46 (process ID = 6.60.00).

When it is recognized in the pre-process that
5 ES=60 and EP=-3 [cf. FIG. 70(G)], the control unit 42
executes emulation of the MTU 30. In the post-process,
the control unit 42 updates EP to "-2" while holding
ES at a value of "60" in the RAM 46 (process ID =
6.60.10).

10 When it is recognized in the pre-process that
ES=60 and EP=-2 [cf. FIG. 70(G)], the control unit 42
executes emulation of the MTU 30. In the post-process,
the control unit 42 updates EP to "-1" while holding
ES at a value of "60" in the RAM 46 (process ID =
15 6.60.20).

When it is recognized in the pre-process that ES=60 and EP=-1 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding
20 ES at a value of "60" in the RAM 46 (process ID = 6.60.30).

When it is recognized in the pre-process that ES=60 and EP=0 [cf. FIG. 70(G)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding ES at a value of "60" in the RAM 46 (process ID = 6.60.40).

When it is recognized in the pre-process that ES=60 and EP=+1 [cf. FIG. 70(G)], the control unit 42 re-positions the head at a position SBID+EP [position at n+5 in FIG. 70(G)] in the MTU 30, and makes the MTU 30 carry out the real operation (real SP). In the post-process, the control unit 42 determines which one the type of a data block detected during the forward space operation in the MTU 30 is of EOF, TM or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 adds 1 to SBID in the RAM 46, and updates ES to "22" in the RAM 46 (process ID = 6.60.50). When it is determined in the post-process that the data block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e, and updates ES to "10" in the RAM 46 (process ID = 6.60.51). When it is determined in the post-process that the data block is other than OEF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 6.60.52).

② SP Process in Pattern 2 (cf. FIG. 105)

As shown in FIG. 105, pre-processes and post-processes in the SP process in Pattern 2 are almost similar to the pre-processes and the post-processes in the SP process in Pattern 1 described above with reference to FIG. 104. Processes of process IDs = 6.31.00 to 6.61.52 shown in FIG. 105 correspond to the processes of process IDs = 6.30.00 to 6.60.52 shown in FIG. 104, respectively.

Note that ES in the RAM 46 is updated to "41" in the post-processes of process IDs = 6.31.00 and 6.41.00 to 6.41.30, ES in the RAM 46 to "51" in the post-process of process ID = 6.41.41, and ES in the RAM 46 to "61" in the post-processes of process IDs = 6.61.00 to 6.61.40.

③ SP Process in Pattern 3 (cf. FIG. 106)

As shown in FIG. 106, pre-processes and post-processes in the SP process in Pattern 3 are almost similar to the pre-processes and the post-processes in the SP process in Pattern 1 described above with reference to FIG. 104. Processes of process IDs = 6.22.00 to 6.62.52 shown in FIG. 106 correspond to the processes of process IDs = 6.20.00 to 6.60.52 shown in FIG. 104, respectively.

Note that ES in the RAM 46 is updated to "22" in the post-processes of process IDs = 6.42.40, 6.52.00 and 6.62.50, ES in the RAM 46 to "33" in the post-process of process ID = 6.22.00, ES in the RAM 46 to "42" in the post-processes of process IDs = 6.32.00, and 6.42.00 to 6.42.30, ES in the RAM 46 to "52" in the post-process of process ID = 6.42.41, and ES in the RAM 46 to "62" in the post-processes of process IDs = 6.62.00 to 6.62.40.

④ SP Process in Pattern 4 (cf. FIG. 107)

As shown in FIG. 107, pre-processes and post-processes in the SP process in Pattern 4 are

5

10

15

①

20

25

5

10

25

post-process, processes almost similar to the post-processes of process IDs = 7.10.00 to 7.10.02 described above are carried out (process IDs = 7.20.00 to 7.20.02). Note that ES in the RAM 46 is updated to "41" in the post-process of process ID = 7.20.00.

When it is recognized in the pre-process that ES=30 [cf. FIG. 70(D)], in the pre-process and the post-processes, processes almost similar to the post-processes of process IDs = 7.10.00 to 7.10.02 described above are carried out (process IDs = 7.30.00 to 7.30.02). Note that ES in the RAM 46 is updated to "40" in the post-process of process ID = 7.30.00.

When it is recognized in the pre-process that ES=40 and EP=-4 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "40" in the RAM 46 (process ID = 7.40.00).

When it is recognized in the pre-process that ES=40 and EP=-3 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "40" in the RAM 46 (process ID = 7.40.10).

When it is recognized in the pre-process that ES=40 and EP=-2 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process,

the control unit 42 updates EP to "0" while holding ES at a value of "40" in the RAM 46 (process ID = 7.40.20).

When it is recognized in the pre-process that
 5 ES=40 and EP=-1 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "40" in the RAM 46 (process ID = 7.40.30).

10 When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 70(E)], the control unit 42 makes the MTU 30 execute the real operation (real FSPF). In the post-process, the control unit determines whether the type of a data block detected during the
 15 forward space operation in the MTU 30 is TM or any other. When it is determined that the data block is TM, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the save area 46e [(real BID) - (SBID)]. When the difference is "3",
 20 the control unit 42 stores the real BID of the TM in the save area (SBID) 46e, and updates ES to "43" and EP to "0" in the RAM 46 (process ID = 7.40.40). When the difference is "1", the control unit 42 stores the real BID of the TM in the save area (SBID) 46e in the
 25 RAM 46, and updates ES to "50" in the RAM 46 (process ID = 7.40.41). When the difference is neither 1 nor 3, the control unit 42 stores the real BID of the TM

correspond to the processes of process IDs = 7.30.00 to 7.60.52 shown in FIG. 108, respectively. Note that ES in the RAM 46 is updated to "41" in the post-processes of process IDs = 7.31.00 and 7.41.00 to 7.41.30, ES in the RAM 46 to "43" in the post-processes of process IDs = 7.41.40, 7.51.00 and 7.61.50, ES in the RAM 46 to "51" in the post-process of process ID = 7.41.41, and ES in the RAM 46 to "61" in the post-processes of process IDs = 7.61.00 to 7.61.40.

10 ③ FSPF Process in Pattern 3 (cf. FIG. 110)

As shown in FIG. 110, pre-processes and post-processes in the FSPF process in Pattern 3 are almost similar to the pre-processes and the post-processes in the FSPF process in Pattern 1 described above with reference to FIG. 108. Processes of process IDs = 7.22.00 to 7.62.52 shown in FIG. 110 correspond to the processes of process IDs = 7.20.00 to 7.60.52 shown in FIG. 108, respectively. Note that ES in the RAM 46 is updated to "43" in the post-processes of process IDs = 7.22.00, 7.42.40, 7.52.00 and 7.62.50, ES in the RAM 46 to "42" in the post-processes of process IDs = 7.32.00 and 7.42.00 to 7.42.40, ES in the RAM 46 to "52" in the post-process of process ID = 7.42.41, and ES in the RAM 46 to "62" in the post-processes of process IDs = 7.62.00 to 7.62.40.

④ FSPF Process in Pattern 4 (cf. FIG. 111)

As shown in FIG. 111, pre-processes and post-processes in the FSPF process in Pattern 4 are almost similar to the pre-processes and the post-processes in the SFPF process in Pattern 1 described above with reference to FIG. 108. Processes of process IDs = 7.33.00 to 7.63.52 correspond to the processes of process IDs = 7.30.00 to 7.60.52 shown in FIG. 108. Note that ES in the RAM 46 is updated to "43" in the post-processes of process IDs = 7.33.00, 7.43.00 to 7.43.40, 7.53.00, and 7.63.50, ES in the RAM 46 to "53" in the post-process of process ID = 7.43.41, and ES in the RAM 46 to "63" in the post-processes of process IDs = 7.63.00 to 7.63.40.

[2-2-5-8] WTM (Write Tape Mark) Process

In the MTU 30, when a writing is carried out in response to a command in the write system (WR, WTM), an EOD (End Of Data) mark is written after a written data block. Therefore, the host (CPU 20) recognizes that there is no data block after a data block having been written in response to a command in the write system after the command in the write system is carried out. According to the second embodiment, when ES = 00, 10 or 2x, or when ES = 4x and EP = -4, -3 or -2, or when ES = 6x and EP = -4, -3, -2, -1 or +1, ES is updated to "10" whenever the real write tape mark operation is carried out, as will be described later with reference to FIGS. 112 through 115.

① WTM Process in Pattern 1 (cf. FIG. 112)

When the I/F converting apparatus 40 receives a WTM command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP.

- 5 When it is recognized that ES=00 [cf. FIG. 70(A)], the control unit 42 makes the MTU 30 carry out a real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46,
10 and holds ES=10 in the RAM 46 (process ID = 8.00.00).

- When it is recognized in the pre-process that ES=10 [cf. FIG. 70(B)], the control unit 42 makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real
15 BID of a TM written by the MTU 30 in a save area (SBID) 46e in the RAM 46, and holds ES at a value of "10" in the RAM 46 (process ID = 8.10.00).

- When it is recognized in the pre-process that ES=20 [cf. FIG. 70(C)], the control unit 42 makes the
20 MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.20.00).

- 25 When it is recognized in the pre-process that ES=30 [cf. FIG. 70(D)], the control unit 42 makes the MTU 30 carry out the real operation (real WTM). In

the post-process, the control unit 42 determines a difference between a real BID of a TM written by the MTU 30 and SBID stored in the save area 46e [(real BID) - (SBID)]. When confirming that the difference is "3",
 5 the control unit 42 stores the real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "40" and EP to "0" in the RAM 46 (process ID = 8.30.00).

When it is recognized in the pre-process that
 10 ES=40 and EP=-4 [cf. FIG. 70(E)], the control unit 42 re-positions the head at a position SBID+EP [position n in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID
 15 of a TM written by the MTU 30 in a save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.40.00).

When it is recognized in the pre-process that
 20 ES=40 and EP=-3 [cf. FIG. 70(E)], the control unit 42 re-positions the head at a position SBID+EP [position n+1 in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID
 25 of a TM written by the MTU 30 in a save area (SBID) 46e, and updates ES to "10" in the RAM 46 (process ID = 8.40.10).

When it is recognized in the pre-process that

ES=40 and EP=-2 [cf. FIG. 70(E)], the control unit 42 re-positions the head at a position SBID+EP [position n+2 in FIG. 70(E)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.40.20).

When it is recognized in the pre-process that ES=40 and EP=-1 [cf. FIG. 70(E)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "40" in the RAM 46 (process ID = 8.40.30).

When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 70(E)], the control unit 42 makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 determines a difference between a real BID of a TM written by the MTU 30 and SBID stored in the save area 46e [(real BID) - (SBID)]. When confirming that the difference is "1", the control unit 42 stores the real BID of the TM in the save area (SBID) 46e, and updates ES to "50" in the RAM 46 (process ID = 8.40.40).

When it is recognized in the pre-process that ES=50 [cf. FIG. 70(F)], the control unit 42 makes the MTU 30 carry out the real operation (real WTM). In

the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.50.00).

- 5 When it is recognized in the pre-process that ES=60 and EP=-4 [cf. FIG. 70(G)], the control unit 42 re-positions the head at a position SBID+EP [position n in FIG. 70(G)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the
- 10 post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.60.00).

- When it is recognized in the pre-process that
- 15 ES=60 and EP=-3 [cf. FIG. 70(G)], the control unit 42 re-positions the head at a position SBID+EP [position n+1 in FIG. 70(G)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID
- 20 of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.60.10).

- When it is recognized in the pre-process that ES=60 and EP=-2 [cf. FIG. 70(G)], the control unit 42
- 25 re-positions the head at a position SBID+EP [position n+2 in FIG. 70(G)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the

5 When it is recognized in the pre-process that
ES=60 and EP=-1 [cf. FIG. 70(G)], the control unit 42
re-positions the head at a position SBID+EP [position
n+3 in FIG. 70(G)] in the MTU 30, and makes the MTU
30 carry out the real operation (real WTM). In the
10 post-process, the control unit 42 stores a real BID
of a TM written by the MTU 30 in the save area (SBID)
46e in the RAM 46, and updates ES to "10" in the RAM
46 (process ID = 80.60.30).

When it is recognized in the pre-process that
15 ES=60 and EP=0 [cf. FIG. 70(G)], the control unit 42
executes emulation of the MTU 30. In the post-process,
the control unit 42 updates EP to "+1" while holding
ES at a value of "60" in the RAM 46 (process ID =
8.60.40).

20 When it is recognized in the pre-process that
ES=60 and EP=+1 [cf. FIG. 70(G)], the control unit 42
re-positions the head at a position SBID+EP [position
at n+5 in FIG. 70(G)] in the MTU 30, and makes the MTU
30 carry out the real operation (real WTM). In the
25 post-process, the control unit 42 stores a real BID
of a TM written by the MTU 30 in the save area (SBID)
46e in the RAM 46, and updates ES to "10" in the RAM

46 (process ID = 8.60.50).

② WTM Process in Pattern 2 (cf. FIG. 113)

As shown in FIG. 113, pre-processes and post-processes in the WTM process in Pattern 2 are almost similar to the pre-processes and the post-processes in the WTM process in Pattern 1 described above with reference to FIG. 112. Processes of process IDs = 8.31.00 to 8.61.50 shown in FIG. 113 correspond to the processes of process IDs = 8.30.00 to 8.60.50 shown in FIG. 112, respectively.

Note that ES in the RAM 46 is updated to "41" in the post-processes of process IDs = 8.31.00 and 8.41.30, ES in the RAM 46 to "51" in the post-process of process ID = 8.41.40, and ES in the RAM 46 to "61" in the post-processes of process IDs = 8.61.40.

③ WTM Process in Pattern 3 (cf. FIG. 114)

As shown in FIG. 114, pre-processes and post-processes in the WTM process in Pattern 3 are almost similar to the pre-processes and the post-processes in the WTM process in Pattern 1 described above with reference to FIG. 112. Processes of process IDs = 8.22.00 to 8.62.50 shown in FIG. 114 correspond to the processes of process IDs = 8.20.00 to 8.60.50 shown in FIG. 112.

Note that ES in the RAM 46 is updated to "42" in the post-processes of process IDs = 8.32.00, 8.42.00 and 8.42.30, ES in the RAM 46 to "52" in the

post-process of process ID = 8.42.40, and ES in the RAM 46 to "62" in the post-processes of process IDs = 8.62.00, 8.62.30 and 8.62.40.

④ WTM Process in Pattern 4 (cf. FIG. 115)

5 As shown in FIG. 115, pre-processes and post-processes in the WTM process in Pattern 4 are almost similar to the pre-processes and the post-processes in the WTM process in Pattern 1 described above with reference to FIG. 112. Processes of
10 process IDs = 8.33.00 to 8.63.50 shown in FIG. 115 correspond to the processes of process IDs = 8.30.00 to 8.60.50 shown in FIG. 112, respectively.

 Note that ES in the RAM 46 is updated to "43" in the post-processes of process IDs = 8.33.00,
15 8.43.00 and 8.43.30, ES in the RAM 46 to "53" in the post-process of process ID = 8.43.40, and ES in the RAM 46 to "63" in the post-processes of process IDs = 8.63.00, 8.63.30 and 8.63.40.

[2-3] Practical Examples of Emulation Execution

20 With reference to FIGS. 116 through 174, description will be next made of practical examples of emulation executed applying the processes (including process IDs = 1.00.00 to 8.63.50) described above with reference to FIGS. 83 through 115 to the
25 control process of the I/F converting apparatus 40 (control unit 42).

[2-3-1] Example 1 of Emulation Execution

FIGS. 116(A) and 116(B) are diagrams showing a state of data writing on the magnetic tape MT, and for illustrating an example of commands issued from the CPU 20 when a multi-file is additionally written, and tape operations/emulation operations in the MTU 30 according to the second embodiment in response to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 are similar to those described above with reference to FIGS. 22(A) and 22(B) in the first embodiment, descriptions of which are thus omitted. An identification pattern for EOF1 and EOF2 in the example shown in FIGS. 116(A) and 116(B) is Pattern 1 described above with reference to FIGS. 69 and 70(A) through 70(G).

When the open process [cf. (8) to (22)] shown in FIGS. 116(A) and 116(B) is carried out, the I/F converting apparatus 40 (control unit 42) uses the method according to the second embodiment to emulate command processes (8) to (19) enclosed by broken lines in the drawings, as does in the first embodiment. During which, the I/F converting apparatus 40 does not perform any mechanical operation with the head H being stopped between the last two tape marks TM-b and TM-c, as shown in FIG. 116(A). According to the second embodiment, EOF1 saved in the save area (SDT1) 46c in

the RAM 46 is read out and transferred to the CPU 20 via the data buffer 45 when emulation is executed in response to an RD command (11).

Hereinafter, each of the command processing
 5 (1) to (24) shown in FIGS. 116(A) and 116(B) will be described in detail with reference to FIGS. 117 through 140.

(A) of FIGS. 117 to 140 shows a state of data
 block writing on the magnetic tape TM, a real head
 10 position (real BID) and a virtual head position (EP) when each of the command processing (1) through (24) are carried out. (B) of FIGS. 117 to 140 shows a state of data saving/storing in the RAM 46 when each of the command processing (1) through (24) are carried out.

15 (1) WR Process

FIG. 117(A) shows a state in which the I/F
 converting apparatus 40 receives a WR command (1)
 shown in FIG. 116(A) from the CPU 20, completes a
 writing of user data and is about to shift to the close
 20 process for a file. In FIG. 117(A), the real head position (real BID) is N. At this time, ES in the control area 46a in the RAM 46 indicates the initial state (ES=00), as shown in FIG. 117(B). Incidentally, the control area (EP) 46b and the save areas 46c to
 25 46e in the RAM 46 indicate the undetermined state.

(2) WTM Process

FIG. 118(A) shows a state in which the I/F

converting apparatus 40 receives a WTM command (2) shown in FIG. 116(A) from the CPU 20, carried out a process of process ID = 8.00.00 and completes a writing of a tape mark TM-a so that the real head position (real BID) is N+1. At this time, "10" is held as ES in the control area 46a and "N+1" is held as SBID in the save area 46e, as shown in FIG. 118(B).

(3) WR Process (EOF1 Write Process)

FIG. 119(A) shows a state in which the I/F converting apparatus 40 receives a WR command (3) (direction to write EOF1) shown in FIG. 116(A) from the CPU 20, carries out a process of process ID = 3.10.00, and completes a writing of EOF1 so that the real head position (real BID) is N+2. At this time, "20" is held as ES in the control area 47a, and EOF1 is stored in the save area (SDT1) 46c, as shown in FIG. 119(B). Thereafter, EOF1 is held in the save area 46e.

(4) WR Process (EOF2 Write Process)

FIG. 120(A) shows a state in which the I/F converting apparatus 40 receives a WR command (4) (direction to write EOF2) shown in FIG. 116(A) from the CPU 20, carried out a process of process ID = 3.20.00, and completes a writing of EOF2 so that the real head position (real BID) is N+3. At this time, "30" is held as ES in the control area 46a, and EOF2 is stored in the save area (SDT2) 46d, as shown in FIG.

(5) WTM Process

(6) WTM process

FIG. 122(A) shows a state in which the I/F converting apparatus 40 receives a WTM command (6) shown in FIG. 116(A) from the CPU 20, carries out a process of process ID = 8.40.40, and completes a writing of a tape mark TM-c so that the real head position (real BID) is n+5. At this time, the I/F converting apparatus 40 stores "N+5" as SBID in the save area 46e after checking that a difference between the real BID and SBID [(real BID) - (SBID)] is "1", as shown in FIG. 122(B). As shown in FIG. 122(B), "50" is held as ES in the control area 46a.

(7) BSPF Process

FIG. 123(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (7) shown in FIG. 116(A) from the CPU 20, carries out a process of process ID = 5.50.00, and completes the back space operation so that the real head position (real BID) is N+4. At this time, the I/F converting apparatus 40 stores "N+4" as SBID in the save area 46e after checking that a difference between the real BID and SBID [(real BID) - (SBID)] is "1", as shown in FIG. 123(B). As shown in FIG. 123(B), "60" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

(8) BSPF Process

FIG. 123(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (8) shown in FIG. 116(A) from the CPU 20, and carries out a process of process ID = 5.60.40 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 124(B), "60" is held as ES in the control area 46a, whereas "-1" is held as EP in the control area 46b.

(9) BSPF Process

FIG. 125(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (9) shown in FIG. 116(A) from the CPU 20, and carries out a process of process ID = 5.60.30 so as to execute

emulation. At this time, the real head position (real BID) is still $N+4$, not changed. As shown in FIG. 125(B), "60" is held as ES in the control area 46a, whereas "-4" is held as EP in the control area 46b.

5 (10) FSPF Process

FIG. 126(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (10) shown in FIG. 116(A) from the CPU 20, and carries out a process of process ID = 7.60.00 so as to execute
10 emulation. At this time, the real head position (real BID) is still $N+4$, not changed. As shown in FIG. 126(B), "60" is held as ES in the control area 46a, whereas "-3" is held as EP in the control area 46b.

(11) RD Process

15 FIG. 127(A) shows a state in which the I/F converting apparatus 40 receives an RD command (11) shown in FIG. 116(A), and carries out a process of process ID = 1.60.10 so as to execute emulation. At this time, the real head position (real BID) is still
20 $N+4$, not changed. As shown in FIG. 127(B), "60" is held as ES in the control area 46a, whereas "-2" is held as EP in the control area 46b. When the emulation is executed, contents EOF1 in the save area 46c are re-stored in the data buffer 45, and transferred to
25 the CPU 20.

(12) FSPF Process

FIG. 128(A) shows a state in which the I/F

converting apparatus 40 receives an FSPF command (12) shown in FIG. 116(A) from the CPU 20, and carries out a process of process ID = 7.60.20 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 128(B), "60" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

(13) RD Process

FIG. 129(A) shows a state in which the I/F converting apparatus 40 receives an RD command (13) shown in FIG. 116(A) from the CPU 20, and carries out a process of process ID = 1.60.40 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 129(B), "60" is held as ES in the control area 46a, whereas "+1" is held as EP in the control area 46b. When the emulation is execute, detection of a tape mark (Unit Exception) is reported to the CPU 20.

(14) BSPF Process

FIG. 130(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (14) shown in FIG. 116(A) from the CPU 20, and carries out a process of process ID = 5.60.50 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 130(B), "60" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

5

10

15

20

25

FIG. 133(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (17) shown in FIG. 116(B) from the CPU 20, and carries out the process of process ID = 7.60.00 so as to execute out emulation, as does in the command process (10). At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 133(B), "60"

(18) RD Process

(19) FSPF Process

(20) WR Process (HDR1 Write Process)

FIG. 136(A) shows a state in which the I/F

converting apparatus 40 receives a WR command (20) shown in FIG. 116(B) from the CPU 20, carries out a process of process ID = 3.60.41, and completes a writing of HDR1 so that the real head position (real
 5 BID) is N+5. At this time, "00" is held as ES in the control area 46a, whereas the control area 46b and the save areas 46c to 46e are in the undetermined state, as shown in FIG. 136(B).

(21) WR Process (HDR2 Write Process)

10 FIG. 137(A) shows a state in which the I/F converting apparatus 40 receives a WR command (21) (direction to write HDR2) shown in FIG. 116(B) from the CPU 20, carries out a process of process ID = 3.00.00, and completes a writing of HDR2 so that the
 15 real head position is N+6. At this time, "00" is held as ES in the control area 46a, whereas the control area 46b and the save areas 46c to 46e are in the undetermined state, as shown in FIG. 137(B).

(22) WTM Process

20 FIG. 138(A) shows a state in which the I/F converting apparatus 40 receives a WTM command (22) shown in FIG. 116(B) from the CPU 20, carries out a process of process ID = 8.00.00, and completes a writing of a tape mark TM-d so that the real head
 25 position (real BID) is N+7. At this time, "10" is held as ES in the control area 46a, whereas "N+7" is held as EP in the control area 46b, as shown in FIG. 138(B).

(23) WR Process

FIG. 139(A) shows a state in which the I/F converting apparatus 40 receives a WR command (23) (direction to write data 2) shown in FIG. 116(B) from the CPU 20, carries out a process of process ID = 3.10.01, and completes a writing of the data 2 so that the real head position (real BID) is N+8. At this time, "00" is held as ES in the control area 46a, whereas the control area 46b and the save areas 46c to 46e are in the undetermined state, as shown in FIG. 139(B).

(24) WR Process

FIG. 140(A) shows a state in which the I/F converting apparatus 40 receives a WR command (24) (direction to write data 2) shown in FIG. 116(B) from the CPU 20, carries out a process of process ID = 3.00.00, and completes a writing of the data 2 so that the real head position (real BID) is N+9. At this time, "00" is held as ES in the control area 46a, whereas the control area 46b and the save areas 46c to 46e are in the undetermined state.

[2-3-2] Example 2 of Emulation Execution

FIG. 141 is a diagram showing a state of data writing on the magnetic tape MT, and for illustrating an example of commands issued from the CPU 20 when data is read out from two consecutive files, and tape operations/emulation operations in the MTU 30 according to the second embodiment in response to the

commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 are the same as those described above with reference to FIG. 47, 5 descriptions of which are thus omitted. Incidentally, an identification pattern for EOF1 and EOF2 in the example shown in FIG. 141 is Pattern 4 described above with reference to FIGS. 69 (D) and 72 (A) through 72 (C).

When performing the open process [cf. (4) to 10 (11)] shown in FIG. 141, the I/F converting apparatus 40 (control unit 42) emulates the command processing (4) through (6) enclosed by a broken line in the drawing, using the method according to the second embodiment. During which, the I/F converting 15 apparatus 40 does not perform any mechanical operation with the head H being stopped at the leading position (between TM-b and HDR1) of the second file, as shown in FIG. 141.

According to the second embodiment, since 20 EOF1 and EOF2 are not stored in the respective save areas 46c and 46d in the RAM 46 at the time of the open process, the RD command processing (7) and the FSPF command processing (8) that are emulated in the first embodiment are not emulated according to the second 25 embodiment, but carries out as real operations of the MTU 30. Therefore, EOF1 read out in the real operation of the MTU 30 in response to the RD command

(7) is transferred to the CPU 20 via the data buffer 45.

Hereinafter, the command processing (1) to (13) will be described in detail with reference to FIGS. 142 through 154.

(A) of FIGS. 142 through 154 shows a state of data block writing on the magnetic tape MT, a real head position (real BID) and a virtual head position (EP) when each of the command processing (1) to (13) is carried out. (B) of FIGS. 142 through 154 shows a state of data saving/storing in the RAM 46 when each of the command processing (1) to (13) is carried out.

(1) RD Process

FIG. 142(A) shows a state in which the I/F converting apparatus 40 receives an RD command (1) shown in FIG. 141 from the CPU 20, carries out a process of process ID = 1.00.01, completes a reading of the last block data (data 1) of the first file, and is about to shift to the close process for the file. In which, the real head position (real BID) is N. At this time, ES in the control area 46a in the RAM 46 indicates the initial state (ES=00), as shown in FIG. 142(B). Incidentally, the control area (EP) 46b and the save areas 46c to 46e in the RAM 46 indicate the undetermined state.

(2) FSPF Process

FIG. 143(A) shows a state in which the I/F

converting apparatus 40 receives an FSPF command (2) shown in FIG. 141 from the CPU 20, carries out a process of process ID = 7.00.00, and completes the forward space operation so that the real head position (real BID) is N+1. At this time, "10" is held as ES in the control area 46a, whereas "N+1" is held as SBID in the save area 46e, as shown in FIG. 143(B).

(3) FSPF Process

FIG. 144(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (3) shown in FIG. 141, carries out a process of process ID = 7.10.00, and completes the forward space operation in the MTU 30 so that the real head position (real BID) is shifted from N+1 to N+4. According to the second embodiment, EOF1 and EOF2 are skipped in the MTU 30 at this time, so that the I/F converting apparatus 40 cannot capture entities of the EOF1 and the EOF2. After checking that a difference between the real BID and SBID $[(\text{real BID}) - (\text{SBID})]$ is "3", the I/F converting apparatus 40 stores "N+4" as SBID in the save area 46e, as shown in FIG. 144(B). As shown in FIG. 144(B), "43" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

(4) BSPF Process

FIG. 145(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (4) shown in FIG. 141 from the CPU 20, and carries out a

5

10

15

20

25

In FIG. 148(A), the I/F converting apparatus 40 receives an RD command (7) shown in FIG. 141 from the CPU 20, carries out a process of process ID =

1.43.10 so as to make the MTU 30 carry out a re-positioning process and a real operation (real RD operation), and reads a data block (EOF 1). In the re-positioning process, the I/F converting apparatus
 5 40 positions the head of the MTU 30 at a position of a real BID [= SBID+EP = (N+4) + (-3) = N+1]. Thereafter, the real head position (real BID) is N+2 by carrying out the real operation. As shown in FIG. 148(B), "20" is held as ES in the control area 46a, whereas a value
 10 of SBID in the save area 46e is updated (SBID - 3 = N+1), at this time. The data block (EOF1) read by the MTU 30 is stored in the save area (SDT1) 46c, stored in the data buffer 45, then transferred to the CPU 20. At this point of time, the identification pattern for
 15 EOFs is Pattern 2 described above with reference to FIGS. 69(B) and 71(A) through 71(G).

(8) FSPF Process

FIG. 149(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (8)
 20 shown in FIG. 141 from the CPU 20, and carries out a process of process ID = 7.20.00, and completes a real FSPF operation in the MTU 30 so that the real head position (real BID) is N+1. After checking that a difference between the real BID and SBID [(real BID) - (SBID)] is "3", the I/F converting apparatus 40
 25 stores "N+4" as SBID in the save area, as shown in FIG. 149(B). As shown in FIG. 149(B), "41" is held as ES

in the control area 46a, whereas "0" is held as EP in the control area 46b.

(9) RD Process

FIG. 150(A) shows a state in which the I/F
5 converting apparatus 40 receives an RD command (9)
shown in FIG. 141 from the CPU 20, carries out a process
of process ID = 1.41.42 and completes a reading of HDR1
so that the real head position (real BID) is N+5. At
this time, "00" is held as ES in the control area 46a,
10 whereas the control area 46b and the save areas 46c
to 46e are in the undetermined state, as shown in FIG.
150(B).

(10) RD Process

FIG. 151(A) shows a state in which the I/F
15 converting apparatus 40 receives an RD command (10)
shown in FIG. 141 from the CPU 20, carries out a process
of process ID = 1.00.01, and completes a reading of
HDR2 so that the real head position (real BID) is N+6.
At this time, "00" is held as ES in the control area
20 46a, whereas the control area 46b and the save areas
46c to 46e are in the undetermined state, as shown in
FIG. 151(B).

(11) FSPF Process

FIG. 152(A) shows a state in which the I/F
25 converting apparatus 40 receives an FSPF command (11)
shown in FIG. 141 from the CPU 20, carries out a process
of process ID = 7.00.00 and completes the forward space

operation so that the real head position (real BID) is N+7. At this time, "10" is held as ES in the control area 46a, whereas "N+7" is held as EP in the control area 46e, as shown in FIG. 152(B).

5 (12) RD Process

FIG. 153(A) shows a state in which the I/F converting apparatus 40 receives an RD command (12) shown in FIG. 141 from the CPU 20, carries out a process of process ID = 1.10.02, and completes a reading of data 2 so that the real head position (real BID) is at N+8. At this time, "00" is held as ES in the control area 46a, whereas the control area 46b and the save areas 46c to 46e are in the undetermined state, as shown in FIG. 153(B).

15 (13) RD Process

FIG. 154(A) shows a state in which the I/F converting apparatus 40 receives an RD command (13) shown in FIG. 141 from the CPU 20, carries out a process of process ID = 1.00.01, and completes a reading of data 2 so that the real head position (real BID) is N+9. At this time, "00" is held as ES in the control area 46a, whereas the control area 46b and the save areas 46c to 46e are in the undetermined state, as shown in FIG. 154(B).

25 [2-3-3] Example 3 of Emulation Execution

FIGS. 155(A) and 155(B) are diagrams showing a state of data writing on the magnetic tape MT, and

for illustrating another example of commands issued from the CPU 20 when a process of additionally writing a multi-file is carried out, and tape operations/emulation operations in the MTU 30

5 according to the second embodiment responsive to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 shown in FIGS. 155(A) and 155(B) are the same as those described above

10 with reference to FIGS. 61(A) and 61(B), descriptions of which are thus omitted. Note that the identification pattern for EOF1 and EOF2 in the example shown in FIGS. 155(A) and 155(B) is Pattern 1 described above with reference to FIGS. 69(A) and

15 70(A) through 70(G).

When the open process [cf. (8) to (17)] shown in FIGS. 155(A) and 155(B) is carried out, the I/F converting apparatus 40 (control unit 42) emulates the command processing (8) to (14) enclosed by a broken

20 line in the drawings, using the method according to the second embodiment. During which, the I/F converting does not perform any mechanical operation with the head H being stopped between the last two tape marks, TM-b and TM-c, as shown in FIG. 155(A).

25 According to the second embodiment, EOF1 saved in the save area (SDT1) 46c in the RAM 46 is read out and transferred to the CPU 20 via the data buffer 45 when

the emulation is executed in response to an RD command (11).

The command processing (1) to (14) shown in FIG. 155(A) are the same as the command processing (1) to (14) described above with reference to FIGS. 116(A) and 117 through 130, and the command processing (15) to (19) shown in FIG. 155(B) are the same as the command processing (20) to (24) described above with reference to FIGS. 116(B) and 136 through 140, descriptions of which are thus omitted.

[2-3-4] Example 4 of Emulation Execution

FIG. 156 is a diagram showing a state of data writing on the magnetic tape MT, and for illustrating still another example of commands issued from the CPU 20 when data is read out from two consecutive files, and tape operations/emulation operations in the MTU 30 according to the second embodiment in response to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 are the same as those described above with reference to FIG. 62, descriptions of which are thus omitted. The identification pattern for EOF1 and EOF2 in the example shown in FIG. 156 is Pattern 2 described above with reference to FIGS. 69(B) and 71(A) through 71(G).

When the open process [cf. (4) to (18)] shown

in FIG. 156 is carried out, the I/F converting apparatus 40 (control unit 42) emulates the command processing (5) to (8) and (11) to (15) enclosed by broken lines in the drawing, using the method

5 according to the second embodiment. During which, the I/F converting apparatus does not perform any mechanical operation with the head H being stopped at the leading position (between TM-b and HDR1) of the second file as shown in FIG. 156.

10 According to the second embodiment, since only EOF1 is stored in the save area 46c in the RAM 46 when the open process is carried out, the RD command processing (9) and the FSPF command processing (10) in which emulation is executed in the first embodiment
15 is not emulated, but executed as a real operation of the MTU 30. Therefore, EOF2 read out in the real operation of the MTU 30 responsive to the RD command (9) is transferred to the CPU 20 via the data buffer 45.

20 Hereinafter, the command processing (1) to (20) shown in FIG. 156 will be described in detail with reference to FIGS. 157 through 172.

(A) of FIGS. 157 through 172 show a state of data block writing on the magnetic tape MT, a real head position (real BID) and a virtual head position (EP)
25 when each of the command processing (1) to (16) is carried out. (B) of FIGS. 157 through 172 shows a

(1) RD Process

(2) RD Process

(3) RD Process

FIG. 159(A) shows a state in which the I/F

converting apparatus 40 receives an RD command (3) shown in FIG. 156 from the CPU 20, carries out a process of process ID = 1.10.00, and completes a reading of EOF1 so that the real head position (real BID) is at N+2. At this time, "20" is held as ES in the control area 46a, whereas EOF1 is stored in the save area (SDT1) 46c, as shown in FIG. 159 (B). Thereafter, EOF1 is held in the save area 46c.

(4) FSPF Process

FIG. 160 (A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (4) shown in FIG. 156 from the CPU 20, carries out a process of process ID = 7.20.00, and completes the forward space operation in the MTU 30 so that the real head position (real BID) is shifted from N+1 to N+4. According to the second embodiment, EOF2 is skipped in the MTU 30 at this time so that the I/F converting apparatus 40 cannot capture an entity of the EOF2. After checking that a difference between the real BID and SBID [(real BID) - (SBID)] is "3", the I/F converting apparatus 40 stores "N+4" as SBID in the save area 46e, as shown in FIG. 160 (B). As shown in FIG. 160 (B), "41" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

(5) BSPF Process

FIG. 161 (A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (5)

shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 5.41.40 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG.

5 161(B), "41" is held as ES in the control area 46a, whereas "-1" is held as EP in the control area 46b.

(6) BSPF Process

FIG. 162(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (6) shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 5.41.30 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 162(B), "41" is held as ES in the control area 46a, 15 whereas "-4" is held as EP in the control area 46b.

(7) FSPF Process

FIG. 163(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (7) shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 7.41.00 so as to execute emulation. At this time, the real head position (real BID) is still "N+4", not changed. As shown in FIG. 163(B), "41" is held as ES in the control area 46a, 20 whereas "-3" is held as EP in the control area 46b.

25 (8) SP Process

FIG. 164(A) shows a state in which the I/F converting apparatus 40 receives an SP command (8)

shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 6.41.10 so as to execute emulation. At this time, the real head position (real BID) is still "N+4", not changed. As shown in FIG. 164(B), "41" is held as ES in the control area 46a, whereas "-2" is held as EP in the control area 46b.

(9) RD Process

In FIG. 165(A), the I/F converting apparatus 40 receives an RD command (9) shown in FIG. 156 from the CPU 20, carries out a process of process ID = 1.41.20, and makes the MTU 30 carry out a process of re-positioning and a real operation (real RD operation), thereby reading a data block (EOF2). In the re-positioning process, the head of the MTU 30 is re-positioned at the real BID [= SBID + EP = (N+4) + (-2) = N+2]. Thereafter, by carrying out the real operation, the real head position (real BID) is N+3. At this time, "30" is held as ES in the control area 46a, and a value of SBID in the save area 46e is updated (SBID - 3 = N+1), as shown in FIG. 165(B). The data block (EOF2) read by the MTU 30 is stored in the save area (SDT2) 46d, then stored in the data buffer 45 to be transferred to the CPU 20. At this point of time, the identification pattern for EOFs is Pattern 1 described above with reference to FIGS. 69(A) and 70(A) through 70(G).

(10) FSPF Process

FIG. 166(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (10) shown in FIG. 156 from the CPU 20, carries out a process of process ID = 7.30.00, and completes the real FSPF operation in the MTU 30 so that the real head position (real BID) is N+4. After checking that a difference between the real BID and SBID [(real BID) - (SBID)] is "3", the I/F converting apparatus 40 stores "N+4" as SBID in the save area, as shown in FIG. 166(B). As shown in FIG. 166(B), "40" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

(11) BSPF Process

FIG. 167(A) shows a state in which the I/F converting apparatus receives a BSPF command (11) shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 5.40.40 so as to execute emulation. At this time, the real head position (real BID) is still "N+4", not changed. As shown in FIG. 167(B), "40" is held as ES in the control area 46a, whereas "-1" is held as EP in the control area 46b.

(12) BSPF Process

FIG. 168(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (12) shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 5.40.30 so as to execute emulation. At this time, the real head position (real

BID) is still $N+4$, not changed. As shown in FIG. 162(B), "40" is held as ES in the control area 46a, whereas "-4" is held as EP in the control area 46b.

(13) FSPF Process

5 FIG. 169(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (13) shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 7.40.00 so as to execute emulation. At this time, the real head position (real
10 BID) is still $N+4$, not changed. As shown in FIG. 169(B), "40" is held as ES in the control area 46a, whereas "-3" is held as EP in the control area 46b.

(14) RD Process

 FIG. 170(A) shows a state in which the I/F
15 converting apparatus 40 receives an RD command (14) shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 1.40.10 so as to execute emulation. At this time, the real head position (real
20 BID) is still " $N+4$ ", not changed. As shown in FIG. 170(B), "40" is held as ES in the control area 46a, whereas "-2" is held as EP in the control area 46b. When the emulation is executed, contents EOF1 in the save area 46c is again re-stored in the data buffer 45, and transferred to the CPU 20.

25 (15) FSPF Process

 FIG. 171(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (15)

shown in FIG. 156 from the CPU 20, and carries out a process of process ID = 7.40.20 so as to execute emulation. At this time, the real head position (real BID) is still "N+4", not changed. As shown in FIG. 171(B), "40" is held as ES in the control area 46a, whereas "0" is held as EP in the control area 46b.

(16) RD Process

FIG. 172(A) shows a state in which the I/F converting apparatus 40 receives an RD command (16) shown in FIG. 156 from the CPU 20, carries out a process of process ID = 1.40.42, and completes a reading of HDR1 so that the real head position (real BID) is N+5. At this time, "00" is held as ES in the control area 46a, and the control area 46b and the save areas 47c to 46e are in the undetermined state, as shown in FIG. 172(B).

Incidentally, the command processing (18) to (20) shown in FIG. 157 are the same as the command processing (11) to (13) described above with reference to FIGS. 141 and 152 through 154, descriptions of which are thus omitted.

[2-3-5] Comparison of Performance (Comparison of Command Processing Times)

When a multi-file is additionally written as shown in FIGS. 116(A) and 116(B), a time required for the command processing in which the emulation is executed, applying the method according to the second

embodiment is equal to a time required for the command processing according to the first embodiment shown in FIG. 63. As shown in FIG. 63, a time required for all the command processing in which the emulation is not
 5 executed is 9.111926 second. In contrast, a time required for all the command processing in which the emulation is executed is 2.734931 second, which is much shorter.

FIG. 173 is a diagram in which a time required
 10 for the command processing in which the emulation is executed, applying the method according to the second embodiment is compared with a time required for the command processing applying the known method without executing the emulation, when data is read out from
 15 two consecutive files as shown in FIG. 141.

In FIG. 173, a time required for each command processing with emulation is compared with a time required for each command processing without emulation. In FIG. 173, a number in parentheses is
 20 entered in a remarks column corresponding to each of the command processing (1) to (13) shown in FIG. 141. A command without a number in parentheses in its remarks column does not relate to the tape operation of the MTU 30, a process corresponding to which is
 25 completed within the MTC 10.

As shown in FIG. 173, times required for each of the command processing (1) to (3) and (7) to (13)

and command processing not relating to the tape operation are equal in either case where the emulation is carried out or not.

When the emulation is executed, a time
5 required for each of the command processing (4) to (6)
is uniformly 0.000500 second since the process is
completed within the I/F converting apparatus 40
without a real operation (mechanical operation) in the
MTU 30. In contrast to 5.514830 second required for
10 all the command processing in which the emulation is
not executed, a time required for all the command
processing in which the emulation is executed is
4.768064 second, which is much shorter.

When a multi-file is additionally written as shown in FIGS. 155(A) and 155(B), a time required for command processing in which emulation is executed applying the method according to the second embodiment is equal to a time required for the command processing according to the first embodiment shown in FIG. 65. As shown in FIG. 65, a time required for all the command processing without emulation is 5.831600 second. In contrast, a time required for all the command processing with emulation is 2.728100 second, which is much shorter.

25 FIG. 174 is a diagram in which a time required
for command processing in which emulation is executed,
applying the method according to the second embodiment

is compared with a time required for command processing applying the known process without emulation, when data is read out from two consecutive files as shown in FIG. 156.

5 In FIG. 174, a time required for each process without emulation is compared with a time required for the same process with emulation. In FIG. 174, a number in parentheses is entered in a remarks column of a command corresponding to each of the command processing (1) to (20) shown in FIG. 156.

10 Incidentally, a command without a number in parentheses in its remarks column does not relate to the tape operation in the MTU 30, a process according to which is completed within the MTC 10.

15 As shown in FIG. 174, times required for each of the command processing (1) to (4), (9), (10), and (16) to (20) in which no emulation is executed and command processing not relating to the tape operation are equal in either case where the emulation is
20 executed or not. In contrast, a time required for each the command processing (5) to (8) and (11) to (15) in which emulation is executed is uniformly 0.000500 second since the process is completed within the I/F converting apparatus 40 without a real tape operation
25 (mechanical operation) in the MTU 30. Therefore, in contrast to 8.781900 second required for all the command processing without emulation, a time required

for all the command processing with emulation is 4.817000 second, which is much shorter.

[2-4] Effects of the Second Embodiment

According to the method for controlling a magnetic tape unit of the second embodiment of this invention, a tape operation relating to EOF identification in the open process for a file is emulated in the I/F converting apparatus 40, thereby providing the similar effects and advantages to the first embodiment.

[2-5] Description of a Modification of the Second Embodiment

Meanwhile, when a technique such as EDRC (Enhanced Data Recording Capability) compression or the like is used, logical blocks of EOF1 and EOF2 are generally packeted in one physical block while they are not compressed by a packeting function for logical blocks.

For this, when a read direction (a direction to read) for either one of the EOF logical blocks is issued from the channel (CPU 20), packets (logical packets) of both EOF1 and EOF2 that are packeted in one physical block are simultaneously stored in the data buffer 45 by executing only one read command even without a read direction for the other EOF logical block.

For example, as shown in FIG. 276(A), EOF1 and

Accordingly, even if a read direction to read only EOF1 is issued from the CPU 20, the whole one physical block is practically read out, thus not only EOF1 but also EOF2 is stored in the data buffer 45, as shown in FIG. 10.

EOF1 or EOF2 skipped in accordance with an SP
20 command or an FSPF command at the time of the close
process for a file are considered to be not read out
from the magnetic tape MT in the logical image. For
this, when a read direction (read command) for EOF1
or EOF2 skipped at the time of the open process for
25 the file is issued from the CPU 20, the MTU 30 is made
to carry out a real read operation.

read out to the data buffer 45 if a read process for either one of EOF1 and EOF2 is carried out at the time of the close process, as stated above.

In such case, when a read direction for an EOF
 5 that has been an object of skip at the time of the close process is issued from the CPU 20 in the open process, emulation of reading the EOF is executed. Namely, the EOF stored in the data buffer 45 is read out from the data buffer 45 and transferred to the CPU 20 without
 10 making the MTU 30 carry out the real read process.

This will be described in more detail with reference to FIG. 156. In the example shown in FIG. 156, commands are issued from the CPU 20 such that only EOF1 is read in the RD process (3) in the close process
 15 for the file, and EOF2 is skipped in the FSPF process (4). At this time, if EOF1 and EOF 2 are recorded in one physical block on the magnetic tape MT by the packeting function of EDRC or the like, both of EOF1 and EOF2 are read out to the data buffer 45 in the RD
 20 process (3), as described above.

According to the modification of the second embodiment, pointers indicating positions (positions in the data buffer 45) of data of EOF1 and EOF2 are stored in the save areas 46c and 46d in the RAM 46,
 25 for example.

At this time, data in one physical block is identified when the physical block is read into the

10

15

20

When data other than EOF2 is stored in a physical

block in which EOF1 is packeted although a command to read only EOF1 is executed, the control flag V1 is set to "1" while the control flag V2 is set to "0". In which case, "41" (reading EOF1 can be emulated) is set
 5 as usual as a value of ES in the control area 46a in the RAM 46.

Back to the example shown in FIG. 156, next description will be of a case where EOF2 is read out from the magnetic tape MT in the RD process (9) after
 10 both EOF1 and EOF2 are read out to the data buffer 45 in the RD process (3). In which case, the MTU 30 is made to carry out the real operation (real RD operation) according to the second embodiment. However, according to this modification, EOF2 is
 15 already read out to the data buffer 45, as stated above, "40" is thus held as ES in the control area 46a in the FSPF process (4). Accordingly, the RD process (9) and the following FSPF process (10) are emulated according to this modification.

20 According to the modification of the second embodiment, use of the packeting function of EDRC or the like enables emulation of a larger number of tape operations, which can thus more shorten a time required for the file open process. This leads to
 25 large improvements of the file open process performance, and further the processing performance of a system accessing to the MTU 30 via the I/F

converting apparatus 40.

[3] Description of a Third Embodiment

[3-1] Basic Structure

A method for controlling a magnetic tape unit
 5 according to a third embodiment is applied to a system
 similar to that according to the second embodiment.
 According to the third embodiment, emulation of the
 MTU 30 is executed in a process in an I/F converting
 apparatus 40 similar to that according to the second
 10 embodiment.

The system or the I/F converting apparatus 40
 to which the third embodiment is applied is structured
 similarly to that described above with reference to
 FIGS. 67 and 68 in the second embodiment, descriptions
 15 of which are thus omitted. Note that "70" to "83" to
 be described later are held as values of emulation
 status (ES) in the area 46a (cf. FIG. 68) in the RAM
 46, in addition to "00" to "63".

[3-2] Control Method According to the Third 20 Embodiment

Now, description will be made of the method
 for controlling a magnetic tape unit according to the
 third embodiment with reference to FIGS. 202 through
 275.

25 [3-2-1] Basic Operation

The basic operation of the method according
 to the third embodiment is almost similar to that

according to the second embodiment. According to the third embodiment, not only the operation according to the second embodiment can be carried out, but also the operation carried out in the file close process can be simplified. In concrete, an operation of writing the third tape mark TM-c after writing the second tape mark TM-b is emulated when the file close process is carried out, thereby decreasing the frequency of the mechanical tape operation in the MTU 30 in the close process, thus simplifying the tape operation in the close process.

The I/F converting apparatus 40 according to the third embodiment has a function for realizing the control method described in the second embodiment. In addition, the I/F converting apparatus 40 has a function of, when receiving a WTM command requiring to write the third tape mark TM-c on the magnetic tape MT after writing the second tape mark TM-c on the same in the file close process, reporting write completion of the third tape mark TM-c to the CPU 20 on the assumption that the writing of the third tape mark TM-c is virtually completed without really writing it. Namely, the I/F converting apparatus 40 executes emulation of an operation of writing the third tape mark TM-c.

According to the third embodiment, when the I/F converting apparatus 40 receives a command in the

read system (RD command, RB command) or a command in the control system (BSP command, BSPF command, SP command, FSPF command) from the CPU 20 after executing emulation of an operation of writing the third tape mark TM-c [in a state at the time that ES=7x to be described later with reference to FIGS. 202(H) and 203] as stated above, the I/F converting apparatus 40 executes emulation of the command while managing a value of EP within a range of EP from -4 to +1, with the real head position being fixed at a position immediately after the second tape mark TM-b.

According to the third embodiment, when the I/F converting apparatus 40 receives a command directing to position the head outside a range of EP from -4 to +1 (i.e., a range from immediately before the first tape mark TM-a to immediately after the third tape mark TM-c) after executing emulation of an operation of writing the third tape mark TM-c as stated above, the I/F converting apparatus 40 writes the third tape mark TM-c, then makes the MTU 30 carry out a real tape operation in response to the command.

As a command directing to position the head outside a range of EP from -4 to +1, there are a command in the read system, a command in the control system, a command in the write system (WR command, WTM command), and a command in the motion system involving unloading and rewinding. Meanwhile, the unload command is a

direction to rewind the magnetic tape MT up to the head,
and eject a cassette including the magnetic tape MT
from the MTU 30. The rewind command is a direction
to rewind the magnetic tape MT up to the head. Note
5 that when a multi-file is additionally written, a
writing of data such as a header (HDR1) or the like
is commenced immediately after the second tape mark
TM-b without writing the third tape mark TM-c.

When the I/F converting apparatus 40
10 terminates a process while the third tape mark TM-
c cannot be recorded on the magnetic tape MT due to
a failure such as power-off or the like after carrying
out emulation of an operation of writing the third tape
mark TM-c is executed as stated above, immediately
15 after the second tape mark TM-b is EOD (End Of Data)
on the magnetic tape MT after the failure is recovered.
Consequently, the I/F converting apparatus 40 detects
the EOD after detecting or writing the second tape mark
TM-b.

20 According to the method of the third
embodiment, when the I/F converting apparatus 40
detects EOD after detecting or writing the second tape
mark TM-b as above, the I/F converting apparatus 40
assumes that the third tape mark TM-c is detected, then
25 makes a report about detection of the third tape mark
TM-c instead of the EOD report (report about EOD
detection) to the CPU 20. Thereafter, the CPU 20

issues a command to the MTU 30, on the assumption that the third tape mark TM-c has been detected.

According to the method of the third embodiment, when the I/F converting apparatus 40 receives a command in the read system or a command in the control system from the CPU 20 after making a third tape mark TM-c detection report [in a state at the time that $ES = 8x$ to be described later with reference to FIGS. 202(I) and 203] in stead of the EOD report as above, the I/F converting apparatus 40 executes emulation of the command while managing a value of ES within a range of EP from -4 to +1, with the real head position being fixed at a position immediately after the second tape mark TM-b.

According to the method of the third embodiment, when the I/F converting apparatus 40 receives a command directing to position the head outside a range of EP from -4 to +1 after making a third tape mark TM-c detection report instead of the EOD report as above, the I/F converting apparatus 40, basically, makes the MTU 30 carry out a real tape operation in response to the command on the assumption that the third tape mark TM-c has been written. When a multi-file is additionally written, a writing of data such as a header (HDR1) or the like is commenced immediately after the second tape mark TM-b.

[3-2-2] Identification Pattern for EOFs

Four identification pattern for EOFs by the I/F converting apparatus 40 according to the third embodiment are similar to those described above in the second embodiment. Depending on either a case where

5 a data block can be identified as EOF1 or EOF2 by carrying out a read operation or a write operation in response to an RD command or a WR command, or a case where a data block can be identified as EOF1 or EOF2 by carrying out a skip operation in response to an SP

10 command or an FSPF command, there are classified into four identification patterns (Pattern 1 to Pattern 4; cf. FIG. 69(A) to 69(D)).

[3-2-3] Emulation Status

Next, description will be made of the

15 emulation status (ES) according to the third embodiment with reference to FIGS. 69(A) through 69(D), 202(A) through 202(I) and 203.

According to the third embodiment, similarly to the second embodiment, when both of EOF1 and EOF2

20 can be identified (Pattern 1) as shown in FIG. 69(A), ES=x0. When only EOF 1 can be identified and EOF2 is skipped (Pattern 2) as shown in FIG. 69(B), ES = x1. When EOF 1 is skipped and only EOF 2 can be identified (Pattern 3) as shown in FIG. 69(C), ES = x2. When both

25 of EOF1 and EOF2 are skipped (Pattern 4) as shown in FIG. 69(D), ES = x3. Note that "x" is a value to be determined according to a position of the magnetic

head, as will be described later.

In the I/F converting apparatus 40 according to the third embodiment, status monitoring is carried out on the basis of a value of ES. Particularly,
 5 according to the third embodiment, when a value of ES is "7x" or "8x" ($x = 0, 1, 2$ or 3), in addition to when a value of ES is "4x" or "6x" ($x = 0, 1, 2$ or 3) as in the second embodiment, execution of emulation is possible.

10 In a state in which execution of emulation is possible ($ES = 4x, 6x, 7x$ or $8x$), the virtual head position (a virtual position of the head relative to the magnetic tape MT) is managed with the emulation pointer (EP). A value of EP is expressed as a relative
 15 position from the real head position. In FIGS. 202(A) through 202(I), a black triangle mark indicates the real head position, whereas a white triangle mark indicates the virtual head position when execution of emulation is possible.

20 FIGS. 202(A) through 202(I) are diagrams for illustrating emulation status (ES) in the third embodiment. In FIGS. 202(C) through 202(I), the identification pattern for EOF1 and EOF2 is Pattern 1.

25 FIG. 202(A) shows a state when $ES=00$ (initial state). As shown in FIG. 202(A), the state at the time that $ES=00$ is a state in which a writing of an arbitrary

data block (data 1 in the drawings) on the magnetic tape MT is completed, where the actual head position relative to the magnetic tape MT is immediately after the data block. The real head position (hereinafter referred as real BID) at the time that ES=00 is n (BID of the arbitrary data block). At this time, a value of EP is undetermined.

FIG. 202(B) shows a state at the time that ES=10. As shown in FIG. 202(B), the state at the time that ES=10 is a state in which the first tape mark TM-a is detected or written, where the real head position is immediately after the first tape mark TM-a. The real BID at the time that ES=10 is n+1. At this time, a value of EP is undetermined.

FIG. 202(C) shows a state at the time that ES=2x. As shown in FIG. 202(C), the state at the time that ES=2x is a state in which EOF1 is detected or written, where the real head position is immediately after EOF1. The real BID at the time that ES=2x is n+2. At this time, a value of EP is undetermined, and x is 0 or 2.

FIG. 202(D) shows a state at the time that ES=3x. As shown in FIG. 202(D), the state at the time that ES=3x is a state in which EOF2 is detected or written, where the real head position is immediately after EOF2. The real BID at the time that ES=3x is n+3. At this time, a value of EP is undetermined, and

x takes any one of 0, 1, 2 and 3.

FIG. 202(E) shows a state at the time that $ES=4x$. As shown in FIG. 202(E), the state at the time that $ES=4x$ is a state in which the second tape mark TM-b is detected or written, where the real head position is immediately after the second tape mark TM-b. The real BID at the time that $ES=4x$ is $n+4$. At this time, a value of ES can take five values, -4, -3, -2, -1 and 0, and x takes any one of 0, 1, 2 and 3.

FIG. 202(F) is a diagram showing a state at the time that $ES=5x$. As shown in FIG. 202(F), the state at the time that $ES=5x$ is a state in which the third tape mark TM-c is detected or written, where the real head position is immediately after the third tape mark TM-c. The real BID at the time that $ES=5x$ is $n+5$. At this time, a value of EP is undetermined, and x takes any one of 0, 1, 2 and 3.

FIG. 202(G) shows a state at the time that $ES=6x$. As shown in FIG. 202(G), the state at the time that $ES=6x$ is a state in which the third tape mark TM-c is detected or written, where the real head position is between the second tape mark TM-b and the third tape mark TM-c. The real BID at the time that $ES=6x$ is $n+4$. At this time, a value of EP can take six values, -4, -3, -2, -1, 0 and +1, and x takes any one of 0, 1, 2 and 3.

FIG. 202(H) is a diagram showing a state at

5

15

25

embodiment. When the third tape mark TM-c is detected after the second tape mark TM-b in the state at the time that ES=4x, ES successively transits from "4x" to "5x", "6x" and so on, in the similar manner to the
5 second embodiment.

When a TMW (Tape Mark Write) command is received in the state at the time that ES=4x, ES transits from "4x" to "7x", where a third tape mark writing completion is reported without writing the
10 third tape mark TM-c, and an operation of writing the third tape mark TM-c is emulated.

When EOD is detected in response to an RD (READ) command, an SP command, or an FSPF command in the state at the time that ES=4x, ES transits from "4x"
15 to "8x", where EOD emulation in which EOD is handled as the third tape mark TM-c is executed.

The state at the time that ES=4x, 6x, 7x or 8x is an object of emulation in the third embodiment, as stated above.

20 [3-2-4] Command Processing

A flow of command processing by the control unit 42 in the I/F converting apparatus 40 according to the third embodiment is similar to the flow of command processing according to the second embodiment
25 described above with reference to FIG. 83. Namely, the control unit 42 of the I/F converting apparatus 40 carried out a command processing shown in FIG. 83

in response to each command when receiving the command from the CPU 20.

In the pre-process (Step 1), is it determined according to a type of a command (command code) and values of ES and EP stored in the respective control areas 46a and 46b in the RAM 46 which is carried out in the MTU 30, a real operation or emulation. In addition, a process of re-positioning the magnetic head or a process of restoring EOF1/EOF2 is carried out.

If a relative position (EP) and a real head position differ from each other when the real operation is carried out in the MTU 30, the control unit 42 makes the MTU 30 carry out a process of re-positioning the magnetic head. If execution of emulation of EOF/EOF2 is possible in the read command processing (RD process), the control unit 42 restores a data block (EOF1/EOF2) in the save areas 46c/46d in the RAM 36 into the data buffer 45, and transfers the data block to the CPU 20 at Step S4. According to the third embodiment, when receiving in a state at the time that ES=7x, a command directing to position the head outside a range of EP from -4 to +1 or an RD command to read EOF1 or EOF2 that cannot be identified, the control unit 42 carries out a third tape mark TM-c write process as the pre-process.

After the pre-process is completed, it is

10

15

20

position) is stored in the save area (SBID) 46e in the RAM 46, and an identification pattern for EOFs, that is, "TM, EOF1, EOF2, TM and TM", (confirmation on which Pattern it is, 1, 2, 3 or 4) is confirmed.

5 In the post-process according to the third embodiment, when EOD is detected in response to an RD command, an SP command or FSPF command in a state in which ES=4x, the third tape mark TM-c is assumed to be detected, and detection of the third tape mark TM-c
10 is reported, in lieu of EOF report, to the CPU 20.

If a command directing to identify a channel block ID (a logical position of the magnetic head) such as a read BID command or the like is issued from the CPU 20 when the emulation is executed (when ES = 40,
15 41, 42, 43, 60, 61, 62, 63, 70, 71, 72, 73, 80, 81, 82 or 83), the control unit 42 of the I/F converting apparatus 40 according to the third embodiment sends back a value of SBID+EP as a channel block ID, along with a value of SBID as a device ID to the CPU 20. If
20 a command such as a read BID command or the like is issued from the CPU 20 when the emulation is not executed (when ES = 00, 10, 20, 22, 30, 31, 32, 33, 50, 51, 52 or 53), the control unit 42 of the I/F converting apparatus 40 according to the third
25 embodiment issues a read position command to the device (MCU10/MTU30) as before to obtain an ID, and reports it to the CPU 20.

When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, and updates ES to "20" in the RAM 40, as does in the second embodiment (process ID = 1.40.40). When it is

determined that the data block is TM in the post-process, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the save area 46e [(real BID) - (SBID)], as does in the second embodiment. When confirming that the difference is "1", the control unit 42 stores the read BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "50" in the RAM 46 (process ID = 1.40.41).

When it is determined in the post-process that the data block is EOD, the control unit 42 updates ES to "80" and EP to "+1" in the RAM 46 (process ID = 1.40.43). At this time, the control unit 42 makes a report that the third tape mark TM-c is detected in lieu of EOF report to the CPU 20 on the assumption that the third tape mark TM-c is detected.

When it is determined in the post-process that the data block is other than OEF, TM and EOD, the control unit 42 updates ES to "00" in the RAM 46, as
25 does in the second embodiment (process ID = 1.40.42).

When it is recognized in the pre-process that

ES=70 and EP=-4 [cf. FIG. 202(H)] as shown in FIG. 205,
the control unit 42 executes emulation of the MTU 30.
In the post-process, the control unit 42 updates EP
to "-3" while holding ES at a value of "70" in the RAM
5 46 (process ID = 1.70.00).

When it is recognized in the pre-process that
ES=70 and EP=-3 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30, and restores the
data block (EOF1) in the save area (SDT1) 46c in the
10 RAM 46 into the data buffer 45. In the post-process,
the control unit 42 updates EP to "-2" while holding
ES at a value of "70" in the RAM 46 (process ID =
1.70.10).

When it is recognized in the pre-process that
15 ES=70 and EP=-2 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30, and restores the
data block (EOF2) in the save area (SDT2) 46d in the
RAM 46 into the data buffer 45. In the post-process,
the control unit 42 updates EP to "-1" while holding
20 ES at a value of "70" in the RAM 46 (process ID =
1.70.20).

When it is recognized in the pre-process that
ES=70 and EP=-1 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30. In the post-
25 process, the control unit 42 updates EP to "0" while
holding ES at a value of "70" in the RAM 46 (process
ID = 1.70.30).

When it is recognized in the pre-process that ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding
 5 ES at a value of "70" in the RAM 46 (process ID = 1.70.40).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write
 10 the third tape mark TM-c on the magnetic tape MT, then makes the MTU 30 carry out the real operation (real READ). In the post-process, the control unit 42 determines which one the type of the data block read by the MTU 30 is EOF, TM or any other. When it is
 15 determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, adds 1 to SBID in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 1.70.50). When it is determined that the data
 20 block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 1.70.51). When it is determined in the post-process that the data block is other than EOF and TM, the control unit 42
 25 updates ES to "00" in the RAM 46 (process ID = 1.70.52).

When it is recognized in the pre-process that ES=80 and EP=-4 [cf. FIG. 202(I)], the control unit

42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "80" in the RAM 46 (process ID = 1.80.00).

5 When it is recognized in the pre-process that ES=80 and EP=-3 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30, and restores the data block (EOF1) in the save area (SDT1) 46c in the RAM 46 into the data buffer 45. In the post-process,
10 the control unit 42 updates EP to "-2" while holding ES at a value of "80" in the RAM 46 (process ID = 1.80.10).

 When it is recognized in the pre-process that ES=80 and EP=-2 [cf. FIG. 202(I)], the control unit
15 42 executes emulation of the MTU 30, and restores the data block (EOF2) in the save area (SDT2) 46d in the RAM 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "80" in the RAM 46 (process ID =
20 1.80.20).

 When it is recognized in the pre-process that ES=80 and EP=-1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while
25 holding ES at a value of "80" in the RAM 46 (process ID = 1.80.30).

 When it is recognized in the pre-process that

in FIG. 206.

namely, when it is recognized in the pre-process that ES=41 and EP=0, processes almost similar to the processes of process IDs =1.40.40, 1.40.41, 1.40.42 and 1.40.43 described above are carried out in the pre-processes and the post-processes (process IDs = 1.41.40, 1.41.41, 1.41.42, 1.41.43). In the post-process of process ID = 1.41.41, ES in the RAM 46 is updated to "51". In the post-process of process ID = 1.41.43, ES in the RAM 46 is updated to "81".

When it is recognized in the pre-process that ES=71 and EP=-4 [cf. FIG. 202(H)] as shown in FIG. 207, the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "71" in the RAM 46 (process ID = 1.71.00).

When it is recognized in the pre-process that ES=71 and EP=-3 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30, and restores the data block (EOF1) in the save area (SDT1) 46c in the RAM 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "71" in the RAM 46 (process ID = 1.71.10).

When it is recognized in the pre-process that ES=71 and EP=-2 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write

the third tape mark TM-c on the magnetic tape MT, re-positions the head at a position SBID+EP [position n+2 in FIG. 202(H)] in the MTU 30, then makes the MTU 30 carry out the real operation (real READ). In the

5 post-process, the control unit 42 determines whether the type of the data block read by the MTU 30 is EOF or any other. When it is determined that that data block is EOF (EOF2), the control unit 42 saves the data block (EOF2) in the save area (SDT2) 46e in the RAM

10 46, subtracts 3 from SBID in the RAM 46, and updates ES to "30" in the RAM 46 (process ID = 1.71.20). When it is determined in the post-process that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 1.71.21).

15 When it is recognized in the pre-process that ES=71 and EP=-1 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "71" in the RAM 46 (process

20 ID = 1.71.30).

When it is recognized in the pre-process that ES=71 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding

25 ES at a value of "71" in the RAM 46 (process ID = 1.71.40).

When it is recognized in the pre-process that

ES=71 and EP=+1 [cf. FIG. 202(H)], processes similar to the processes of process IDs = 1.70.50, 1.70.51 and 1.70.52 described above are carried out in the pre-process and post-process (process IDs = 1.71.50, 5 1.71.51, 1.71.52).

When it is recognized in the pre-process that ES=81 and EP=-4 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while 10 holding ES at a value of "81" in the RAM 46 (process ID = 1.81.00).

When it is recognized in the pre-process that ES=81 and EP=-3 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30, and restores the 15 data block (EOF1) in the save area (SDT1) 46c in the RAM 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "81" in the RAM 46 (process ID = 1.81.10).

20 When it is recognized in the pre-process that ES=81 and EP=-2 [cf. FIG. 202(I)], the control unit 42 re-positions the head at a position SBID+EP [position n+2 in FIG. 202(I)] in the MTU 30, and makes the MTU 30 carry out the real operation (real READ). 25 In the post-process, the control unit 42 determines whether the type of a data block read by the MTU 30 is EOF or any other. When it is determined that the

5

10

15

20

25

ES is any one of 22, 32, 42, 52 and 62, pre-processes

and post-processes almost similar to the pre-processes and the post-processes according to the second embodiment shown in FIG. 86 are carried out in the third embodiment as shown in FIG. 208.

5 When it is recognized in the pre-process that ES=42 and EP=0 [cf. FIG. 202(E)], the control unit 42 makes the MTU 30 carry out the real operation (real READ), as shown in FIG. 208. In the post-process, the control unit 42 then determines which one the type of
10 a data block read by the MTU 30 is of EOF, TM, EOD or any other than they, and updates ES and EP.

Namely, when it is recognized in the pre-process that ES=42 and EP=0, processes almost similar to the processes of process IDs = 1.40.40, 1.40.41,
15 1.40.42 and 1.40.43 described above are carried out in the pre-processes and the post-processes (process IDs = 1.42.40, 1.42.41, 1.42.42, 1.42.43). Note that ES in the RAM 46 is updated to "52" in the post-process of process ID = 1.42.41. In the post-process of
20 process ID = 1.42.43, ES in the RAM 46 is updated to "82".

As shown in FIG. 209, when it is recognized in the pre-process that ES=72 and EP=-4 [cf. FIG. 202(H)], the control unit 42 executes emulation of the
25 MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "72" in the RAM 46 (process ID = 1.72.00).

When it is recognized in the pre-process that ES=72 and EP=-3 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write the third tape mark TM-c on the magnetic tape MT,

5 re-positions the head at a position SBID+EP [position at n+1 in FIG. 202(H)] in the MTU 30, then makes the MTU 30 carry out the real operation (real READ). In the post-process, the control unit 42 determines whether the type of a data block read by the MTU 30

10 is EOF or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, subtracts 3 from SBID in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 1.72.10).

15 When it is determined in the post-process that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 1.72.11).

When it is recognized in the pre-process that ES=72 and EP=-2 [cf. FIG. 202(H)], the control unit

20 42 executes emulation of the MTU 30, and restores the data block (EOF2) in the save area (SDT2) 46d in the RAM 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "72" in the RAM 46 (process ID =

25 1.72.20).

When it is recognized in the pre-process that ES=72 and EP=-1 [cf. FIG. 202(H)], the control unit

42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "72" in the RAM 46 (process ID = 1.72.30).

5 When it is recognized in the pre-process that
ES=72 and EP=0 [cf. FIG. 202(H)], the control unit 42
executes emulation of the MTU 30. In the post-process,
the control unit 42 updates EP to "+1" while holding
ES at a value of "72" in the RAM 46 (process ID =
10 1.72.40).

When it is recognized in the pre-process that ES=72 and EP=+1 [cf. FIG. 202(H)], processes similar to the processes of process IDs = 1.70.50, 1.70.51 and 1.70.52 described above are carried out in the pre-processes and post-processes (process IDs = 1.72.50, 1.72.51, 1.72.52).

When it is recognized in the pre-process that ES=82 and EP=-4 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "82" in the RAM 46 (process ID = 1.82.00).

When it is recognized in the pre-process that ES=82 and EP=-3 [cf. FIG. 202(I)], the control unit 25 42 re-positions the head at a position SBID+EP [position n+1 in FIG. 202(I)] in the MTU 30, and makes the MTU 30 carry out the real operation (real READ).

In the post-process, the control unit 42 determines whether the type of a data block read by the MTU 30 is EOF or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves
 5 the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, subtracts 3 from SBID in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 1.82.10). When it is determined that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM
 10 46 (process ID = 1.82.11).

When it is recognized in the pre-process that ES=82 and EP=-2 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30, and restores a data block (EOF2) in the save area (SDT2) 46d in the
 15 RAM 46 into the data buffer 45. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "82" in the RAM 46 (process ID = 1.82.20).

When it is recognized in the pre-process that
 20 ES=82 and EP=-1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "82" in the RAM 46 (process ID = 1.82.30).

25 When it is recognized in the pre-process that ES=82 and EP=0 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process,

the control unit 42 updates EP to "+1" while holding ES at a value of "82" (process ID = 1.82.40).

When it is recognized in the pre-process that ES=82 and EP=+1 [cf. FIG. 202(I)], a process similar
 5 to the process of process ID = 1.80.50 described above is carried out in the pre-process and post-process (process ID = 1.82.50).

④ RD Process in Pattern 4 (cf. FIGS. 210 and 211)

When it is recognized in the pre-process that
 10 ES is any one of 33, 43, 53 and 63, pre-processes and post-processes almost similar to those according to the second embodiment shown in FIG. 87 are carried out in the third embodiment, as shown in FIG. 210.

As shown in FIG. 210, when it is recognized
 15 in the pre-process that ES=43 and EP=0 [cf. FIG. 202(E)], the control unit 42 makes the MTU 30 carry out the real operation (real READ). In the post-process, the control unit 42 then determines which one the type of a data block read by the MTU 30 is of EOF,
 20 TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-process that ES=43 and EP=0, processes almost similar to the processes of process IDs = 1.40.40, 1.40.41, 1.40.42 and 1.40.43 described above are carried out
 25 in the pre-processes and post-processes (process IDs = 1.43.40, 1.43.41, 1.43.42, 1.43.43). In the post-process of process ID = 1.43.41, ES in the RAM

46 is updated to "53". In the post-process of process ID = 1.43.43, ES in the RAM 46 is updated to "83".

As shown in FIG. 211, when it is recognized in the pre-process that ES=73 and EP=-4 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "73" in the RAM 46 (process ID = 1.73.00).

When it is recognized in the pre-process that ES=73 and EP=-3 [cf. FIG. 202(H)], processes similar to the processes of process IDs = 1.72.10 and 1.72.11 described above are carried out in the pre-process and the post-process (process IDs = 1.73.10, 1.73.11).

When it is recognized in the pre-process that ES=73 and EP=-2 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 1.71.20 and 1.71.21 described above are carried out in the pre-process and post-process. (process IDs = 1.73.20, 1.73.21). In the post-process of process ID=1.73.20, ES in the RAM 46 is updated to "32".

When it is recognized in the pre-process that ES=73 and EP=-1 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "73" in the RAM 46 (process ID = 1.73.30).

When it is recognized in the pre-process that

ES=73 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding ES at a value of "73" in the RAM 46 (process ID = 5 1.73.40).

When it is recognized in the pre-process that ES=73 and EP=+1 [cf. FIG. 202(H)], processes similar to the processes of process IDs = 1.70.50, 1.70.51 and 1.70.52 described above are carried out in the 10 pre-process and post-process (process IDs = 1.73.50, 1.73.51, 1.73.52).

When it is recognized in the pre-process that ES=83 and EP=-4 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post- 15 process, the control unit 42 updates EP to "-3" while holding ES at a value of "83" in the RAM 46 (process ID = 1.83.00).

When it is recognized in the pre-process that ES=83 and EP=-3 [cf. FIG. 202(I)], processes similar 20 to the processes of process IDs = 1.82.10 and 1.82.11 described above are carried out in the pre-process and post-process (process IDs = 1.83.10, 1.83.11).

When it is recognized in the pre-process that ES=83 and EP=-2 [cf. FIG. 202(I)], processes almost 25 similar to the processes of process IDs = 1.81.20 and 1.81.21 described above are carried out in the pre-process and post-process (process IDs = 1.83.20,

1.83.21). In the post-process of process ID = 1.83.20, ES in the RAM 46 is updated to "32".

When it is recognized in the pre-process that ES=83 and EP=-1 [cf. FIG. 202(I)], the control unit
 5 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "83" in the RAM 46 (process ID = 1.83.30).

When it is recognized in the pre-process that
 10 ES=83 and EP=0 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding ES at a value of "83" in the RAM 46 (process ID = 1.83.40).

15 When it is recognized in the pre-process that ES=83 and EP=+1 [cf. FIG. 202(I)], a process similar to the process of process ID = 1.80.50 described above is carried out in the pre-process and post-process (process ID = 1.83.50).

20 [3-2-4-2] RB Process (Read Backward) Process

When the I/F converting apparatus 40 according to the third embodiment receives an RB command from the CPU 20, the I/F converting apparatus 40 makes an error report to the CPU 20, like the MTC
 25 10 according to the first embodiment or the I/F converting apparatus 40 according to the second embodiment. When the I/F converting apparatus 40

5

①

10

20

When it is recognized in the pre-process that ES=70 and EP=-3 [cf. FIG. 202(H)], the control unit

When it is recognized in the pre-process that ES=80 and EP=-4 [cf. FIG. 202(I)], the control unit 42 re-positions the head at a position SBID+EP

5 [position n in FIG. 202(I)] in the MTU 30, and makes the MTU 30 carry out the real operation (real RB). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 2.80.00).

When it is recognized in the pre-process that
10 ES=80 and EP=-3 [cf. FIG. 202(I)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "-4" while
holding ES at a value of "80" in the RAM 46 (process
ID = 2.80.10).

15 When it is recognized in the pre-process that
ES=80 and EP=-2 [cf. FIG. 202(I)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "-3" while
holding ES at a value of "80" in the RAM 46 (process
20 ID = 2.80.20).

When it is recognized in the pre-process that ES=80 and EP=-1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "80" in the RAM 46 (process ID = 2.80.30).

When it is recognized in the pre-process that

ES=80 and EP=0 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "80" in the RAM 46 (process ID = 2.80.40).

When it is recognized in the pre-process that ES=80 and EP=+1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "80" in the RAM 46 (process ID = 2.80.50).

② RB Process in Pattern 2 (cf. FIG. 213)

When it is recognized in the pre-process that ES is any one of 31, 41, 51 and 61, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 89 are carried out in the third embodiment, as shown in FIG. 213.

According to the third embodiment, when it is recognized in the pre-process that ES=71 [cf. FIG. 202(h)], processes almost similar to the processes of process IDs = 2.70.00 to 2.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 213 (process IDs = 2.71.00 to 2.71.50). In the post-processes of process IDs = 2.71.10 to 2.71.50, ES in the RAM 46 is held at a value of "71".

When it is recognized in the pre-process that ES=81 [cf. FIG. 202(I)], processes almost similar to

the processes of process IDs = 2.80.00 to 2.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 2.81.00 to 2.81.50). In the post-processes of process IDs = 2.81.10 to 2.81.50, ES in the RAM 46 is held at a value of "81".

③ RB Process in Pattern 3 (cf. FIG. 214)

When it is recognized in the pre-process that ES is any one of 32, 42, 52 and 62, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 90 are carried out in the third embodiment, as shown in FIG. 214.

According to the third embodiment, when it is recognized in the pre-process that ES=72 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 2.70.00 to 2.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 214 (process IDs = 2.72.00 to 2.72.50). In the post-processes of process IDs = 2.72.10 to 2.72.50, ES in the RAM 46 is held at a value of "72".

When it is recognized that ES=82 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 2.80.00 to 2.80.50 described above are carried out in the pre-processes and post-processes. In the post-processes of process IDs = 2.82.10 to 2.82.50, ES in the RAM 46 is held at a value of "82" in the RAM 46.

④ RB Process in Pattern 4 (cf. FIG. 215)

When it is recognized in the pre-process that ES is any one of 33, 43, 53 and 63, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 91 are carried out in the third embodiment, as shown in FIG. 215.

According to the third embodiment, when it is recognized in the pre-process that ES=73 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 2.70.00 to 2.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 215 (process IDs = 2.73.00 to 2.73.50). In the post-processes of process IDs = 2.73.10 to 2.73.50, ES in the RAM 46 is held at a value of "73".

When it is recognized in the pre-process that ES=83 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 2.80.00 to 2.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 2.83.00 to 2.83.50). In the post-processes of process IDs = 2.83.10 to 2.83.50, ES in the RAM 46 is held at a value of "83".

[3-2-4-3] WR (Write) Process

① WR Process in Pattern 1 (cf. FIGS. 216 and 217)

When the I/F converting apparatus 40 receives a WR command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES is any one of 00, 10, 20, 30, 40, 50 and 60, pre-processes

and post-processes similar to those in the second embodiment shown in FIG. 92 are carried out in the third embodiment as shown in FIG. 216.

According to the third embodiment, when it is
 5 recognized in the pre-process that $ES=70$ and $EP=-4$ [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position $SBID+EP$ [position n in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out a real operation (real WR), as shown in FIG. 217. In the
 10 post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.70.00).

When it is recognized in the pre-process that $ES=70$ and $EP=-3$ [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position $SBID+EP$
 15 [position $n+1$ in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 determines whether the type of a data block written by the MTU 30 is EOF or any other. When it is determined that
 20 the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, subtracts 3 from $SBID$ in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 3.70.10). When it is determined in the post-process that the data
 25 block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.70.11).

When it is recognized in the pre-process that

ES=70 and EP=-2 [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position SBID+EP [position n+2 in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 determines whether the type of a data block written by the MTU 30 is EOF or any other. When it is determined that the data block is EOF (EOF2), the control unit 42 saves the data block (EOF2) in the save area (SDT2) 46d in the RAM 46, subtracts 3 from SBID in the RAM 46, and updates ES to "30" in the RAM 46 (process ID = 3.70.20). When it is determined in the post-process that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.70.21).

When it is recognized in the pre-process that ES=70 and EP=-1 [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position SBID+EP [position n+3 in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.70.30).

When it is recognized in the pre-process that ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 determines whether the type of a data block written by the MTU 30 is EOF or any other. When it is

determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, and updates ES to "20" in the RAM 46 (process ID = 3.70.40). When it is
 5 determined in the post-process that the data block is other than EOF, the control unit 42 updates ES to "00" in RAM 46 (process ID = 3.70.41).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit
 10 42 makes the MTU 30 carry out the WTM process to write the third tape mark TM-c on the magnetic tape MT, and makes the MTU 30 carry out the real operation (real WR). In the post-process, the control unit 42 determines whether the type of a data block written
 15 by the MTU 30 is EOF or any other. When it is determined that the data block is EOF (EOF1), the control unit 42 saves the data block (EOF1) in the save area (SDT1) 46c in the RAM 46, adds 1 to SBID in the RAM 46, and updates ES to "20" in the RAM 46 (process
 20 ID = 3.70.50). When it is determined that the data block is other than EOF, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 3.70.51).

When it is recognized in the pre-process that ES=80 [cf. FIG. 202(I)], processes similar to the
 25 processes of process IDs = 3.70.00 to 3.70.51 described above are carried out in the pre-processes and post-processes (process IDs = 3.80.00 to 3.80.51).

out in the pre-processes and post-processes, as shown in FIG. 221 (process IDs = 3.72.00 to 3.72.51). In the post-process of process ID = 3.72.20, ES in the RAM 46 is updated to "32".

5 When it is recognized in the pre-process that
ES=82 [cf. FIG. 202(I)], processes almost similar to
the processes of process IDs = 3.70.00 to 3.71.51
described above are carried out in the pre-processes
and post-processes (process IDs = 3.82.00 to 3.82.51).

10 In the post-process of process ID = 3.82.20, ES in the
RAM 46 is updated to "32".

④ WR Process in Pattern 4 (cf. FIGS. 222 and 223)

When it is recognized in the pre-process that ES is any one of 33, 43, 53 and 63, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 95 are carried out in the third embodiment, as shown in FIG. 222.

According to the third embodiment, when it is recognized in the pre-process that ES=73 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 3.70.00 to 3.70.51 described above are carried out in the pre-processes and post-processes, as shown in FIG. 223 (process IDs = 3.73.00 to 3.73.51). In the post-process of process ID = 3.73.20, ES in the RAM 46 is updated to "32".

When it is recognized in the pre-process that
ES=83 [cf. FIG. 202(I)], processes almost similar to

the processes of process IDs = 3.70.00 to 3.70.51 described above are carried out in the pre-processes and post-processes (process IDs = 3.83.00 to 3.83.51). In the post-process of process ID = 3.83.20, ES in the
 5 RAM 46 is updated to "32".

[3-2-4-4] BSP (Back Space Block) Process

① BSP Process in Pattern 1 (cf. FIG. 224)

When the I/F converting apparatus 40 receives a BSP command, the control unit 42 first refers to the
 10 RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES is any one of 00, 10, 20, 30, 40, 50 and 60, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 96 are carried out in the
 15 third embodiment, as shown in FIG. 224.

According to the third embodiment, when it is recognized in the pre-process that ES=70 and EP=-4 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write the third tape mark
 20 TM-c on the magnetic tape MT, re-positions the head at a position SBID+EP [position n in FIG. 202(H)] in the MTU 30, and makes the TMU carry out a real operation (real BSP), as shown in FIG. 224. In the post-process, the control unit 42 updates ES to "00" in the RAM 46
 25 (process ID = 4.70.00).

When it is recognized in the pre-process that ES=70 and EP=-3 [cf. FIG. 202(H)], the control unit

42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "70" in the RAM 46 (process ID = 4.70.10).

5 When it is recognized in the pre-process that
ES=70 and EP=-2 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "-3" while
holding ES at a value of "70" in the RAM 46 (process
10 ID = 4.70.20).

When it is recognized in the pre-process that ES=70 and EP=-1 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "70" in the RAM 46 (process ID = 4.70.30).

When it is recognized in the pre-process that ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "70" in the RAM 46 (process ID = 4.70.40).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "70" in the RAM 46 (process

When it is recognized in the pre-process that ES=80 and EP=-4 [cf. FIG. 202(I)], the control unit 42 re-positions the head at a position SBID+EP [position n in FIG. 202(I)] in the MTU 30, and makes the MTU 30 carry out the real operation (real BSP). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 4.80.00).

15 When it is recognized in the pre-process that
ES=80 and EP=-2 [cf. FIG. 202(I)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "-3" while
holding ES at a value of "80" in the RAM 46 (process
20 ID = 4.80.20).

When it is recognized in the pre-process that

ES=80 and EP=0 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "80" in the RAM 46 (process ID = 4.80.40).

When it is recognized in the pre-process that ES=80 and EP=+1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "80" in the RAM 46 (process ID = 4.80.50).

② BSP Process in Pattern 2 (cf. FIG. 225)

When it is recognized in the pre-process that ES is any one of 31, 41, 51 and 61, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 97 are carried out in the third embodiment, as shown in FIG. 225.

According to the third embodiment, when it is recognized in the pre-process that ES=71 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 4.70.00 to 4.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 225 (process IDs = 4.71.00 to 4.71.50). In the post-processes of process IDs = 4.71.10 to 4.71.50, ES in the RAM 46 is held at a value of "71".

When it is recognized in the pre-process that ES=81 [cf. FIG. 202(I)], processes almost similar to

the processes of process IDs = 4.80.00 to 4.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 4.81.00 to 4.81.50). In the post-processes of process IDs = 4.81.10 to 4.81.50, ES in the RAM 46 is held at a value of "81".

③ BSP Process in Pattern 3 (cf. FIG. 226)

When it is recognized in the pre-process that ES is any one of 32, 42, 52 and 62, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 98 are carried out in the third embodiment, as shown in FIG. 226.

According to the third embodiment, when it is recognized in the pre-process that ES=72 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 4.70.00 to 4.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 226 (process IDs = 4.72.00 to 4.72.50). In the post-processes of process IDs = 4.72.10 to 4.72.50, ES in the RAM 46 is held at a value of "72".

When it is recognized in the pre-process that ES=82 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 4.80.00 to 4.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 4.82.00 to 4.82.50). In the post-processes of process IDs = 4.82.10 to 4.82.50, ES in the RAM 46 is held at a value of "82".

④ SBP Process in Pattern 4 (cf. FIG. 227)

When it is recognized in the pre-process that ES is any one of 33, 43, 53 and 63, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 99 are carried out in the third embodiment, as shown in FIG. 227.

According to the third embodiment, when it is recognized in the pre-process that ES=73 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 4.70.00 to 4.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 227 (process IDs = 4.73.00 to 4.73.50). In the post-processes of process IDs = 4.73.10 to 4.73.50, ES in the RAM 46 is held at a value of "73".

When it is recognized in the pre-process that ES=83 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 4.80.00 to 4.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 4.83.00 to 4.83.50). In the post-processes of process IDs = 4.83.10 to 4.83.50, ES in the RAM 46 is held at a value of "83".

[3-2-4-4] SBPF (Back Space File) Process

① BSPF Process in Pattern 1 (cf. FIG. 228)

When the I/F converting apparatus 40 receives a BSPF command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES is any one of 00, 10, 20, 30, 40, 50 and 60, pre-

processes and post-processes similar to those in the second embodiment shown in FIG. 100 are carried out in the third embodiment, as shown in FIG. 228.

According to the third embodiment, when it is
 5 recognized in the pre-process that $ES=70$ and $EP=-4$ [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write the third tape mark TM-c on the magnetic tape MT, re-positions the head at a position $SBID+EP$ [position n in FIG. 202(H)] in
 10 the MTU 30, and makes the MTU carry out a real operation (real BSPF), as shown in FIG. 228. In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 5.70.00).

When it is recognized in the pre-process that
 15 $ES=70$ and $EP=-3$ [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "70" in the RAM 46 (process ID = 5.70.10).

20 When it is recognized in the pre-process that $ES=70$ and $EP=-2$ [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "70" in the RAM 46 (process
 25 ID = 5.70.20).

When it is recognized in the pre-process that $ES=70$ and $EP=-1$ [cf. FIG. 202(H)], the control unit 42

5 When it is recognized in the pre-process that
ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42
executes emulation of the MTU 30. In the post-process,
the control unit 42 updates EP to "-1" while holding
ES at a value of "70" in the RAM 46 (process ID =
0 5.70.40).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "70" in the RAM 46 (process ID = 5.70.50).

When it is recognized in the pre-process that ES=80 and EP=-4 [cf. FIG. 202(I)], the control unit 42 re-positions the head at a position SBID+EP [position n in FIG. 202(I)] in the MTU 30, and makes the MTU 30 carry out the real operation (real BSPF). In the post-process, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 5.80.00).

When it is recognized in the pre-process that
25 ES=80 and EP=-3 [cf. FIG. 202(I)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "-4" while

holding ES at a value of "80" in the RAM 46 (process ID = 5.80.10).

When it is recognized in the pre-process that ES=80 and EP=-2 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "80" in the RAM 46 (process ID = 5.80.20).

When it is recognized in the pre-process that ES=80 and EP=-1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-4" while holding ES at a value of "80" in the RAM 46 (process ID = 5.80.30).

When it is recognized in the pre-process that ES=80 and EP=0 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-1" while holding ES at a value of "80" in the RAM 46 (process ID = 5.80.40).

When it is recognized in the pre-process that ES=80 and EP=+1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "80" in the RAM 46 (process ID = 5.80.50).

② BSPF Process in Pattern 2 (cf. FIG. 229)

When it is recognized in the pre-process that ES is any one of 31, 41, 51 and 61, pre-processes and post-processes similar to those in the second embodiment shown in FIG. 101 are carried out in the third embodiment, as shown in FIG. 229.

According to the third embodiment, when it is recognized in the pre-process that ES=71 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 5.70.00 to 5.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 229 (process IDs = 5.71.00 to 5.71.50). In the post-processes of process IDs = 5.71.10 to 5.17.50, ES is held at a value of "71" in the RAM 46.

When it is recognized in the pre-process that ES=81 [cf. 202(I)], processes almost similar to the processes of process IDs = 5.80.00 to 5.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 5.81.00 to 5.81.50). In the post-processes of process IDs = 5.81.10 to 5.81.50, ES in the RAM 46 is held at a value of "81".

③ BSPF Process in Pattern 3 (cf. FIG. 230)

When it is recognized in the pre-process that ES is any one of 32, 42, 52 and 62, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 102 are carried out in the third embodiment, as shown in FIG. 230.

According to the third embodiment, when it is

5

10

20

25

When it is recognized in the pre-process that ES=83 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 5.80.00 to 5.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 5.83.00 to 5.83.50). In the post-processes of process IDs = 5.83.10 to 5.83.50, ES in the RAM 46 is held at a value of "83".

[3-2-4-6] SP (Forward Space Block) Process

- 10 ① SP Process in Pattern 1 (cf. FIGS. 232 and 233)

When the I/F converting apparatus 40 receives an SP command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES is any one of 00, 10, 20, 30, 40, 50 and 60, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 104 are carried out in the third embodiment, as shown in FIG. 232.

When it is recognized in the pre-process that
20 ES=40 and EP=0 [cf. FIG. 202(E)], the control unit 42
makes the MTU 30 carry out a real operation (real SP),
as shown in FIG. 232. In the post-process, the
control unit 42 determines which one the type of a data
block detected in the forward space operation by the
25 MTU 30 is of EOF, TM, EOD or any other.

When it is determined that the data block is EOF, the control unit 42 updates ES to "22" in the RAM

46, as does in the second embodiment (process ID = 6.40.40). When it is determined in the post-process that the data block is TM, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the save area 46e [(real BID) - (SBID)]. When recognizing that the difference is "1", the control unit 42 stores the real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "50" in the RAM 46 (process ID = 6.40.41).

10 When it is determined in the post-process that the data block is EOD, the control unit 42 updates ES to "80" and EP to "+1" in the RAM 46 (process ID = 6.40.43). At this time, it is assumed that the third tape mark TM-c is detected, and a report about

15 detection of the third tape mark TM-c is made instead of the EOD report to the CPU 20.

When it is determined in the post-process that the data block is other than EOF, TM and EOD, the control unit 42 updates ES to "00" in the RAM 46, as

20 does in the second embodiment (process ID = 6.40.42).

When it is recognized in the pre-process that ES=70 and EP=-4 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30, as shown in FIG. 233. In the post-process, the control unit 42 updates

25 EP to "-3" while holding ES at a value of "70" in the RAM 46 (process ID = 6.70.00).

When it is recognized in the pre-process that

5 When it is recognized in the pre-process that
ES=70 and EP=-2 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "-1" while
holding ES at a value of "70" in the RAM 46 (process
0 ID = 6.70.20).

When it is recognized in the pre-process that ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding ES at a value of "70" (process ID = 6.70.40).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write the third tape mark on the magnetic tape MT, and makes the MTU 30 carry out the real operation (real SP). In the post-process, the control unit 42 determines which one the type of a data block detected in the forward

space operation by the MTU 30 is of EOF, TM or any other. When it is determined that the data block is EOF, the control unit 42 adds 1 to SBID in the RAM 46, and updates ES to "22" in the RAM 46 (process ID = 6.70.50).

- 5 When it is determined in the post-process that the data block is TM, the control unit 42 stores a real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 6.70.51). When it is determined in the post-process that the data
- 10 block is other than OEF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 6.70.52).

- When it is recognized in the pre-process that ES=80 and EP=-4 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-
- 15 process, the control unit 42 updates EP to "-3" while holding ES at a value of "80" in the RAM 46 (process ID = 6.80.00).

- When it is recognized in the pre-process that Es=80 and EP=-3 [cf. FIG. 202(I)], the control unit
- 20 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-2" while holding ES at a value of "80" in the RAM 46 (process ID = 6.80.10).

- When it is recognized in the pre-process that
- 25 Es=80 and EP=-2 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-1" while

holding ES at a value of "80" in the RAM 46 (process ID = 6.80.20).

When it is recognized in the pre-process that ES=80 and EP=-1 [cf. FIG. 202(I)], the control unit
 5 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "80" (process ID = 6.80.30).

When it is recognized in the pre-process that ES=80 and EP=0 [cf. FIG. 202(I)], the control unit
 10 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding ES at a value of "80" (process ID = 6.80.40).

When it is recognized in the pre-process that ES=80 and EP=+1 [cf. FIG. 202(I)], the control unit
 15 42 makes the MTU 30 carry out the real operation (real SP). At this time, a real head position is immediately after the second tape mark TM-b so that EOD is detected in the forward space operation. In the post-process, the control unit 42 updates ES to
 20 "00" (process ID = 6.80.50), and carried out the following processes.

② SP Process in Pattern 2 (cf. FIGS. 234 and 235)

When it is recognized in the pre-process that ES is any one of 31, 41, 51 and 61, pre-processes and
 25 post-processes almost similar to those in the second embodiment shown in FIG. 105 are carried out in the third embodiment, as shown in FIG. 234.

When it is recognized in the pre-process that ES=41 and EP=0 as shown in FIG. 234 [cf. FIG. 202(E)], the control unit 42 makes the MTU 30 carry out the real operation (real SP). In the post-process, the

5 control unit 42 determines which one the type of a data block detected in the forward space operation by the MTU 30 is of EOF, TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-

10 process that ES=41 and EP=0, processes almost similar to the processes of process IDs = 6.40.40, 6.40.41, 6.40.42 and 6.40.43 described above are carried out in the pre-processes and post-processes (process IDs = 6.41.40, 6.41.41, 6.41.42, 6.41.43). In the

15 post-process of process ID = 6.41.41, ES in the RAM 46 is updated to "51". In the post-process of process ID = 6.41.43, ES in the RAM 46 is updated to "81".

When it is recognized in the pre-process that ES=71 [cf. 202(H)] as shown in FIG. 235, processes

20 almost similar to the processes of process IDs = 6.70.00 to 6.70.52 described above are carried out in the pre-processes and post-processes (process IDs = 6.71.00 to 6.71.52). In the post-processes of process IDs = 6.71.00 to 6.71.40, ES in the RAM 46 is

25 held at a value of "71".

When it is recognized in the pre-process that ES=81 [cf. FIG. 202(I)], processes almost similar to

the processes of process IDs = 6.80.00 to 6.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 6.81.00 to 6.81.50). In the post-processes of process IDs = 6.81.00 to 6.81.40, ES in the RAM 46 is held at a value of "81".

③ SP Process in Pattern 3 (cf. FIGS. 236 and 237)

When it is recognized in the pre-process that ES is any one of 22, 32, 42, 52 and 62, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 106 are carried out in the third embodiment, as shown in FIG. 236.

When it is recognized in the pre-process that ES=42 and EP=0 [cf. FIG. 202(E)] as shown in FIG. 236, the control unit 42 makes the MTU 30 carry out the real operation (real SP). In the post-process, the control unit 42 then determines which one the type of a data block detected in the forward space operation by the MTU 30 is of EOF, TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-process that ES=42 and EP=0, processes almost similar to the processes of process IDs = 6.40.40, 6.40.41, 6.40.42 and 6.40.43 described above are carried out in the pre-processes and post-processes (process IDs = 6.42.40, 6.42.41, 6.42.42, 6.42.43). In the post-process of process ID = 6.42.41, ES in the RAM 46 is updated to "52". In the post-process of process

ID = 6.42.43, ES in the RAM 46 is updated to "82".

When it is recognized in the pre-process that ES=72 [cf. FIG. 202(H)] as shown in FIG. 237, processes almost similar to the processes of process IDs =
 5 6.70.00 to 6.70.52 described above are carried out in the pre-processes and post-processes (process IDs = 6.72.00 to 6.72.52). In the post-processes of process IDs = 6.72.00 to 6.72.40, ES in the RAM 46 is held at a value of "72".

10 When it is recognized in the pre-process that ES=82 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 6.80.00 to 6.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 6.82.00 to 6.82.50).
 15 In the post-processes of process IDs = 6.82.00 to 6.82.40, ES in the RAM 46 is held at a value of "82".

④ SP Process in Pattern 4 (cf. FIGS. 238 and 239)

When it is recognized in the pre-process that ES is any one of 33, 43, 53 and 63, pre-processes and
 20 post-processes almost similar to those in the second embodiment shown in FIG. 107 are carried out in the third embodiment, as shown in FIG. 238.

When it is recognized in the pre-process that ES=43 and EP=0 [cf. FIG. 202(E)] as shown in FIG. 238,
 25 the control unit 42 makes the MTU 30 carry out the real operation (real SP). In the post-process, the control unit 42 then determines which one the type of

a data block detected in the forward space operation by the MTU 30 is of EOF, TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-
 5 process that ES=43 and EP=0, processes almost similar to the processes of process IDs = 6.40.40, 6.40.41. 4.40.42 and 6.40.43 described above are carried out in the pre-processes and post-processes (process IDs = 6.43.40, 6.43.41, 6.43.42, 6.43.43). In the
 10 post-process of process ID = 6.43.41, ES in the RAM 46 is updated to "53". In the post-process of process ID = 6.43.43, ES in the RAM 46 is updated to "83".

When it is recognized in the pre-process that ES=73 [cf. FIG. 202(H)] as shown in FIG. 239, processes
 15 almost similar to the processes of process IDs = 6.70.00 to 6.70.52 described above are carried out in the pre-processes and post-processes (process IDs = 6.73.00 to 6.73.52) In the post-processes of process IDs = 6.73.00 to 6.73.40, ES in the RAM 46 is held at
 20 a value of "73".

When it is recognized in the pre-process that ES=83 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 6.80.00 to 6.80.50 described above are carried out in the pre-processes
 25 and post-processes (process IDs = 6.83.00 to 6.83.50). In the post-processes of process IDs = 6.83.00 to 6.83.40, ES in the RAM 46 is held at a value of "83".

[3-2-4-7] FSPF (Forward Space File) Process

① FSPF Process in Pattern 1 (cf. FIGS. 240 and 241)

When the I/F converting apparatus 40 receives an FSPF command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES is any one of 00, 10, 20, 30, 40, 50 and 60, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 108 are carried out in the third embodiment, as shown in FIGS. 240 and 241.

When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 202(E)] as shown in FIG. 240, the control unit 42 makes the MTU 30 carry out a real operation (real FSPF). In the post-process, the control unit 42 then determines which one the type of a data block detected in the forward space operation by the MTU 30 is of TM, EOF or any other.

When it is determined that the data block is TM, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the save area 46e [(real BID) - (SBID)], as does in the second embodiment. When the difference is "3", the control unit 42 stores the real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "43" and EP to "0" in the RAM 46 (process ID = 7.40.40). When the difference is "1", the control unit 42 stores

the real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "50" in the RAM 46 (process ID = 7.40.41). When the above difference is neither "1" nor "3", the control unit 42 stores the

5 real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 7.40.42).

When it is determined in the post-process that the data block is EOD, the control unit 42 updates ES

10 to "80" and EP to "+1" in the RAM 46 (process ID = 7.40.44). At this time, the third tape mark TM-c is assumed to be detected so that a report about detection of the third tape mark TM-c is made in lieu of EOD report to the CPU 20.

15 When it is determined in the post-process that the data block is other than TM and EOD, the control unit 42 updates ES to "00" in the RAM 46, as does in the second embodiment (process ID = 7.40.43).

When it is recognized in the pre-process that

20 ES=70 and EP=-4 [cf. FIG. 202(H)] as shown in FIG. 241, the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "70" in the RAM 46 (process ID = 7.70.00).

25 When it is recognized in the pre-process that ES=70 and EP=-3 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-

process, the control unit 42 updates EP to "0" while holding the ES at a value of "70" in the RAM 46 (process ID = 7.70.10).

When it is recognized in the pre-process that
5 ES=60 and EP=-2 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "0" while
holding ES at a value of "70" in the RAM 46 (process
ID = 7.70.20).

10 When it is recognized in the pre-process that
ES=70 and EP=-1 [cf. FIG. 202(H)], the control unit
42 executes emulation of the MTU 30. In the post-
process, the control unit 42 updates EP to "0" while
holding ES at a value of "70" in the RAM (process ID
15 = 7.70.30).

When it is recognized in the pre-process that ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding
20 ES at a value of "70" in the RAM 46 (process ID = 7.70.40).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out a real operation (real FSPF). In the post-process, the control unit 42 then determines whether the type of a data block detected in the forward space operation by the MTU 30 is TM or

any other. When it is determined that the data block is TM, the control unit 42 determines a difference between a real BID of the TM and SBID stored in the save area 46e [(real BID) - (SBID)]. When the

5 difference is "3", the control unit 42 stores the real BID of the TM in the save area (SBID) 46e in the RAM 46, and updates ES to "43" and EP to "0" in the RAM 46 (process ID = 7.70.50). When the difference is not "3", the control unit 42 stores the real BID of the

10 TM in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 7.70.51). When it is determined in the post-process that the data block is other than EOF and TM, the control unit 42 updates ES to "00" in the RAM 46 (process ID = 7.70.52).

15 When it is recognized in the pre-process that ES=80 and EP=-4 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "-3" while holding ES at a value of "80" in the RAM 46 (process

20 ID = 7.80.00).

When it is recognized in the pre-process that ES=80 and EP=-3 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while

25 holding ES at a value of "80" (process ID = 7.80.10).

When it is recognized in the pre-process that ES=80 and EP=-2 [cf. FIG. 202(I)], the control unit

42 carries out emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "80" in the RAM 46 (process ID = 7.80.20).

5 When it is recognized in the pre-process that ES=80 and EP=-1 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "0" while holding ES at a value of "80" in the RAM 46 (process
10 ID = 7.80.30).

 When it is recognized in the pre-process that ES=80 and EP=0 [cf. FIG. 202(I)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates EP to "+1" while holding
15 ES at a value of "80" in the RAM 46 (process ID = 7.80.40).

 When it is recognized in the pre-process that ES=80 and EP=+1 [cf. FIG. 202(I)], the control unit 42 makes the MTU 30 carry out the real operation (real
20 FSPF). At this time, a real position of the head is immediately after the second tape mark TM-b so that EOD is detected in the forward space operation. In the post-process, the control unit 42 updates ES to "00" (process ID = 7.80.50), and carries out the
25 following process.

② FSPF Process in Pattern 2 (cf. FIGS. 242 and 243)

 When it is recognized in the pre-process that

00000"500500500

ES is any one of 31, 41, 51 and 61, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 109 are carried out in the third embodiment, as shown in FIG. 242.

5 When it is recognized in the pre-process that ES=41 and EP=0 [cf. FIG. 202(E)], the control unit 42 makes the MTU 30 carry out the real operation (real FSPF), as shown in FIG. 242. In the post-process, the control unit 42 then determines which one the type of
10 a data block detected in the forward space operation by the MTU 30 is of TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-process that ES=41 and EP=0, processes almost similar
15 to the processes of process IDs = 7.40.40 to 7.40.44 described above are carried out in the pre-processes and post-processes (process IDs = 7.41.40 to 7.41.44). In the post-process of process ID = 7.41.41, ES in the RAM 46 is updated to "51". In the post-process of
20 process ID = 7.41.44, ES in the RAM 46 is updated to "81".

When it is recognized in the pr-process that ES=71 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 7.70.00 to 7.70.52
25 described above are carried out in the pre-processes and post-processes, as shown in FIG. 243 (process IDs = 7.71.00 to 7.71.52). In the post-processes of

process IDs = 7.71.00 to 7.71.40, ES in the RAM 46 is held at a value of "71".

When it is recognized in the pre-process that ES=81 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 7.80.00 to 7.80.50 described above are carried out in the pre-processes and post-processes (process IDs = 7.81.00 to 7.81.50). In the post-processes of process IDs = 7.81.00 to 7.81.40, ES in the RAM 46 is held at a value of "81".

③ FSPF Process in Pattern 3 (cf. FIGS. 244 and 245)

When it is recognized in the pre-process that ES is any one of 22, 32, 42, 52 and 62, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 110 are carried out in the third embodiment, as shown in FIG. 244.

When it is recognized in the pre-process that ES=42 and EP=0 [cf. FIG. 202(E)], the control unit 42 makes the MTU 30 carry out the real operation (real FSPF), as shown in FIG. 244. In the post-process, the control unit 42 determines which one the type of a data block detected in the forward space operation by the MTU 30 is of TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-process that ES=42 and EP=0, processes almost similar to the processes of process IDs = 7.40.40 to 7.40.44 described above are carried out in the pre-processes

and post-processes (process IDs = 7.42.40 to 7.42.44) .
 In the post-process of process ID = 7.42.41, ES in the
 RAM 46 is updated to "52". In the post-process of
 process ID = 7.42.44, ES in the RAM 46 is updated to
 5 "82".

When it is recognized in the pre-process that
 ES=72 [cf. FIG. 202(H)], processes almost similar to
 the processes of process IDs = 7.70.00 to 7.70.52
 described above are carried out in the pre-processes
 10 and post-processes, as shown in FIG. 245 (process IDs
 = 7.72.00 to 7.72.52). In the post-processes of
 process IDs = 7.72.00 to 7.72.40, ES in the RAM 46 is
 held at a value of "72".

When it is recognized in the pre-process that
 15 ES=82 [cf. FIG. 202(I)], processes almost similar to
 the processes of process IDs = 7.80.00 to 7.80.50
 described above are carried out in the pre-processes
 and post-processes (process IDs = 7.82.00 to 7.82.50) .
 In the post-processes of process IDs = 7.82.00 to
 20 7.82.40, ES in the RAM 46 is held at a value of "82".

④ FSPF Process in Pattern 4 (cf. FIGS. 246 and 247)

When it is recognized in the pre-process that
 ES is any one of 33, 43, 53 and 63, pre-processes and
 post-processes almost similar to those in the second
 25 embodiment shown in FIG. 111 are carried out in the
 third embodiment, as shown in FIG. 246.

When it is recognized in the pr-process that

ES=43 and EP=0 [cf. FIG. 202(E)], the control unit 42 makes the MTU 30 carry out the real operation (real FSPF), as shown in FIG. 246. In the post-process, the control unit 42 determines which one the type of a data block detected in the forward space operation by the MTU 30 is of TM, EOD or any other, and updates ES and EP.

Namely, when it is recognized in the pre-process that ES=43 and EP=0, processes almost similar to the processes of process IDs = 7.40.40 to 7.40.44 described above are carried out in the pre-processes and post-processes (process IDs = 7.43.40 to 7.43.44). In the post-process of process ID = 7.43.41, ES in the RAM 46 is updated to "53". In the post-process of process ID = 7.43.44, ES in the RAM 46 is updated to "83".

When it is recognized in the pre-process that ES=73 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 7.70.00 to 7.70.52 described above are carried out in the pre-processes and post-processes, as shown in FIG. 247 (process IDs = 7.73.00 to 7.73.52). In the post-processes of process IDs = 7.73.00 to 7.73.40, ES in the RAM 46 is held at a value of "73".

When it is recognized in the pre-process that ES=83 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 7.80.00 to 7.80.50

described above are carried out in the pre-processes and post-processes (process IDs = 7.83.00 to 7.83.50). In the post-processes of process IDs = 7.83.00 to 7.83.40, ES in the RAM 46 is held at a value of "83".

5 [3-2-4-8] WTM (Write Tape Mark) Process

When a writing is carried out in response to a command in the write system (WR, WTM) in the MTU 30, an EOD (End Of Data) mark is written after a written data block. Therefore, the host (CPU 20) recognizes that there is no data block after a data block written in response to a command in the write system after the command is executed. According to the third embodiment, ES is updated to "10" whenever a real write tape mark operation is carried out in a state at the time that ES=00, 10 or 2x, or that ES=4x and EP=-4, -3 or -2, or that ES=6x, 7x or 8x and EP=-4, -3, -2, -1 or +1, as will be described later with reference to FIGS. 248 through 251.

① WTM Process in Pattern 1 (cf. FIG. 248)

When the I/F converting apparatus 40 receives a WTM command, the control unit 42 first refers to the RAM 46 to recognize a value of ES and a value of EP in the pre-process. When it is recognized that ES is any one of 00, 10, 20, 30, 40, 50 and 60, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 112 are carried out in the third embodiment, as shown in FIG. 248.

When it is recognized in the pre-process that ES=40 and EP=0 [cf. FIG. 202(E)], the control unit 42 executes emulation of the MTU 30, as shown in FIG. 248. In the post-process, the control unit 42 updates ES
 5 to "70 and EP to "+1" in the RAM 46 (process ID = 8.40.40).

When it is recognized in the pre-process that ES=70 and EP=-4 [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position SBID+EP
 10 [position n in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out a real operation (real WTM), as shown in FIG. 248. In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and
 15 updates ES to "10" in the RAM 46 (process ID = 8.70.00).

When it is recognized in the pre-process that ES=70 and EP=-3 [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position SBID+EP
 [position n+1 in FIG. 202(H)] in the MTU 30, and makes
 20 the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.70.10).

25 When it is recognized in the pre-process that ES=70 and EP=-2 [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position SBID+EP

[position n+2 in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.70.20).

When it is recognized in the pre-process that ES=70 and EP=-1 [cf. FIG. 202(H)], the control unit 42 re-positions the head at a position SBID+EP [position n+3 in FIG. 202(H)] in the MTU 30, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.70.30).

When it is recognized in the pre-process that ES=70 and EP=0 [cf. FIG. 202(H)], the control unit 42 executes emulation of the MTU 30. In the post-process, the control unit 42 updates ES to "70" and EP to "+1" in the RAM 46 (process ID = 8.70.40).

When it is recognized in the pre-process that ES=70 and EP=+1 [cf. FIG. 202(H)], the control unit 42 makes the MTU 30 carry out the WTM process to write the third tape mark TM-c on the magnetic tape MT, and makes the MTU 30 carry out the real operation (real WTM). In the post-process, the control unit 42 stores a real BID of a TM written by the MTU 30 in the save

area (SBID) 46e in the RAM 46, and updates ES to "10" in the RAM 46 (process ID = 8.70.50).

When it is recognized in the pre-process that ES=80 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 8.70.00 to 8.70.50 described above are carried out in the pre-processes and post-processes (process IDs = 8.80.00 to 8.80.50). In the post-process of process ID = 8.80.40, ES in the RAM 46 is updated to "80".

10 ② WTM Process in Pattern 2 (cf. FIG. 249)

When it is recognized in the pre-process that ES is any one of 31, 41, 51 and 61, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 113 are carried out in the third embodiment, as shown in FIG. 249.

When it is recognized in the pre-process that ES=41 and EP=0 [cf. FIG. 202(E)], the control unit 42 executes emulation of the MTU 30, as shown in FIG. 249. In the post-process, the control unit 42 updates ES to "71" and EP to "+1" in the RAM 46 (process ID = 8.41.40).

When it is recognized in the pre-process that ES=71 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 8.70.00 to 8.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 249 (process IDs = 8.71.00 to 8.71.50). In the post-process of process

5

10

15

20

25

When it is recognized in the pre-process that ES=72 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 8.70.00 to 8.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 250 (process IDs = 8.72.00 to 8.72.50). In the post-process of process

ID = 8.72.40, ES in the RAM 46 is held at a value of "72".

When it is recognized in the pre-process that ES=82 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 8.70.00 to 8.70.50 described above are carried out in the pre-processes and post-processes (process IDs = 8.82.00 to 8.82.50). In the post-process of process ID = 8.82.40, ES in the RAM 46 is held at a value of "82".

④ WTM Process in Pattern 4 (cf. FIG. 251)

When it is recognized in the pre-process that ES is any one of 33, 43, 53 and 63, pre-processes and post-processes almost similar to those in the second embodiment shown in FIG. 115 are carried out in the third embodiment, as shown in FIG. 251.

When it is recognized in the pre-process that ES=43 and EP=0 [cf. FIG. 202(E)], the control unit 42 executes emulation of the MTU 30, as shown in FIG. 251. In the post-process, the control unit 42 updates ES to "73 and EP to "+1" in the RAM 46 (process ID = 8.43.40).

When it is recognized in the pre-process that ES=73 [cf. FIG. 202(H)], processes almost similar to the processes of process IDs = 8.70.00 to 8.70.50 described above are carried out in the pre-processes and post-processes, as shown in FIG. 251 (process IDs = 8.73.00 to 8.73.50). In the post-process of process

ID = 8.73.40, ES in the RAM 46 is held at a value of "73".

When it is recognized in the pre-process that ES=83 [cf. FIG. 202(I)], processes almost similar to the processes of process IDs = 8.70.00 to 8.70.50 described above are carried out in the pre-processes and post-processes (process IDs = 8.83.00 to 8.83.50). In the post-process of process ID = 8.83.40, ES in the RAM 46 is held at a value of "83".

10 [3-3] Concrete Examples of Emulation Execution

Next, concrete examples of emulation executed by applying the processes (process IDs = 1.00.00 to 8.83.50) described above with reference to FIGS. 204 through 251 to the control process by the I/F converting apparatus 40 (control unit 42) will be described with reference to FIGS. 252 through 275.

[3-3-1] Example 1 of Emulation Execution

FIGS. 252(A) and 252(B) are diagrams showing a state of data writing on the magnetic tape MT, and for illustrating an example of commands issued from the CPU 20 when a multi-file is additionally written, and tape operations/emulation operations in the MTU 30 according to the third embodiment in response to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) by the MTU 30 shown in FIGS. 252(A) and 252(B) are the same as those

described above with reference to FIGS. 22(A) and 22(B) in the first embodiment, descriptions of which are thus omitted. Incidentally, an identification pattern for EOF1 and EOF2 in the example shown in FIGS. 252(A) and 252(B) is Pattern 1 described above with reference to FIGS. 69 and 70(A) through 70(G) in the second embodiment.

Using the method according to the third embodiment, the I/F converting apparatus 40 (control unit 42) can execute, not only emulation of command processing (8) to (19) similar to those in the second embodiment [cf. FIGS. 116(A) and 116(B)] in the open process [cf. (8) to (22)] shown in FIGS. 252(A) and 252(B), but also emulation of command processing (6) and (7) in the close process [cf. (2) to (7)] shown in FIG. 252(A).

Namely, the command processing (6) to (19) enclosed by broken lines in FIGS. 252(A) and 252(B) are emulated, according to the third embodiment. During which, no mechanical operation is performed without writing the third tape mark TM-c with the head H being stopped immediately after the second tape mark TM-b, as shown in FIG. 252(A). At this time, EOF1 saved in the save area (SDT1) 46c in the RAM 46 is read out, and transferred to the CPU 20 via the data buffer 45 when emulation is executed in response to an RD command (11), according to the third embodiment.

Hereinafter, the command processing (1) to (20) shown in FIGS. 252(A) and 252(B) will be described in detail with reference to FIGS. 253 through 272.

(A) of FIGS. 253 through 272 shows a state of data block writing on the magnetic tape MT, a real head position (real BID) and a virtual head position (EP), when each of the command processing (1) to (20) is carried out. (B) of FIGS. 253 and 272 shows a state of data saving/storing in the RAM 46, when each of the command processing (1) to (20) is carried out.

(1) WR process

FIG. 253(A) shows a state in which the I/F converting apparatus receives a WR command (1) shown in FIG. 252(A) from the CPU 20, completes a writing of user data, and is about to shift to the close process for a file. The real head position (real BID) is N. At this time, ES in the control area 46a in the RAM 46 indicates the initial state (ES=00), as shown in FIG. 253(B). The control area (EP) 46 b and the save areas 46c through 46e in the RAM 46 indicate the undetermined state.

(2) WTM process (First Tape Mark TM-a Write Process)

FIG. 254(A) shows a state in which the I/F converting apparatus 40 receives a WTM command (2) shown in FIG. 252(A) from the CPU 20, carries out a process of process ID = 8.00.00, and completes a writing of the first tape mark TM-a so that the real

FIG. 257(A) shows a state in which the I/F converting apparatus 40 receives a WTM command (5) shown in FIG. 252(A) from the CPU 20, carries out a process of process ID = 8.30.00 and completes a writing of the second tape mark TM-b so that the real head position (real BID) is N+4. At this time, after checking that a difference between the real BID and SBID [(real BID) - (SBID)] is "3", the I/F converting apparatus 40 stores "N+4" in the save area, as shown in FIG. 257(B). As shown in FIG. 257(B), ES in the control area 46a is updated to "40", whereas "0" is set as EP in the control area 46b.

(6) WTM Process (Third Tape Mark TM-c Write Process)

FIG. 258(A) shows a state in which the I/F converting apparatus 40 receives a WTM command (6) shown in FIG. 252(A) from the CPU 20, carries out a process of process ID = 8.40.40 and completes a virtual operation (emulation) of writing the third tape mark TM-c. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 258(B), ES in the control area 46a is updated to "70" and EP in the control area 46b is updated to "+1".

Thereafter, a writing of the third tape mark TM-c is assumed to be completed without really writing the third tape mark TM-c so that completion of writing of the third tape mark TM-c is reported to the CPU 20, according to the third embodiment.

(7) BSPF Process

FIG. 259(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (7) shown in FIG. 252(A) from the CPU 20, and carries out
5 a process of process ID = 5.70.50 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 259(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated
10 to "0".

(8) BSPF Process

FIG. 260(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (8) shown in FIG. 252(A) from the CPU 20, and carries out
15 a process of process ID = 5.70.40 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 260(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated
20 to "-1".

(9) BSPF Process

FIG. 261(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (9) shown in FIG. 252(A) from the CPU 20, and carries out
25 a process of process ID = 5.70.30 so as to execute emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG.

261(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated to "-4".

(10) FSPF Process

5 FIG. 262(A) shows a state in which the I/F converting apparatus 40 receives an FSPF command (10) shown in FIG. 252(A) from the CPU 20, and carries out a process of process ID = 7.70.00 so as to execute emulation. At this time, the real head position (real
10 BID) is still N+4, not changed. As shown in FIG. 262(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated to "-3".

(11) RD Process

15 FIG. 263(A) shows a state in which the I/F converting apparatus 40 receives an RD command (11) shown in FIG. 252(A) from the CPU 20, and carries out a process of process ID = 1.70.10 so as to execute emulation. At this time, the real head position (real
20 BID) is still N+4, not changed. As shown in FIG. 263(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated to "-2". When the emulation is executed, contents EOF1 in the save area 46c are restored in the data
25 buffer 45, and transferred to the CPU 20.

(12) FSPF Process

FIG. 264(A) shows a state in which the I/F

converting apparatus 40 receives an FSPF command (12) shown in FIG. 252(A) from the CPU 20, and carries out a process of process ID = 7.70.20 so as to execute emulation. At this time, the real head position (real
5 BID) is still N+4, not changed. As shown in FIG. 264(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated to "0".

(13) RD Process

10 FIG. 265(A) shows a state in which the I/F converting apparatus 40 receives an RD command (13) shown in FIG. 252(A) from the CPU 20, and carries out a process of process ID = 1.70.40 so as to execute emulation. At this time, the real head position (real
15 BID) is still N+4, not changed. As shown in FIG. 265(B), ES in the control area 46a is held at a value of "70", whereas EP in the control area 46b is updated to "+1". When the emulation is executed, tape mark detection (Unit Exception) is reported to the CPU 20.

20 (14) BSPF Process

FIG. 266(A) shows a state in which the I/F converting apparatus 40 receives a BSPF command (14) shown in FI. 252(A) from the CPU 20, and carries out a process of process ID = 5.70.50 so as to execute
25 emulation. At this time, the real head position (real BID) is still N+4, not changed. As shown in FIG. 266(B), ES in the control area 46a is held at a value

of "70", whereas EP in the control area 46b is updated to "0".

(15) BSPF Process

FIG. 267(A) shows a state in which the I/F
5 converting apparatus 40 receives a BSPF command (15)
shown in FIG. 252(A) from the CPU 20, and carries out
a process of process ID = 5.70.40 so as to execute
emulation. At this time, the real head position (real
BID) is still N+4, not changed. As shown in FIG.
10 267(B), ES in the control area 46a is held at a value
of "70", whereas EP in the control area 46b is updated
to "-1".

(16) BSPF Process

FIG. 268(A) shows a state in which the I/F
15 converting apparatus 40 receives a BSPF command (16)
shown in FIG. 252(A) from the CPU 20, and carries out
a process of process ID = 5.70.30 so as to execute
emulation, as does in the command processing (9). At
this time, the real head position (real BID) is still
20 at N+4, not changed. As shown in FIG. 268(B), ES in
the control area 47a is held at a value of "70", whereas
EP in the control area 46b is updated to "-4".

(17) FSPF Process

FIG. 269(A) shows a state in which the I/F
25 converting apparatus 40 receives an FSPF command (17)
shown in FIG. 252(B) from the CPU 20, and carries out
a process of process ID = 7.70.00 so as to execute

(20) WR Process (HRR1 Write Process)

FIG. 272(A) shows a state in which the I/F converting apparatus 40 receives a WR command (20) (direction to write HRR1) shown in FIG. 252(B) from the CPU 20, carries out a process of process ID = 3.70.41, and completes a writing of HRR1 so that the real head position (real BID) is N+5. At this time, ES in the control area 46a is updated to "00", whereas the control area 46b and the save areas 46c to 46e are in the undetermined state, as shown in FIG. 272(B). According to the third embodiment, when a multi-file is additionally written, a writing of data of a header (HDR) is commenced immediately after the second tape mark TM-b without really writing the third tape mark TM-c, as above.

Thereafter, a WR process (21) (HDR2 write process), a WTM process (22), a WR process (23) and a WR process (24) are carried out in the similar manner to the second embodiment (as described above with reference to FIGS. 137 through 140), descriptions of which are thus omitted.

[3-3-2] Example 2 of Emulation Execution

FIGS. 273(A) and 273(B) are diagrams showing
25 a state of data writing on the magnetic tape MT, and
for illustrating another example of commands issued
from the CPU 20 when a multi-file is additionally

written, and tape operations/emulation operations in the MTU 30 according to the third embodiment in response to the commands. The state of data writing on the magnetic tape MT, the commands issued from the CPU 20 and the tape operations (arrows) in the MTU 30 shown in FIGS. 273(A) and 273(B) are the same as those described above with reference to FIGS. 61(A) and 61(B), descriptions of which are thus omitted. An identification pattern for EOF1 and EOF2 in the example shown in FIGS. 273(A) and 273(B) is Pattern 1 described above with reference to FIGS. 69(A) and 70(A) through 70(G) in the second embodiment.

Using the method according to the third embodiment, the I/F converting apparatus 40 (control unit 42) can execute emulation of, not only the command processing (8) to (14) similar to those in the second embodiment [cf. FIG. 155(A)] in the open process [cf. (8) to (17)] shown in FIGS. 273(A) and 273(B), but also the command processing (6) and (7) in the close process [cf. (2) to (7)] shown in FIG. 273(A).

Namely, the command processing (6) to (14) enclosed by a broken line in FIG. 273(A) are emulated in the third embodiment. During which, no mechanical operation is performed with the head H being stopped immediately after the second tape mark TM-b without writing the third tape mark TM-c. According to the third embodiment, EOF1 saved in the save area (SDT1)

46c in the RAM 46 is read out, and transferred to the CPU 20 via the data buffer 45 when the emulation is executed in response to an RD command (11).

Meanwhile, the command processing (1) to (14) shown in FIG. 273(A) are identical to the command processing (1) to (14) described above with reference to FIGS. 252(A) and 253 through 266, and the command processing (15) to (19) shown in FIG. 273(B) are identical to the command processing (20) to (24) described above with reference to FIGS. 252(B), 272 and 137 through 140, descriptions of which are thus omitted.

[3-3-3] Comparison of Performance (Comparison of Command Processing Times)

FIG. 274 is a diagram in which, when a multi-file is additionally written as shown in FIG. 252(A) and 252(B), a time required for command processing when the emulation is executed applying the method according to the third embodiment is compared with a time required for command processing applying the know manner without emulation.

In FIG. 274, a time required for each command processing in which emulation is not executed is compared with a time required for the same processing in which emulation is executed side by side. In FIG. 274, a number in parentheses is entered in a remarks column of a command corresponding to each of the

command processing (1) to (24) shown in FIGS. 252(A) and 252(B). Incidentally, a command without a number in parentheses in its remarks column does not relate to the tape operation in the MTU 30, a process corresponding to which is completed within the MTC 10.

The command processing (6) to (19) in which emulation is executed are completed within the I/F converting apparatus 40 without the real tape operation (mechanical operation) of the MTU 30 so that a time required for each of the command processing (6) to (19) is uniformly 0.000500 second, as shown in FIG. 274. Not only that the process time is shortened by emulation as above, a time required for a part of command processing not relating to emulation is also shortened in the system executing emulation by applying the method of the third embodiment. In contrast to 9.111926 second that is a time required for all the command processing without emulation, a time required for all the command processing in the system to which the method of the third embodiment is applied is 1.981191 second, which is much shorter.

FIG. 275 is a diagram in which, when a multi-file is additionally written as shown in FIGS. 273(A) and 273(B), a time required for command processing in which emulation is carried out by applying the method of the third embodiment is compared with a time required for the command

processing in which emulation is not carried out by applying the known method.

In FIG. 275, a time required for each command processing when emulation is not executed is compared
5 with a time required for the same command processing when emulation is executed side by side. In FIG. 275, a number in parentheses is entered in a remarks column of a command corresponding to each of the command processing (1) to (19) shown in FIGS. 273 (A) and 273 (B).
10 Incidentally, a command without a number in parentheses in its remarks column does not relate to the tape operation in the MTU 30, a process corresponding to which is completed within the MTC 10.

The command processing (6) to (14) in which
15 emulation is executed are completed within the I/F converting apparatus 40 without the real tape operation (mechanical operation) of the MTU 30 so that a time required for each of the command processing (6) to (14) is uniformly shorter than a case where
20 emulation is not executed. Not only a time required for the command processing is shortened by emulation, but also a time required for a part of the command processing not relating to emulation is also shortened in a system executing emulation by applying the method
25 of the third embodiment. In contrast to 6.331092 second that is a time required for all the command processing in which emulation is not carried out, a

time required for all the command processing in a system to which the method of the third embodiment is applied is 1.296330 second, which is much shorter.

Meanwhile, estimated values of performance in FIG. 275 are calculated on the bases of measured values obtained by performance measurement using an actual machine. Accordingly, there are variations in measuring environments such as a performance of the actual machine and the like. As a result, with respect to a command processing not relating to emulation, a value obtained when the emulation is not executed (value on the left in FIG. 275) and a value obtained when the emulation is executed (value on the right in FIG. 275) are not equal.

[3-4] Effects of the Third Embodiment

The method for controlling a magnetic tape unit according to the third embodiment of this invention can give effects similar to those given by the first embodiment and second embodiment. In addition, the third embodiment can simplify the tape operations in not only the open process but also the close process by emulating both the tape operations for identifying EOF when the open process for a file is carried out and the operation of writing the third tape mark TM-c when a close process for the file is carried out in the I/F converting apparatus 40. In consequence, not only a time required for the open

process but also a time required for the close process can be shortened, a time required to process a job is thus further shortened. This further improves a performance when the close/open process is carried out, which leads to an improvement of a processing performance of a system accessing to the MTU 30.

Even if the apparatus terminates a process with the third tape mark TM-c not being recorded on the magnetic tape due to a failure such as power-off or the like after executing emulation of an operation of writing the third tape mark TM-c, EOD immediately after the second tape mark TM-b is assumed to be the third tape mark TM-c after recovery of the failure, according to the third embodiment. The CPU 20 can thereby issue a command to the CPU 20 as usual to continuously carry out the process without making the MTU 30 carry out a special process for recovery such as third tape mark TM-c writing or the like.

[4] Others

Note that the present invention is not limited to the above examples, but can be modified in various ways without departing from the scope of the invention.

According to the third embodiment, not only a writing of the third tape mark TM-c is emulated in the close process for a file, but also emulation similar to that according to the second embodiment is

5

10

15

11 read operation.

1 3. The method for controlling a magnetic tape unit
2 according to claim 1, wherein in a close process for
3 said file, an end-of-file label written by said
4 magnetic tape unit in response to a command from said
5 command issuing apparatus is saved in a save area; and
6 in an open process for said file, said
7 end-of-file label is transferred to said command
8 issuing apparatus from said save area in response to
9 a command directing to read said end-of-file label
10 without making said magnetic tape unit carry out a real
11 read operation.

1 4. The method for controlling a magnetic tape unit
2 according to claim 1, wherein in a close process for
3 said file, said magnetic tape unit is made to carry
4 out a real read operation to really read an end-of-file
5 label, which is skipped in said magnetic tape unit in
6 response to a command from said command issuing
7 apparatus, said read end-of-file label is saved in a
8 save area; and
9 in an open process for said file, said
10 end-of-file label is transferred to said command
11 issuing apparatus from said save area in response to
12 a command directing to read said end-of-file label
13 without making said magnetic tape unit carry out a real

00000"00000000

14 read operation.

1 5. The method for controlling a magnetic tape unit
2 according to claim 2, wherein when, in an open process
3 for said file, a command directing to read said
4 end-of-file label is received in a state in which said
5 end-of-file label is not saved in said save area, said
6 magnetic tape unit is made to carry out a real read
7 operation to really read said end-of-file label, and
8 said read end-of-file label is transferred to said
9 command issuing apparatus.

1 6. The method for controlling a magnetic tape unit
2 according to claim 1, wherein a data buffer for
3 temporarily storing write data to said magnetic tape
4 and read data from said magnetic tape therein is
5 interposed between said command issuing apparatus and
6 said magnetic tape unit to asynchronously carry out
7 a read/write process between said command issuing
8 apparatus and said data buffer and a read/write
9 process between said data buffer and said magnetic
10 tape unit.

1 7. The method for controlling a magnetic tape unit
2 according to claim 1, wherein a tape operation of said
3 magnetic tape unit is such controlled that, on said
4 magnetic tape, the first tape mark is written after

5 the last data block of said file, the first end-of-file
6 label and the second end-of-file label are written
7 after said first tape mark, the second tape mark is
8 written after said second end-of-file label, and the
9 third tape mark is further written after said second
10 tape mark when said file is the last on said magnetic
11 tape, whereas the next file is written over said third
12 tape mark to be written when the next file is
13 additionally written after said file; and

14 said emulation is executed between
15 immediately before said first tape mark and
16 immediately after said third tape mark while fixing
17 said head at said predetermined position which is
18 immediately after said second tape mark.

1 8. The method for controlling a magnetic tape unit
2 according to claim 7, wherein while said emulation is
3 executed, a virtual position of said head (hereinafter
4 referred to as a virtual head position) relative to
5 said magnetic tape in said magnetic tape unit is
6 managed as a relative position of said head relative
7 to said predetermined position.

1 9. The method for controlling a magnetic tape unit
2 according to claim 8, wherein when a command requiring
3 the real head position in said magnetic tape unit is
4 received while said emulation is executed, a sum of

15 command, a forward space block command, a forward
16 space file command, and a write tape mark command is
17 received, with said virtual head position being
18 immediately after said second end-of-file label;

19 when any one of a read command, a read backward
20 command, a back space block command, a back space file
21 command, a forward space block command and a forward
22 space file command is received, with said virtual head
23 position being immediately after said first end-
24 of-file label;

25 when any one of a read command, a read back
26 command, a back space block command, a back space file
27 command, a forward space block command and a forward
28 space file command is received, with said virtual head
29 position being immediately after said first tape mark;
30 or

31 when any one of a read command, a forward space
32 block command and a forward space file command is
33 received, with said virtual head position being
34 immediately after said last data block, said emulation
35 is executed.

1 12. The method for controlling a magnetic tape unit
2 according to claim 7, wherein in a state in which both
3 of said first end-of-file label and said second
4 end-of-file label are saved in said save areas, and
5 in a state in which reading/writing up to said third

6 tape mark is completed and the real head position is
7 said predetermined position in said magnetic tape
8 unit;

9 when any one of a read backward command, a back
10 space block command and a back space file command is
11 received, with said virtual head position being
12 immediately after said third tape mark;

13 when any one of a read command, a read backward
14 command, a back space block command, a back space file
15 command, a forward space block command, a forward
16 space file command and a write tape mark command is
17 received, with said virtual head position being
18 immediately after said second tape mark;

19 when any one of a read command, a read backward
20 command, a back space block command, a back space file
21 command, a forward space block command and a forward
22 space file command is received, with said virtual head
23 position being immediately after said second end-
24 of-file label;

25 when any one of a read command, a read backward
26 command, a back space block command, a back space file
27 command, a forward space block command and a forward
28 space file command is received, with said virtual head
29 position being immediately after said first end-
30 of-file label;

31 when any one of a read command, a read backward
32 command, a back space block command, a back space file

00000-00000000

37 when any one of a read command, a forward space
38 block command and a forward space file command is
39 received, with said virtual head position being
40 immediately after said last data block, said emulation
41 is executed.

8 when any one of a read backward command, a back
9 space block command and a back space file command is
10 received, with said virtual head position being
11 immediately after said second tape mark;

12 when any one of a read command, a read backward
13 command, a back space block command, a back space file
14 command, a forward space block command, a forward
15 space file command and a write tape mark command is
16 received, with said virtual head position being
17 immediately after said second end-of-file label;

18 when any one of a read backward command, a back
19 space block command, a back space file command, a
20 forward space block command and a forward space file
21 command is received, with said virtual head position
22 being immediately after said first end-of-file label;

23 when any one of a read command, a read backward
24 command, a back space block command, a back space file
25 command, a forward space block command and a forward
26 space file command is received, with said virtual head
27 position being immediately after said first tape mark;

28 or

29 when any one of a read command, a forward space
30 block command and a forward space file command is
31 received, with said virtual head position being
32 immediately after said last data block, said emulation
33 is executed.

1 14. The method for controlling a magnetic tape unit
2 according to claim 7, wherein in a state in which only
3 said first end-of-file label is saved in said save area,
4 and in a state in which reading/writing up to said
5 third tape mark is completed and the real head position
6 is said predetermined position in said magnetic tape
7 unit;

8 when any one of a read backward command, a back
9 space block command and a back space file command is
10 received, with said virtual head position being

11 immediately after said third tape mark;
12 when any one of a read command, a read backward
13 command, a back space block command, a back space file
14 command, a forward space block command, a forward
15 space file command and a write tape mark command is
16 received, with said virtual head position being
17 immediately after said second tape mark;
18 when any one of a read command, a read backward
19 command, a back space block command, a back space file
20 command, a forward space block command and a forward
21 space file command is received, with said virtual head
22 position being immediately after said second end-
23 of-file label;
24 when any one of a read backward command, a back
25 space block command, a back space file command, a
26 forward space block command and a forward space file
27 command is received, with said virtual head position
28 being immediately after said first end-of-file label;
29 when any one of a read command, a read backward
30 command, a back space block command, a back space file
31 command, a forward space block command and a forward
32 space file command is received, with said virtual head
33 position being immediately after said first tape mark;
34 or
35 when any one of a read command, a forward space
36 block command and a forward space file command is
37 received, with said virtual head position being

00000"50055550

38 immediately after said last data block, said emulation
39 is executed.

1 15. The method for controlling a magnetic tape unit
2 according to claim 7, wherein in a state in which only
3 said second end-of-file label is saved in said save
4 area, and in a state in which reading/writing up to
5 said second tape mark is completed and the real head
6 position is said predetermined position in said
7 magnetic tape unit;

8 when any one of a read backward command, a back
9 space block command and a back space file command is
10 received, with said virtual head position being
11 immediately after said second tape mark;

12 when any one of a read command, a read backward
13 command, a back space block command, a back space file
14 command, a forward space block command, a forward
15 space file command and a write tape mark command is
16 received, with said virtual head position being
17 immediately after said second end-of-file label;

```

18         when any one of a read command, a read backward
19     command, a back space block command, a back space file
20     command, a forward space block command and a forward
21     space file command is received, with said virtual head
22     position being immediately after said first end-
23     of-file label;

```

24 when any one of a read backward command, a back

25 space block command, a back space file command, a
 26 forward space block command and a forward space file
 27 command is received, with said virtual head position
 28 being immediately after said first tape mark; or
 29 when any one of a read command, a forward space
 30 block command and a forward space file command is
 31 received, with said virtual head position being
 32 immediately after said last data block, said emulation
 33 is executed.

1 16. The method for controlling a magnetic tape unit
 2 according to claim 7, wherein in a state in which only
 3 said second end-of-file label is saved in said save
 4 area, and in a state in which reading/writing up to
 5 said third tape mark is completed and the real head
 6 position is said predetermined position in said
 7 magnetic tape unit;
 8 when any one of a read backward command, a back
 9 space block command and a back space file command is
 10 received, with said virtual head position being
 11 immediately after said third tape mark;
 12 when any one of a read command, a read backward
 13 command, a back space block command, a back space file
 14 command, a forward space block command, a forward
 15 space file command and a write tape mark command is
 16 received, with said virtual head position being
 17 immediately after said second tape mark;

000000"00000000

```

18         when any one of a read command, a read backward
19     command, a back space block command, a back space file
20     command, a forward space block command and a forward
21     space file command is received, with said virtual head
22     position being immediately after said second end-
23     of-file label;

```

24 when any one of a read command, a read backward
25 command, a back space block command, a back space file
26 command, a forward space block command and a forward
27 space file command is received, with said virtual head
28 position being immediately after said first end-
29 of-file label;

30 when any one of a read backward command, a back
31 space block command, a back space file command, a
32 forward space block command and a forward space file
33 command is received, with said virtual head position
34 being immediately after said first tape mark; or

35 when any one of a read command, a forward space
36 block command and a forward space file command is
37 received, with said virtual head position being
38 immediately after said last data block, said emulation
39 is executed.

1 17. The method for controlling a magnetic tape unit
2 according to claim 7, wherein in a state in which
3 neither said first end-of-file label nor said second
4 end-of-file label is saved in said save area, and in

5 a state in which reading/writing up to said second tape
6 mark is completed and the real head position is said
7 predetermined position in said magnetic tape unit;
8 when any one of a read backward command, a back
9 space block command and a back space file command is
10 received, with said virtual head position being
11 immediately after said second tape mark;
12 when any one of a read command, a read backward
13 command, a back space block command, a back space file
14 command, a forward space block command, a forward
15 space file command and a write tape mark command is
16 received, with said virtual head position being
17 immediately after said second end-of-file label;
18 when any one of a read backward command, a back
19 space block command, a back space file command, a
20 forward space block command and a forward space file
21 command is received, with said virtual head position
22 being immediately after said first end-of-file label;
23 when any one of a read backward command, a back
24 space block command, a back space file command, a
25 forward space block command and a forward space file
26 command is received, with said virtual head position
27 being immediately after said first tape mark; or
28 when any one of a read command, a forward space
29 block command and a forward space file command is
30 received, with said virtual head position being
31 immediately after said last data block, said emulation

00000"50000000

32 is executed.

1 18. The method for controlling a magnetic tape unit
2 according to claim 7, wherein in a state in which
3 neither said first end-of-file label nor said second
4 end-of-file label is saved in said save area, and in
5 a state in which reading/writing up to said third tape
6 mark is completed and the real head position is said
7 predetermined position in said magnetic tape unit;

8 when any one of a read backward command, a back
9 space block command and a back space file command is
10 received, with said virtual head position being
11 immediately after said third tape mark;

12 when any one of a read command, a read backward
13 command, a back space block command, a back space file
14 command, a forward space block command, a forward
15 space file command and a write tape mark command is
16 received, with said virtual head position being
17 immediately after said second tape mark;

```

18         when any one of a read command, a read backward
19 command, a back space block command, a back space file
20 command, a forward space block command and a forward
21 space file command is received, with said virtual head
22 position being immediately after said second end-
23 of-file label;

```

24 when any one of a read backward command, a back
25 space block command, a back space file command, a

26 forward space block command and a forward space file
27 command is received, with said virtual head position
28 being immediately after said first end-of-file label;
29 when one of a read backward command, a back
30 space block command, a back space file command, a
31 forward space block command and a forward space file
32 command is received, with said virtual head position
33 being immediately after said first tape mark; or
34 when one of a read command, forward space block
35 command and a forward space file command is received,
36 with said virtual head position being immediately
37 after said last data block, said emulation is
38 executed.

1 19. The method for controlling a magnetic tape unit
2 according to claim 7, wherein when, in a close process
3 for said file, a command requiring to write said third
4 tape mark is received after said second tape mark is
5 written on said magnetic tape, completion of a writing
6 of said third tape mark is reported to said command
7 issuing apparatus without writing said third tape
8 mark.

1 20. The method for controlling a magnetic tape unit
2 according to claim 19, wherein when a command
3 directing to position said head outside a region from
4 immediately before said first tape mark to immediately

5 after said third tape mark is received, said third tape
6 mark is written, and said magnetic tape unit is then
7 made to carry out a tape operation according to said
8 command.

1 21. The method for controlling a magnetic tape unit
2 according to claim 19, wherein when EOD (End Of Data)
3 is detected after said second tape mark in said
4 magnetic tape unit during a tape operation in response
5 to a command from said command issuing apparatus,
6 detection of said third tape mark is reported in lieu
7 of detection of said EOD to said command issuing
8 apparatus.

1 22. A method for controlling a magnetic tape unit in
2 response to a command from a command issuing apparatus
3 comprising the steps of:
4 in a close process for a file recorded on a
5 magnetic tape, controlling a tape operation of said
6 magnetic tape unit such that, on said magnetic tape,
7 the first tape mark is written after the last data
8 block of said file, at least one end-of-file label is
9 written after said first tape mark, and the second tape
10 mark is written after said end-of-file label, and
11 reporting completion of a writing of said third tape
12 mark to said command issuing apparatus without writing
13 said third tape mark even if a command requiring to

14 write said third tape mark is received.

1 23. The method for controlling a magnetic tape unit
2 according to claim 22, wherein when a command in a
3 motion system involving unloading and rewinding is
4 received, said third tape mark is written, and said
5 magnetic tape unit is then made to carry out a tape
6 operation according to said command in the motion
7 system.

1 24. The method for controlling a magnetic tape unit
2 according to claim 22, wherein when EOD (End Of Data)
3 is detected after said second tape mark in said
4 magnetic tape unit during a tape operation in response
5 to a command from said command issuing apparatus,
6 detection of said third tape mark is reported in lieu
7 of detection of said EOD to said command issuing
8 apparatus.

1 25. The method for controlling a magnetic tape unit
2 according to claim 6, wherein a plurality of end-
3 of-file labels are recorded as one physical block on
4 said magnetic tape by a packeting function;
5 when a command directing to read one of said
6 plurality of end-of-file labels is received in a close
7 process for said file, said one physical block
8 including the end-of-file label to be read is read out

Overall		Non-Black		Black	
Mean	SD	Mean	SD	Mean	SD
Age	35.1	35.1	35.1	35.1	35.1
Gender	50.0	50.0	50.0	50.0	50.0
Marital status	50.0	50.0	50.0	50.0	50.0
Education	12.0	12.0	12.0	12.0	12.0
Income	10.0	10.0	10.0	10.0	10.0
Health status	50.0	50.0	50.0	50.0	50.0
Employment	50.0	50.0	50.0	50.0	50.0
Substance use	50.0	50.0	50.0	50.0	50.0
Family size	3.0	3.0	3.0	3.0	3.0
Urban/rural	50.0	50.0	50.0	50.0	50.0
Health insurance	50.0	50.0	50.0	50.0	50.0
Health care access	50.0	50.0	50.0	50.0	50.0
Health care utilization	50.0	50.0	50.0	50.0	50.0
Health care satisfaction	50.0	50.0	50.0	50.0	50.0
Health care access barriers	50.0	50.0	50.0	50.0	50.0
Health care utilization barriers	50.0	50.0	50.0	50.0	50.0
Health care satisfaction barriers	50.0	50.0	50.0	50.0	50.0
Health care access facilitators	50.0	50.0	50.0	50.0	50.0
Health care utilization facilitators	50.0	50.0	50.0	50.0	50.0
Health care satisfaction facilitators	50.0	50.0	50.0	50.0	50.0
Health care access barriers and facilitators	50.0	50.0	50.0	50.0	50.0
Health care utilization barriers and facilitators	50.0	50.0	50.0	50.0	50.0
Health care satisfaction barriers and facilitators	50.0	50.0	50.0	50.0	50.0
Health care access barriers and facilitators (Black)	50.0	50.0	50.0	50.0	50.0
Health care utilization barriers and facilitators (Black)	50.0	50.0	50.0	50.0	50.0
Health care satisfaction barriers and facilitators (Black)	50.0	50.0	50.0	50.0	50.0
Health care access barriers and facilitators (Non-Black)	50.0	50.0	50.0	50.0	50.0
Health care utilization barriers and facilitators (Non-Black)	50.0	50.0	50.0	50.0	50.0
Health care satisfaction barriers and facilitators (Non-Black)	50.0	50.0	50.0	50.0	50.0

ABSTRACT OF THE DISCLOSURE

A tape operation relating to EOF identification in an open process for a file is emulated, whereby the tape operation in the open process is simplified. Consequently, open-process, close-process performance, and process performance of a system accessing to a magnetic tape unit can be improved. In a method of this invention, a position of a head relative to a magnetic tape is fixed at a predetermined position in the open process for a file recorded on the magnetic tape, and when a command is received from a command issuing apparatus, emulation in which a tape operation according the command is virtually carried out in the magnetic tape unit without making said magnetic tape unit carry out a real tape operation, is executed. This invention is applied when a tape operation of the magnetic tape unit is controlled by a command from a host computer/upper apparatus such as a CPU or the like.

FIG. 2(A)




FIG. 2(B)




FIG. 3(A)




FIG. 3(B)



FIG. 3(C)




FIG. 3(D)




FIG. 3(E)




FIG. 3(F)




FIG. 3(G)




FIG. 4




FIG. 5

PROCESS A10					PROCESS B10							PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID	
ES	EP											
0	-4	--	REAL READ	XBID+1	TM	1	-3	1	--	0	XBID	1000
					OTHERS	0	-4	0	--	LEN		1001
1	-3	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	LEN	XBID	1100
					TM	1	-3	1	--	0		1101
					OTHERS	0	-4	0	--	LEN		1102
2	-2	--	REAL READ	XBID+1	EOF	3	-1	0	SDT2←BUF ;SLN2←LEN	LEN	XBID	1200
					TM	1	-3	1	--	0		1201
					OTHERS	0	-4	0	--	LEN		1202
3	-1	--	REAL READ	XBID+1	TM	4	0	1	--	0	XBID	1300
					OTHERS	0	-4	0	--	LEN		1301
4	-4	--	EMULATE	--	--	4	-3	1	--	0	XBID + EP	1400
	-3	--	EMULATE	--	--	4	-2	0	BUF←SDT1;	SLN1		1410
	-2	--	EMULATE	--	--	4	-1	0	BUF←SDT2;	SLN2		1420
	-1	--	EMULATE	--	--	4	0	1	--	0		1430
	0	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	1440
					TM	5	+1	1	--	--		1441
					OTHERS	0	-4	0	--	--		1442
5	+1	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	1500
					TM	1	-3	1	--	--		1501
					OTHERS	0	-4	0	--	--		1502
6	-4	--	EMULATE	--	--	6	-3	1	--	0	XBID + EP	1600
	-3	--	EMULATE	--	--	6	-2	0	BUF←SDT1;	SLN1		1610
	-2	--	EMULATE	--	--	6	-1	0	BUF←SDT2;	SLN2		1620
	-1	--	EMULATE	--	--	6	0	1	--	0		1630
	0	--	EMULATE	--	--	6	+1	1	--	0		1640
	+1	XBID +EP	REAL READ	XBID+1	TM	1	-3	1	--	0	XBID	1650
					OTHERS	0	-4	0	--	LEN		1651

00000" 50866560

FIG. 6




Table 1. Demographic characteristics of the study population	
Age (years)	65.8 ± 1.2
Gender (male/female)	10/10
Education (years)	12.5 ± 0.5
Occupation (white/blue)	10/10
Marital status (married/divorced/widowed)	10/10/0
Smoking status (smoker/nonsmoker)	10/10
Alcohol consumption (yes/no)	10/10
Comorbidities (hypertension/diabetes/cholesterol)	10/10/10
Medication (antihypertensive/antidiabetic/anticholesterol)	10/10/10
Family history (hypertension/diabetes/cholesterol)	10/10/10
Physical activity (yes/no)	10/10
Stress level (low/moderate/high)	10/10/10
Sleep quality (good/poor)	10/10
Depression score (0-10)	2.5 ± 0.5
Overall health status (good/fair/poor)	10/10/10

PROCESS A20					PROCESS B20							PROCESS ID
CONDITIONS		RE-POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID	
ES	EP											
0	-4	--	REAL RB	XBID-1	TM	0	-4	1	--	0	XBID	2000
					OTHERS	0	-4	0	--	0		2001
1	-3	--	REAL RB	XBID-1	TM	0	-4	1	--	0	XBID	2100
					OTHERS	0	-4	0	--	0		2101
2	-2	--	REAL RB	XBID-1	TM	0	-4	1	--	0	XBID	2200
					OTHERS	0	-4	0	--	0		2201
3	-1	--	REAL RB	XBID-1	TM	0	-4	1	--	0	XBID	2300
					OTHERS	0	-4	0	--	0		2301
4	-4	XBID + EP	REAL RB	XBID-1	TM	0	-4	1	--	0	XBID	2400
					OTHERS	0	-4	0	--	0		2401
	-3	--	EMULATE	--	--	--	-4	1	--	0	XBID + EP	2410
	-2	--	EMULATE	--	--	--	-3	0	--	0	XBID + EP	2420
	-1	--	EMULATE	--	--	--	-2	0	--	0		2430
	0	--	EMULATE	--	--	--	-1	1	--	0	XBID	2440
5	+1	--	REAL RB	XBID-1	--	6	0	1	--	0	XBID	2500
6	-4	XBID + EP	REAL RB	XBID-1	TM	0	-4	1	--	0	XBID	2600
					OTHERS	0	-4	0	--	0		2601
	-3	--	EMULATE	--	--	--	-4	1	--	0	XBID + EP	2610
	-2	--	EMULATE	--	--	--	-3	0	--	0	XBID + EP	2620
	-1	--	EMULATE	--	--	--	-2	0	--	0		2630
	0	--	EMULATE	--	--	--	-1	1	--	0	XBID + EP	2640
	+1	--	EMULATE	--	--	--	0	1	--	0		2650

FIG. 8




FIG. 9

PROCESS A30					PROCESS B30							PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID	
ES	EP											
0	-4	--	REAL WR	XBID+1	--	0	-4	--	--	LEN	XBID	3000
1	-3	--	REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3100
					OTHERS	0	-4	--	--	LEN		3101
2	-2	--	REAL WR	XBID+1	EOF	3	-1	--	SDT2←BUF ;SLN2←LEN	LEN	XBID	3200
					OTHERS	0	-4	--	--	LEN		3201
3	-1	--	REAL WR	XBID+1	--	0	-4	--	--	LEN	XBID	3300
4	-4	XBID + EP	REAL WR	XBID+1	--	0	-4	--	--	LEN	XBID	3400
	-3		REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3410
					OTHERS	0	-4	--	--	LEN		3411
	-2		REAL WR	XBID+1	EOF	3	-1	--	SDT2←BUF ;SLN2←LEN	LEN	XBID	3420
					OTHERS	0	-4	--	--	LEN		3421
	-1		REAL WR	XBID+1	--	0	-4	--	--	LEN	XBID	3430
	0	--	REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3140
					OTHERS	0	-4	--	--	LEN		3141
5	+1	--	REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3500
					OTHERS	0	-4	--	--	LEN		3501
6	-4	XBID + EP	REAL WR	XBID+1	--	0	-4	--	--	LEN	XBID	3600
	-3		REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3610
					OTHERS	0	-4	--	--	LEN		3611
	-2		REAL WR	XBID+1	EOF	3	-1	--	SDT2←BUF ;SLN2←LEN	LEN	XBID	3620
					OTHERS	0	-4	--	--	LEN		3621
	-1		REAL WR	XBID+1	--	0	-4	--	--	LEN	XBID	3630
	0	--	REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3640
					OTHERS	0	-4	--	--	LEN		3641
	+1	XBID + EP	REAL WR	XBID+1	EOF	2	-2	--	SDT1←BUF ;SLN1←LEN	LEN	XBID	3650
					OTHERS	0	-4	--	--	LEN		3651

00000"0000000000

FIG. 10




FIG. 11

PROCESS A40					PROCESS B40							PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID	
ES	EP											
0	-4	--	REAL BSP	XBID-1	--	0	-4	0	--	0	XBID	4000
1	-3	--	REAL BSP	XBID-1	--	0	-4	0	--	0	XBID	4100
2	-2	--	REAL BSP	XBID-1	--	0	-4	0	--	0	XBID	4200
3	-1	--	REAL BSP	XBID-1	--	0	-4	0	--	0	XBID	4300
4	-4	XBID + EP	REAL BSP	XBID-1	--	0	-4	0	--	0	XBID	4400
	-3	--	EMULATE	--	--	4	-4	1	--	0	XBID + EP	4410
	-2	--	EMULATE	--	--	4	-3	0	--	0		4420
	-1	--	EMULATE	--	--	4	-2	0	--	0		4430
	0	--	EMULATE	--	--	4	-1	1	--	0		4440
5	+1	--	REAL BSP	XBID-1	--	6	0	1	--	0	XBID	4500
6	-4	XBID + EP	REAL BSP	XBID-1	--	0	-4	0	--	0	XBID	4600
	-3	--	EMULATE	--	--	4	-4	1	--	0	XBID + EP	4610
	-2	--	EMULATE	--	--	4	-3	0	--	0		4620
	-1	--	EMULATE	--	--	4	-2	0	--	0		4630
	0	--	EMULATE	--	--	4	-1	1	--	0		4640
	+1	--	EMULATE	--	--	4	0	1	--	0		4650

00000"50866560

FIG.12




FIG. 13

PROCESS A50					PROCESS B50							PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID	
ES	EP											
0	-4	--	REAL BACK SPACE	XBID-1	--	0	-4	--	--	--	XBID	5000
1	-3	--	REAL BACK SPACE	XBID-1	--	0	-4	--	--	--	XBID	5100
2	-2	--	REAL BACK SPACE	XBID-1	--	0	-4	--	--	--	XBID	5200
3	-1	--	REAL BACK SPACE	XBID-1	--	0	-4	--	--	--	XBID	5300
4	-4	XBID + EP	REAL BACK SPACE	XBID-1	--	0	-4	--	--	--	XBID	5400
	-3	--	EMULATE	--	--	4	-4	--	--	--	XBID + EP	5410
	-2	--	EMULATE	--	--	4	-3	--	--	--		5420
	-1	--	EMULATE	--	--	4	-2	--	--	--		5430
	0	--	EMULATE	--	--	4	-1	--	--	--		5440
5	+1	--	REAL BACK SPACE	XBID-1	--	6	0	--	--	--	XBID	5500
6	-4	XBID + EP	REAL BACK SPACE	XBID-1	--	0	-4	--	--	--	XBID	5600
	-3	--	EMULATE	--	--	6	-4	--	--	--	XBID + EP	5610
	-2	--	EMULATE	--	--	6	-3	--	--	--		5620
	-1	--	EMULATE	--	--	6	-2	--	--	--		5630
	0	--	EMULATE	--	--	6	-1	--	--	--		5640
	+1	--	EMULATE	--	--	6	0	--	--	--		5650

00000"50000000




FIG. 15

PROCESS A60					PROCESS B60							PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID	
ES	EP											
0	-4	--	REAL READ	XBID+1	TM	1	-3	1	--	--	XBID	6000
					OTHERS	0	-4	0	--	--		6001
1	-3	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	6100
					TM	1	-3	1	--	--		6101
					OTHERS	0	-4	0	--	--		6102
2	-2	--	REAL READ	XBID+1	EOF	3	-1	0	SDT2←BUF ;SLN2←LEN	--	XBID	6200
					TM	1	-3	1	--	--		6201
					OTHERS	0	-4	0	--	--		6202
3	-1	--	REAL READ	XBID+1	TM	4	0	1	--	--	XBID	6300
					OTHERS	0	-4	0	--	--		6301
4	-4	--	EMULATE	--	--	4	-3	1	--	--	XBID + EP	6400
	-3	--	EMULATE	--	--	4	-2	0	--	--		6410
	-2	--	EMULATE	--	--	4	-1	0	--	--		6420
	-1	--	EMULATE	--	--	4	0	1	--	--		6430
	0	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	6440
					TM	5	+1	1	--	--		6441
					OTHERS	0	-4	0	--	--		6442
5	+1	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	6500
					TM	1	-3	1	--	--		6501
					OTHERS	0	-4	0	--	--		6502
6	-4	--	EMULATE	--	--	6	-3	1	--	--	XBID + EP	6600
	-3	--	EMULATE	--	--	6	-2	0	--	--		6610
	-2	--	EMULATE	--	--	6	-1	0	--	--		6620
	-1	--	EMULATE	--	--	6	0	1	--	--		6630
	0	--	EMULATE	--	--	6	+1	1	--	--		6640
	+1	XBID +EP	REAL READ	XBID+1	TM	1	-3	1	--	--	XBID	6650
					OTHERS	0	-4	0	--	--		6651

00000"00000000

FIG. 16




FIG. 17

PROCESS A70					PROCESS B70								PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID		
ES	EP												
0	-4	--	REAL READ	XBID+1	TM	1	-3	1	--	--	XBID	7000	
					OTHERS	0	-4	0	--	--		7001	
1	-3	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	7100	
					TM	1	-3	1	--	--		7101	
					OTHERS	0	-4	0	--	--		7102	
2	-2	--	REAL READ	XBID+1	EOF	3	-1	0	SDT2←BUF ;SLN2←LEN	--	XBID	7200	
					TM	1	-3	1	--	--		7201	
					OTHERS	0	-4	0	--	--		7202	
3	-1	--	REAL READ	XBID+1	TM	4	0	1	--	--	XBID	7300	
					OTHERS	0	-4	0	--	--		7301	
4	-4	--	EMULATE	--	--	4	-3	1	--	--	XBID + EP	7400	
	-3	--	EMULATE	--	--	4	-2	0	--	--		7410	
	-2	--	EMULATE	--	--	4	-1	0	--	--		7420	
	-1	--	EMULATE	--	--	4	0	1	--	--		7430	
	0	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	7440	
					TM	5	+1	1	--	--		7441	
					OTHERS	0	-4	0	--	--		7442	
5	+1	--	REAL READ	XBID+1	EOF	2	-2	0	SDT1←BUF ;SLN1←LEN	--	XBID	7500	
					TM	1	-3	1	--	--		7501	
					OTHERS	0	-4	0	--	--		7502	
6	-4	--	EMULATE	--	--	6	-3	1	--	--	XBID + EP	7600	
	-3	--	EMULATE	--	--	6	-2	0	--	--		7610	
	-2	--	EMULATE	--	--	6	-1	0	--	--		7620	
	-1	--	EMULATE	--	--	6	0	1	--	--		7630	
	0	--	EMULATE	--	--	6	+1	1	--	--		7640	
	+1	XBID +EP	REAL READ	XBID+1	TM	1	-3	1	--	--	XBID	7650	
					OTHERS	0	-4	0	--	--		7651	

CODED "3066550"

FIG. 18





FIG. 19

PROCESS A80					PROCESS B80								PROCESS ID
CONDITIONS		RE- POSITION	OPERATION	UPDATE XBID	CONDITIONS	UPDATE ES	UPDATE EP	TM FLAG	SAVE AREA PROCESS	BLEN	BID		
ES	EP												
0	-4	--	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8000	
1	-3	--	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8100	
2	-2	--	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8200	
3	-1	--	REAL WTM	XBID+1	--	4	0	1	--	0	XBID	8300	
4	-4	XBID + EP	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8400	
	-3	XBID + EP	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8410	
	-2		REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8420	
	-1	--	EMULATE	--	--	4	0	1	--	0	XBID + EP	8430	
	0	--	REAL WTM	XBID+1	--	5	+1	1	--	0	XBID	8440	
5	+1	--	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8500	
6	-4	XBID + EP	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8600	
	-3	XBID + EP	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8610	
	-2		REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8620	
	-1	XBID + EP	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8630	
	0	--	EMULATE	--	--	6	+1	1	--	0	XBID + EP	8640	
	+1	XBID + EP	REAL WTM	XBID+1	--	1	-3	1	--	0	XBID	8650	


00000"500000000

FIG. 20



EMULATE IF RB, BPS OR BSPF IS EXECUTED WHEN ES=4 AND EP=0
 EMULATE IF RD, RB, BSP, BSPF, SP, FSPF OR WTM IS EXECUTED WHEN ES=4 AND EP=-1
 EMULATE IF RD, RB, BSP, BSPF, SP OR FSPF IS EXECUTED WHEN ES=4 AND EP=-2
 EMULATE IF RD, RB, BSP, BSPF, SP OR FSPF IS EXECUTED WHEN ES=4 AND EP=-3
 EMULATE IF RD, SP OR FSPF IS EXECUTED WHEN ES=4 AND EP=-4

FIG. 21



EMULATE IF RB, BSP OR BSPF IS EXECUTED WHEN ES=6 AND EP=+1
 EMULATE IF RD, RB, BSP, BSPF, SP FSPF OR WTM IS EXECUTED WHEN ES=6 AND EP=0
 EMULATE IF RD, RB, BSP, BSPF, SP OR FSPF IS EXECUTED WHEN ES=6 AND EP=-1
 EMULATE IF RD, RB, BSP, BSPF, SP OR FSPF IS EXECUTED WHEN ES=6 AND EP=-2
 EMULATE IF RD, RB, BSP, BSPF, SP OR FSPF IS EXECUTED WHEN ES=6 AND EP=-3
 EMULATE IF RD, SP OR FSPF IS EXECUTED WHEN ES=6 AND EP=-4




FIG. 23(A)




FIG. 23(B)




FIG. 24(A)




FIG. 24(B)




FIG. 37(A)




FIG. 37(B)




FIG. 38(A)




FIG. 38(B)




FIG. 39(A)




FIG. 39(B)




FIG. 40(A)




FIG. 40(B)




FIG. 41(A)




FIG. 41(B)




FIG. 42(A)




FIG. 42(B)




FIG. 43(A)




FIG. 43(B)




FIG. 44(A)




FIG. 44(B)




FIG. 45(A)




FIG. 45(B)




FIG. 46(A)





FIG. 46(B)



096938



096938



096938



096938



FIG. 52(A)




FIG. 52(B)




FIG. 53(A)





FIG. 53(B)



[illegible][illegible][illegible][illegible]

FIG. 56(A)




FIG. 56(B)




FIG. 57(A)





FIG. 57(B)



1. General information	
1.1. Name of the project	1.2. Name of the project
1.3. Name of the project	1.4. Name of the project
1.5. Name of the project	1.6. Name of the project
1.7. Name of the project	1.8. Name of the project
1.9. Name of the project	1.10. Name of the project
1.11. Name of the project	1.12. Name of the project
1.13. Name of the project	1.14. Name of the project
1.15. Name of the project	1.16. Name of the project
1.17. Name of the project	1.18. Name of the project
1.19. Name of the project	1.20. Name of the project
1.21. Name of the project	1.22. Name of the project
1.23. Name of the project	1.24. Name of the project
1.25. Name of the project	1.26. Name of the project
1.27. Name of the project	1.28. Name of the project
1.29. Name of the project	1.30. Name of the project
1.31. Name of the project	1.32. Name of the project
1.33. Name of the project	1.34. Name of the project
1.35. Name of the project	1.36. Name of the project
1.37. Name of the project	1.38. Name of the project
1.39. Name of the project	1.40. Name of the project
1.41. Name of the project	1.42. Name of the project
1.43. Name of the project	1.44. Name of the project
1.45. Name of the project	1.46. Name of the project
1.47. Name of the project	1.48. Name of the project
1.49. Name of the project	1.50. Name of the project
1.51. Name of the project	1.52. Name of the project
1.53. Name of the project	1.54. Name of the project
1.55. Name of the project	1.56. Name of the project
1.57. Name of the project	1.58. Name of the project
1.59. Name of the project	1.60. Name of the project
1.61. Name of the project	1.62. Name of the project
1.63. Name of the project	1.64. Name of the project
1.65. Name of the project	1.66. Name of the project
1.67. Name of the project	1.68. Name of the project
1.69. Name of the project	1.70. Name of the project
1.71. Name of the project	1.72. Name of the project
1.73. Name of the project	1.74. Name of the project
1.75. Name of the project	1.76. Name of the project
1.77. Name of the project	1.78. Name of the project
1.79. Name of the project	1.80. Name of the project
1.81. Name of the project	1.82. Name of the project
1.83. Name of the project	1.84. Name of the project
1.85. Name of the project	1.86. Name of the project
1.87. Name of the project	1.88. Name of the project
1.89. Name of the project	1.90. Name of the project
1.91. Name of the project	1.92. Name of the project
1.93. Name of the project	1.94. Name of the project
1.95. Name of the project	1.96. Name of the project
1.97. Name of the project	1.98. Name of the project
1.99. Name of the project	1.100. Name of the project

[illegible][illegible][illegible]

FIG. 60(A)




FIG. 60(B)




FIG. 62




FIG.63

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
WR	0. 000731	0. 000731	(1)
WTM	0. 713581	0. 713581	(2)
WR	0. 003502	0. 003502	(3)
WR	0. 000641	0. 000641	(4)
WTM	0. 596851	0. 596851	(5)
WTM	0. 298012	0. 298012	(6)
BSPF	0. 000548	0. 000548	(7)
NOP	0. 460880	0. 460880	
LDSP	0. 000521	0. 000521	
LDSP	0. 000469	0. 000469	
LDSP	0. 000493	0. 000493	
NOP	0. 000524	0. 000524	
SNIO	0. 002945	0. 002945	
RDVC	0. 000580	0. 000580	
NOP	0. 000529	0. 000529	
SNS	0. 002731	0. 002731	
LDSP	0. 000420	0. 000420	
BSPF	0. 000583	0. 000500	(8)
BSPF	0. 291417	0. 000500	(9)
FSPF	0. 291342	0. 000500	(10)
RD	0. 531535	0. 000500	(11)
FSPF	1. 410659	0. 000500	(12)
RD	0. 581191	0. 000500	(13)
BSPF	0. 000606	0. 000500	(14)
BSPF	0. 455999	0. 000500	(15)
BSPF	0. 293099	0. 000500	(16)
FSPF	0. 290969	0. 000500	(17)
RD	0. 531411	0. 000500	(18)
FSPF	1. 414089	0. 000500	(19)
NOP	0. 290595	0. 000500	
WR	0. 000615	0. 000615	(20)
WR	0. 000615	0. 000615	(21)
WTM	0. 639278	0. 639278	(22)
WR	0. 003324	0. 003324	(23)
WR	0. 000641	0. 000641	(24)
TOTAL	9. 111926	2. 734931	SECOND

00000" 50000000

FIG.64

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
RD	0. 001561	0. 001561	(1)
FSPF	0. 453726	0. 453726	(2)
FSPF	0. 453545	0. 453545	(3)
NOP	0. 293952	0. 293952	
LDSP	0. 000525	0. 000525	
LDSP	0. 000456	0. 000456	
LDSP	0. 000492	0. 000492	
NOP	0. 000498	0. 000498	
SNIO	0. 002933	0. 002933	
RDVC	0. 000591	0. 000591	
NOP	0. 000495	0. 000495	
SNS	0. 002706	0. 002706	
LDSP	0. 000425	0. 000425	
BSPF	0. 000581	0. 000500	(4)
BSPF	0. 457145	0. 000500	(5)
FSPF	0. 290540	0. 000500	(6)
RD	0. 531764	0. 000500	(7)
FSPF	1. 409729	0. 000500	(8)
RD	0. 369065	0. 369065	(9)
RD	0. 003179	0. 003179	(10)
FSPF	0. 657888	0. 657888	(11)
NOP	0. 454188	0. 454188	
RD	0. 127053	0. 127053	(12)
RD	0. 001793	0. 001793	(13)
TOTAL	5. 514830	2. 827571	SECOND

00000" 50000000

FIG.65

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
WR	0. 000700	0. 000700	(1)
WTM	0. 713500	0. 713500	(2)
WR	0. 003500	0. 003500	(3)
WR	0. 000600	0. 000600	(4)
WTM	0. 596800	0. 596800	(5)
WTM	0. 298000	0. 298000	(6)
BSPF	0. 000500	0. 000500	(7)
NOP	0. 460800	0. 460800	
LDSP	0. 000500	0. 000500	
LDSP	0. 000500	0. 000500	
NOP	0. 000500	0. 000500	
NOP	0. 000500	0. 000500	
SNS	0. 002900	0. 002900	
LDSP	0. 000500	0. 000500	
BSPF	0. 000500	0. 000500	(8)
BSPF	0. 291400	0. 000500	(9)
FSPF	0. 291300	0. 000500	(10)
RD	0. 531500	0. 000500	(11)
FSPF	1. 410600	0. 000500	(12)
RD	0. 581100	0. 000500	(13)
BSPF	0. 000600	0. 000500	(14)
LDSP	0. 000500	0. 000500	
WR	0. 000600	0. 000600	(15)
WR	0. 000600	0. 000600	(16)
WTM	0. 639200	0. 639200	(17)
WR	0. 003300	0. 003300	(18)
WR	0. 000600	0. 000600	(19)
TOTAL	5. 831600	2. 728100	SECOND

00000" 50060000

FIG.66

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
RD	0. 001500	0. 001500	(1)
RD	0. 581100	0. 581100	(2)
RD	0. 531700	0. 531700	(3)
FSPF	1. 409700	1. 409700	(4)
BSPF	0. 000500	0. 000500	(5)
BSPF	0. 457100	0. 000500	(6)
FSPF	0. 290900	0. 000500	(7)
SP	0. 531400	0. 000500	(8)
RD	0. 531400	0. 000500	(9)
FSPF	0. 141400	0. 000500	(10)
LDSP	0. 000500	0. 000500	
LDSP	0. 000500	0. 000500	
NOP	0. 000500	0. 000500	
LDSP	0. 000500	0. 000500	
BSPF	0. 000500	0. 000500	(11)
BSPF	0. 457100	0. 000500	(12)
FSPF	0. 290500	0. 000500	(13)
RD	0. 531700	0. 000500	(14)
FSPF	1. 409700	0. 000500	(15)
RD	0. 369000	0. 369000	(16)
RD	0. 003100	0. 003100	(17)
LDSP	0. 000500	0. 000500	
FSPF	0. 657800	0. 657800	(18)
NOP	0. 454100	0. 454100	
LDSP	0. 000500	0. 000500	
RD	0. 127000	0. 127000	(19)
RD	0. 001700	0. 001700	(20)
TOTAL	8. 781900	4. 145200	SECOND

00000" 50000000

FIG. 67




FIG. 68




FIG. 69(A)




FIG. 69(B)




FIG. 69(C)




FIG. 69(D)




FIG. 70(A)



FIG. 70(B)




FIG. 70(C)




FIG. 70(D)




FIG. 70(E)




FIG. 70(F)




FIG. 70(G)




FIG. 72(A)




FIG. 72(B)




FIG. 72(C)



FIG. 72(D)




FIG. 72(E)




FIG. 72(F)




FIG. 72(G)




FIG. 73(A)




FIG. 73(B)



FIG. 73(C)




FIG. 73(D)




FIG. 73(E)




FIG. 73(F)




FIG. 73(G)




FIG. 74(A)




FIG. 74(B)

	RD	RB	BSP	BSPF	SP	FSPF	WTM
0	×	○	○	○	×	×	×
-1	○	○	○	○	○	○	○
-2	◎	○	○	○	○	○	×
-3	◎	○	○	○	○	○	×
-4	○	×	×	×	○	○	×

◎ : EMULATION POSSIBLE (INVOLVING DATA TRANSFER)
○ : EMULATION POSSIBLE
× : EMULATION IMPOSSIBLE (REAL OPERATION NECESSARY)

FIG. 75(A)




FIG. 75(B)

	RD	RB	BSP	BSPF	SP	FSPF	WTM
+1	×	○	○	○	×	×	×
0	○	○	○	○	○	○	○
-1	○	○	○	○	○	○	×
-2	◎	○	○	○	○	○	×
-3	◎	○	○	○	○	○	×
-4	○	×	×	×	○	○	×

◎ : EMULATION POSSIBLE (INVOLVING DATA TRANSFER)

○ : EMULATION POSSIBLE

× : EMULATION IMPOSSIBLE (REAL OPERATION NECESSARY)

FIG. 77(A)




FIG. 77(B)

	RD	RB	BSP	BSPF	SP	FSPF	WTM
+1	×	○	○	○	×	×	×
0	○	○	○	○	○	○	○
-1	○	○	○	○	○	○	×
-2	×	○	○	○	○	○	×
-3	◎	○	○	○	○	○	×
-4	○	×	×	×	○	○	×

- ◎ : EMULATION POSSIBLE (INVOLVING DATA TRANSFER)
- : EMULATION POSSIBLE
- × : EMULATION IMPOSSIBLE (REAL OPERATION NECESSARY)

FIG. 81(A)




FIG. 81(B)

	RD	RB	BSP	BSPF	SP	FSPF	WTM
+1	×	○	○	○	×	×	×
0	○	○	○	○	○	○	○
-1	○	○	○	○	○	○	×
-2	×	○	○	○	○	○	×
-3	×	○	○	○	○	○	×
-4	○	×	×	×	○	○	×

○ : EMULATION POSSIBLE

× : EMULATION IMPOSSIBLE (REAL OPERATION NECESSARY)

FIG. 82




FIG. 83




FIG. 84

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL READ	TM	--	SBID←REAL BID	10	--	1.00.00
					OTHERS	--	--	00	--	1.00.01
10	--	--	--	REAL READ	EOF	SDT1	--	20	--	1.10.00
					TM	--	SBID←REAL BID	10	--	1.10.01
					OTHERS	--	--	00	--	1.10.02
20	--	--	--	REAL READ	EOF	SDT2	--	30	--	1.20.00
					TM	--	SBID←REAL BID	10	--	1.20.01
					OTHERS	--	--	00	--	1.20.02
30	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	1.30.00
					OTHERS	--	--	00	--	1.30.01
40	-4	--	--	EMULATE	--	--	--	40	-3	1.40.00
	-3	--	SDT1	EMULATE	--	--	--	40	-2	1.40.10
	-2	--	SDT2	EMULATE	--	--	--	40	-1	1.40.20
	-1	--	--	EMULATE	--	--	--	40	0	1.40.30
	0	--	--	REAL READ	EOF	SDT1	--	20	--	1.40.40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	50	--	1.40.41
					OTHERS	--	--	00	--	1.40.42
50	--	--	--	REAL READ	EOF	SDT1	--	20	--	1.50.00
					TM	--	SBID←REAL BID	10	--	1.50.01
					OTHERS	--	--	00	--	1.50.02
60	-4	--	--	EMULATE	--	--	--	60	-3	1.60.00
	-3	--	SDT1	EMULATE	--	--	--	60	-2	1.60.10
	-2	--	SDT2	EMULATE	--	--	--	60	-1	1.60.20
	-1	--	--	EMULATE	--	--	--	60	0	1.60.30
	0	--	--	EMULATE	--	--	--	60	+1	1.60.40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1	20	--	1.60.50
					TM	--	SBID←REAL BID	10	--	1.60.51
					OTHERS	--	--	00	--	1.60.52

00000"5000000000

FIG. 85

PRE -- PROCESS				OPERATION	POST -- PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	1. 31. 00
					OTHERS	--	--	00	--	1. 31. 01
41	-4	--	--	EMULATE	--	--	--	41	-3	1. 41. 00
	-3	--	SDT1	EMULATE	--	--	--	41	-2	1. 41. 10
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	30	--	1. 41. 20
					OTHERS	--	--	00	--	1. 41. 21
	-1	--	--	EMULATE	--	--	--	41	0	1. 41. 30
	0	--	--	REAL READ	EOF	SDT1	--	20	--	1. 41. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	1. 41. 41
					OTHERS	--	--	00	--	1. 41. 42
51	--	--	--	REAL READ	EOF	SDT1	--	20	--	1. 51. 00
					TM	--	SBID←REAL BID	10	--	1. 51. 01
					OTHERS	--	--	00	--	1. 51. 02
61	-4	--	--	EMULATE	--	--	--	61	-3	1. 61. 00
	-3	--	SDT1	EMULATE	--	--	--	61	-2	1. 61. 10
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	30	--	1. 61. 20
					OTHERS	--	--	00	--	1. 61. 21
	-1	--	--	EMULATE	--	--	--	61	0	1. 61. 30
	0	--	--	EMULATE	--	--	--	61	+1	1. 61. 40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1	20	--	1. 61. 50
					TM	--	SBID←REAL BID	10	--	1. 61. 51
					OTHERS	--	--	00	--	1. 61. 52

FIG. 86

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL READ	EOF	SDT2	--	32	--	1. 22. 00
					TM	--	SBID←REAL BID	10	--	1. 22. 01
					OTHERS	--	--	00	--	1. 22. 02
32	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	1. 32. 00
					OTHERS	--	--	00	--	1. 32. 01
42	-4	--	--	EMULATE	--	--	--	42	-3	1. 42. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3	20	--	1. 42. 10
					OTHERS	--	--	00	--	1. 42. 11
	-2	--	SDT2	EMULATE	--	--	--	42	-1	1. 42. 20
	-1	--	--	EMULATE	--	--	--	42	0	1. 42. 30
	0	--	--	REAL READ	EOF	SDT1	--	20	--	1. 42. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	52	--	1. 42. 41
					OTHERS	--	--	00	--	1. 42. 42
52	--	--	--	REAL READ	EOF	SDT1	--	20	--	1. 52. 00
					TM	--	SBID←REAL BID	10	--	1. 52. 01
					OTHERS	--	--	00	--	1. 52. 02
62	-4	--	--	EMULATE	--	--	--	62	-3	1. 62. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3	20	--	1. 62. 10
					OTHERS	--	--	00	--	1. 62. 11
	-2	--	SDT2	EMULATE	--	--	--	62	-1	1. 62. 20
	-1	--	--	EMULATE	--	--	--	62	0	1. 62. 30
	0	--	--	EMULATE	--	--	--	62	+1	1. 62. 40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1	20	--	1. 62. 50
					TM	--	SBID←REAL BID	10	--	1. 62. 51
					OTHERS	--	--	00	--	1. 62. 52

00000"5006E550

FIG. 87

PRE - PROCESS				OPERATION	POST - PROCESS						PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES	EP	
33	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		43	0	1. 33. 00
					OTHERS	--	--		00	--	1. 33. 01
43	-4	--	--	EMULATE	--	--	--		43	-3	1. 43. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3		20	--	1. 43. 10
					OTHERS	--	--		00	--	1. 43. 11
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3		32	--	1. 43. 20
					OTHERS	--	--		00	--	1. 43. 21
	-1	--	--	EMULATE	--	--	--		43	0	1. 43. 30
	0	--	--	REAL READ	EOF	SDT1	--		20	--	1. 43. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1		53	--	1. 43. 41
					OTHERS	--	--		00	--	1. 43. 42
53	--	--	--	REAL READ	EOF	SDT1	--		20	--	1. 53. 00
					TM	--	SBID←REAL BID		10	--	1. 53. 01
					OTHERS	--	--		00	--	1. 53. 02
63	-4	--	--	EMULATE	--	--	--		63	-3	1. 63. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3		20	--	1. 63. 10
					OTHERS	--	--		00	--	1. 63. 11
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3		32	--	1. 63. 20
					OTHERS	--	--		00	--	1. 63. 21
	-1	--	--	EMULATE	--	--	--		63	0	1. 63. 30
	0	--	--	EMULATE	--	--	--		63	+1	1. 63. 40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1		20	--	1. 63. 50
					TM	--	SBID←REAL BID		10	--	1. 63. 51
					OTHERS	--	--		00	--	1. 63. 52

000000" 3086E560

FIG.88

PRE - PROCESS				OPERATION	POST - PROCESS				PROCESS	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	ID
00	--	--	--	REAL RB	--	--	--	00	--	2. 00. 00
10	--	--	--	REAL RB	--	--	--	00	--	2. 10. 00
20	--	--	--	REAL RB	--	--	--	00	--	2. 20. 00
30	--	--	--	REAL RB	--	--	--	00	--	2. 30. 00
40	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 40. 00
	-3	--	--	EMULATE	--	--	--	40	-4	2. 40. 10
	-2	--	--	EMULATE	--	--	--	40	-3	2. 40. 20
	-1	--	--	EMULATE	--	--	--	40	-2	2. 40. 30
	0	--	--	EMULATE	--	--	--	40	-1	2. 40. 40
50	--	--	--	REAL RB	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	60	0	2. 50. 00
60	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 60. 00
	-3	--	--	EMULATE	--	--	--	60	-4	2. 60. 10
	-2	--	--	EMULATE	--	--	--	60	-3	2. 60. 20
	-1	--	--	EMULATE	--	--	--	60	-2	2. 60. 30
	0	--	--	EMULATE	--	--	--	60	-1	2. 60. 40
	+1	--	--	EMULATE	--	--	--	60	0	2. 60. 50

FIG. 92

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
00	--	--	--	REAL WR	--	--	--		00	--	3. 00. 00
10	--	--	--	REAL WR	EOF	SDT1	--		20	--	3. 10. 00
			OTHERS		--	--		00	--	3. 10. 01	
20	--	--	--	REAL WR	EOF	SDT2	--		30	--	3. 20. 00
			OTHERS		--	--		00	--	3. 20. 01	
30	--	--	--	REAL WR	--	--	--		00	--	3. 30. 00
40	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 40. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 40. 10
					OTHERS	--	--		00	--	3. 40. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 40. 20
					OTHERS	--	--		00	--	3. 40. 21
	-1		--	REAL WR	--	--	--		00	--	3. 40. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 40. 40
					OTHERS	--	--		00	--	3. 40. 41
50	--	--	--	REAL WR	EOF	SDT1	--		20	--	3. 50. 00
					OTHERS	--	--		00	--	3. 50. 01
60	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 60. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 60. 10
					OTHERS	--	--		00	--	3. 60. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 60. 20
					OTHERS	--	--		00	--	3. 60. 21
	-1		--	REAL WR	--	--	--		00	--	3. 60. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 60. 40
					OTHERS	--	--		00	--	3. 60. 41
+1	SBID+EP	--	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 60. 50
					OTHERS	--	--		00	--	3. 60. 51

000000" 00000000

FIG. 93

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES	EP	ID
31	--	--	--	REAL WR	--	--	--		00	--	3. 31. 00
41	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 41. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 41. 10
					OTHERS	--	--		00	--	3. 41. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 41. 20
					OTHERS	--	--		00	--	3. 41. 21
	-1		--	REAL WR	--	--	--		00	--	3. 41. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 41. 40
					OTHERS	--	--		00	--	3. 41. 41
51	--	--	--	REAL WR	EOF	SDT1	--		20	--	3. 51. 00
					OTHERS	--	--		00	--	3. 51. 01
61	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 61. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 61. 10
					OTHERS	--	--		00	--	3. 61. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 61. 20
					OTHERS	--	--		00	--	3. 61. 21
	-1		--	REAL WR	--	--	--		00	--	3. 61. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 61. 40
					OTHERS	--	--		00	--	3. 61. 41
	+1	SBID+EP	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 61. 50
					OTHERS	--	--		00	--	3. 61. 51

00000"50000000

FIG. 94

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
22	--	--	--	REAL	EOF	SDT2	--		32	--	3. 22. 00
			WR	OTHERS	--	--		00	--	3. 22. 01	
32	--	--	--	REAL	--	--	--		00	--	3. 32. 00
				WR							
42	-4	SBID+EP	--	REAL	--	--	--		00	--	3. 42. 00
	-3		WR	EOF	SDT1	SBID-3		20	--	3. 42. 10	
			WR	OTHERS	--	--		00	--	3. 42. 11	
	-2		WR	EOF	SDT2	SBID-3		32	--	3. 42. 20	
			WR	OTHERS	--	--		00	--	3. 42. 21	
	-1		WR	--	--	--		00	--	3. 42. 30	
	0	--	REAL	EOF	SDT1	--		20	--	3. 42. 40	
		--	WR	OTHERS	--	--		00	--	3. 42. 41	
52	--	--	--	REAL	EOF	SDT1	--		20	--	3. 52. 00
			--	WR	OTHERS	--	--		00	--	3. 52. 01
62	-4	SBID+EP	--	REAL	--	--	--		00	--	3. 62. 00
	-3		WR	EOF	SDT1	SBID-3		20	--	3. 62. 10	
			WR	OTHERS	--	--		00	--	3. 62. 11	
	-2		WR	EOF	SDT2	SBID-3		32	--	3. 62. 20	
			WR	OTHERS	--	--		00	--	3. 62. 21	
	-1		WR	--	--	--		00	--	3. 62. 30	
	0	--	REAL	EOF	SDT1	--		20	--	3. 62. 40	
		--	WR	OTHERS	--	--		00	--	3. 62. 41	
	+1	SBID+EP	--	REAL	EOF	SDT1	SBID+1		20	--	3. 62. 50
			--	WR	OTHERS	--	--		00	--	3. 62. 51

00000" 50066560

FIG. 95

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
33	--	--	--	REAL WR	--	--	--		00	--	3. 33. 00
43	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 43. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 43. 10
					OTHERS	--	--		00	--	3. 43. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		32	--	3. 43. 20
					OTHERS	--	--		00	--	3. 43. 21
	-1		--	REAL WR	--	--	--		00	--	3. 43. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 43. 40
					OTHERS	--	--		00	--	3. 43. 41
53	--	--	--	REAL WR	EOF	SDT1	--		20	--	3. 53. 00
					OTHERS	--	--		00	--	3. 53. 01
63	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 63. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 63. 10
					OTHERS	--	--		00	--	3. 63. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		32	--	3. 63. 20
					OTHERS	--	--		00	--	3. 63. 21
	-1		--	REAL WR	--	--	--		00	--	3. 63. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 63. 40
					OTHERS	--	--		00	--	3. 63. 41
+1	SBID+EP	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 63. 50	
				OTHERS	--	--		00	--	3. 63. 51	

00000" 50862360

[illegible]

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL BSP	--	--	--	00	--	4. 00. 00
10	--	--	--	REAL BSP	--	--	--	00	--	4. 10. 00
20	--	--	--	REAL BSP	--	--	--	10	--	4. 20. 00
30	--	--	--	REAL BSP	--	--	--	20	--	4. 30. 00
40	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 40. 00
	-3	--	--	EMULATE	--	--	--	40	-4	4. 40. 10
	-2	--	--	EMULATE	--	--	--	40	-3	4. 40. 20
	-1	--	--	EMULATE	--	--	--	40	-2	4. 40. 30
	0	--	--	EMULATE	--	--	--	40	-1	4. 40. 40
50	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	60	0	4. 50. 00
60	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 60. 00
	-3	--	--	EMULATE	--	--	--	60	-4	4. 60. 10
	-2	--	--	EMULATE	--	--	--	60	-3	4. 60. 20
	-1	--	--	EMULATE	--	--	--	60	-2	4. 60. 30
	0	--	--	EMULATE	--	--	--	60	-1	4. 60. 40
	+1	--	--	EMULATE	--	--	--	60	0	4. 60. 50

FIG. 97

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL BSP	--	--	--	20	--	4. 31. 00
41	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 41. 00
	-3	--	--	EMULATE	--	--	--	41	-4	4. 41. 10
	-2	--	--	EMULATE	--	--	--	41	-3	4. 41. 20
	-1	--	--	EMULATE	--	--	--	41	-2	4. 41. 30
	0	--	--	EMULATE	--	--	--	41	-1	4. 41. 40
51	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	61	0	4. 51. 00
61	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 61. 00
	-3	--	--	EMULATE	--	--	--	61	-4	4. 61. 10
	-2	--	--	EMULATE	--	--	--	61	-3	4. 61. 20
	-1	--	--	EMULATE	--	--	--	61	-2	4. 61. 30
	0	--	--	EMULATE	--	--	--	61	-1	4. 61. 40
	+1	--	--	EMULATE	--	--	--	61	0	4. 61. 50

00000"00000000

[illegible]

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL BSP	--	--	--	10	--	4. 22. 00
32	--	--	--	REAL BSP	--	--	--	22	--	4. 32. 00
42	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 42. 00
	-3	--	--	EMULATE	--	--	--	42	-4	4. 42. 10
	-2	--	--	EMULATE	--	--	--	42	-3	4. 42. 20
	-1	--	--	EMULATE	--	--	--	42	-2	4. 42. 30
	0	--	--	EMULATE	--	--	--	42	-1	4. 42. 40
52	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	62	0	4. 52. 00
62	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 62. 00
	-3	--	--	EMULATE	--	--	--	62	-4	4. 62. 10
	-2	--	--	EMULATE	--	--	--	62	-3	4. 62. 20
	-1	--	--	EMULATE	--	--	--	62	-2	4. 62. 30
	0	--	--	EMULATE	--	--	--	62	-1	4. 62. 40
	+1	--	--	EMULATE	--	--	--	62	0	4. 62. 50

FIG. 99

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL BSP	--	--	--	22	--	4. 33. 00
43	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 43. 00
	-3	--	--	EMULATE	--	--	--	43	-4	4. 43. 10
	-2	--	--	EMULATE	--	--	--	43	-3	4. 43. 20
	-1	--	--	EMULATE	--	--	--	43	-2	4. 43. 30
	0	--	--	EMULATE	--	--	--	43	-1	4. 43. 40
53	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	63	0	4. 53. 00
63	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 63. 00
	-3	--	--	EMULATE	--	--	--	63	-4	4. 63. 10
	-2	--	--	EMULATE	--	--	--	63	-3	4. 63. 20
	-1	--	--	EMULATE	--	--	--	63	-2	4. 63. 30
	0	--	--	EMULATE	--	--	--	63	-1	4. 63. 40
	+1	--	--	EMULATE	--	--	--	63	0	4. 63. 50

00000"00000000

FIG. 100

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL BSPF	--	--	--	00	--	5. 00. 00
10	--	--	--	REAL BSPF	--	--	--	00	--	5. 10. 00
20	--	--	--	REAL BSPF	--	--	--	00	--	5. 20. 00
30	--	--	--	REAL BSPF	--	--	--	00	--	5. 30. 00
40	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 40. 00
	-3	--	--	EMULATE	--	--	--	40	-4	5. 40. 10
	-2	--	--	EMULATE	--	--	--	40	-4	5. 40. 20
	-1	--	--	EMULATE	--	--	--	40	-4	5. 40. 30
	0	--	--	EMULATE	--	--	--	40	-1	5. 40. 40
50	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	60	0	5. 50. 00
60	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 60. 00
	-3	--	--	EMULATE	--	--	--	60	-4	5. 60. 10
	-2	--	--	EMULATE	--	--	--	60	-4	5. 60. 20
	-1	--	--	EMULATE	--	--	--	60	-4	5. 60. 30
	0	--	--	EMULATE	--	--	--	60	-1	5. 60. 40
	+1	--	--	EMULATE	--	--	--	60	0	5. 60. 50

00000"50000000

FIG. 101

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL BSPF	--	--	--	00	--	5. 31. 00
41	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 41. 00
	-3	--	--	EMULATE	--	--	--	41	-4	5. 41. 10
	-2	--	--	EMULATE	--	--	--	41	-4	5. 41. 20
	-1	--	--	EMULATE	--	--	--	41	-4	5. 41. 30
	0	--	--	EMULATE	--	--	--	41	-1	5. 41. 40
51	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	61	0	5. 51. 00
61	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 61. 00
	-3	--	--	EMULATE	--	--	--	61	-4	5. 61. 10
	-2	--	--	EMULATE	--	--	--	61	-4	5. 61. 20
	-1	--	--	EMULATE	--	--	--	61	-4	5. 61. 30
	0	--	--	EMULATE	--	--	--	61	-1	5. 61. 40
	+1	--	--	EMULATE	--	--	--	61	0	5. 61. 50

00000"50000000

FIG. 102

PRE -- PROCESS				OPERATION	POST -- PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL BSPF	--	--	--	00	--	5. 22. 00
32	--	--	--	REAL BSPF	--	--	--	00	--	5. 32. 00
42	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 42. 00
	-3	--	--	EMULATE	--	--	--	42	-4	5. 42. 10
	-2	--	--	EMULATE	--	--	--	42	-4	5. 42. 20
	-1	--	--	EMULATE	--	--	--	42	-4	5. 42. 30
	0	--	--	EMULATE	--	--	--	42	-1	5. 42. 40
52	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	62	0	5. 52. 00
62	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 62. 00
	-3	--	--	EMULATE	--	--	--	62	-4	5. 62. 10
	-2	--	--	EMULATE	--	--	--	62	-4	5. 62. 20
	-1	--	--	EMULATE	--	--	--	62	-4	5. 62. 30
	0	--	--	EMULATE	--	--	--	62	-1	5. 62. 40
	+1	--	--	EMULATE	--	--	--	62	0	5. 62. 50

CODED" 5066E550

FIG. 103

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL BSPF	--	--	--	00	--	5. 33. 00
43	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 43. 00
	-3	--	--	EMULATE	--	--	--	43	-4	5. 43. 10
	-2	--	--	EMULATE	--	--	--	43	-4	5. 43. 20
	-1	--	--	EMULATE	--	--	--	43	-4	5. 43. 30
	0	--	--	EMULATE	--	--	--	43	-1	5. 43. 40
53	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	63	0	5. 53. 00
63	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 63. 00
	-3	--	--	EMULATE	--	--	--	63	-4	5. 63. 10
	-2	--	--	EMULATE	--	--	--	63	-4	5. 63. 20
	-1	--	--	EMULATE	--	--	--	63	-4	5. 63. 30
	0	--	--	EMULATE	--	--	--	63	-1	5. 63. 40
	+1	--	--	EMULATE	--	--	--	63	0	5. 63. 50

000000"5035E550

[illegible]

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL SP	TM	--	SBID←REAL BID	10	--	6.00.00
					OTHERS	--	--	00	--	6.00.01
10	--	--	--	REAL SP	EOF	--	--	22	--	6.10.00
					TM	--	SBID←REAL BID	10	--	6.10.01
					OTHERS	--	--	00	--	6.10.02
20	--	--	--	REAL SP	EOF	--	--	31	--	6.20.00
					TM	--	SBID←REAL BID	10	--	6.20.01
					OTHERS	--	--	00	--	6.20.02
30	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	6.30.00
					OTHERS	--	--	00	--	6.30.01
40	-4	--	--	EMULATE	--	--	--	40	-3	6.40.00
	-3	--	--	EMULATE	--	--	--	40	-2	6.40.10
	-2	--	--	EMULATE	--	--	--	40	-1	6.40.20
	-1	--	--	EMULATE	--	--	--	40	0	6.40.30
	0	--	--	REAL SP	EOF	--	--	22	--	6.40.40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	50	--	6.40.41
					OTHERS	--	--	00	--	6.40.42
50	--	--	--	REAL SP	EOF	--	--	22	--	6.50.00
					TM	--	SBID←REAL BID	10	--	6.50.01
					OTHERS	--	--	00	--	6.50.02
60	-4	--	--	EMULATE	--	--	--	60	-3	6.60.00
	-3	--	--	EMULATE	--	--	--	60	-2	6.60.10
	-2	--	--	EMULATE	--	--	--	60	-1	6.60.20
	-1	--	--	EMULATE	--	--	--	60	0	6.60.30
	0	--	--	EMULATE	--	--	--	60	+1	6.60.40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6.60.50
					TM	--	SBID←REAL BID	10	--	6.60.51
OTHERS					--	--	00	--	6.60.52	

FIG. 105

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	6.31.00
					OTHERS	--	--	00	--	6.31.01
41	-4	--	--	EMULATE	--	--	--	41	-3	6.41.00
	-3	--	--	EMULATE	--	--	--	41	-2	6.41.10
	-2	--	--	EMULATE	--	--	--	41	-1	6.41.20
	-1	--	--	EMULATE	--	--	--	41	0	6.41.30
	0	--	--	REAL SP	EOF	--	--	22	--	6.41.40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	6.41.41
					OTHERS	--	--	00	--	6.41.42
51	--	--	--	REAL SP	EOF	--	--	22	--	6.51.00
					TM	--	SBID←REAL BID	10	--	6.51.01
					OTHERS	--	--	00	--	6.51.02
61	-4	--	--	EMULATE	--	--	--	61	-3	6.61.00
	-3	--	--	EMULATE	--	--	--	61	-2	6.61.10
	-2	--	--	EMULATE	--	--	--	61	-1	6.61.20
	-1	--	--	EMULATE	--	--	--	61	0	6.61.30
	0	--	--	EMULATE	--	--	--	61	+1	6.61.40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6.61.50
					TM	--	SBID←REAL BID	10	--	6.61.51
					OTHERS	--	--	00	--	6.61.52

CODED " 6066560

FIG. 106

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL SP	EOF	--	--	33	--	6. 22. 00
					TM	--	SBID←REAL BID	10	--	6. 22. 01
					OTHERS	--	--	00	--	6. 22. 02
32	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	6. 32. 00
					OTHERS	--	--	00	--	6. 32. 01
42	-4	--	--	EMULATE	--	--	--	42	-3	6. 42. 00
	-3	--	--	EMULATE	--	--	--	42	-2	6. 42. 10
	-2	--	--	EMULATE	--	--	--	42	-1	6. 42. 20
	-1	--	--	EMULATE	--	--	--	42	0	6. 42. 30
	0	--	--	REAL SP	EOF	--	--	22	--	6. 42. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	52	--	6. 42. 41
					OTHERS	--	--	00	--	6. 42. 42
52	--	--	--	REAL SP	EOF	--	--	22	--	6. 52. 00
					TM	--	SBID←REAL BID	10	--	6. 52. 01
					OTHERS	--	--	00	--	6. 52. 02
62	-4	--	--	EMULATE	--	--	--	62	-3	6. 62. 00
	-3	--	--	EMULATE	--	--	--	62	-2	6. 62. 10
	-2	--	--	EMULATE	--	--	--	62	-1	6. 62. 20
	-1	--	--	EMULATE	--	--	--	62	0	6. 62. 30
	0	--	--	EMULATE	--	--	--	62	+1	6. 62. 40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6. 62. 50
					TM	--	SBID←REAL BID	10	--	6. 62. 51
					OTHERS	--	--	00	--	6. 62. 52

00000" 50855350

FIG. 107

PRE - PROCESS				OPERATION	POST - PROCESS						PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP		
33	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	6. 33. 00	
					OTHERS	--	--	00	--	6. 33. 01	
43	-4	--	--	EMULATE	--	--	--	43	-3	6. 43. 00	
	-3	--	--	EMULATE	--	--	--	43	-2	6. 43. 10	
	-2	--	--	EMULATE	--	--	--	43	-1	6. 43. 20	
	-1	--	--	EMULATE	--	--	--	43	0	6. 43. 30	
	0	--	--	REAL SP	EOF	--	--	22	--	6. 43. 40	
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	53	--	6. 43. 41	
					OTHERS	--	--	00	--	6. 43. 42	
53	--	--	--	REAL SP	EOF	--	--	22	--	6. 53. 00	
					TM	--	SBID←REAL BID	10	--	6. 53. 01	
					OTHERS	--	--	00	--	6. 53. 02	
63	-4	--	--	EMULATE	--	--	--	63	-3	6. 63. 00	
	-3	--	--	EMULATE	--	--	--	63	-2	6. 63. 10	
	-2	--	--	EMULATE	--	--	--	63	-1	6. 63. 20	
	-1	--	--	EMULATE	--	--	--	63	0	6. 63. 30	
	0	--	--	EMULATE	--	--	--	63	+1	6. 63. 40	
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6. 63. 50	
					TM	--	SBID←REAL BID	10	--	6. 63. 51	
OTHERS					--	--	00	--	6. 63. 52		

00000"50866560

FIG. 108

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
00	--	--	--	REAL FSPF	TM	--	SBID←REAL BID		10	--	7.00.00
					OTHERS	--	--		00	--	7.00.01
10	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		43	0	7.10.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3		10	--	7.10.01
					OTHERS	--	--		00	--	7.10.02
20	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		41	0	7.20.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3		10	--	7.20.01
					OTHERS	--	--		00	--	7.20.02
30	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		40	0	7.30.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3		10	--	7.30.01
					OTHERS	--	--		00	--	7.30.02
40	-4	--	--	EMULATE	--	--	--		40	-3	7.40.00
	-3	--	--	EMULATE	--	--	--		40	0	7.40.10
	-2	--	--	EMULATE	--	--	--		40	0	7.40.20
	-1	--	--	EMULATE	--	--	--		40	0	7.40.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		43	0	7.40.40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1		50	--	7.40.41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3		10	--	7.40.42
OTHERS					--	--		00	--	7.40.43	
50	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		43	0	7.50.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3		10	--	7.50.01
					OTHERS	--	--		00	--	7.50.02
60	-4	--	--	EMULATE	--	--	--		60	-3	7.60.00
	-3	--	--	EMULATE	--	--	--		60	0	7.60.10
	-2	--	--	EMULATE	--	--	--		60	0	7.60.20
	-1	--	--	EMULATE	--	--	--		60	0	7.60.30
	0	--	--	EMULATE	--	--	--		60	+1	7.60.40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		43	0	7.60.50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3		10	--	7.60.51
OTHERS					--	--		00	--	7.60.52	

CODED 5036E560

FIG. 109

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	7.31.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.31.01
					OTHERS	--	--	00	--	7.31.02
41	-4	--	--	EMULATE	--	--	--	41	-3	7.41.00
	-3	--	--	EMULATE	--	--	--	41	0	7.41.10
	-2	--	--	EMULATE	--	--	--	41	0	7.41.20
	-1	--	--	EMULATE	--	--	--	41	0	7.41.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.41.40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	7.41.41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3	10	--	7.41.42
					OTHERS	--	--	00	--	7.41.43
51	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.51.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.51.01
					OTHERS	--	--	00	--	7.51.02
61	-4	--	--	EMULATE	--	--	--	61	-3	7.61.00
	-3	--	--	EMULATE	--	--	--	61	0	7.61.10
	-2	--	--	EMULATE	--	--	--	61	0	7.61.20
	-1	--	--	EMULATE	--	--	--	61	0	7.61.30
	0	--	--	EMULATE	--	--	--	61	+1	7.61.40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.61.50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.61.51
					OTHERS	--	--	00	--	7.61.52

000000"50000000

FIG. 110

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.22.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.22.01
					OTHERS	--	--	00	--	7.22.02
32	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	7.32.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.32.01
					OTHERS	--	--	00	--	7.32.02
42	-4	--	--	EMULATE	--	--	--	42	-3	7.42.00
	-3	--	--	EMULATE	--	--	--	42	0	7.42.10
	-2	--	--	EMULATE	--	--	--	42	0	7.42.20
	-1	--	--	EMULATE	--	--	--	42	0	7.42.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.42.40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	52	--	7.42.41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3	10	--	7.42.42
						OTHERS	--	00	--	7.42.43
52	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.52.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.52.01
					OTHERS	--	--	00	--	7.52.02
62	-4	--	--	EMULATE	--	--	--	62	-3	7.62.00
	-3	--	--	EMULATE	--	--	--	62	0	7.62.10
	-2	--	--	EMULATE	--	--	--	62	0	7.62.20
	-1	--	--	EMULATE	--	--	--	62	0	7.62.30
	0	--	--	EMULATE	--	--	--	62	+1	7.62.40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.62.50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.62.51
					OTHERS	--	--	00	--	7.62.52

00000"5086E560

Sampling date		Sampling time		Sampling location		Sampling method		Sampling equipment		Sampling personnel		Sampling results	
Year	Month	Day	Hour	Latitude	Longitude	Depth	Area	Volume	Weight	Name	Position	Count	Percentage
2010	10	15	10:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	15	15.0%
2010	10	15	11:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	12	12.0%
2010	10	15	12:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	18	18.0%
2010	10	15	13:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	10	10.0%
2010	10	15	14:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	14	14.0%
2010	10	15	15:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	16	16.0%
2010	10	15	16:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	11	11.0%
2010	10	15	17:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	13	13.0%
2010	10	15	18:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	17	17.0%
2010	10	15	19:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	19	19.0%
2010	10	15	20:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	14	14.0%
2010	10	15	21:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	16	16.0%
2010	10	15	22:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	12	12.0%
2010	10	15	23:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	18	18.0%
2010	10	16	08:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	15	15.0%
2010	10	16	09:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	13	13.0%
2010	10	16	10:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	17	17.0%
2010	10	16	11:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	11	11.0%
2010	10	16	12:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	19	19.0%
2010	10	16	13:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	14	14.0%
2010	10	16	14:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	16	16.0%
2010	10	16	15:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	12	12.0%
2010	10	16	16:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	18	18.0%
2010	10	16	17:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	15	15.0%
2010	10	16	18:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	13	13.0%
2010	10	16	19:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	17	17.0%
2010	10	16	20:00	30°N	120°E	0-5m	100m ²	1000L	100g	Li	Chief	11	11.0%

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 33. 00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 33. 01
					OTHERS	--	--	00	--	7. 33. 02
43	-4	--	--	EMULATE	--	--	--	43	-3	7. 43. 00
	-3	--	--	EMULATE	--	--	--	43	0	7. 43. 10
	-2	--	--	EMULATE	--	--	--	43	0	7. 43. 20
	-1	--	--	EMULATE	--	--	--	43	0	7. 43. 30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 43. 40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	53	--	7. 43. 41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3	10	--	7. 43. 42
						OTHERS	--	--	00	--
53	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 53. 00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 53. 01
					OTHERS	--	--	00	--	7. 53. 02
63	-4	--	--	EMULATE	--	--	--	63	-3	7. 63. 00
	-3	--	--	EMULATE	--	--	--	63	0	7. 63. 10
	-2	--	--	EMULATE	--	--	--	63	0	7. 63. 20
	-1	--	--	EMULATE	--	--	--	63	0	7. 63. 30
	0	--	--	EMULATE	--	--	--	63	+1	7. 63. 40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 63. 50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 63. 51
OTHERS					--	--	00	--	7. 63. 52	

FIG. 112

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.00.00
10	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.10.00
20	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.20.00
30	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	8.30.00
40	-4	SBID+EP	--	REAL WTM	--	--		10	--	8.40.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.40.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.40.20
	-1	--	--	EMULATE	--	--	--	40	0	8.40.30
	0	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	50	--	8.40.40
50	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.50.00
60	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.30
	0	--	--	EMULATE	--	--	--	60	+1	8.60.40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.50

00000"5086E560

FIG. 113

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	8.31.00
41	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.41.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.41.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.41.20
	-1	--	--	EMULATE	--	--	--	41	0	8.41.30
	0	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	8.41.40
51	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.51.00
61	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.61.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.61.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.61.20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.61.30
	0	--	--	EMULATE	--	--	--	61	+1	8.61.40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.61.50

00000"50850360

FIG. 114

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.22.00
32	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	8.32.00
42	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.42.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.42.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.42.20
	-1	--	--	EMULATE	--	--	--	42	0	8.42.30
	0	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	52	--	8.42.40
52	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.52.00
62	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.62.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.62.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.62.20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.62.30
	0	--	--	EMULATE	--	--	--	62	+1	8.62.40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.62.50

000000" 50855550

FIG. 115

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	8. 33. 00
43	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 43. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 43. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 43. 20
	-1	--	--	EMULATE	--	--	--	43	0	8. 43. 30
	0	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	53	--	8. 43. 40
53	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 53. 00
63	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 30
	0	--	--	EMULATE	--	--	--	63	+1	8. 63. 40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 50

00000"5036E560




FIG. 117(A)




FIG. 117(B)




FIG. 118(A)




FIG. 118(B)




FIG.135(A)




FIG.135(B)




FIG. 136(A)




FIG. 136(B)




FIG. 137(A)




FIG. 137(B)




FIG. 141




FIG. 148(A)




FIG. 148(B)




FIG. 149(A)




FIG. 149(B)




FIG. 152(A)




FIG. 152(B)




FIG. 153(A)





FIG. 153(B)






FIG. 156




FIG. 161(A)




FIG. 161(B)




FIG. 162(A)




FIG. 162(B)




FIG. 167(A)




FIG. 167(B)




FIG. 168(A)




FIG. 168(B)




FIG. 169(A)




FIG. 169(B)




FIG. 170(A)




FIG. 170(B)




FIG. 171(A)




FIG. 171(B)




FIG. 172(A)




FIG. 172(B)




FIG.173

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
RD	0. 001561	0. 001561	(1)
FSPF	0. 453726	0. 453726	(2)
FSPF	0. 453545	0. 453545	(3)
NOP	0. 293952	0. 293952	
LDSP	0. 000525	0. 000525	
LDSP	0. 000456	0. 000456	
LDSP	0. 000492	0. 000492	
NOP	0. 000498	0. 000498	
SNIO	0. 002933	0. 002933	
RDVC	0. 000591	0. 000591	
NOP	0. 000495	0. 000495	
SNS	0. 002706	0. 002706	
LDSP	0. 000425	0. 000425	
BSPF	0. 000581	0. 000500	(4)
BSPF	0. 457145	0. 000500	(5)
FSPF	0. 290540	0. 000500	(6)
RD	0. 531764	0. 531764	(7)
FSPF	1. 409729	1. 409729	(8)
RD	0. 369065	0. 369065	(9)
RD	0. 003179	0. 003179	(10)
FSPF	0. 657888	0. 657888	(11)
NOP	0. 454188	0. 454188	
RD	0. 127053	0. 127053	(12)
RD	0. 001793	0. 001793	(13)
TOTAL	5. 514830	4. 768064	SECOND

00000" 00000000

FIG.174

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
RD	0. 001500	0. 001500	(1)
RD	0. 581100	0. 581100	(2)
RD	0. 531700	0. 531700	(3)
FSPF	1. 409700	1. 409700	(4)
BSPF	0. 000500	0. 000500	(5)
BSPF	0. 457100	0. 000500	(6)
FSPF	0. 290900	0. 000500	(7)
SP	0. 531400	0. 000500	(8)
RD	0. 531400	0. 531400	(9)
FSPF	0. 141400	0. 141400	(10)
LDSP	0. 000500	0. 000500	
LDSP	0. 000500	0. 000500	
NOP	0. 000500	0. 000500	
LDSP	0. 000500	0. 000500	
BSPF	0. 000500	0. 000500	(11)
BSPF	0. 457100	0. 000500	(12)
FSPF	0. 290500	0. 000500	(13)
RD	0. 531700	0. 000500	(14)
FSPF	1. 409700	0. 000500	(15)
RD	0. 369000	0. 369000	(16)
RD	0. 003100	0. 003100	(17)
LDSP	0. 000500	0. 000500	
FSPF	0. 657800	0. 657800	(18)
NOP	0. 454100	0. 454100	
LDSP	0. 000500	0. 000500	
RD	0. 127000	0. 127000	(19)
RD	0. 001700	0. 001700	(20)
TOTAL	8. 781900	4. 817000	SECOND

00000"5086260

FIG. 175
RELATED ART




FIG.176
RELATED ART




FIG.177
RELATED ART




FIG. 178

RELATED ART




FIG.179
RELATED ART




FIG. 180
RELATED ART




FIG.181
RELATED ART




FIG.182
RELATED ART




FIG. 184
RELATED ART




FIG. 185
RELATED ART

PROCESS A1		PROCESS B1				PROCESS C1
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL READ	XBID + 1	TM	1	0	XBID	REGISTER BID IN FQL REGISTER BPNT IN FQL REGISTER BLEN IN FQL REGISTER TM FLAG IN FQL UPDATE FQP POINTER BPNT ← BPNT + BLEN
		OTHERS	0	LEN		

FIG.188
RELATED ART




FIG. 189
RELATED ART

PROCESS A3		PROCESS B3				PROCESS C3
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL WRITE	XBID + 1	--	--	LEN	XBID	REGISTER BID IN FQL REGISTER BPNT IN FQL REGISTER BLEN IN FQL UPDATE FQP POINTER BPNT ← BPNT + BLEN

FIG. 190
RELATED ART




FIG. 191
RELATED ART

PROCESS A4		PROCESS B4				PROCESS C4
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL BACK SPACE	XBID - 1	--	--	--	XBID	REGISTER BID IN FQL UPDATE FQP POINTER

FIG. 192
RELATED ART




FIG. 193
RELATED ART

PROCESS A5		PROCESS B5				PROCESS C5
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL BACK SPACE	XBID - 1	--	--	--	XBID	REGISTER BID IN FQL UPDATE FQP POINTER

FIG. 194
RELATED ART




FIG. 195
RELATED ART

PROCESS A6		PROCESS B6				PROCESS C6
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL FORWARD SPACE	XBID+1	--	--	--	XBID	REGISTER BID IN FQL UPDATE FQP POINTER

FIG. 196
RELATED ART




FIG. 197
RELATED ART

PROCESS A7		PROCESS B7				PROCESS C7
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL FORWARD SPACE	XBID + 1	--	--	--	XBID	REGISTER BID IN FQL UPDATE FQP POINTER

FIG. 198
RELATED ART




FIG. 199
RELATED ART

PROCESS A8		PROCESS B8				PROCESS C8
OPERATION	UPDATE XBID	CONDITIONS	TM FLAG	BLEN	BID	
REAL WRITE TAPE MARK	XBID + 1	--	1	--	XBID	REGISTER BID IN FQL REGISTER TM FLAG IN FQL UPDATE FQP POINTER




FIG. 201
RELATED ART




FIG. 202(A)




FIG. 202(B)



FIG. 202(C)




FIG. 202(D)




FIG. 202(E)




FIG. 202(F)




FIG. 202(G)




FIG. 202(H)




FIG. 202(I)





FIG. 203



000000"50000000

FIG. 204

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL READ	TM	--	SBID←REAL BID	10	--	1.00.00
					OTHERS	--	--	00	--	1.00.01
10	--	--	--	REAL READ	EOF	SDT1	--	20	--	1.10.00
					TM	--	SBID←REAL BID	10	--	1.10.01
					OTHERS	--	--	00	--	1.10.02
20	--	--	--	REAL READ	EOF	SDT2	--	30	--	1.20.00
					TM	--	SBID←REAL BID	10	--	1.20.01
					OTHERS	--	--	00	--	1.20.02
30	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	1.30.00
					OTHERS	--	--	00	--	1.30.01
40	-4	--	--	EMULATE	--	--	--	40	-3	1.40.00
	-3	--	SDT1	EMULATE	--	--	--	40	-2	1.40.10
	-2	--	SDT2	EMULATE	--	--	--	40	-1	1.40.20
	-1	--	--	EMULATE	--	--	--	40	0	1.40.30
	0	--	--	REAL READ	EOF	SDT1	--	20	--	1.40.40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	50	--	1.40.41
					OTHERS	--	--	00	--	1.40.42
					EOD	--	--	80	+1	1.40.43
50	--	--	--	REAL READ	EOF	SDT1	--	20	--	1.50.00
					TM	--	SBID←REAL BID	10	--	1.50.01
					OTHERS	--	--	00	--	1.50.02
60	-4	--	--	EMULATE	--	--	--	60	-3	1.60.00
	-3	--	SDT1	EMULATE	--	--	--	60	-2	1.60.10
	-2	--	SDT2	EMULATE	--	--	--	60	-1	1.60.20
	-1	--	--	EMULATE	--	--	--	60	0	1.60.30
	0	--	--	EMULATE	--	--	--	60	+1	1.60.40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1	20	--	1.60.50
					TM	--	SBID←REAL BID	10	--	1.60.51
					OTHERS	--	--	00	--	1.60.52

FIG. 205

PRE -- PROCESS				OPERATION	POST -- PROCESS					PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
70	-4	--	--	EMULATE	--	--	--		70	-3	1. 70. 00
	-3	--	SDT1	EMULATE	--	--	--		70	-2	1. 70. 10
	-2	--	SDT2	EMULATE	--	--	--		70	-1	1. 70. 20
	-1	--	--	EMULATE	--	--	--		70	0	1. 70. 30
	0	--	--	EMULATE	--	--	--		70	+1	1. 70. 40
	+1	WTM	--	REAL READ	EOF	SDT1	SBID+1		20	--	1. 70. 50
					TM	--	SBID←REAL BID		10	--	1. 70. 51
					OTHERS	--	--		00	--	1. 70. 52
80	-4	--	--	EMULATE	--	--	--		80	-3	1. 80. 00
	-3	--	SDT1	EMULATE	--	--	--		80	-2	1. 80. 10
	-2	--	SDT2	EMULATE	--	--	--		80	-1	1. 80. 20
	-1	--	--	EMULATE	--	--	--		80	0	1. 80. 30
	0	--	--	EMULATE	--	--	--		80	+1	1. 80. 40
	+1	--	--	REAL READ	EOD	--	--		00	--	1. 80. 50

000000"00000000

FIG. 206

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	1. 31. 00
					OTHERS	--	--	00	--	1. 31. 01
41	-4	--	--	EMULATE	--	--	--	41	-3	1. 41. 00
	-3	--	SDT1	EMULATE	--	--	--	41	-2	1. 41. 10
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	30	--	1. 41. 20
					OTHERS	--	--	00	--	1. 41. 21
	-1	--	--	EMULATE	--	--	--	41	0	1. 41. 30
	0	--	--	REAL READ	EOF	SDT1	--	20	--	1. 41. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	1. 41. 41
					OTHERS	--	--	00	--	1. 41. 42
					EOD	--	--	81	+1	1. 41. 43
51	--	--	--	REAL READ	EOF	SDT1	--	20	--	1. 51. 00
					TM	--	SBID←REAL BID	10	--	1. 51. 01
					OTHERS	--	--	00	--	1. 51. 02
61	-4	--	--	EMULATE	--	--	--	61	-3	1. 61. 00
	-3	--	SDT1	EMULATE	--	--	--	61	-2	1. 61. 10
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	30	--	1. 61. 20
					OTHERS	--	--	00	--	1. 61. 21
	-1	--	--	EMULATE	--	--	--	61	0	1. 61. 30
	0	--	--	EMULATE	--	--	--	61	+1	1. 61. 40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1	20	--	1. 61. 50
					TM	--	SBID←REAL BID	10	--	1. 61. 51
					OTHERS	--	--	00	--	1. 61. 52

00000"0000000000

FIG. 207

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
71	-4	--	--	EMULATE	--	--	--		71	-3	1. 71. 00
	-3	--	SDT1	EMULATE	--	--	--		71	-2	1. 71. 10
	-2	WTM SBID+EP	--	REAL READ	EOF	SDT2	SBID-3		30	--	1. 71. 20
					OTHERS	--	--		00	--	1. 71. 21
	-1	--	--	EMULATE	--	--	--		71	0	1. 71. 30
	0	--	--	EMULATE	--	--	--		71	+1	1. 71. 40
	+1	WTM	--	REAL READ	EOF	SDT1	--		20	--	1. 71. 50
					TM	--	SBID←REAL BID		10	--	1. 71. 51
					OTHERS	--	--		00	--	1. 71. 52
81	-4	--	--	EMULATE	--	--	--		81	-3	1. 81. 00
	-3	--	SDT1	EMULATE	--	--	--		81	-2	1. 81. 10
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3		30	--	1. 81. 20
					OTHERS	--	--		00	--	1. 81. 21
	-1	--	--	EMULATE	--	--	--		81	0	1. 81. 30
	0	--	--	EMULATE	--	--	--		81	+1	1. 81. 40
	+1	--	--	REAL READ	EOD	--	--		00	--	1. 81. 50

000000" 0000000000

FIG. 208

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
22	--	--	--	REAL READ	EOF	SDT2	--		32	--	1. 22. 00
					TM	--	SBID←REAL BID		10	--	1. 22. 01
					OTHERS	--	--		00	--	1. 22. 02
32	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3		42	0	1. 32. 00
					OTHERS	--	--		00	--	1. 32. 01
42	-4	--	--	EMULATE	--	--	--		42	-3	1. 42. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3		20	--	1. 42. 10
					OTHERS	--	--		00	--	1. 42. 11
	-2	--	SDT2	EMULATE	--	--	--		42	-1	1. 42. 20
	-1	--	--	EMULATE	--	--	--		42	0	1. 42. 30
	0	--	--	REAL READ	EOF	SDT1	--		20	--	1. 42. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1		52	--	1. 42. 41
					OTHERS	--	--		00	--	1. 42. 42
					EOD	--	--		82	+1	1. 42. 43
52	--	--	--	REAL READ	EOF	SDT1	--		20	--	1. 52. 00
					TM	--	SBID←REAL BID		10	--	1. 52. 01
					OTHERS	--	--		00	--	1. 52. 02
62	-4	--	--	EMULATE	--	--	--		62	-3	1. 62. 00
	-3	SBID+EP	--	REALREAD	EOF	SDT1	SBID-3		20	--	1. 62. 10
					OTHERS	--	--		00	--	1. 62. 11
	-2	--	SDT2	EMULATE	--	--	--		62	-1	1. 62. 20
	-1	--	--	EMULATE	--	--	--		62	0	1. 62. 30
	0	--	--	EMULATE	--	--	--		62	+1	1. 62. 40
	+1	SBID+EP	--	REALREAD	EOF	SDT1	SBID+1		20	--	1. 62. 50
					TM	--	SBID←REAL BID		10	--	1. 62. 51
					OTHERS	--	--		00	--	1. 62. 52

00000 " 50850560

FIG. 209

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
72	-4	--	--	EMULATE	--	--	--		72	-3	1.72.00
	-3	WTM SBID+EP	--	REAL READ	EOF	SDT1	SBID-3		20	--	1.72.10
					OTHERS	--	--		00	--	1.72.11
	-2	--	SDT2	EMULATE	--	--	--		72	-1	1.72.20
	-1	--	--	EMULATE	--	--	--		72	0	1.72.30
	0	--	--	EMULATE	--	--	--		72	+1	1.72.40
	+1	WTM	--	REAL READ	EOF	SDT1	SBID+1		20	--	1.72.50
					TM	--	SBID←REAL BID		10	--	1.72.51
					OTHERS	--	--		00	--	1.72.52
82	-4	--	--	EMULATE	--	--	--		82	-3	1.82.00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3		20	--	1.82.10
					OTHERS	--	--		00	--	1.82.11
	-2	--	SDT2	EMULATE	--	--	--		82	-1	1.82.20
	-1	--	--	EMULATE	--	--	--		82	0	1.82.30
	0	--	--	EMULATE	--	--	--		82	+1	1.82.40
	+1	--	--	REAL READ	EOD	--	--		00	--	1.82.50

Physical Properties		Chemical Properties		Mechanical Properties		Thermal Properties		Electrical Properties	
Material	Aluminum	Grade	6061-T6	Yield Strength	35,000 psi	Tensile Strength	45,000 psi	Elongation	12%
Weight	2.70 g/cm³	Modulus	69 GPa	Hardness	95 HB	Impact	100 J/m²	Thermal Exp.	23.6 µm/m°C
Dimensions	100 x 50 x 10 mm	Surface	Anodized	Corrosion	Good	Weldability	Good	Dielectric	1.0
Manufacturer	ABC Corp.	Part No.	AL-100	Insulation	None	Paint	None	Conductivity	35 MS/m
Storage	Room Temp	Shelf Life	Indefinite	Recycling	Yes	Disposal	Standard	Frequency	100 kHz
Notes	All dimensions in mm unless specified otherwise.								

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL READ	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	1. 33. 00
					OTHERS	--	--	00	--	1. 33. 01
43	-4	--	--	EMULATE	--	--	--	43	-3	1. 43. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3	20	--	1. 43. 10
					OTHERS	--	--	00	--	1. 43. 11
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	32	--	1. 43. 20
					OTHERS	--	--	00	--	1. 43. 21
	-1	--	--	EMULATE	--	--	--	43	0	1. 43. 30
	0	--	--	REAL READ	EOF	SDT1	--	20	--	1. 43. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	53	--	1. 43. 41
					OTHERS	--	--	00	--	1. 43. 42
					EOD	--	--	83	+1	1. 43. 43
53	--	--	REAL READ	EOF	SDT1	--	20	--	1. 53. 00	
				TM	--	SBID←REAL BID	10	--	1. 53. 01	
				OTHERS	--	--	00	--	1. 53. 02	
63	-4	--	--	EMULATE	--	--	--	63	-3	1. 63. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3	20	--	1. 63. 10
					OTHERS	--	--	00	--	1. 63. 11
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	32	--	1. 63. 20
					OTHERS	--	--	00	--	1. 63. 21
	-1	--	--	EMULATE	--	--	--	63	0	1. 63. 30
	0	--	--	EMULATE	--	--	--	63	+1	1. 63. 40
	+1	SBID+EP	--	REAL READ	EOF	SDT1	SBID+1	20	--	1. 63. 50
					TM	--	SBID←REAL BID	10	--	1. 63. 51
OTHERS					--	--	00	--	1. 63. 52	

FIG. 211

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
73	-4	--	--	EMULATE	--	--	--	73	-3	1. 73. 00
	-3	WTM SBID+EP	--	REAL READ	EOF	SDT1	SBID-3	20	--	1. 73. 10
					OTHERS	--	--	00	--	1. 73. 11
	-2	WTM SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	32	--	1. 73. 20
					OTHERS	--	--	00	--	1. 73. 21
	-1	--	--	EMULATE	--	--	--	73	0	1. 73. 30
	0	--	--	EMULATE	--	--	--	73	+1	1. 73. 40
	+1	WTM	--	REAL READ	EOF	SDT1	SBID+1	20	--	1. 73. 50
					TM	--	SBID←REAL BID	10	--	1. 73. 51
					OTHERS	--	--	00	--	1. 73. 52
83	-4	--	--	EMULATE	--	--	--	83	-3	1. 83. 00
	-3	SBID+EP	--	REAL READ	EOF	SDT1	SBID-3	20	--	1. 83. 10
					OTHERS	--	--	00	--	1. 83. 11
	-2	SBID+EP	--	REAL READ	EOF	SDT2	SBID-3	32	--	1. 83. 20
					OTHERS	--	--	00	--	1. 83. 21
	-1	--	--	EMULATE	--	--	--	83	0	1. 83. 30
	0	--	--	EMULATE	--	--	--	83	+1	1. 83. 40
	+1	--	--	REAL READ	EOD	--	--	00	--	1. 83. 50

000000" 50000000

FIG. 212

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL RB	--	--	--	00	--	2.00.00
10	--	--	--	REAL RB	--	--	--	00	--	2.10.00
20	--	--	--	REAL RB	--	--	--	00	--	2.20.00
30	--	--	--	REAL RB	--	--	--	00	--	2.30.00
40	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2.40.00
	-3	--	--	EMULATE	--	--	--	40	-4	2.40.10
	-2	--	--	EMULATE	--	--	--	40	-3	2.40.20
	-1	--	--	EMULATE	--	--	--	40	-2	2.40.30
	0	--	--	EMULATE	--	--	--	40	-1	2.40.40
50	--	--	--	REAL RB	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	60	0	2.50.00
60	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2.60.00
	-3	--	--	EMULATE	--	--	--	60	-4	2.60.10
	-2	--	--	EMULATE	--	--	--	60	-3	2.60.20
	-1	--	--	EMULATE	--	--	--	60	-2	2.60.30
	0	--	--	EMULATE	--	--	--	60	-1	2.60.40
	+1	--	--	EMULATE	--	--	--	60	0	2.60.50
70	-4	WTM SBID+EP	--	REAL RB	--	--	--	00	--	2.70.00
	-3	--	--	EMULATE	--	--	--	70	-4	2.70.10
	-2	--	--	EMULATE	--	--	--	70	-3	2.70.20
	-1	--	--	EMULATE	--	--	--	70	-2	2.70.30
	0	--	--	EMULATE	--	--	--	70	-1	2.70.40
	+1	--	--	EMULATE	--	--	--	70	0	2.70.50
80	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2.80.00
	-3	--	--	EMULATE	--	--	--	80	-4	2.80.10
	-2	--	--	EMULATE	--	--	--	80	-3	2.80.20
	-1	--	--	EMULATE	--	--	--	80	-2	2.80.30
	0	--	--	EMULATE	--	--	--	80	-1	2.80.40
	+1	--	--	EMULATE	--	--	--	80	0	2.80.50

00000"0000000000

FIG. 213

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL RB	--	--	--	00	--	2. 31. 00
41	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 41. 00
	-3	--	--	EMULATE	--	--	--	41	-4	2. 41. 10
	-2	--	--	EMULATE	--	--	--	41	-3	2. 41. 20
	-1	--	--	EMULATE	--	--	--	41	-2	2. 41. 30
	0	--	--	EMULATE	--	--	--	41	-1	2. 41. 40
	0	--	--	EMULATE	--	--	--	41	-1	2. 41. 40
51	--	--	--	REAL RB	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	61	0	2. 51. 00
61	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 61. 00
	-3	--	--	EMULATE	--	--	--	61	-4	2. 61. 10
	-2	--	--	EMULATE	--	--	--	61	-3	2. 61. 20
	-1	--	--	EMULATE	--	--	--	61	-2	2. 61. 30
	0	--	--	EMULATE	--	--	--	61	-1	2. 61. 40
	0	--	--	EMULATE	--	--	--	61	-1	2. 61. 40
	+1	--	--	EMULATE	--	--	--	61	0	2. 61. 50
71	-4	WTM SBID+EP	--	REAL RB	--	--	--	00	--	2. 71. 00
	-3	--	--	EMULATE	--	--	--	71	-4	2. 71. 10
	-2	--	--	EMULATE	--	--	--	71	-3	2. 71. 20
	-1	--	--	EMULATE	--	--	--	71	-2	2. 71. 30
	0	--	--	EMULATE	--	--	--	71	-1	2. 71. 40
	0	--	--	EMULATE	--	--	--	71	-1	2. 71. 40
	+1	--	--	EMULATE	--	--	--	71	0	2. 71. 50
81	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 81. 00
	-3	--	--	EMULATE	--	--	--	81	-4	2. 81. 10
	-2	--	--	EMULATE	--	--	--	81	-3	2. 81. 20
	-1	--	--	EMULATE	--	--	--	81	-2	2. 81. 30
	0	--	--	EMULATE	--	--	--	81	-1	2. 81. 40
	0	--	--	EMULATE	--	--	--	81	-1	2. 81. 40
	+1	--	--	EMULATE	--	--	--	81	0	2. 81. 50

00000" 50000000

FIG. 214

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
32	--	--	--	REAL RB	--	--	--		00	--	2. 32. 00
42	-4	SBID+EP	--	REAL RB	--	--	--		00	--	2. 42. 00
	-3	--	--	EMULATE	--	--	--		42	-4	2. 42. 10
	-2	--	--	EMULATE	--	--	--		42	-3	2. 42. 20
	-1	--	--	EMULATE	--	--	--		42	-2	2. 42. 30
	0	--	--	EMULATE	--	--	--		42	-1	2. 42. 40
52	--	--	--	REAL RB	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1		62	0	2. 52. 00
62	-4	SBID+EP	--	REAL RB	--	--	--		00	--	2. 62. 00
	-3	--	--	EMULATE	--	--	--		62	-4	2. 62. 10
	-2	--	--	EMULATE	--	--	--		62	-3	2. 62. 20
	-1	--	--	EMULATE	--	--	--		62	-2	2. 62. 30
	0	--	--	EMULATE	--	--	--		62	-1	2. 62. 40
	+1	--	--	EMULATE	--	--	--		62	0	2. 62. 50
72	-4	WTM SBID+EP	--	REAL RB	--	--	--		00	--	2. 72. 00
	-3	--	--	EMULATE	--	--	--		72	-4	2. 72. 10
	-2	--	--	EMULATE	--	--	--		72	-3	2. 72. 20
	-1	--	--	EMULATE	--	--	--		72	-2	2. 72. 30
	0	--	--	EMULATE	--	--	--		72	-1	2. 72. 40
	+1	--	--	EMULATE	--	--	--		72	0	2. 72. 50
82	-4	SBID+EP	--	REAL RB	--	--	--		00	--	2. 82. 00
	-3	--	--	EMULATE	--	--	--		82	-4	2. 82. 10
	-2	--	--	EMULATE	--	--	--		82	-3	2. 82. 20
	-1	--	--	EMULATE	--	--	--		82	-2	2. 82. 30
	0	--	--	EMULATE	--	--	--		82	-1	2. 82. 40
	+1	--	--	EMULATE	--	--	--		82	0	2. 82. 50

00000 " 50000000

FIG. 215

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL RB	--	--	--	00	--	2. 33. 00
43	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 43. 00
	-3	--	--	EMULATE	--	--	--	43	-4	2. 43. 10
	-2	--	--	EMULATE	--	--	--	43	-3	2. 43. 20
	-1	--	--	EMULATE	--	--	--	43	-2	2. 43. 30
	0	--	--	EMULATE	--	--	--	43	-1	2. 43. 40
53	--	--	--	REAL RB	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	63	0	2. 53. 00
63	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 63. 00
	-3	--	--	EMULATE	--	--	--	63	-4	2. 63. 10
	-2	--	--	EMULATE	--	--	--	63	-3	2. 63. 20
	-1	--	--	EMULATE	--	--	--	63	-2	2. 63. 30
	0	--	--	EMULATE	--	--	--	63	-1	2. 63. 40
	+1	--	--	EMULATE	--	--	--	63	0	2. 63. 50
73	-4	WTM SBID+EP	--	REAL RB	--	--	--	00	--	2. 73. 00
	-3	--	--	EMULATE	--	--	--	73	-4	2. 73. 10
	-2	--	--	EMULATE	--	--	--	73	-3	2. 73. 20
	-1	--	--	EMULATE	--	--	--	73	-2	2. 73. 30
	0	--	--	EMULATE	--	--	--	73	-1	2. 73. 40
	+1	--	--	EMULATE	--	--	--	73	0	2. 73. 50
83	-4	SBID+EP	--	REAL RB	--	--	--	00	--	2. 83. 00
	-3	--	--	EMULATE	--	--	--	83	-4	2. 83. 10
	-2	--	--	EMULATE	--	--	--	83	-3	2. 83. 20
	-1	--	--	EMULATE	--	--	--	83	-2	2. 83. 30
	0	--	--	EMULATE	--	--	--	83	-1	2. 83. 40
	+1	--	--	EMULATE	--	--	--	83	0	2. 83. 50

00000"00000000

FIG. 216

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
00	--	--	--	REAL WR	--	--	--		00	--	3. 00. 00
10	--	--	--	REAL WR	EOF	SDT1	--		20	--	3. 10. 00
			--		OTHERS	--	--		00	--	3. 10. 01
20	--	--	--	REAL WR	EOF	SDT2	--		30	--	3. 20. 00
			--		OTHERS	--	--		00	--	3. 20. 01
30	--	--	--	REAL WR	--	--	--		00	--	3. 30. 00
40	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 40. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 40. 10
			--		OTHERS	--	--		00	--	3. 40. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 40. 20
			--		OTHERS	--	--		00	--	3. 40. 21
	-1		--	REAL WR	--	--	--		00	--	3. 40. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 40. 40
			--		OTHERS	--	--		00	--	3. 40. 41
50	--	--	--	REAL WR	EOF	SDT1	--		20	--	3. 50. 00
			--		OTHERS	--	--		00	--	3. 50. 01
60	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 60. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 60. 10
			--		OTHERS	--	--		00	--	3. 60. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 60. 20
			--		OTHERS	--	--		00	--	3. 60. 21
	-1		--	REAL WR	--	--	--		00	--	3. 60. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 60. 40
			--		OTHERS	--	--		00	--	3. 60. 41
	+1	SBID+EP	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 60. 50
		--		OTHERS	--	--		00	--	3. 60. 51	

00000" 5086550

FIG. 217

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
70	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 70. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 70. 10
			--	REAL WR	OTHERS	--	--		00	--	3. 70. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 70. 20
			--	REAL WR	OTHERS	--	--		00	--	3. 70. 21
	-1		--	REAL WR	--	--	--		00	--	3. 70. 30
	0	--	REAL WR	EOF	SDT1	--		20	--	3. 70. 40	
		--	REAL WR	OTHERS	--	--		00	--	3. 70. 41	
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 70. 50
			--	REAL WR	OTHERS	--	--		00	--	3. 70. 51
80	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 80. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 80. 10
			--	REAL WR	OTHERS	--	--		00	--	3. 80. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		30	--	3. 80. 20
			--	REAL WR	OTHERS	--	--		00	--	3. 80. 21
	-1		--	REAL WR	--	--	--		00	--	3. 80. 30
	0	--	REAL WR	EOF	SDT1	--		20	--	3. 80. 40	
		--	REAL WR	OTHERS	--	--		00	--	3. 80. 41	
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 80. 50
			--	REAL WR	OTHERS	--	--		00	--	3. 80. 51

00000"50060000

FIG. 218

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL WR	--	--	--	00	--	3. 31. 00
41	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 41. 00
	-3		REAL WR	EOF	SDT1	SBID-3	20	--	3. 41. 10	
				OTHERS	--	--	00	--	3. 41. 11	
	-2		REAL WR	EOF	SDT2	SBID-3	30	--	3. 41. 20	
				OTHERS	--	--	00	--	3. 41. 21	
	-1		REAL WR	--	--	--	00	--	3. 41. 30	
	0	REAL WR	EOF	SDT1	--	20	--	3. 41. 40		
			OTHERS	--	--	00	--	3. 41. 41		
51	--	--	REAL WR	EOF	SDT1	--	20	--	3. 51. 00	
				OTHERS	--	--	00	--	3. 51. 01	
61	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 61. 00
	-3		REAL WR	EOF	SDT1	SBID-3	20	--	3. 61. 10	
				OTHERS	--	--	00	--	3. 61. 11	
	-2		REAL WR	EOF	SDT2	SBID-3	30	--	3. 61. 20	
				OTHERS	--	--	00	--	3. 61. 21	
	-1		REAL WR	--	--	--	00	--	3. 61. 30	
	0	REAL WR	EOF	SDT1	--	20	--	3. 61. 40		
			OTHERS	--	--	00	--	3. 61. 41		
+1	SBID+EP	--	REAL WR	EOF	SDT1	SBID+1	20	--	3. 61. 50	
				OTHERS	--	--	00	--	3. 61. 51	

FIG. 219

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
71	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 71. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3	20	--	3. 71. 10
			--	REAL WR	OTHERS	--	--	00	--	3. 71. 11
			--	REAL WR	EOF	SDT2	SBID-3	30	--	3. 71. 20
	-2		--	REAL WR	OTHERS	--	--	00	--	3. 71. 21
	-1	--	REAL WR	--	--	--	00	--	3761. 30	
	0	--	--	REAL WR	EOF	SDT1	--	20	--	3. 71. 40
		--	REAL WR	OTHERS	--	--	00	--	3. 71. 41	
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1	20	--	3. 71. 50
			--	REAL WR	OTHERS	--	--	00	--	3. 71. 51
81	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 81. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3	20	--	3. 81. 10
			--	REAL WR	OTHERS	--	--	00	--	3. 81. 11
			--	REAL WR	EOF	SDT2	SBID-3	30	--	3. 81. 20
	-2		--	REAL WR	OTHERS	--	--	00	--	3. 81. 21
	-1	--	REAL WR	--	--	--	00	--	3. 81. 30	
	0	--	--	REAL WR	EOF	SDT1	--	20	--	3. 81. 40
		--	REAL WR	OTHERS	--	--	00	--	3. 81. 41	
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1	20	--	3. 81. 50
			--	REAL WR	OTHERS	--	--	00	--	3. 81. 51

00000"0000000000

FIG. 220

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
22	--	--	--	REAL	EOF	SDT2	--		32	--	3. 22. 00
			WR	OTHERS	--	--		00	--	3. 22. 01	
32	--	--	--	REAL	--	--	--		00	--	3. 32. 00
42	-4	SBID+EP	--	REAL	--	--	--		00	--	3. 42. 00
	-3		WR	EOF	SDT1	SBID-3		20	--	3. 42. 10	
			WR	OTHERS	--	--		00	--	3. 42. 11	
	-2		WR	EOF	SDT2	SBID-3		32	--	3. 42. 20	
			WR	OTHERS	--	--		00	--	3. 42. 21	
	-1		WR	--	--	--		00	--	3. 42. 30	
	0	--	REAL	EOF	SDT1	--		20	--	3. 42. 40	
		--	WR	OTHERS	--	--		00	--	3. 42. 41	
52	--	--	--	REAL	EOF	SDT1	--		20	--	3. 52. 00
			WR	OTHERS	--	--		00	--	3. 52. 01	
62	-4	SBID+EP	--	REAL	--	--	--		00	--	3. 62. 00
	-3		WR	EOF	SDT1	SBID-3		20	--	3. 62. 10	
			WR	OTHERS	--	--		00	--	3. 62. 11	
	-2		WR	EOF	SDT2	SBID-3		32	--	3. 62. 20	
			WR	OTHERS	--	--		00	--	3. 62. 21	
	-1		WR	--	--	--		00	--	3. 62. 30	
	0	--	REAL	EOF	SDT1	--		20	--	3. 62. 40	
		--	WR	OTHERS	--	--		00	--	3. 62. 41	
	+1	SBID+EP	--	REAL	EOF	SDT1	SBID+1		20	--	3. 62. 50
		--	WR	OTHERS	--	--		00	--	3. 62. 51	

00000"30000000

FIG. 221

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS		ES		EP
72	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 72. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 72. 10
			--	REAL WR	OTHERS	--	--		00	--	3. 72. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		32	--	3. 72. 20
			--	REAL WR	OTHERS	--	--		00	--	3. 72. 21
	-1		--	REAL WR	--	--	--		00	--	3. 72. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 72. 40
			--	REAL WR	OTHERS	--	--		00	--	3. 72. 41
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 72. 50
			--	REAL WR	OTHERS	--	--		00	--	3. 72. 51
82	-4	SBID+EP	--	REAL WR	--	--	--		00	--	3. 82. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3		20	--	3. 82. 10
			--	REAL WR	OTHERS	--	--		00	--	3. 82. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3		32	--	3. 82. 20
			--	REAL WR	OTHERS	--	--		00	--	3. 82. 21
	-1		--	REAL WR	--	--	--		00	--	3. 82. 30
	0	--	--	REAL WR	EOF	SDT1	--		20	--	3. 82. 40
			--	REAL WR	OTHERS	--	--		00	--	3. 82. 41
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1		20	--	3. 82. 50
			--	REAL WR	OTHERS	--	--		00	--	3. 82. 51

00000" 50866660

1. Demographic Information	
Variable	Frequency
Age	
18-24	150
25-34	200
35-44	180
45-54	120
55-64	90
65+	60
Gender	
Male	250
Female	250
Ethnicity	
White	150
Black	100
Hispanic	80
Asian	50
Other	20
Education	
High School	100
College	150
Postgraduate	50
Income	
< \$10,000	50
\$10,000 - \$20,000	100
\$20,000 - \$30,000	80
\$30,000 - \$40,000	60
\$40,000 - \$50,000	40
\$50,000+	30
Marital Status	
Married	150
Single	100
Divorced	50
Widowed	20
Occupation	
Managerial	80
Professional	70
Service	60
Unemployed	40
Retired	30
Health Status	
Excellent	50
Good	100
Fair	80
Poor	40
Very Poor	20
Smoking Status	
Smoker	100
Non-smoker	150
Alcohol Consumption	
Regular	50
Occasional	100
Never	100
Exercise Frequency	
Daily	80
Weekly	100
Monthly	50
Never	20
Stress Level	
High	100
Medium	80
Low	50
Life Satisfaction	
Very Satisfied	50
Satisfied	100
Dissatisfied	80
Very Dissatisfied	20

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL WR	--	--	--	00	--	3. 33. 00
43	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 43. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3	20	--	3. 43. 10
					OTHERS	--	--	00	--	3. 43. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3	32	--	3. 43. 20
					OTHERS	--	--	00	--	3. 43. 21
	-1		--	REAL WR	--	--	--	00	--	3. 43. 30
	0		--	REAL WR	EOF	SDT1	--	20	--	3. 43. 40
					OTHERS	--	--	00	--	3. 43. 41
53	--	--	REAL WR	EOF	SDT1	--	20	--	3. 53. 00	
				OTHERS	--	--	00	--	3. 53. 01	
63	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 63. 00
	-3		--	REAL WR	EOF	SDT1	SBID-3	20	--	3. 63. 10
					OTHERS	--	--	00	--	3. 63. 11
	-2		--	REAL WR	EOF	SDT2	SBID-3	32	--	3. 63. 20
					OTHERS	--	--	00	--	3. 63. 21
	-1		--	REAL WR	--	--	--	00	--	3. 63. 30
	0		--	REAL WR	EOF	SDT1	--	20	--	3. 63. 40
					OTHERS	--	--	00	--	3. 63. 41
+1	SBID+EP	--	REAL WR	EOF	SDT1	SBID+1	20	--	3. 63. 50	
				OTHERS	--	--	00	--	3. 63. 51	

1990-1991		1991-1992		1992-1993		1993-1994		1994-1995		1995-1996		1996-1997		1997-1998		1998-1999		1999-2000		2000-2001		2001-2002		2002-2003		2003-2004		2004-2005		2005-2006		2006-2007		2007-2008		2008-2009		2009-2010		2010-2011		2011-2012		2012-2013		2013-2014		2014-2015		2015-2016		2016-2017		2017-2018		2018-2019		2019-2020		2020-2021		2021-2022		2022-2023		2023-2024		2024-2025		2025-2026		2026-2027		2027-2028		2028-2029		2029-2030		2030-2031		2031-2032		2032-2033		2033-2034		2034-2035		2035-2036		2036-2037		2037-2038		2038-2039		2039-2040		2040-2041		2041-2042		2042-2043		2043-2044		2044-2045		2045-2046		2046-2047		2047-2048		2048-2049		2049-2050		2050-2051		2051-2052		2052-2053		2053-2054		2054-2055		2055-2056		2056-2057		2057-2058		2058-2059		2059-2060		2060-2061		2061-2062		2062-2063		2063-2064		2064-2065		2065-2066		2066-2067		2067-2068		2068-2069		2069-2070		2070-2071		2071-2072		2072-2073		2073-2074		2074-2075		2075-2076		2076-2077		2077-2078		2078-2079		2079-2080		2080-2081		2081-2082		2082-2083		2083-2084		2084-2085		2085-2086		2086-2087		2087-2088		2088-2089		2089-2090		2090-2091		2091-2092		2092-2093		2093-2094		2094-2095		2095-2096		2096-2097		2097-2098		2098-2099		2099-2100		2100-2101		2101-2102		2102-2103		2103-2104		2104-2105		2105-2106		2106-2107		2107-2108		2108-2109		2109-2110		2110-2111		2111-2112		2112-2113		2113-2114		2114-2115		2115-2116		2116-2117		2117-2118		2118-2119		2119-2120		2120-2121		2121-2122		2122-2123		2123-2124		2124-2125		2125-2126		2126-2127		2127-2128		2128-2129		2129-2130		2130-2131		2131-2132		2132-2133		2133-2134		2134-2135		2135-2136		2136-2137		2137-2138		2138-2139		2139-2140		2140-2141		2141-2142		2142-2143		2143-2144		2144-2145		2145-2146		2146-2147		2147-2148		2148-2149		2149-2150		2150-2151		2151-2152		2152-2153		2153-2154		2154-2155		2155-2156		2156-2157		2157-2158		2158-2159		2159-2160		2160-2161		2161-2162		2162-2163		2163-2164		2164-2165		2165-2166		2166-2167		2167-2168		2168-2169		2169-2170		2170-2171		2171-2172		2172-2173		2173-2174		2174-2175		2175-2176		2176-2177		2177-2178		2178-2179		2179-2180		2180-2181		2181-2182		2182-2183		2183-2184		2184-2185		2185-2186		2186-2187		2187-2188		2188-2189		2189-2190		2190-2191		2191-2192		2192-2193		2193-2194		2194-2195		2195-2196		2196-2197		2197-2198		2198-2199		2199-2200		2200-2201		2201-2202		2202-2203		2203-2204		2204-2205		2205-2206		2206-2207		2207-2208		2208-2209		2209-2210		2210-2211		2211-2212		2212-2213		2213-2214		2214-2215		2215-2216		2216-2217	
-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--	-----------	--

PRE -- PROCESS				OPERATION	POST -- PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
73	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 73. 00
	-3		REAL WR	EOF	SDT1	SBID-3	20	--	3. 73. 10	
				OTHERS	--	--	00	--	3. 73. 11	
	-2		REAL WR	EOF	SDT2	SBID-3	32	--	3. 73. 20	
				OTHERS	--	--	00	--	3. 73. 21	
	-1	REAL WR	--	--	--	00	--	3. 73. 30		
	0	--	REAL WR	EOF	SDT1	--	20	--	3. 73. 40	
				OTHERS	--	--	00	--	3. 73. 41	
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1	20	--	3. 73. 50
					OTHERS	--	--	00	--	3. 73. 51
83	-4	SBID+EP	--	REAL WR	--	--	--	00	--	3. 83. 00
	-3		REAL WR	EOF	SDT1	SBID-3	20	--	3. 83. 10	
				OTHERS	--	--	00	--	3. 83. 11	
	-2		REAL WR	EOF	SDT2	SBID-3	32	--	3. 83. 20	
				OTHERS	--	--	00	--	3. 83. 21	
	-1	REAL WR	--	--	--	00	--	3. 83. 30		
	0	--	REAL WR	EOF	SDT1	--	20	--	3. 83. 40	
				OTHERS	--	--	00	--	3. 83. 41	
	+1	WTM	--	REAL WR	EOF	SDT1	SBID+1	20	--	3. 83. 50
					OTHERS	--	--	00	--	3. 83. 51

FIG. 224

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL BSP	--	--	--	00	--	4. 00. 00
10	--	--	--	REAL BSP	--	--	--	00	--	4. 10. 00
20	--	--	--	REAL BSP	--	--	--	10	--	4. 20. 00
30	--	--	--	REAL BSP	--	--	--	20	--	4. 30. 00
40	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 40. 00
	-3	--	--	EMULATE	--	--	--	40	-4	4. 40. 10
	-2	--	--	EMULATE	--	--	--	40	-3	4. 40. 20
	-1	--	--	EMULATE	--	--	--	40	-2	4. 40. 30
	0	--	--	EMULATE	--	--	--	40	-1	4. 40. 40
50	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	60	0	4. 50. 00
60	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 60. 00
	-3	--	--	EMULATE	--	--	--	60	-4	4. 60. 10
	-2	--	--	EMULATE	--	--	--	60	-3	4. 60. 20
	-1	--	--	EMULATE	--	--	--	60	-2	4. 60. 30
	0	--	--	EMULATE	--	--	--	60	-1	4. 60. 40
	+1	--	--	EMULATE	--	--	--	60	0	4. 60. 50
70	-4	WTM SBID+EP	--	REAL BSP	--	--	--	00	--	4. 70. 00
	-3	--	--	EMULATE	--	--	--	70	-4	4. 70. 10
	-2	--	--	EMULATE	--	--	--	70	-3	4. 70. 20
	-1	--	--	EMULATE	--	--	--	70	-2	4. 70. 30
	0	--	--	EMULATE	--	--	--	70	-1	4. 70. 40
	+1	--	--	EMULATE	--	--	--	70	0	4. 70. 50
80	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 80. 00
	-3	--	--	EMULATE	--	--	--	80	-4	4. 80. 10
	-2	--	--	EMULATE	--	--	--	80	-3	4. 80. 20
	-1	--	--	EMULATE	--	--	--	80	-2	4. 80. 30
	0	--	--	EMULATE	--	--	--	80	-1	4. 80. 40
	+1	--	--	EMULATE	--	--	--	80	0	4. 80. 50

[illegible]

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL BSP	--	--	--	20	--	4. 31. 00
41	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 41. 00
	-3	--	--	EMULATE	--	--	--	41	-4	4. 41. 10
	-2	--	--	EMULATE	--	--	--	41	-3	4. 41. 20
	-1	--	--	EMULATE	--	--	--	41	-2	4. 41. 30
	0	--	--	EMULATE	--	--	--	41	-1	4. 41. 40
51	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	61	0	4. 51. 00
61	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 61. 00
	-3	--	--	EMULATE	--	--	--	61	-4	4. 61. 10
	-2	--	--	EMULATE	--	--	--	61	-3	4. 61. 20
	-1	--	--	EMULATE	--	--	--	61	-2	4. 61. 30
	0	--	--	EMULATE	--	--	--	61	-1	4. 61. 40
	+1	--	--	EMULATE	--	--	--	61	0	4. 61. 50
71	-4	WTM SBID+EP	--	REAL BSP	--	--	--	00	--	4. 71. 00
	-3	--	--	EMULATE	--	--	--	71	-4	4. 71. 10
	-2	--	--	EMULATE	--	--	--	71	-3	4. 71. 20
	-1	--	--	EMULATE	--	--	--	71	-2	4. 71. 30
	0	--	--	EMULATE	--	--	--	71	-1	4. 71. 40
	+1	--	--	EMULATE	--	--	--	71	0	4. 71. 50
81	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 81. 00
	-3	--	--	EMULATE	--	--	--	81	-4	4. 81. 10
	-2	--	--	EMULATE	--	--	--	81	-3	4. 81. 20
	-1	--	--	EMULATE	--	--	--	81	-2	4. 81. 30
	0	--	--	EMULATE	--	--	--	81	-1	4. 81. 40
	+1	--	--	EMULATE	--	--	--	81	0	4. 81. 50

[illegible]

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL BSP	--	--	--	10	--	4. 22. 00
32	--	--	--	REAL BSP	--	--	--	22	--	4. 32. 00
42	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 42. 00
	-3	--	--	EMULATE	--	--	--	42	-4	4. 42. 10
	-2	--	--	EMULATE	--	--	--	42	-3	4. 42. 20
	-1	--	--	EMULATE	--	--	--	42	-2	4. 42. 30
	0	--	--	EMULATE	--	--	--	42	-1	4. 42. 40
52	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	62	0	4. 52. 00
62	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 62. 00
	-3	--	--	EMULATE	--	--	--	62	-4	4. 62. 10
	-2	--	--	EMULATE	--	--	--	62	-3	4. 62. 20
	-1	--	--	EMULATE	--	--	--	62	-2	4. 62. 30
	0	--	--	EMULATE	--	--	--	62	-1	4. 62. 40
	+1	--	--	EMULATE	--	--	--	62	0	4. 62. 50
72	-4	WTM SBID+EP	--	REAL BSP	--	--	--	00	--	4. 72. 00
	-3	--	--	EMULATE	--	--	--	72	-4	4. 72. 10
	-2	--	--	EMULATE	--	--	--	72	-3	4. 72. 20
	-1	--	--	EMULATE	--	--	--	72	-2	4. 72. 30
	0	--	--	EMULATE	--	--	--	72	-1	4. 72. 40
	+1	--	--	EMULATE	--	--	--	72	0	4. 72. 50
82	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 82. 00
	-3	--	--	EMULATE	--	--	--	82	-4	4. 82. 10
	-2	--	--	EMULATE	--	--	--	82	-3	4. 82. 20
	-1	--	--	EMULATE	--	--	--	82	-2	4. 82. 30
	0	--	--	EMULATE	--	--	--	82	-1	4. 82. 40
	+1	--	--	EMULATE	--	--	--	82	0	4. 82. 50

FIG. 227

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL BSP	--	--	--	22	--	4. 33. 00
43	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 43. 00
	-3	--	--	EMULATE	--	--	--	43	-4	4. 43. 10
	-2	--	--	EMULATE	--	--	--	43	-3	4. 43. 20
	-1	--	--	EMULATE	--	--	--	43	-2	4. 43. 30
	0	--	--	EMULATE	--	--	--	43	-1	4. 43. 40
53	--	--	--	REAL BSP	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	63	0	4. 53. 00
63	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 63. 00
	-3	--	--	EMULATE	--	--	--	63	-4	4. 63. 10
	-2	--	--	EMULATE	--	--	--	63	-3	4. 63. 20
	-1	--	--	EMULATE	--	--	--	63	-2	4. 63. 30
	0	--	--	EMULATE	--	--	--	63	-1	4. 63. 40
	+1	--	--	EMULATE	--	--	--	63	0	4. 63. 50
73	-4	WTM SBID+EP	--	REAL BSP	--	--	--	00	--	4. 73. 00
	-3	--	--	EMULATE	--	--	--	73	-4	4. 73. 10
	-2	--	--	EMULATE	--	--	--	73	-3	4. 73. 20
	-1	--	--	EMULATE	--	--	--	73	-2	4. 73. 30
	0	--	--	EMULATE	--	--	--	73	-1	4. 73. 40
	+1	--	--	EMULATE	--	--	--	73	0	4. 73. 50
83	-4	SBID+EP	--	REAL BSP	--	--	--	00	--	4. 83. 00
	-3	--	--	EMULATE	--	--	--	83	-4	4. 83. 10
	-2	--	--	EMULATE	--	--	--	83	-3	4. 83. 20
	-1	--	--	EMULATE	--	--	--	83	-2	4. 83. 30
	0	--	--	EMULATE	--	--	--	83	-1	4. 83. 40
	+1	--	--	EMULATE	--	--	--	83	0	4. 83. 50

CODED "50358560"

[illegible]

PRE -- PROCESS				OPERATION	POST -- PROCESS				PROCESS ID	
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES		
00	--	--	--	REAL BSPF	--	--	--	00	--	5.00.00
10	--	--	--	REAL BSPF	--	--	--	00	--	5.10.00
20	--	--	--	REAL BSPF	--	--	--	00	--	5.20.00
30	--	--	--	REAL BSPF	--	--	--	00	--	5.30.00
40	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.40.00
	-3	--	--	EMULATE	--	--	--	40	-4	5.40.10
	-2	--	--	EMULATE	--	--	--	40	-4	5.40.20
	-1	--	--	EMULATE	--	--	--	40	-4	5.40.30
	0	--	--	EMULATE	--	--	--	40	-1	5.40.40
50	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	60	0	5.50.00
60	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.60.00
	-3	--	--	EMULATE	--	--	--	60	-4	5.60.10
	-2	--	--	EMULATE	--	--	--	60	-4	5.60.20
	-1	--	--	EMULATE	--	--	--	60	-4	5.60.30
	0	--	--	EMULATE	--	--	--	60	-1	5.60.40
	+1	--	--	EMULATE	--	--	--	60	0	5.60.50
70	-4	WTM SBID+EP	--	REAL BSPF	--	--	--	00	--	5.70.00
	-3	--	--	EMULATE	--	--	--	70	-4	5.70.10
	-2	--	--	EMULATE	--	--	--	70	-4	5.70.20
	-1	--	--	EMULATE	--	--	--	70	-4	5.70.30
	0	--	--	EMULATE	--	--	--	70	-1	5.70.40
	+1	--	--	EMULATE	--	--	--	70	0	5.70.50
80	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.80.00
	-3	--	--	EMULATE	--	--	--	80	-4	5.80.10
	-2	--	--	EMULATE	--	--	--	80	-4	5.80.20
	-1	--	--	EMULATE	--	--	--	80	-4	5.80.30
	0	--	--	EMULATE	--	--	--	80	-1	5.80.40
	+1	--	--	EMULATE	--	--	--	80	0	5.80.50

FIG. 229

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL BSPF	--	--	--	00	--	5.31.00
41	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.41.00
	-3	--	--	EMULATE	--	--	--	41	-4	5.41.10
	-2	--	--	EMULATE	--	--	--	41	-4	5.41.20
	-1	--	--	EMULATE	--	--	--	41	-4	5.41.30
	0	--	--	EMULATE	--	--	--	41	-1	5.41.40
	0	--	--	EMULATE	--	--	--	41	-1	5.41.40
51	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	61	--	5.51.00
61	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.61.00
	-3	--	--	EMULATE	--	--	--	61	-4	5.61.10
	-2	--	--	EMULATE	--	--	--	61	-4	5.61.20
	-1	--	--	EMULATE	--	--	--	61	-4	5.61.30
	0	--	--	EMULATE	--	--	--	61	-1	5.61.40
	+1	--	--	EMULATE	--	--	--	61	0	5.61.50
71	-4	WTM SBID+EP	--	REAL BSPF	--	--	--	00	--	5.71.00
	-3	--	--	EMULATE	--	--	--	71	-4	5.71.10
	-2	--	--	EMULATE	--	--	--	71	-4	5.71.20
	-1	--	--	EMULATE	--	--	--	71	-4	5.71.30
	0	--	--	EMULATE	--	--	--	71	-1	5.71.40
	+1	--	--	EMULATE	--	--	--	71	0	5.71.50
81	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.81.00
	-3	--	--	EMULATE	--	--	--	81	-4	5.81.10
	-2	--	--	EMULATE	--	--	--	81	-4	5.81.20
	-1	--	--	EMULATE	--	--	--	81	-4	5.81.30
	0	--	--	EMULATE	--	--	--	81	-1	5.81.40
	+1	--	--	EMULATE	--	--	--	81	0	5.81.50

00000" 50000000

FIG. 230

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL BSPF	--	--	--	00	--	5. 22. 00
32	--	--	--	REAL BSPF	--	--	--	00	--	5. 32. 00
42	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 42. 00
	-3	--	--	EMULATE	--	--	--	42	-4	5. 42. 10
	-2	--	--	EMULATE	--	--	--	42	-4	5. 42. 20
	-1	--	--	EMULATE	--	--	--	42	-4	5. 42. 30
	0	--	--	EMULATE	--	--	--	42	-1	5. 42. 40
52	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	62	--	5. 52. 00
62	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 62. 00
	-3	--	--	EMULATE	--	--	--	62	-4	5. 62. 10
	-2	--	--	EMULATE	--	--	--	62	-4	5. 62. 20
	-1	--	--	EMULATE	--	--	--	62	-4	5. 62. 30
	0	--	--	EMULATE	--	--	--	62	-1	5. 62. 40
	+1	--	--	EMULATE	--	--	--	62	0	5. 62. 50
72	-4	WTM SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 72. 00
	-3	--	--	EMULATE	--	--	--	72	-4	5. 72. 10
	-2	--	--	EMULATE	--	--	--	72	-4	5. 72. 20
	-1	--	--	EMULATE	--	--	--	72	-4	5. 72. 30
	0	--	--	EMULATE	--	--	--	72	-1	5. 72. 40
	+1	--	--	EMULATE	--	--	--	72	0	5. 72. 50
82	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5. 82. 00
	-3	--	--	EMULATE	--	--	--	82	-4	5. 82. 10
	-2	--	--	EMULATE	--	--	--	82	-4	5. 82. 20
	-1	--	--	EMULATE	--	--	--	82	-4	5. 82. 30
	0	--	--	EMULATE	--	--	--	82	-1	5. 82. 40
	+1	--	--	EMULATE	--	--	--	82	0	5. 82. 50

000000 " 50866660

Table 1. Demographic characteristics of the study population	
Age (years)	Mean (SD)
Male	55.2 (10.5)
Female	56.8 (11.2)
Overall	56.0 (10.8)
Education (years)	Mean (SD)
Male	12.5 (2.1)
Female	12.8 (2.3)
Overall	12.6 (2.2)
Marital status	
Married	78%
Divorced	12%
Widowed	10%
Single	2%
Occupation	
Professional	35%
Managerial	25%
Technical	20%
Service	15%
Unemployed	5%
Retired	2%
Health status	
Good	65%
Fair	25%
Poor	10%
Very poor	2%
Smoking status	
Smoker	30%
Non-smoker	70%
Alcohol consumption	
Regular	15%
Occasional	35%
Never	50%
Family size	Mean (SD)
Male	3.2 (1.5)
Female	3.5 (1.6)
Overall	3.3 (1.5)
Income (USD/month)	Mean (SD)
Male	1,200 (300)
Female	1,150 (280)
Overall	1,175 (290)

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL BSPF	--	--	--	00	--	5.33.00
43	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.43.00
	-3	--	--	EMULATE	--	--	--	43	-4	5.43.10
	-2	--	--	EMULATE	--	--	--	43	-4	5.43.20
	-1	--	--	EMULATE	--	--	--	43	-4	5.43.30
	0	--	--	EMULATE	--	--	--	43	-1	5.43.40
53	--	--	--	REAL BSPF	TM	--	SBID←REAL BID WHEN (SBID)-(REAL BID)=1	63	--	5.53.00
63	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.63.00
	-3	--	--	EMULATE	--	--	--	63	-4	5.63.10
	-2	--	--	EMULATE	--	--	--	63	-4	5.63.20
	-1	--	--	EMULATE	--	--	--	63	-4	5.63.30
	0	--	--	EMULATE	--	--	--	63	-1	5.63.40
	+1	--	--	EMULATE	--	--	--	63	0	5.63.50
73	-4	WTM SBID+EP	--	REAL BSPF	--	--	--	00	--	5.73.00
	-3	--	--	EMULATE	--	--	--	73	-4	5.73.10
	-2	--	--	EMULATE	--	--	--	73	-4	5.73.20
	-1	--	--	EMULATE	--	--	--	73	-4	5.73.30
	0	--	--	EMULATE	--	--	--	73	-1	5.73.40
	+1	--	--	EMULATE	--	--	--	73	0	5.73.50
83	-4	SBID+EP	--	REAL BSPF	--	--	--	00	--	5.83.00
	-3	--	--	EMULATE	--	--	--	83	-4	5.83.10
	-2	--	--	EMULATE	--	--	--	83	-4	5.83.20
	-1	--	--	EMULATE	--	--	--	83	-4	5.83.30
	0	--	--	EMULATE	--	--	--	83	-1	5.83.40
	+1	--	--	EMULATE	--	--	--	83	0	5.83.50

FIG. 232

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL SP	TM	--	SBID←REAL BID	10	--	6. 00. 00
					OTHERS	--	--	00	--	6. 00. 01
10	--	--	--	REAL SP	EOF	--	--	22	--	6. 10. 00
					TM	--	SBID←REAL BID	10	--	6. 10. 01
					OTHERS	--	--	00	--	6. 10. 02
20	--	--	--	REAL SP	EOF	--	--	31	--	6. 20. 00
					TM	--	SBID←REAL BID	10	--	6. 20. 01
					OTHERS	--	--	00	--	6. 20. 02
30	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	6. 30. 00
					OTHERS	--	--	00	--	6. 30. 01
40	-4	--	--	EMULATE	--	--	--	40	-3	6. 40. 00
	-3	--	--	EMULATE	--	--	--	40	-2	6. 40. 10
	-2	--	--	EMULATE	--	--	--	40	-1	6. 40. 20
	-1	--	--	EMULATE	--	--	--	40	0	6. 40. 30
	0	--	--	REAL SP	EOF	--	--	22	--	6. 40. 40
			--		TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	50	--	6. 40. 41
			--		OTHERS	--	--	00	--	6. 40. 42
			--		EOD	--	--	80	+1	6. 40. 43
50	--	--	--	REAL SP	EOF	--	--	22	--	6. 50. 00
					TM	--	SBID←REAL BID	10	--	6. 50. 01
					OTHERS	--	--	00	--	6. 50. 02
60	-4	--	--	EMULATE	--	--	--	60	-3	6. 60. 00
	-3	--	--	EMULATE	--	--	--	60	-2	6. 60. 10
	-2	--	--	EMULATE	--	--	--	60	-1	6. 60. 20
	-1	--	--	EMULATE	--	--	--	60	0	6. 60. 30
	0	--	--	EMULATE	--	--	--	60	+1	6. 60. 40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6. 60. 50
					TM	--	SBID←REAL BID	10	--	6. 60. 51
					OTHERS	--	--	00	--	6. 60. 52

000000" 5086E560

FIG. 234

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	6. 31. 00
					OTHERS	--	--	00	--	6. 31. 01
41	-4	--	--	EMULATE	--	--	--	41	-3	6. 41. 00
	-3	--	--	EMULATE	--	--	--	41	-2	6. 41. 10
	-2	--	--	EMULATE	--	--	--	41	-1	6. 41. 20
	-1	--	--	EMULATE	--	--	--	41	0	6. 41. 30
	0	--	--	REAL SP	EOF	--	--	22	--	6. 41. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	6. 41. 41
					OTHERS	--	--	00	--	6. 41. 42
					EOD	--	--	81	+1	6. 41. 43
51	--	--	--	REAL SP	EOF	--	--	22	--	6. 51. 00
					TM	--	SBID←REAL BID	10	--	6. 51. 01
					OTHERS	--	--	00	--	6. 51. 02
61	-4	--	--	EMULATE	--	--	--	61	-3	6. 61. 00
	-3	--	--	EMULATE	--	--	--	61	-2	6. 61. 10
	-2	--	--	EMULATE	--	--	--	61	-1	6. 61. 20
	-1	--	--	EMULATE	--	--	--	61	0	6. 61. 30
	0	--	--	EMULATE	--	--	--	61	+1	6. 61. 40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6. 61. 50
					TM	--	SBID←REAL BID	10	--	6. 61. 51
					OTHERS	--	--	00	--	6. 61. 52

00000" 00000000

[illegible]

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
71	-4	--	--	EMULATE	--	--	--	71	-3	6. 71. 00
	-3	--	--	EMULATE	--	--	--	71	-2	6. 71. 10
	-2	--	--	EMULATE	--	--	--	71	-1	6. 71. 20
	-1	--	--	EMULATE	--	--	--	71	0	6. 71. 30
	0	--	--	EMULATE	--	--	--	71	+1	6. 71. 40
	+1	WTM	--	REAL SP	EOF	--	SBID+1	22	--	6. 71. 50
					TM	--	SBID←REAL BID	10	--	6. 71. 51
OTHERS					--	--	00	--	6. 71. 52	
81	-4	--	--	EMULATE	--	--	--	81	-3	6. 81. 00
	-3	--	--	EMULATE	--	--	--	81	-2	6. 81. 10
	-2	--	--	EMULATE	--	--	--	81	-1	6. 81. 20
	-1	--	--	EMULATE	--	--	--	81	0	6. 81. 30
	0	--	--	EMULATE	--	--	--	81	+1	6. 81. 40
	+1	--	--	REAL SP	EOD	--	--	00	--	6. 81. 50

FIG. 236

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL SP	EOF	--	--	33	--	6. 22. 00
					TM	--	SBID←REAL BID	10	--	6. 22. 01
					OTHERS	--	--	00	--	6. 22. 02
32	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	6. 32. 00
					OTHERS	--	--	00	--	6. 32. 01
42	-4	--	--	EMULATE	--	--	--	42	-3	6. 42. 00
	-3	--	--	EMULATE	--	--	--	42	-2	6. 42. 10
	-2	--	--	EMULATE	--	--	--	42	-1	6. 42. 20
	-1	--	--	EMULATE	--	--	--	42	0	6. 42. 30
	0	--	--	REAL SP	EOF	--	--	22	--	6. 42. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	52	--	6. 42. 41
					OTHERS	--	--	00	--	6. 42. 42
					EOD	--	--	82	+1	6. 42. 43
52	--	--	--	REAL SP	EOF	--	--	22	--	6. 52. 00
					TM	--	SBID←REAL BID	10	--	6. 52. 01
					OTHERS	--	--	00	--	6. 52. 02
62	-4	--	--	EMULATE	--	--	--	62	-3	6. 62. 00
	-3	--	--	EMULATE	--	--	--	62	-2	6. 62. 10
	-2	--	--	EMULATE	--	--	--	62	-1	6. 62. 20
	-1	--	--	EMULATE	--	--	--	62	0	6. 62. 30
	0	--	--	EMULATE	--	--	--	62	+1	6. 62. 40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6. 62. 50
					TM	--	SBID←REAL BID	10	--	6. 62. 51
					OTHERS	--	--	00	--	6. 62. 52

FIG. 237

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
72	-4	--	--	EMULATE	--	--	--	72	-3	6.72.00
	-3	--	--	EMULATE	--	--	--	72	-2	6.72.10
	-2	--	--	EMULATE	--	--	--	72	-1	6.72.20
	-1	--	--	EMULATE	--	--	--	72	0	6.72.30
	0	--	--	EMULATE	--	--	--	72	+1	6.72.40
	+1	WTM	--	REAL SP	EOF	--	SBID+1	22	--	6.72.50
					TM	--	SBID←REAL BID	10	--	6.72.51
OTHERS					--	--	00	--	6.72.52	
82	-4	--	--	EMULATE	--	--	--	82	-3	6.82.00
	-3	--	--	EMULATE	--	--	--	82	-2	6.82.10
	-2	--	--	EMULATE	--	--	--	82	-1	6.82.20
	-1	--	--	EMULATE	--	--	--	82	0	6.82.30
	0	--	--	EMULATE	--	--	--	82	+1	6.82.40
	+1	--	--	REAL SP	EOD	--	--	00	--	6.82.50

FIG. 238

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL SP	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	6. 33. 00
					OTHERS	--	--	00	--	6. 33. 01
43	-4	--	--	EMULATE	--	--	--	43	-3	6. 43. 00
	-3	--	--	EMULATE	--	--	--	43	-2	6. 43. 10
	-2	--	--	EMULATE	--	--	--	43	-1	6. 43. 20
	-1	--	--	EMULATE	--	--	--	43	0	6. 43. 30
	0	--	--	REAL SP	EOF	--	--	22	--	6. 43. 40
					TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	53	--	6. 43. 41
					OTHERS	--	--	00	--	6. 43. 42
					EOD	--	--	83	+1	6. 43. 43
53	--	--	--	REAL SP	EOF	--	--	22	--	6. 53. 00
					TM	--	SBID←REAL BID	10	--	6. 53. 01
					OTHERS	--	--	00	--	6. 53. 02
63	-4	--	--	EMULATE	--	--	--	63	-3	6. 63. 00
	-3	--	--	EMULATE	--	--	--	63	-2	6. 63. 10
	-2	--	--	EMULATE	--	--	--	63	-1	6. 63. 20
	-1	--	--	EMULATE	--	--	--	63	0	6. 63. 30
	0	--	--	EMULATE	--	--	--	63	+1	6. 63. 40
	+1	SBID+EP	--	REAL SP	EOF	--	SBID+1	22	--	6. 63. 50
					TM	--	SBID←REAL BID	10	--	6. 63. 51
					OTHERS	--	--	00	--	6. 63. 52

CODED SUBSESSO

FIG. 239

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
73	-4	--	--	EMULATE	--	--	--	73	-3	6. 73. 00
	-3	--	--	EMULATE	--	--	--	73	-2	6. 73. 10
	-2	--	--	EMULATE	--	--	--	73	-1	6. 73. 20
	-1	--	--	EMULATE	--	--	--	73	0	6. 73. 30
	0	--	--	EMULATE	--	--	--	73	+1	6. 73. 40
	+1	WTM	--	REAL SP	EOF	--	SBID+1	22	--	6. 73. 50
					TM	--	SBID←REAL BID	10	--	6. 73. 51
					OTHERS	--	--	00	--	6. 73. 52
83	-4	--	--	EMULATE	--	--	--	83	-3	6. 83. 00
	-3	--	--	EMULATE	--	--	--	83	-2	6. 83. 10
	-2	--	--	EMULATE	--	--	--	83	-1	6. 83. 20
	-1	--	--	EMULATE	--	--	--	83	0	6. 83. 30
	0	--	--	EMULATE	--	--	--	83	+1	6. 83. 40
	+1	--	--	REAL SP	EOD	--	--	00	--	6. 83. 50

00000" 5085550

FIG. 240

PRE -- PROCESS				OPERATION	POST -- PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL FSPF	TM	--	SBID←REAL BID	10	--	7.00.00
					OTHERS	--	--	00	--	7.00.01
10	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.10.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.10.01
					OTHERS	--	--	00	--	7.10.02
20	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	7.20.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.20.01
					OTHERS	--	--	00	--	7.20.02
30	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	7.30.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.30.01
					OTHERS	--	--	00	--	7.30.02
40	-4	--	--	EMULATE	--	--	--	40	-3	7.40.00
	-3	--	--	EMULATE	--	--	--	40	0	7.40.10
	-2	--	--	EMULATE	--	--	--	40	0	7.40.20
	-1	--	--	EMULATE	--	--	--	40	0	7.40.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.40.40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	50	--	7.40.41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3	10	--	7.40.42
					OTHERS	--	--	00	--	7.40.43
EOD	--	--	80	+1	7.40.44					
50	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.50.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.50.01
					OTHERS	--	--	00	--	7.50.02

000000 "50000000"

FIG. 241

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
60	-4	--	--	EMULATE	--	--	--	60	-3	7. 60. 00
	-3	--	--	EMULATE	--	--	--	60	0	7. 60. 10
	-2	--	--	EMULATE	--	--	--	60	0	7. 60. 20
	-1	--	--	EMULATE	--	--	--	60	0	7. 60. 30
	0	--	--	EMULATE	--	--	--	60	+1	7. 60. 40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 60. 50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 60. 51
OTHERS					--	--	00	--	7. 60. 52	
70	-4	--	--	EMULATE	--	--	--	70	-3	7. 70. 00
	-3	--	--	EMULATE	--	--	--	70	0	7. 70. 10
	-2	--	--	EMULATE	--	--	--	70	0	7. 70. 20
	-1	--	--	EMULATE	--	--	--	70	0	7. 70. 30
	0	--	--	EMULATE	--	--	--	70	+1	7. 70. 40
	+1	WTM	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 70. 50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 70. 51
OTHERS					--	--	00	--	7. 70. 52	
80	-4	--	--	EMULATE	--	--	--	80	-3	7. 80. 00
	-3	--	--	EMULATE	--	--	--	80	0	7. 80. 10
	-2	--	--	EMULATE	--	--	--	80	0	7. 80. 20
	-1	--	--	EMULATE	--	--	--	80	0	7. 80. 30
	0	--	--	EMULATE	--	--	--	80	+1	7. 80. 40
	+1	--	--	REAL FSPF	EOD	--	--	00	--	7. 80. 50

00000" 5086E560

FIG. 242

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	7.31.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.31.01
					OTHERS	--	--	00	--	7.31.02
41	-4	--	--	EMULATE	--	--	--	41	-3	7.41.00
	-3	--	--	EMULATE	--	--	--	41	0	7.41.10
	-2	--	--	EMULATE	--	--	--	41	0	7.41.20
	-1	--	--	EMULATE	--	--	--	41	0	7.41.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.41.40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	51	--	7.41.41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3	10	--	7.41.42
					OTHERS	--	--	00	--	7.41.43
					EOD	--	--	81	+1	7.41.44
51	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.51.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.51.01
					OTHERS	--	--	00	--	7.51.02
61	-4	--	--	EMULATE	--	--	--	61	-3	7.61.00
	-3	--	--	EMULATE	--	--	--	61	0	7.61.10
	-2	--	--	EMULATE	--	--	--	61	0	7.61.20
	-1	--	--	EMULATE	--	--	--	61	0	7.61.30
	0	--	--	EMULATE	--	--	--	61	+1	7.61.40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.61.50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.61.51
					OTHERS	--	--	00	--	7.61.52

FIG. 243

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
71	-4	--	--	EMULATE	--	--	--	71	-3	7. 71. 00
	-3	--	--	EMULATE	--	--	--	71	0	7. 71. 10
	-2	--	--	EMULATE	--	--	--	71	0	7. 71. 20
	-1	--	--	EMULATE	--	--	--	71	0	7. 71. 30
	0	--	--	EMULATE	--	--	--	71	+1	7. 71. 40
	+1	WTM	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 71. 50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 71. 51
					OTHERS	--	--	00	--	7. 71. 52
81	-4	--	--	EMULATE	--	--	--	81	-3	7. 81. 00
	-3	--	--	EMULATE	--	--	--	81	0	7. 81. 10
	-2	--	--	EMULATE	--	--	--	81	0	7. 81. 20
	-1	--	--	EMULATE	--	--	--	81	0	7. 81. 30
	0	--	--	EMULATE	--	--	--	81	+1	7. 81. 40
	+1	--	--	REAL FSPF	EOD	--	--	00	--	7. 81. 50

000000" 50855550

FIG. 244

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.22.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.22.01
					OTHERS	--	--	00	--	7.22.02
32	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	7.32.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.32.01
					OTHERS	--	--	00	--	7.32.02
42	-4	--	--	EMULATE	--	--	--	42	-3	7.42.00
	-3	--	--	EMULATE	--	--	--	42	0	7.42.10
	-2	--	--	EMULATE	--	--	--	42	0	7.42.20
	-1	--	--	EMULATE	--	--	--	42	0	7.42.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.42.40
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)=1	52	--	7.42.41
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠1AND3	10	--	7.42.42
					OTHERS	--	--	00	--	7.42.43
					EOD	--	--	82	+1	7.42.44
52	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.52.00
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.52.01
					OTHERS	--	--	00	--	7.52.02
62	-4	--	--	EMULATE	--	--	--	62	-3	7.62.00
	-3	--	--	EMULATE	--	--	--	62	0	7.62.10
	-2	--	--	EMULATE	--	--	--	62	0	7.62.20
	-1	--	--	EMULATE	--	--	--	62	0	7.62.30
	0	--	--	EMULATE	--	--	--	62	+1	7.62.40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.62.50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.62.51
					OTHERS	--	--	00	--	7.62.52

000000"50866360

FIG. 245

PRE – PROCESS				OPERATION	POST – PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
72	-4	--	--	EMULATE	--	--	--	72	-3	7.72.00
	-3	--	--	EMULATE	--	--	--	72	0	7.72.10
	-2	--	--	EMULATE	--	--	--	72	0	7.72.20
	-1	--	--	EMULATE	--	--	--	72	0	7.72.30
	0	--	--	EMULATE	--	--	--	72	+1	7.72.40
	+1	WTM	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7.72.50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7.72.51
OTHERS					--	--	00	--	7.72.52	
82	-4	--	--	EMULATE	--	--	--	82	-3	7.82.00
	-3	--	--	EMULATE	--	--	--	82	0	7.82.10
	-2	--	--	EMULATE	--	--	--	82	0	7.82.20
	-1	--	--	EMULATE	--	--	--	82	0	7.82.30
	0	--	--	EMULATE	--	--	--	82	+1	7.82.40
	+1	--	--	REAL FSPF	EOD	--	--	00	--	7.82.50

Table 1. Demographic characteristics of the study population	
Age (years)	50.0 ± 10.0
Gender	
Male	50.0%
Female	50.0%
Education	
High school	50.0%
University	50.0%
Occupation	
Physician	50.0%
Nurse	50.0%
Other	50.0%
Marital status	
Married	50.0%
Single	50.0%
Divorced	50.0%
Widowed	50.0%
Religion	
Muslim	50.0%
Christian	50.0%
Jewish	50.0%
Hindu	50.0%
Buddhist	50.0%
Sikh	50.0%
Other	50.0%
Smoking status	
Smoker	50.0%
Non-smoker	50.0%
Alcohol consumption	
Alcoholic	50.0%
Non-alcoholic	50.0%
Family size	
1-2	50.0%
3-4	50.0%
5-6	50.0%
7-8	50.0%
9-10	50.0%
11-12	50.0%
13-14	50.0%
15-16	50.0%
17-18	50.0%
19-20	50.0%
21-22	50.0%
23-24	50.0%
25-26	50.0%
27-28	50.0%
29-30	50.0%
31-32	50.0%
33-34	50.0%
35-36	50.0%
37-38	50.0%
39-40	50.0%
41-42	50.0%
43-44	50.0%
45-46	50.0%
47-48	50.0%
49-50	50.0%
51-52	50.0%
53-54	50.0%
55-56	50.0%
57-58	50.0%
59-60	50.0%
61-62	50.0%
63-64	50.0%
65-66	50.0%
67-68	50.0%
69-70	50.0%
71-72	50.0%
73-74	50.0%
75-76	50.0%
77-78	50.0%
79-80	50.0%
81-82	50.0%
83-84	50.0%
85-86	50.0%
87-88	50.0%
89-90	50.0%
91-92	50.0%
93-94	50.0%
95-96	50.0%
97-98	50.0%
99-100	50.0%
101-102	50.0%
103-104	50.0%
105-106	50.0%
107-108	50.0%
109-110	50.0%
111-112	50.0%
113-114	50.0%
115-116	50.0%
117-118	50.0%
119-120	50.0%
121-122	50.0%
123-124	50.0%
125-126	50.0%
127-128	50.0%
129-130	50.0%
131-132	50.0%
133-134	50.0%
135-136	50.0%
137-138	50.0%
139-140	50.0%
141-142	50.0%
143-144	50.0%
145-146	50.0%
147-148	50.0%
149-150	50.0%
151-152	50.0%
153-154	50.0%
155-156	50.0%
157-158	50.0%
159-160	50.0%
161-162	50.0%
163-164	50.0%
165-166	50.0%
167-168	50.0%
169-170	50.0%
171-172	50.0%
173-174	50.0%
175-176	50.0%
177-178	50.0%
179-180	50.0%
181-182	50.0%
183-184	50.0%
185-186	50.0%
187-188	50.0%
189-190	50.0%
191-192	50.0%
193-194	50.0%
195-196	50.0%
197-198	50.0%
199-200	50.0%

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)–(SBID)=3	43	0	7.33.00
						--	SBID←REAL BID WHEN (REAL BID)–(SBID)≠3	10	--	7.33.01
					OTHERS	--	--	00	--	7.33.02
43	-4	--	--	EMULATE	--	--	--	43	-3	7.43.00
	-3	--	--	EMULATE	--	--	--	43	0	7.43.10
	-2	--	--	EMULATE	--	--	--	43	0	7.43.20
	-1	--	--	EMULATE	--	--	--	43	0	7.43.30
	0	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)–(SBID)=3	43	0	7.43.40
						--	SBID←REAL BID WHEN (REAL BID)–(SBID)=1	53	--	7.43.41
						--	SBID←REAL BID WHEN (REAL BID)–(SBID)≠1AND3	10	--	7.43.42
					OTHERS	--	--	00	--	7.43.43
				EOD	--	--	83	+1	7.43.44	
53	--	--	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)–(SBID)=3	43	0	7.53.00
						--	SBID←REAL BID WHEN (REAL BID)–(SBID)≠3	10	--	7.53.01
					OTHERS	--	--	00	--	7.53.02
63	-4	--	--	EMULATE	--	--	--	63	-3	7.63.00
	-3	--	--	EMULATE	--	--	--	63	0	7.63.10
	-2	--	--	EMULATE	--	--	--	63	0	7.63.20
	-1	--	--	EMULATE	--	--	--	63	0	7.63.30
	0	--	--	EMULATE	--	--	--	63	+1	7.63.40
	+1	SBID+EP	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)–(SBID)=3	43	0	7.63.50
						--	SBID←REAL BID WHEN (REAL BID)–(SBID)≠3	10	--	7.63.51
					OTHERS	--	--	00	--	7.63.52

FIG. 247

PRE — PROCESS				OPERATION	POST — PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
73	-4	--	--	EMULATE	--	--	--	73	-3	7. 73. 00
	-3	--	--	EMULATE	--	--	--	73	0	7. 73. 10
	-2	--	--	EMULATE	--	--	--	73	0	7. 73. 20
	-1	--	--	EMULATE	--	--	--	73	0	7. 73. 30
	0	--	--	EMULATE	--	--	--	73	+1	7. 73. 40
	+1	WTM	--	REAL FSPF	TM	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	7. 73. 50
						--	SBID←REAL BID WHEN (REAL BID)-(SBID)≠3	10	--	7. 73. 51
OTHERS					--	--	00	--	7. 73. 52	
83	-4	--	--	EMULATE	--	--	--	83	-3	7. 83. 00
	-3	--	--	EMULATE	--	--	--	83	0	7. 83. 10
	-2	--	--	EMULATE	--	--	--	83	0	7. 83. 20
	-1	--	--	EMULATE	--	--	--	83	0	7. 83. 30
	0	--	--	EMULATE	--	--	--	83	+1	7. 83. 40
	+1	--	--	REAL FSPF	EOD	--	--	00	--	7. 83. 50

000000" 500666560

FIG. 248

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
00	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.00.00
10	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.10.00
20	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.20.00
30	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	40	0	8.30.00
40	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.40.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.40.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.40.20
	-1	--	--	EMULATE	--	--	--	40	0	8.40.30
	0	--	--	EMULATE	--	--	--	70	+1	8.40.40
50	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.50.00
60	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.30
	0	--	--	EMULATE	--	--	--	60	+1	8.60.40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.60.50
70	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.70.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.70.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.70.20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.70.30
	0	--	--	EMULATE	--	--	--	70	+1	8.70.40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.70.50
80	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.80.00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.80.10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.80.20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.80.30
	0	--	--	EMULATE	--	--	--	80	+1	8.80.40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8.80.50

FIG. 249

PRE -- PROCESS				OPERATION	POST -- PROCESS					PROCESS ID
ES	EP	RE- POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
31	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	41	0	8. 31. 00
41	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 41. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 41. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 41. 20
	-1	--	--	EMULATE	--	--	--	41	0	8. 41. 30
	0	--	--	EMULATE	--	--	--	71	+1	8. 41. 40
51	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 51. 00
61	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 61. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 61. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 61. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 61. 30
	0	--	--	EMULATE	--	--	--	61	+1	8. 61. 40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 61. 50
71	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 71. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 71. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 71. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 71. 30
	0	--	--	EMULATE	--	--	--	71	+1	8. 71. 40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 71. 50
81	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 81. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 81. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 81. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 81. 30
	0	--	--	EMULATE	--	--	--	81	+1	8. 81. 40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 81. 50

00000"5086E560

FIG. 250

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
22	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 22. 00
32	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	42	0	8. 32. 00
42	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 42. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 42. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 42. 20
	-1	--	--	EMULATE	--	--	--	42	0	8. 42. 30
	0	--	--	EMULATE	--	--	--	72	+1	8. 42. 40
52	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 52. 00
62	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 62. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 62. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 62. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 62. 30
	0	--	--	EMULATE	--	--	--	62	+1	8. 62. 40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 62. 50
72	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 72. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 72. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 72. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 72. 30
	0	--	--	EMULATE	--	--	--	72	+1	8. 72. 40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 72. 50
82	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 82. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 82. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 82. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 82. 30
	0	--	--	EMULATE	--	--	--	82	+1	8. 82. 40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 82. 50

00000"50000000

FIG. 251

PRE - PROCESS				OPERATION	POST - PROCESS					PROCESS ID
ES	EP	RE-POSITION	RESTORE		BLOCK	SAVE	BID PROCESS	ES	EP	
33	--	--	--	REAL WTM	--	--	SBID←REAL BID WHEN (REAL BID)-(SBID)=3	43	0	8. 33. 00
43	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 43. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 43. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 43. 20
	-1	--	--	EMULATE	--	--	--	43	0	8. 43. 30
	0	--	--	EMULATE	--	--	--	73	+1	8. 43. 40
53	--	--	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 53. 00
63	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 30
	0	--	--	EMULATE	--	--	--	63	+1	8. 63. 40
	+1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 63. 50
73	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 73. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 73. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 73. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 73. 30
	0	--	--	EMULATE	--	--	--	73	+1	8. 73. 40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 73. 50
83	-4	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 83. 00
	-3	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 83. 10
	-2	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 83. 20
	-1	SBID+EP	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 83. 30
	0	--	--	EMULATE	--	--	--	83	+1	8. 83. 40
	+1	WTM	--	REAL WTM	--	--	SBID←REAL BID	10	--	8. 83. 50

00000"5086E560




FIG. 269(A)




FIG. 269(B)




FIG. 270(A)






FIG. 270(B)








FIG. 272(A)




FIG. 272(B)




FIG.274

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
WR	0. 000731	0. 000731	(1)
WTM	0. 713581	0. 713581	(2)
WR	0. 003502	0. 003502	(3)
WR	0. 000641	0. 000641	(4)
WTM	0. 596851	0. 596851	(5)
WTM	0. 298012	0. 000500	(6)
BSPF	0. 460880	0. 000500	(7)
NOP	0. 000548	0. 000500	
LDSP	0. 000521	0. 000521	
LDSP	0. 000469	0. 000469	
LDSP	0. 000493	0. 000493	
NOP	0. 000524	0. 000524	
SNIO	0. 002945	0. 002945	
RDVC	0. 000580	0. 000580	
NOP	0. 000529	0. 000529	
SNS	0. 002731	0. 002731	
LDSP	0. 000420	0. 000420	
BSPF	0. 000583	0. 000500	(8)
BSPF	0. 291417	0. 000500	(9)
FSPF	0. 291342	0. 000500	(10)
RD	0. 531535	0. 000500	(11)
FSPF	1. 410659	0. 000500	(12)
RD	0. 581191	0. 000500	(13)
BSPF	0. 000606	0. 000500	(14)
BSPF	0. 455999	0. 000500	(15)
BSPF	0. 293099	0. 000500	(16)
FSPF	0. 290969	0. 000500	(17)
RD	0. 531411	0. 000500	(18)
FSPF	1. 414089	0. 000500	(19)
NOP	0. 290595	0. 000500	
WR	0. 000615	0. 000615	(20)
WR	0. 000615	0. 000615	(21)
WTM	0. 639278	0. 339278	(22)
WR	0. 003324	0. 003324	(23)
WR	0. 000641	0. 000641	(24)
TOTAL	9. 111926	1. 981191	SECOND

00000" 50066550

[illegible]

COMMAND	WITHOUT EMULATION	WITH EMULATION	REMARKS
WR	0. 000700	0. 000700	(1)
WTM	0. 843145	0. 541334	(2)
WR	0. 011607	0. 011771	(3)
WR	0. 005543	0. 005291	(4)
WTM	0. 615312	0. 310921	(5)
WTM	0. 308603	0. 005847	(6)
BSPF	0. 482427	0. 005927	(7)
NOP	0. 003681	0. 003799	
LDSP	0. 006880	0. 006852	
LDSP	0. 006785	0. 006929	
NOP	0. 003463	0. 003419	
NOP	0. 003500	0. 003514	
SNS	0. 011085	0. 011727	
LDSP	0. 006662	0. 006966	
BSPF	0. 300570	0. 005836	(8)
BSPF	0. 305450	0. 005990	(9)
FSPF	0. 474757	0. 005934	(10)
RD	0. 097280	0. 008346	(11)
FSPF	0. 205869	0. 005892	(12)
RD	0. 306587	0. 004664	(13)
BSPF	0. 476655	0. 005798	(14)
LDSP	0. 006960	0. 006918	
WR	0. 004667	0. 004711	(15)
WR	0. 005425	0. 005041	(16)
WTM	1. 833579	0. 308303	(17)
WR	0. 003300	0. 003300	(18)
WR	0. 000600	0. 000600	(19)
TOTAL	6. 331092	1. 296330	SECOND




FIG. 276(A) LOGICAL IMAGE




FIG. 276(B) PHYSICAL IMAGE




FIG. 276(C)